

## RF Exposure evaluation

According to 447498 D04 Interim General RF Exposure Guidance v01

$$P_{th} \text{ (mW)} = ERP_{20 \text{ cm}} \text{ (mW)} = \begin{cases} 2040f & 0.3 \text{ GHz} \leq f < 1.5 \text{ GHz} \\ 3060 & 1.5 \text{ GHz} \leq f \leq 6 \text{ GHz} \end{cases} \quad (\text{B.1})$$

$$P_{th} \text{ (mW)} = \begin{cases} ERP_{20 \text{ cm}} (d/20 \text{ cm})^x & d \leq 20 \text{ cm} \\ ERP_{20 \text{ cm}} & 20 \text{ cm} < d \leq 40 \text{ cm} \end{cases} \quad (\text{B.2})$$

where

$$x = -\log_{10} \left( \frac{60}{ERP_{20 \text{ cm}} \sqrt{f}} \right)$$

and  $f$  is in GHz,  $d$  is the separation distance (cm), and  $ERP_{20 \text{ cm}}$  is per Formula (B.1).  
The example values shown in Table B.2 are for illustration only.

Table B.2—Example Power Thresholds (mW)

Frequency (MHz)	Distance (mm)									
	5	10	15	20	25	30	35	40	45	50
300	39	65	88	110	129	148	166	184	201	217
450	22	44	67	89	112	135	158	180	203	226
835	9	25	44	66	90	116	145	175	207	240
1900	3	12	26	44	66	92	122	157	195	236
2450	3	10	22	38	59	83	111	143	179	219
3600	2	8	18	32	49	71	96	125	158	195
5800	1	6	14	25	40	58	80	106	136	169

$$ERP/EIRP = P_T + G_T - L_C$$

ERP/EIRP is the equivalent (or effective) radiated power [in same units as  $P_T$ , typically dBW, dBm, or power spectral density (psd)], relative to either a dipole antenna (ERP) or an isotropic antenna (EIRP).

$P_T$  is the transmitter output power, in dBW, dBm, or psd (power over a specified reference bandwidth).

$G_T$  is the gain of the transmitting antenna, in dBd (ERP) or dBi (EIRP).

$L_C$  is the signal attenuation in the connecting cable between the transmitter and the antenna, in dB.

### For BLE mode

Frequency (MHz)	Output power to antenna (dBm)	Ant gain(dBi)	EIRP(dBm)	ERP(dBm)	ERP(mw)	Distance (cm)	$P_{th}$ (mW)
2480	2.02	4.16	6.18	4.03	2.53	0.5	2.7

$$ERP = EIRP - 2.15 \text{ dB}$$

WORSE CASE

$$2.53 \text{ mW} < 2.7 \text{ mW}$$

**For WIFI 2.4G mode**

Frequency (MHz)	Output power to antenna (dBm)	Ant gain(dBi)	EIRP(dBm)	ERP(dBm)	ERP(mw)	Distance (cm)	P <sub>th</sub> (mW)
2462	2.19	4.16	6.35	4.20	2.63	0.5	2.7

ERP = EIRP -2.15 dB

WORSE CASE

2.63mW<2.7mW

Remark:

Then SAR evaluation is not required