

# RF Exposure evaluation

**Product Name** : GEEK ONE  
**FCC ID** : 2A8MI-AMP06  
**Test Standard** : KDB447498D04 General RF Exposure Guidance v01

According to 447498 D04 Interim General RF Exposure Guidance v01

$$P_{th} \text{ (mW)} = ERP_{20 \text{ cm}} \text{ (mW)} = \begin{cases} 2040f & 0.3 \text{ GHz} \leq f < 1.5 \text{ GHz} \\ 3060 & 1.5 \text{ GHz} \leq f \leq 6 \text{ GHz} \end{cases} \quad (\text{B.1})$$

$$P_{th} \text{ (mW)} = \begin{cases} ERP_{20 \text{ cm}} (d/20 \text{ cm})^x & d \leq 20 \text{ cm} \\ ERP_{20 \text{ cm}} & 20 \text{ cm} < d \leq 40 \text{ cm} \end{cases} \quad (\text{B.2})$$

where

$$x = -\log_{10} \left( \frac{60}{ERP_{20 \text{ cm}} \sqrt{f}} \right)$$

and  $f$  is in GHz,  $d$  is the separation distance (cm), and  $ERP_{20 \text{ cm}}$  is per Formula (B.1). The example values shown in Table B.2 are for illustration only.

Table B.2—Example Power Thresholds (mW)

Frequency (MHz)	Distance (mm)									
	5	10	15	20	25	30	35	40	45	50
300	39	65	88	110	129	148	166	184	201	217
450	22	44	67	89	112	135	158	180	203	226
835	9	25	44	66	90	116	145	175	207	240
1900	3	12	26	44	66	92	122	157	195	236
2450	3	10	22	38	59	83	111	143	179	219
3600	2	8	18	32	49	71	96	125	158	195
5800	1	6	14	25	40	58	80	106	136	169

**BT:**

**TX:**

Ant gain = 1.9 dBi

MAX output power : [3.041dBm@2480MHz](#)

ERP=3.041+1.9-2.15=2.791dBm

WORSE CASE:

$10^{0.3041}=2.014\text{mW} < 2.715 \text{ mW}$

Then SAR evaluation is not required

**RX:**

Ant gain = 1.7 dBi

MAX output power : [2.851dBm@2402MHz](#)

ERP=2.851+1.7-2.15=2.401dBm

WORSE CASE:

$10^{0.2851}=1.93\text{mW} < 2.715 \text{ mW}$

Then SAR evaluation is not required

**BLE:**

**TX:**

Ant gain = 1.9 dBi

MAX output power : [0.49dBm@2402MHz](#)

ERP=0.49+1.9-2.15=0.24dBm

WORSE CASE:

$10^{0.049}=1.12\text{mW} < 2.715 \text{ mW}$

Then SAR evaluation is not required

**RX:**

Ant gain = 1.7 dBi

MAX output power : [0.486dBm@2402MHz](#)

ERP=0.486+1.7-2.15=0.036dBm

WORSE CASE:

$10^{0.0486}=1.12\text{mW} < 2.715 \text{ mW}$

Then SAR evaluation is not required