

二、按键操作说明

RGB幻彩灯

音乐播放/暂停

2.1、开关机 长按3秒开关机 **音乐模式下**:短按播放或暂停音乐; 来电模式下

1、短按接听电话,再次短按挂段电话; 2、长按拒接挂断来电

3、双击末码重播。来电时会伴随电话号码播报。 低电提示: "电量低请充电"中文

FM模式下: 短按自动搜台

音乐播放模式下:长按音量"+"为音量增加;短按 切换到下一曲;

FM模式下: 短按向下切换已保存电台, 长按加大 音量;

双击: 开机模式下, 双击音量加键, 可切换选择手 动接听和10S后自动接听来电,并伴随语音播放提 示"自动接听"和"手动接听"。

2.3、音量减 **音乐播放模式下:**长按音量"-"为音量减小;短按

FM模式下: 短按向上切换已保存电台, 长按减小

2.4. M键RGB模式键

短按切换6种RGB灯效模式,短按最后可以关闭所 有灯光;长按在蓝牙和FM模式间切换。

三、LED指示灯状态显示

蓝牙等待配对状态: 栅格内LED灯快闪; 蓝牙配对成功: 栅格内LED灯恒亮; 蓝牙模式:播放栅格内LED灯慢闪;

待机状态: 蓝牙模式未连接5分钟无操作自动关机; **充电状态**: 电池充满电状态,红色LED 熄灭; 在机器开机情况下:插入充电器充电,机器会自动 关机,此时如需开机,请重新长按开关机键3秒开

五、规格参数

电池容量: 2000MAH 蓝牙名称: QINLIFE Y60 待机时长: 270H **蓝牙版本:** V5.3 **充电时间:**约2.5小时 传输距离: 10M **充电电压**: 5V/1A **耳机接口:** Type-C **通话时长:** 连续通话20H **充电接口:** Type-C Fm收音: (支持频段范围: 87.5MHZ-108.0MHZ)

六、蓝牙耳机安装

Y60适用于各类头盔。

全盔安装方法

掀开头盔内衬,魔术贴贴在耳朵、与嘴巴的位置上,将喇

叭与麦贴在魔术贴的位置,再将设备安装在头盔的边缘。其

它类型的头盔安装方法一样。配件3M胶,根据头盔类型进行

Half helmet installation method

Open the helmet liner, place the velcro on the ear and mouth,

place the horn and microphone on the velcro, and then install the

device on the edge of the helmet. The installation method of other types of helmets is the same. Accessories 3M glue can be

installed in different ways according to the helmet type to

选择不同的安装方式,达到更佳的使用效果。







七、包装清单







八、注意事项

- 1、请勿将产品投入明火中,避免发生爆炸;
- 2、请勿拆卸产品。避免产品电子器件损坏; 3、请勿靠近尖锐器,物对产品造成损坏;


4、长时间不用、请放置干燥处。

HELMET Bluetooth Headset an instruction manual



CE SRRC ROHS 🗏 🕰 🐠

1.Description of function keys Physical key design allows riders to operate



Æ, Long press the volume to increase Short press one song Long press the volume to decrease Light mode switching

2. Key operation instructions

2.1 Switch on/off
Press for 3 seconds to turn on/off
In music mode: short press to play or pause music; In incoming call mode:

1. Short press to answer the call, and short press to hang up the call again;

2. Long press to reject and end the call; 3. Double click Last Code Replay. Call will be accompanied by the telephone number broadcast Low battery prompt: "Charge if the battery is low" in **Under FM mode:** short press to search automatically

2.2 Volume increase In music playing mode: long press "+" to increase the volume; Press briefly to switch to the next song;

In FM mode: short press to switch to the saved radio station long press to increase the volume; **Double click:** In the power on mode, double click the volume increase button to switch between manual answer and automatic answer after 10S, and the voice playback prompts "automatic answer" and "manual answer

In music playing mode: Long press "-" to decrease the volume; Short pressSwitch to the previous song; In FM mode: short press to switch to the saved radio station, long press to decrease the tone. Long press to switch between Bluetooth and FM modes.

2.4 M key RGB mode keyShort press to switch 6 RGB light effect modes. Long press to switch between Bluetooth and FM modes.

3.LED indicator status display

Bluetooth waiting for pairing status: LED in the grid flashes; Bluetooth pairing succeeded: LED in the grid is always on; Bluetooth mode: LED light in the playback grid flashes slowly; Standby mode: automatically shut down when the Bluetooth mode is not connected for 5 minutes without operation; Charging state: the battery is fully charged, and the red LED is

When the machine is turned on: insert the charger to charge, the machine will automatically shut down. If you need to turn on the machine at this time, please press and hold the On/Off key for 3 seconds to turn on the machine

4. Voice prompt description

Power on prompt tone: "Power on" Chinese Shutdown prompt tone: "Shutdown" in Chinese Manual answer: "Manual answer" Chinese Auto answer: "Auto answer" Chinese Bluetooth mode prompt tone: "Bluetooth mode" Chinese Maximum volume: "Dong Dong" prompt tone

Prompt tone for successful Bluetooth connection Bluetooth connected" in Chinese Bluetooth disconnection prompt tone: "Bluetooth Bluetooth back connection prompt tone: "Bluetooth connected" Chinese Incoming call prompt tone: "beep" prompt tone

5. Specifications

四、语音提示说明

开机提示音: "开机"中文

关机提示音: "关机"中文

手动接听:"手动接听"中文

自动接听: "自动接听"中文

音量最大: "咚咚"提示音

来电提示音:"嘟嘟"提示音

蓝牙模式提示音: "蓝牙模式"中文

蓝牙连接成功提示音: "蓝牙已连接"中文

蓝牙断开提示音音: "蓝牙已断开"中文

蓝牙回连提示音: "蓝牙已连接"中文

Bluetooth name: QINLIFE Y60 Battery capacity: 2000MAH Call duration: continuous call 20H Bluetooth version: V5.3 ransmission distance: 10M Charging time: about 2.5 hours Charging voltage: 5V/1A Headphone connector: Type-C standby duration: 270H Charging interface: Type-C FM radio: (support frequency band range: 87.5MHZ-108.0MHZ)

6.Bluetooth headset installation Y60 is applicable to all kinds of helmets







Installation method of full helmet

Y60 host

7. Packing list

charging cable an instruction manual

Installation package Velcro

MADE IN CHINA

Instruction warning

Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmfulinterference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions may cause harmfulinterference to radio communications. However, there is

quarantee that interference wil not occur in a particular installation, ifthis equipment does cause harmful interference to radio or television reception.

whichcan be determined by turning the equipment offand on, the user is encouraged totry to correct the interference by one or more of the following measures. -Reorient or relocate the receiving antenna


-Increase the separation between the equipment and rereiver.
-Connect the equipment into an outlet on a circuit different from that to -Consult the dealer or an experienced radio/TV technician for help Changes or modifications not expressly approved by the party responsible

for compliancecould void the user's authority to operate the equipment. This device complies with Part 15 of the FcC Rules. Operation is subject to the following two conditions. (2) this device may not cause harmful interference. and
(2) this device must accept any interference received, including interference

头盔蓝牙耳机 使用说明书



CE SRRC Rohs 🗷 🗘 🌚



长按音量加 短按下一曲 长按音量减 灯光模式切换

二、按键操作说明

2.1、开关机 长按3秒开关机 **音乐模式下**:短按播放或暂停音乐; 来电模式下:

1、短按接听电话,再次短按挂段电话; 2、长按拒接挂断来电;

3、双击末码重播。来电时会伴随电话号码播报。 低电提示: "电量低请充电"中文 FM模式下: 短按自动搜台

2.2、音量加

音乐播放模式下: 长按音量"+"为音量增加; 短按

FM模式下: 短按向下切换已保存电台, 长按加大 音量:

双击: 开机模式下, 双击音量加键, 可切换选择手 动接听和10S后自动接听来电,并伴随语音播放提 示"自动接听"和"手动接听"。

2.3、音量减

机。

音乐播放模式下: 长按音量"-"为音量减小; 短按 切换到上一曲;

FM模式下: 短按向上切换已保存电台, 长按减小

2.4、M键RGB模式键

短按切换6种RGB灯效模式,短按最后可以关闭所 有灯光;长按在蓝牙和FM模式间切换。

三、LED指示灯状态显示 蓝牙等待配对状态: 栅格内LED灯快闪;

蓝牙配对成功: 栅格内LED灯恒亮; **蓝牙模式:**播放栅格内LED灯慢闪;

待机状态: 蓝牙模式未连接5分钟无操作自动关机; **充电状态:** 电池充满电状态,红色LED熄灭; 在机器开机情况下:插入充电器充电,机器会自动 关机,此时如需开机,请重新长按开关机键3秒开

四、语音提示说明 **开机提示音**: "开机"中文

关机提示音: "关机"中文 **手动接听**:"手动接听"中文 自动接听: "自动接听"中文 蓝牙模式提示音: "蓝牙模式"中文 **音量最大:** "咚咚"提示音 **蓝牙连接成功提示音**: "蓝牙已连接"中文 **蓝牙断开提示音音**: "蓝牙已断开"中文 蓝牙回连提示音: "蓝牙已连接"中文 来电提示音:"嘟嘟"提示音

五、规格参数

蓝牙名称: QINLIFE Y60 电池容量: 2000MAH **蓝牙版本:** V5.3 **待机时长**: 270H **充电时间:**约2.5小时 传输距离: 10M **耳机接口:** Type-C **充电电压:** 5V/1A **通话时长**: 连续通话20H **充电接口**: Type-C Fm收音: (支持频段范围: 87.5MHZ-108.0MHZ)

六、蓝牙耳机安装









掀开头盔内衬, 魔术贴贴在耳朵, 与嘴巴的位置上, 将喇 叭与麦贴在魔术贴的位置,再将设备安装在头盔的边缘。其 它类型的头盔安装方法一样。配件3M胶,根据头盔类型进行 选择不同的安装方式,达到更佳的使用效果。

Half helmet installation method

Open the helmet liner, place the velcro on the ear and mouth, place the horn and microphone on the velcro, and then install the

device on the edge of the helmet. The installation method of

other types of helmets is the same. Accessories 3M glue can be installed in different ways according to the helmet type to

achieve better use effect.

Y70 host

7. Packing list

→ | **→** | **→** | **→** |

七、包装清单

Y70 主机

喇叭麦克风











八、注意事项

1、请勿将产品投入明火中,避免发生爆炸;

2、请勿拆卸产品。避免产品电子器件损坏; 3、请勿靠近尖锐器,物对产品造成损坏;


4、长时间不用、请放置干燥处。

HELMET Bluetooth Headset an instruction manual



(E SRRC Rohs 🖹 🕸 🐠

1.Description of function keys Physical key design allows riders to operate blindly and press keys accurately



Light mode switching

Long press the volume to decrease

Short press the previous song

2. Key operation instructions 2.1 Switch on/off Press for 3 seconds to turn on/off

In music mode: short press to play or pause music; In incoming call mode: 1. Short press to answer the call, and short press to hang up

2. Long press to reject and end the call; 3. Double click Last Code Replay. Call will be accompanied by the telephone number broadcast.

Low battery prompt: "Charge if the battery is low" in **Under FM mode:** short press to search automatically

In music playing mode: long press "+" to increase the volume; Press briefly to switch to the next song; In FM mode: short press to switch to the saved radio station, long press to increase the volume: **Double click:** In the power on mode, double click the volume increase button to switch between manual answer and automatic answer after 10S, and the voice playback prompts "automatic answer" and "manual answer 2.3 Volume reduction

In music playing mode: Long press "-" to decrease the

In FM mode: short press to switch to the saved radio station,

volume; Short pressSwitch to the previous song;

long press to decrease the tone. Long press to switch

2.4 M key RGB mode keyShort press to switch 6 RGB light effect modes. Long press to switch between Bluetooth and FM modes. 3.LED indicator status display

Bluetooth waiting for pairing status: LED in the grid flashes; Bluetooth pairing succeeded: LED in the grid is always on; Bluetooth mode: LED light in the playback grid flashes slowly; Standby mode: automatically shut down when the Bluetooth node is not connected for 5 minutes without operation: Charging state: the battery is fully charged, and the red LED is

When the machine is turned on: insert the charger to charge, the machine will automatically shut down. If you need to turn on the machine at this time, please press and hold the On/Off key for 3 seconds to turn on the machine

4. Voice prompt description

Power on prompt tone: "Power on" Chinese Shutdown prompt tone: "Shutdown" in Chinese Manual answer: "Manual answer" Chinese Auto answer: "Auto answer" Chinese Bluetooth mode prompt tone: "Bluetooth mode" Chinese Maximum volume: "Dong Dong" prompt tone Prompt tone for successful Bluetooth connection 'Bluetooth connected" in Chinese Bluetooth disconnection prompt tone: "Bluetooth

disconnected" Chinese

Bluetooth back connection prompt tone: "Bluetooth connected" Chinese Incoming call prompt tone: "beep" prompt tone **5. Specifications**

Bluetooth name: QINLIFE Y60 Battery capacity: 2000MAH Bluetooth version: V5.3 Call duration: continuous call 20H Transmission distance: 10M Charging time: about 2.5 hours Headphone connector: Type-C Charging voltage: 5V/1A Standby duration: 270H Charging interface: Type-C FM radio: (support frequency band range: 87.5MHZ-108.0MHZ)

6.Bluetooth headset installation Y60 is applicable to all kinds of helmets.













MADE IN CHINA

Installation package Velcro

Instruction warning

Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmfulinterference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with

may cause harmfulinterference to radio communications. However, there is guarantee that interference wil not occur in a particular installation. ifthis

equipment does cause harmful interference to radio or television reception. whichcan be determined by turning the equipment offand on, the user is encouraged totry to correct the interference by one or more of the following measures. -Reorient or relocate the receiving antenna

-Increase the separation between the equipment and rereiver Connect the equipment into an outlet on a circuit different from that to which thereceiver is connected. -Consult the dealer or an experienced radio/TV technician for help

Changes or modifications not expressly approved by the party responsible for compliancecould void the user's authority to operate the equipment. This device complies with Part 15 of the FcC Rules. Operation is subject to the following two conditions. (1) this device may not cause harmful interference. and (2) this device must accept any interference received, including interference

cause undesired operation