

# RF Exposure Considerations for the Fibar Group S.A. Motion Sensor

### FCC ID: 2AA9MFGBHMS001

The FCC requires that the calculated MPE for mobile equipment to be equal to or less than a given limit dependent on frequency at a distance of 20 cm from a device to the body of a user.

The transmitter in the Fibar Group S.A., Motion Sensor covers the 2402-2480MHz frequency band using Bluetooth Low Energy technology.

The following FCC Rule Parts and procedures are applicable:

Part 1.1310 - Radiofrequency radiation exposure limits

Part 2.1091 - Radiofrequency radiation exposure evaluation: mobile devices

KDB447498 D01 v06 Mobile and Portable Devices RF Exposure Procedures and Equipment Authorisation Policies

## **MPE** calculation

# $S = EIRP/(4 \pi R^2)$

Where

S = Power density

EIRP = P x G

- P = Maximum transmitter power
- G = Antenna gain
- R = distance to the centre of radiation of the antenna

Fibar Group S.A. FIBARO System Manufacturer ul. Lotnicza 1, 60-421 Poznań **KRS** (reg.no): 0000553265 **NIP:** 7811858097 Registered capital: 1 182 100,00 PLN

Podiato koskursu WZÓR 2013





er 🌠





CES Innovation Awards



#### For the 2.4GHz band (Bluetooth Low Energy):

Values $S = 1.0 \text{ mW/cm}^2$  for General population uncontrolled exposure<br/>(FCC Part 1.1310, Table 1(B) Radiofrequency radiation exposure limits) $S = 1.0 \text{mW/cm}^2$  $P_{max} = 6.0 \text{dBm} (3.98 \text{mW})$ G = 3 dBi (x2.00)R = 20 cm

### **Calculation:**

S = PG/4 π R<sup>2</sup> S = 3.98 x 2.00/(12.56 x (20)<sup>2</sup>) S = 7.96/5026

S = 0.0016 mW/cm<sup>2</sup>

### **Conclusion**

This confirms compliance to the required FCC Part 1.1310 Radio frequency radiation exposure limit of 1.0mW/cm<sup>2</sup> at 20cm operation and, hence, meets the requirements of FCC rule part 2.1091(c) and KDB447498 D01 v06, section 7.1.



Strona  $2 \ge 2$