

Specification of CG2CH15RX433

Parameter:

Working Voltage: DC5~12V

Working Current: 6mA

Frequency: 433.92MHZ

Modulation: ASK

High sensitivity: -107dBm

Decode: MCU, Rolling code HCS301

Temperature: -20-70°C

Dimension: 50*19*7MM

Matching Transmitter:

1. Match code:

When the receiver module is powered, hold the learning button and learning LED indicator blinks, then press any button of remote control or power a transmitter module to launch, if indicator lights flashes 3 times, match code successfully.

Maximum 20 remote controls / transmitter modules can be matched.

2. Delete code:

Hold learning button till the indicator LED lights and then off, delete successfully.

3. Working mode:

The working mode is fixed and default is Momentary. If you prefer other modes such as Toggle or Latching, please contact us before placing an order.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Caution: Any changes or modifications to this device not explicitly approved by manufacturer could void your authority to operate this equipment.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Notice: The test board method

- 1) After power-on , Install the receiver into pin holder .
- 2) Press any button of matched remote control , matching red LED indicator shine,blue led also on when receive signal at same time