



i.safe MOBILE



IS910.1



KEYS AND SPECIAL FEATURES



Document No. 1016MM01REV01
Version: 2018-01-18

(c) 2017 i.safe MOBILE GmbH

i.safe MOBILE GmbH
i_Park Tauberfranken 10
97922 Lauda-Koenigshofen,
Germany

Tel. +49 9343/60148-0
info@isafe-mobile.com
www.isafe-mobile.com

Template: TEMPMM01REV10

ENGLISH

› INTRODUCTION

This document contains information and safety regulations which are to be observed without fail for safe operation of the device **IS910.1** under the described conditions. Non-observance of this information and instructions can have serious consequences and/or may violate regulations.

Please read the manual and these safety instructions before using the device.

In case of contradicting information, the text of these safety instructions shall apply.

In case of any doubt, the German version shall apply.

The current EU-declaration of conformity, certificates, safety instructions and manuals can be found at www.isafe-mobile.com or requested from **i.safe MOBILE GmbH**.

› RESERVATION

The content of this document is presented as it currently exists. **i.safe MOBILE GmbH** does not provide any explicit or tacit guarantee for the accuracy or completeness of the content of this document, including, but not restricted to, the tacit guarantee of market suitability or fitness for a specific purpose unless applicable laws or court decisions make liability mandatory. **i.safe MOBILE GmbH** reserves the right to make changes to this document or to withdraw it any time without prior notice. Changes, errors and misprints may not be used as a basis for any claim for damages. All rights reserved.

i.safe MOBILE GmbH cannot be held responsible for any data or other loss and direct or indirect damages caused by any improper use of this device.

› EX-SPECIFICATIONS

The device **IS910.1** is suitable for use in potentially explosive atmospheres classified (zone 1/21 and 2/22) in accordance with directives 2014/34/EU, as well as the IECEx scheme.

EX-MARKINGS

› ATEX:

Ⓢ 2G Ex ib IIC T4 Gb

Ⓢ 2D Ex ib IIIC T135°C Db IP6X

EU Type Examination Certificate:

EPS 16 ATEX 1 145 X

CE-designation: CE 2004

› IECEx:

Ex ib IIC T4 Gb

Ex ib IIIC T135°C Db IP6X

IECEx Certificate: IECEx EPS 16.0061X

› Temperature range:

-20°C ... +60°C

› Manufactured by:

i.safe MOBILE GmbH

i_Park Tauberfranken 10

97922 Lauda-Koenigshofen,

Germany

› EU-DECLARATION OF CONFORMITY

The EU-declaration of conformity can be found at the end of this manual.

» FAULTS AND DAMAGES

If there is any reason to suspect that the safety of the device has been compromised, it must be withdrawn from use and removed from any ex-hazardous areas immediately.

Measures must be taken to prevent any accidental restarting of the device.

The safety of the device may be compromised, if for example:

- » Malfunctions occur.
- » The housing of the device shows damage.
- » The device has been subjected to excessive loads.
- » The device has been stored improperly.
- » Markings or labels on the device are illegible.

We recommend that a device displaying errors or in which an error is suspected be sent back to **i.safe MOBILE GmbH** to be checked.

» EX-RELEVANT SAFETY REGULATIONS

Use of this device assumes that the operator observes the conventional safety regulations and has read and understood manual, safety instructions and certificate.

The following safety regulations must also be complied with:

- » Inside ex-hazardous areas the covers of all interfaces must be closed.
- » To ensure the IP-protection, it has to be ensured that the all gaskets are present and functional. IP protection is not guaranteed anymore if gaps are visible.
- » The device may only be charged outside ex-hazardous areas using the **i.safe PROTECTOR 2.0** or **i.safe PROTECTOR 3.0** USB-cable or other equipment approved by **i.safe MOBILE GmbH**.
- » Physical connections to other equipment are only allowed outside ex-hazardous areas using the **i.safe PROTECTOR 2.0** or **i.safe PROTECTOR 3.0** USB-cable or other equipment approved by **i.safe MOBILE GmbH**.
- » The device may be charged only at ambient temperatures in between +5°C ... +35°C.
- » The device must not be exposed to abrasive acids or bases.
- » The device must not be taken into zones 0 or 20.
- » Only accessories approved by **i.safe MOBILE GmbH** may be used.
- » In case the device has a hand strap, it is not allowed to do the adjustment of the hand strap in ex-hazardous areas.

» FURTHER SAFETY ADVISES

- » Do not touch the screen of the device with sharp objects. Dust particles and nails may scratch the screen. Please maintain the screen clean. Remove dust on the screen with a soft cloth gently, and do not scratch the screen.
- » Do not put the device in environments with excessive temperatures, as this could lead to heating of the battery, resulting in fire or explosion.
- » Do not charge the device near any flammable or explosive substances.
- » Charge the device under dry indoor conditions only.
- » Do not charge the device in environments with much dust or humidity.



- » The device may be charged only at ambient temperatures in between +5°C ... +35°C.
- » Do not use the device in areas where regulations or legislatives prohibit the use.
- » Do not expose the device or charger to strong magnetic fields, such as are emitted from induction ovens or micro-waves.
- » Do not attempt to open or repair the device. Improper repair or opening can lead to the destruction of the device, fire or explosion. Only authorized personnel are allowed to repair the device.
- » Only use accessories approved by **i.safe MOBILE GmbH**.
- » Power off the device in hospitals or other places where the use of mobile phones is prohibited. This device may affect proper work of medical equipment, such as pacemakers, so always keep a distance of at least 15 cm between the device and these devices.
- » Observe all corresponding laws that are in force in the respective countries regarding the use of devices while operating a vehicle.
- » Please power off the device and disconnect the charging cable before cleaning the device.
- » Do not use any chemical cleaning agents to clean the device or the charger. Use a damp and anti-static soft cloth for cleaning.
- » Do not discard old and abandoned lithium batteries into the trash, send them to designated waste disposal locations.
- » The user alone is responsible for any and all damages and liabilities caused by malware downloaded when using the network or other data-exchange functions of the device. **i.safe MOBILE GmbH** cannot be held responsible for any of those claims.

WARNING

i.safe MOBILE GmbH will not assume any liability for damages caused by disregarding any of these advices or by any inappropriate use of the device.

» MAINTENANCE/REPAIR

Please note any legal requirements for periodic inspection.

The device itself has no user-serviceable parts. It is recommended to perform inspections according to the safety regulations and advises. If there is a problem with the device, please contact your vendor or consult the service center. If your device is in need of repair, you can either contact the service center or your vendor.

» BATTERY

The device may only be charged at ambient temperatures in a range from +5°C ... +35°C.

» INSTALLATION OF THE MICRO SIM CARD

The device features a micro SIM card slot. The slot is accessible on the top of the device (see page 2).

**WARNING**

Do only change the SIM card when the device is switched off. Do not try to insert or remove the SIM cards when any external power supply is connected, otherwise the SIM card may be damaged.

› INSTALLATION OF THE microSD CARD

The device features a microSD card slot (up to 32GB). The slot for the microSD card is on the top of the device (see page 2). If you want to remove the microSD card, please make sure that the card is not in use by the device. To remove the microSD card follow the instructions given in <Settings> → <Storage>.



**WARNING**

Do only change the microSD card when the device is switched off. Do not try to insert or remove the microSD card when any external power supply is connected, otherwise the microSD card may be damaged.

› KEYS AND SPECIAL FEATURES

(see illustration on page 2)

- 1) SOS KEY:** Long press automatically selects an emergency number stored by you. This function can only be used in conjunction with an optionally available LWP app.
- 2) SD CARD SLOT:** Use for microSD card.
- 3) SIM CARD SLOT:** Use for SIM card.
- 4) CAMERA:** Front camera.
- 5) VOLUME UP KEY:** Volume up.

- 
- 
- 6) VOLUME DOWN KEY:** Volume down.
- 7) CONTROL LED:** Control LEDs for SD card, SIM and flash.
- 8) POWER KEY:** Long press to power ON/OFF the device. Short press to power ON/OFF the standby mode.
- 9) FUNCTION KEY M1:** Optional key used by different apps.
- 10) FUNCTION KEY M2:** Optional key used by different apps.
- 11) BACK KEY:** Return to previous screen.
- 12) HOME KEY:** Return to Homescreen.
- 13) CURRENT APPLICATION:** Close all applications.
- 14) USB OTG:** Connect external USB devices.
- 15) EARPHONE JACK:** Connect an earphone.
- 16) MAGNETIC CHARGER PORT:** To charge the device with the delivered magnetic **i.safe PROTECTOR 3.0** USB cable.
- 17) DOCKING STATION:** Connect to external docking station.
- 18) MICRO USB TYP C:** To charge and to connect the device with the delivered **i.safe PROTECTOR 2.0** USB cable.



› SETTING PASSWORD



In settings a password is required, use standard password "1234".

› IMPORTANT INFORMATION!

FACTORY RESET/ACTIVATE OEM MODE

If you have set up a Google™ Account, it is important to proceed with the following steps before you make a factory reset. This ensures that all private data will be deleted on the device:

<Settings> → <About tablet> → tip seven times on <Build number> (to activate the developer mode) → back to <Settings> → <Developer options> → enable <OEM unlocking> → activate → <Allow> → back to <Settings> → <Backup & reset> → <Factory data reset> → <Reset tablet> → <Erase everything>

If you do not enable the OEM unlocking, the device will ask you to sign in with the previously synced Google Account after the restart. In that case the device is unusable for other user.

› RECYCLING

The crossed-out wheeled-bin symbol on your product, battery, literature, or packaging reminds you that all electrical and electronic products, batteries, and accumulators must be taken to separate collection at the end of their working life. This requirement applies in the European Union. Do not dispose of these products as unsorted municipal waste. Always return your used electronic products, batteries, and packaging materials



to dedicated collection points. This way you help prevent uncontrolled waste disposal and promote the recycling of materials. More detailed information is available from the product retailer, local waste authorities, national producer responsibility organisations, or your local **i.safe MOBILE GmbH** representative.

› SPECIFIC ABSORPTION RATE (SAR) CERTIFICATION INFORMATION

Maximum SAR for this model and conditions under which it was recorded:

SAR (body - worn) 1.12W/kg

› FCC CAUTION

Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Note:

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- › Reorient or relocate the receiving antenna.
- › Increase the separation between the equipment and receiver.
- › Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- › Consult the dealer or an experienced radio/TV technician for help.

› SPECIFIC ABSORPTION RATE (SAR) INFORMATION

SAR tests are conducted using standard operating positions accepted by the FCC with the tablet transmitting at its highest certified power level in all tested frequency bands, although the SAR is determined at the highest certified power level, the actual SAR level of the tablet while operating can be well below the maximum value. Before a new model tablet is available for sale to the public, it must be tested and certified to the FCC that it does not exceed the exposure limit established by the FCC, tests for each tablet are performed in positions and locations as required by the FCC.

For body worn operation, this model tablet has been tested and meets the FCC RF exposure guidelines



» ISEDC WARNING

This device complies with ISEDC RSS standard(s). Operation is subject to the following two conditions:

- (1) this device may not cause interference, and
- (2) this device must accept any interference, including interference that may cause undesired operation of the device.

Le présent appareil est conforme aux CNR d'ISEDC applicables aux appareils radio de licence. L'exploitation est autorisée aux deux conditions suivantes :

- (1) l'appareil ne doit pas produire de brouillage, et
- (2) l'utilisateur de l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement

This Class B digital apparatus complies with Canadian ICES-003.

Cet appareil numérique de la classe B est conforme à la norme NMB-003 du Canada.

SAR tests are conducted using standard operating positions accepted by the ISEDC with the tablet transmitting at its highest certified power level in all tested frequency bands, although the SAR is determined at the highest certified power level, the actual SAR level of the tablet while operating can be well below the maximum value. Before a new model tablet is available for sale to the public, it must be tested and certified to the ISEDC that it does not exceed the exposure limit established by the ISEDC, tests for each tablet are performed in positions and locations as required by the ISEDC.

For body worn operation, this model tablet has been tested and meets the ISEDC RF exposure guidelines

Le présent appareil est conforme

Après examen de ce matériel aux limites DAS et/ou aux limites d'intensité de champ RF, les utilisateurs peuvent sur l'exposition aux radiofréquences et la conformité and compliance d'acquérir les informations correspondantes

» TRADEMARKS

- » **i.safe MOBILE** and the **i.safe MOBILE** logo are registered trademarks of the **i.safe MOBILE GmbH**.
- » Google is a trademark of Google LLC.
- » All other trademarks and copyrights are the properties of their respective owners.

