



12. Radio Frequency Exposure

12.1 Applicable Standards

| <input type="checkbox"/> §1.1307(b)(3)(i)(A) | The available maximum time-averaged power is no more than 1 mW, regardless of separation distance. | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
|--|---|---------------------|--------------------|---|--------------------|--------------------------------------|--|---------------|-----------|--|-----------|--------------------|--|--------------------|---|-----|---|------|-------|---|--------|----------------------|------|---|----|--------|---|-------|--------------------------------------|----|---|-----|-------|---|--------|---------------------|-----|---|-------|--------|---|---------|-------------------------|-------|---|---------|---------|---|--------|--------------------|
| <input type="checkbox"/> §1.1307(b)(3)(i)(c) | ERP is below a threshold calculated based on the distance , R between the person and t antenna / radiating structure, where $R > \lambda / 2 \pi$. <p style="text-align: center;">TABLE B.1—THRESHOLDS FOR SINGLE RF SOURCES SUBJECT TO ROUTINE ENVIRONMENTAL EVALUATION</p> <table border="1" style="margin-left: auto; margin-right: auto;"> <thead> <tr> <th colspan="3">RF Source Frequency</th> <th colspan="3">Minimum Distance</th> <th>Threshold ERP</th> </tr> <tr> <th>f_L MHz</th> <th></th> <th>f_H MHz</th> <th>$\lambda_L / 2\pi$</th> <th></th> <th>$\lambda_H / 2\pi$</th> <th>W</th> </tr> </thead> <tbody> <tr> <td>0.3</td> <td>–</td> <td>1.34</td> <td>159 m</td> <td>–</td> <td>35.6 m</td> <td>1,920 R²</td> </tr> <tr> <td>1.34</td> <td>–</td> <td>30</td> <td>35.6 m</td> <td>–</td> <td>1.6 m</td> <td>3,450 R²/f²</td> </tr> <tr> <td>30</td> <td>–</td> <td>300</td> <td>1.6 m</td> <td>–</td> <td>159 mm</td> <td>3.83 R²</td> </tr> <tr> <td>300</td> <td>–</td> <td>1,500</td> <td>159 mm</td> <td>–</td> <td>31.8 mm</td> <td>0.0128 R²f</td> </tr> <tr> <td>1,500</td> <td>–</td> <td>100,000</td> <td>31.8 mm</td> <td>–</td> <td>0.5 mm</td> <td>19.2R²</td> </tr> </tbody> </table> <p>Subscripts L and H are low and high; λ is wavelength. From § 1.1307(b)(3)(i)(C), modified by adding Minimum Distance columns.</p> | RF Source Frequency | | | Minimum Distance | | | Threshold ERP | f_L MHz | | f_H MHz | $\lambda_L / 2\pi$ | | $\lambda_H / 2\pi$ | W | 0.3 | – | 1.34 | 159 m | – | 35.6 m | 1,920 R ² | 1.34 | – | 30 | 35.6 m | – | 1.6 m | 3,450 R ² /f ² | 30 | – | 300 | 1.6 m | – | 159 mm | 3.83 R ² | 300 | – | 1,500 | 159 mm | – | 31.8 mm | 0.0128 R ² f | 1,500 | – | 100,000 | 31.8 mm | – | 0.5 mm | 19.2R ² |
| RF Source Frequency | | | Minimum Distance | | | Threshold ERP | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| f_L MHz | | f_H MHz | $\lambda_L / 2\pi$ | | $\lambda_H / 2\pi$ | W | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 0.3 | – | 1.34 | 159 m | – | 35.6 m | 1,920 R ² | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 1.34 | – | 30 | 35.6 m | – | 1.6 m | 3,450 R ² /f ² | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 30 | – | 300 | 1.6 m | – | 159 mm | 3.83 R ² | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 300 | – | 1,500 | 159 mm | – | 31.8 mm | 0.0128 R ² f | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| 1,500 | – | 100,000 | 31.8 mm | – | 0.5 mm | 19.2R ² | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| <input checked="" type="checkbox"/> § 1.1307(b)(3)(i)(B). | Device operates between 300 MHz and 6 GHz and the maximum time-averaged power or effective radiated power (ERP), whichever is greater, $\leq P_{th}$ $P_{th} \text{ (mW)} = \begin{cases} ERP_{20 \text{ cm}}(d/20 \text{ cm})^x & d \leq 20 \text{ cm} \\ ERP_{20 \text{ cm}} & 20 \text{ cm} < d \leq 40 \text{ cm} \end{cases}$ <p>Where</p> $x = -\log_{10} \left(\frac{60}{ERP_{20 \text{ cm}} \sqrt{f}} \right) \text{ and } f \text{ is in GHz;}$ <p>and</p> $ERP_{20 \text{ cm}} \text{ (mW)} = \begin{cases} 2040f & 0.3 \text{ GHz} \leq f < 1.5 \text{ GHz} \\ 3060 & 1.5 \text{ GHz} \leq f \leq 6 \text{ GHz} \end{cases}$ <p>$d = \text{the separation distance (cm);}$</p> | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |



12.2 EUT Specification

| | |
|---|--|
| Frequency band (Operating) | 902MHz~928MHz |
| Device category | <input type="checkbox"/> Portable (<20cm separation) <input checked="" type="checkbox"/> Mobile (>20cm separation) |
| Antenna diversity | <input checked="" type="checkbox"/> Single antenna <input type="checkbox"/> Multiple antennas <input type="checkbox"/> Tx diversity <input type="checkbox"/> Rx diversity <input type="checkbox"/> Tx/Rx diversity |
| Evaluation applied | <input type="checkbox"/> Blanket 1 mW Blanket Exemption <input checked="" type="checkbox"/> MPE-based Exemption <input type="checkbox"/> SAR-based Exemption |
| Remark: | |
| 1. <i>The maximum conducted output power is <u>26.14 dBm (411.150 mW)</u> at <u>923.3MHz</u> (with <u>1.45dB antenna gain.</u>) Lora 500K</i> | |

12.3 Results

Lora 500K

| Channel Frequency (MHz) | Max. Conducted output power(dBm) | Max. Tune up power (dBm) | Antenna Gain(dBi) | Max.Tune up e.r.p. Power (dBm) | Max. Tune up e.r.p power (mW) | Limit (mW) |
|-------------------------|----------------------------------|--------------------------|-------------------|--------------------------------|-------------------------------|------------|
| 923.3 | 26.14 | 26.64 | 1.45 | 25.94 | 392.64 | 1853.3 |

No non-compliance noted.

-----THE END OF REPORT-----