

刀模线不印刷

单号:



型号: 8B050BT



印刷材质及要求: 80G书纸, 双面黑白印刷, 折页

尺寸: 折后尺寸90*90MM

美工: 谢海建

文件完成时间:

<p>Bluetooth headphone with LED flashing light JP-738</p>  <p>User Manual</p> <p>1</p> <p>Product Description. This LED Bluetooth headphone is a wireless headphone, which integrate MIC, Bluetooth, TF card, AUX function together. This headphone 's power is class II, supporting headset, hands free function. And headphone itself has built-in battery. The headphone with frequency spectrum lights and the default led lights, also has the traditional ordinary headset functions.</p>	<p>1. Product information A. Can brings you to enjoy wireless stereo music. B. Hands-free shift between music and calls/receive or dial a Bluetooth phone;and music playing again automatically in a few seconds after ends the calls . C. Besides wireless stereo Bluetooth and hands free function. You can use this headphone on the PC which supports Bluetooth, talk on line with others by on-line communication,such as Skype and MSN messenger. D. The headphone support TF card , which capacity up to 32G at most. Download music to TF card, and insert the card to headphone , then you can enjoy MP3 music ,which will be played automatically. E. With ordinary headphone function: link the 3.5mm jack with PC or other media audio system, then it becomes a ordinary headphone. F. Spectrum flash function: after power on ,some led light go on , when play music , the spectrum flash light will go with music .</p> <p>2. Specifications BT version: compatibility 4.1 and support V2.1+EDR BT range:10m BT call/play duration: when led on ,play time up to 3 hours, when led off ,play time up to 5 hours . Battery: chargeable Li, 300mAh Charger: DC 5V</p>  <p>2</p>	<p>3. Fundamental Operations A. Turn on: push power switch to "ON", then head phone search Bluetooth ; B. Turn off: push power switch to "OFF" to turn off the headphone Bluetooth ; C. Play/pause: short press play/pause/" button to control music to pause and play . D. Playing previous song : turn the "Volume/last song/led switch" while playing . E. Playing next song: turn the " Volume/next song while playing . F. Volume+: press and hold " Volume/next song for jumps to maximal if keep pressing . G. Volume-: press and hold volume-/last song /switch jumps to minimal if kept pressed</p> <p>TF Card Function: Insert TF card of long -time press "mode/phone" shift to TF card function, then headphones start to play TF card music, the LED will flash slowly, after a while, the light will change colors as the music .</p> <p>FM Function: FM function: after headphone turn on , short press the "mode/phone" button shift to FM radio mode , short-time press this button to radio search state ,the blue light will flash quickly next radio, last radio, Volume- and Volume+ same operation with MP3 Play .</p> <p>Bluetooth Function: 1. Bluetooth function : switch to the "ON" and enter Bluetooth function .if current state is TF card or FM, through short time press "Mode" button to Bluetooth function Bluetooth function. 2. Bluetooth pairing : when under the Bluetooth mode, headset will automatically search other BT devices for pairing, the blue light will flash quickly . 3. The pairing name is "12-850ML" . When Bluetooth connecting successfully ,green light will flash slowly . Now we can play music or make phone calls . 4. Answer a phone: when a call in , short -time press "Pause/phone" button to</p>	<p>answer the phone . 5. Hang up or reject calls : when in a calls or a call in ,short-time press : mode/phone "button to hang up or reject calls . 6. Call back :when in Bluetooth mode, continue double press " mode/phone" button to call back the last dial number . 7. Volume + and Volume - : long press the button for two seconds, the volume will up to max step by step when at the max/minimum volume, can hear "DO---" 8. Long/next song : when playing music , press Volume-/volume + 9. Play /pause : when playing music , short press the button .</p> <p>Package contents 1. LED Bluetooth earphone 2. User Manual 3. Micro USB charging cable 4. Audio cable</p> <p>Charging When normally charging , the indicator light will be red ,after finish charging ,the indicator light will go off .Charging time may take 2.5 hours . when it fully charged , the red light will off .</p> <p>4</p>
---	--	--	--

<p>AURICULARES BLUETOOTH CON LED LUZ INTERMITENTE JP-738</p>  <p>Manual de usuario</p> <p>1</p> <p>Descripción del producto. Auriculares Bluetooth de este LED es un auricular inalámbrico, que integran la MIC, Bluetooth, TF Tarjeta, la función AUX juntos. Estos auriculares 's potencia es de clase II, apoyando los auriculares, función manos libres. Si tiene auriculares y construir en la batería. Los auriculares con luces de espectro de frecuencias y las luces led predeterminado, también tiene las tradicionales funciones de auriculares normales.</p>	<p>1. Información sobre el producto A. Puede traer a disfrutar de música estéreo de forma inalámbrica. B. Cambio de manos libres entre música y llamadas/recebir o marcar un teléfono Bluetooth y la música tocando de nuevo automáticamente en unos segundos después de que termina las llamadas . C. Además de estereo inalámbricos Bluetooth y la función manos libres. Puede utilizar estos auriculares en el PC que admite Bluetooth, converse en línea con otras personas mediante la comunicación en línea, tales como Skype y MSN Messenger . D. El auricular de la tarjeta del TF de la ayuda con una capacidad de hasta 32G a la mayoría. Descargar música a la tarjeta de TF, e inserte la tarjeta para auriculares, entonces usted puede disfrutar de la música MP3, que se reproducirá de forma automática. E. Con función de auriculares normales; vincular el jack de 3.5 mm con PC u otro sistema de audio multimedia, entonces se convierte en un auricular normal. F. Función flash de espectro: después del encendido, unos led luminan, al reproducir música, el espectro de luz de flash irá con música .</p> <p>2. Las Especificaciones Version BT : la compatibilidad de la versión 4.1 y soporte V2.1+EDR. BT Rango:10m. Llamada B T/reproducción de duración: (cuando el led de, el tiempo de reproducción de hasta 3 horas, cuando se apaga el LED, el tiempo de reproducción de hasta 5 horas. Batería: imputables Li, 300mAh Cargador: DC 5V.</p>  <p>2</p>	<p>3. Operaciones fundamentales A. encender : pulsar interruptor de encendido a la posición "ON", el entonces jefe de búsqueda teléfono Bluetooth ; B. Desactivar: empujar el interruptor de encendido a la posición "OFF" para desactivar los auriculares Bluetooth ; C. Reproducir/Pausa: pulse brevemente "reproducir/pausa/" para controlar la música en pausa y reproducción . D. Reproduce la canción anterior: girar el "Volumen-/última canción/led switch" mientras juega . E. tocando la canción siguiente: gire el " Volumen / siguiente canción mientras juegas . F. Volumen ++ : Mantenga pulsado el botón " Volumen / siguiente canción para saltos al máximo si presiona . G. Volumen - : mantenga pulsado el botón de volumen/última canción /conmutador salta a la mínima si mantiene pulsado.</p> <p>TF tarjeta de función: Inserte la tarjeta del TF de largo -tiempo pulse el "modo/telefono" cambie a la función de la tarjeta del TF de auriculares y, a continuación, empiece a jugar TF tarjeta de música, el LED parpadeará lentamente, después de un rato, la luz cambiará de color como la música .</p> <p>Función FM: FM función: después de encender los auriculares, pulse brevemente el "modo/phone" el botón Cambiar a modo radio FM, corto tiempo pulse este botón para radio búsqueda estado .La luz azul parpadeará rápidamente, radio siguiente Último radio. Volumen y volumen misma operación con MP3 jugar .</p> <p>Función de Bluetooth: 1. Función Bluetooth : poner al "ON" y escriba la función Bluetooth. Si el estado actual</p>	<p>es la tarjeta T Fo FM, por corto tiempo pulse el botón "Mode" para la función Bluetooth función Bluetooth. 2. El emparejamiento Bluetooth : cuando en el modo de Bluetooth, auriculares buscará automáticamente otros dispositivos Bluetooth para emparejar .Ja luz azul parpadeará rápidamente . 3. El nombre de emparejamiento es "12-850ML" cuando la conexión Bluetooth correctamente .Juz verde parpadeará lentamente . Ahora podemos reproducir música o hacer llamadas telefónicas . 4. Un telefono de respuesta: cuando una llamada en corto tiempo , -pulsar Pausa/telefono" botón para contestar el teléfono . 5. Colgar o rechazar llamadas: cuando en una llama o una llamada en ,a corto plazo : pulse mode/telefono "botón para colgar o rechazar llamadas . 6. Devolver llamada: cuando está en el modo de Bluetooth, continúe prensa doble " mode/telefono" botón para volver a llamar al último número marcado . 7. Volumen + y Volumen - largo: pulse el botón durante dos segundos ,el volumen hasta un máximo de paso por paso cuando en el volumen mínimo/máximo, puede escuchar "DO---" 8. Largo/Canción siguiente: cuando reproduce música, pulse VOLUME-/volume + 9. Play/Pause: Cuando se reproduce música, pulse brevemente el botón .</p> <p>Contenido del Paquete 1. Auricular Bluetooth LED 2. Manual del usuario 3. Cable de carga micro USB 4. Cable de audio</p> <p>La carga Cuando normalmente se carga, la luz indicadora de color rojo, después de finalizar la carga, la luz indicadora se apagará. El tiempo de carga puede tomar 2.5 horas. Cuando completamente cargada, la luz roja será desactivada.</p> <p>4</p>
---	--	---	---

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Caution: Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation.

This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

--Reorient or relocate the receiving antenna.

--Increase the separation between the equipment and receiver.

--Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

--Consult the dealer or an experienced radio/TV technician for help.