

RF Exposure Evaluation

FCC ID: 2AAZR-HSD8032A

1. Client Information

Applicant : Shenzhen Highstar Electrical Co., Ltd
Address : 2F&4F, Building 6, Highstar Industrial zone, Gangtou, Bantian Street, Longgang District, Shenzhen, China
Manufacturer : Shenzhen Highstar Electrical Co., Ltd
Address : 2F&4F, Building 6, Highstar Industrial zone, Gangtou, Bantian Street, Longgang District, Shenzhen, China

2. General Description of EUT

EUT Name	:	ICAN OUTDOOR BLUETOOTH SPEAKER WITH LED LIGHT	
Models No.	:	HSD80312A, HSD8032B, HSD8032C	
Model Difference	:	All these models are identical in the same PCB, layout and electrical circuit, the only difference is model name for commercial.	
Product Description	:	Operation Frequency:	Bluetooth V2.1+EDR: 2402~2480 MHz
	:	RF Output Power:	Bluetooth: -0.827dBm(π /4-DQPSK)
	:	Antenna Gain:	0dBi PCB Antenna
Power Supply	:	DC Voltage supplied by USB cable DC Voltage supplied by Li-ion battery	
Power Rating	:	DC 5.0V from the USB cable DC 3.7V by 2200mAh Li-ion battery	
Connecting I/O Port(S)	:	Please refer to the User's Manual	

Note: More test information about the EUT please refer the RF Test Report.

SAR Test Exclusion Calculations

1. FCC: According to KDB 447498 D01 Mobile and Portable Devices RF Exposure Procedures and Equipment Authorization Policies v06.

- (1) Clause 4.3: General SAR test reduction and exclusion guidance

- Sub clause 4.31: Standalone SAR test exclusion considerations

- 1) The 1-g and 10-g SAR test exclusion thresholds for 100 MHz to 6GHz at test separation distance ≤ 5 mm are determined by:

- [(max. power of channel, including tune-up tolerance, mW)/(min. test separation, mm)] * $\sqrt{f_{\text{GHz}}}$] ≤ 3.0 for 1-g SAR

- [(max. power of channel, including tune-up tolerance, mW)/(min. test separation, mm)] * $\sqrt{f_{\text{GHz}}}$] $\leq 7.5.0$ for 10-g SAR

2. Calculation:

Test separation: 5mm						
Bluetooth Mode (GFSK)						
Frequency (GHz)	Conducted Power (dBm)	Turn-up Power Tolerance (dB)	Max power of tune up tolerance (dbm)	Max power of tune up tolerance (mw)	Calculation Value	Threshold Value
2.402	-2.191	-2±1	-1	0.794	0.246	3.0
2.441	-1.998	-2±1	-1	0.794	0.248	3.0
2.480	-2.090	-2±1	-1	0.794	0.250	3.0
Bluetooth Mode (π/4-DQPSK)						
Frequency (GHz)	Conducted Power (dBm)	Turn-up Power Tolerance (dB)	Max power of tune up tolerance (dbm)	Max power of tune up tolerance (mw)	Calculation Value	Threshold Value
2.402	-1.037	-1±1	0	1.000	0.310	3.0
2.441	-0.827	-1±1	0	1.000	0.312	3.0
2.480	-0.921	-1±1	0	1.000	0.315	3.0

So standalone SAR measurements are not required.

-----END OF REPORT-----