

RF exposure Estimation

Introduction

7A-SS-ZABC-H0 (FCC ID: 2AB2Q7ASSZABCH) is a Sensors (4-in-1 Multi-Sensor), which contain Zigbee function inside.

1. Limit and Guidelines on Exposure to Electromagnetic Fields

According to §15.247(e)(i) and §1.1307(b)(1), systems operating under the provisions of this section shall be operated in a manner that ensure that the public is not exposed to radio frequency energy level in excess of the Commission's guideline.

According to KDB 447498 Mobile Portable RF Exposure, no SAR required if power is lower than the flowing threshold:

The 1-g and 10-g SAR test exclusion thresholds for 100 MHz to 6 GHz at test separation distances ≤ 50 mm are determined by:

$[(\text{max. power of channel, including tune-up tolerance, mW}) / (\text{min. test separation distance, mm})] \cdot \sqrt{f(\text{GHz})} \leq 3.0$ for 1-g SAR and ≤ 7.5 for 10-g extremity SAR, where

- $f(\text{GHz})$ is the RF channel transmit frequency in GHz
- Power and distance are rounded to the nearest mW and mm before calculation²⁵
- The result is rounded to one decimal place for comparison
- 3.0 and 7.5 are referred to as the numeric thresholds in the step 2 below

The test exclusions are applicable only when the minimum test separation distance is ≤ 50 mm and for transmission frequencies between 100 MHz and 6 GHz. When the minimum test separation distance is < 5 mm, a distance of 5 mm according to 5) in section 4.1 is applied to determine SAR test exclusion.

2. Calculation method

$[(\text{max. power of channel, including tune-up tolerance, mW}) / (\text{min. test separation distance, mm})] \cdot \sqrt{f(\text{GHz})} \leq 3.0$

Conducted Power + tune up tolerance = 2.48mW

Distance = 5 mm

$f = 2.480$ GHz

$[2.48/5] \cdot \text{SQRT}(2.480) = 0.78$


$0.78 \leq 3.0$

Therefore, excluded from SAR testing.

Result: Compliant

TUV SUD China, Shenzhen Branch

Reviewed by:



Laurent Yuan/ EMC Project Manager

Date: 2019-01-29

Prepared By:



Henry Chen/EMC Project Engineer

Date: 2019-01-29