

Bluetooth 4.2 Stereo headset

SH236

Operation Instructions

Turning On /Off

Press & hold the MFB for 4 seconds to turn SH236 on,the blue indicator will flash fast 5 times.

Press & hold the MFB for 3 seconds to turn SH236 on,the blue indicator will flash fast 5 times.

Pairing

1. When the headset is off , pres and hold down the MFB Button for 7 seconds to enter pairing mode automatically. The LED indicator will flash in red and blue alternatively.
2. Activate the bluetooth feature on the mobile phone and set the media device to 'search for" or "add" new bluetooth devices.
3. Select " SH236" from the list of found devices to pair. If applicable. enter '0000' as passkey.
4. LED indicator will turn to solid blue when connection is completed.
5. If pairing fails, remove the excessive unused Bluetooth devices from a list of paired devices and re-start the pairing process from step 1.

Headset recognizes the previous paired device and will re-connect when it' s powered on.To reset, after turn it on,press and hold both Volume up and Volume down buttons simultaneously for 5 seconds to enter into the pairing mode.

Managing Phone Calls

Answer/End call: Briefly press MFB.

Reject incoming call: Press and hold MFB for 2 seconds.

Redial the last number: Double dick the MFB.

Mute/Unmute: Press and hold the Volume down button for 2 seconds.

Transfer calls between headset and phone:
Press and hold the Volume up button for 3 seconds in the calling.

To Adjust Volume

Short press Volume up button to increase volume, you will hear an indication tone when increase to maximum volume.

Short press Volume down button to decrease the volume, and also hear an indication tone when decrease to minimum volume.

Siri or Voice Command

In the standby mode, press & hold the Multi Function button for 2 seconds to activate the voice command function on Android or iOS devices. Refer to the phone manual for detailed instruction if applicable.

Music Control

Play/Pause music: Briefly press MFB.

Play next/previous song: Long Press Volume up button /Long Press Volume down in the music.

Multi-Point Connectivity

1. Disconnect headset from the first paired mobile phone by disable the Bluetooth function on the mobile phone. And turn off the headset.
2. Turn on headset again and search on your second Bluetooth enabled device and pair.
3. Enable the Bluetooth feature on the first paired Mobile phone. Headset will be connected with both mobile phones now.
4. After first pairing with two mobile phones, headset will re-connect one mobile phone only when it's powered on, but you need to re-connect the second mobile phone manually.

While you are having a phone call with first mobile, and same time there is a incoming call from second mobile. Double press multi function button to answer the second phone call and hold the first one or long press multi function 2s to reject.

Double press multi function button to transfer between two mobiles phone call.

After you have successfully connected with an Apple devices like iPhone or iPad, you will see a small battery icon indicating the battery level of your headset so you are always ready to party. (only applicable for selected Apple devices)

Battery charging and low-voltage alert

When connected normally to charge, the red LED is on when charging and LED turn off when charging is complete. This takes 2-3 hours.

When the battery is running low, the red LED will flash twice every fifteen seconds. Charge as soon as possible or it will automatically shut down.

Remarks

- 1) If headset stand by with pairing mode for 5 min and without connection, It will be exit pairing mode automatically, also, the device will power off after another 5 min.
- 2) Automatic re-connection can happen in the two cases:
 - a. When headset is turned on, it will connect to the pre-set device automatically.
 - b. When headset disconnects from the device due to an exceeded effective range (normally < 10 meters), it will re-connect to your device if it is back in the effective range within 5 minutes.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment. This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) this device may not cause harmful interference, and

(2) this device must accept any interference received, including interference that may cause undesired operation.