
 <p style="text-align: center;"><b>MEE audio EB1 Bluetooth Earphone User Manual</b></p>	<p style="text-align: center;"><b>APPEARANCE AND PARAMETER</b></p>  <p><b>Button illustration:</b></p> <ol style="list-style-type: none"> <li>1. Volume+</li> <li>2. Multi-function button</li> <li>3. LED indicator</li> <li>4. Volume-</li> <li>5. Micro-USB</li> <li>6. MIC</li> </ol> <p style="text-align: center;">①</p>	<p style="text-align: center;"><b>CHARGING YOUR EARPHONE</b></p> <p>Your Bluetooth earphone comes with a built-in rechargeable battery and a Micro-USB charging cable</p> <p><b>Charge fully before use</b></p> <p>Using the charging cable through the corresponding port to charge the battery, the LED indicator will show red while charging, and show red once fully charged. Charging time is approximately 2hrs, providing up to 6hrs* playing.</p> <p style="text-align: center;"><b>GETTING STARTED</b></p> <p>To use your Bluetooth earphone, please follow the steps below:</p> <ol style="list-style-type: none"> <li>1. Ensure your Bluetooth earphone is fully charged.</li> <li>2. Pair your Bluetooth earphone to a Bluetooth-enabled device prior to use.(See Pairing instructions)</li> </ol> <p><b>Powering On the Earphone</b></p> <p>Press and hold the Multi-Function Button for 3 seconds until blue lights on</p> <p style="text-align: center;">②</p>	<p><b>Powering Off the Earphone</b></p> <p>Once powered on, press and hold the Multi-Function Button for 3 seconds until red lights on and out.</p> <p style="text-align: center;"><b>PAIRING YOUR EARPHONE</b></p> <ol style="list-style-type: none"> <li>1. Power on your Bluetooth earphone</li> <li>2. Press and hold the Multi-Function Button for approximately 9-10 seconds until the indicator flashes blue and red alternatively, your earphone is now in pairing mode.</li> <li>3. Activate the Bluetooth function of your devices and start to search.</li> <li>4. Select "EQ-S15E" from the listed devices and connect.</li> <li>5. The indicator will flash blue twice every 7 seconds once successfully paired/connected.</li> </ol> <p><b>Note:</b></p> <ol style="list-style-type: none"> <li>1. The earphone should be within 3ft range from your Bluetooth devices while pairing/playing.</li> <li>2. Once paired, you don't have to pair the earphone with your Bluetooth devices for future use. Just power on the earphone and enable the Bluetooth function and they will automatically detect and connect with each other.</li> </ol> <p style="text-align: center;">③</p>																																												
<p>3. The earphone will automatically power off without connection for 5 minutes</p> <p style="text-align: center;"><b>MUSIC MODE</b></p> <ul style="list-style-type: none"> <li>● <b>Adjust Volume:</b> Short press the Volume+ to raise the volume or Volume- to lower the volume.You can also adjust the volume by your Bluetooth devices.</li> <li>● <b>Play/Pause Music:</b> Once connected, short press the Multi-Function Button to play or pause music.</li> <li>● <b>Previous Track:</b> Press and hold the Volume- to the previous track.</li> <li>● <b>Next Track:</b> Press and hold the volume+ to the next track.</li> </ul> <p style="text-align: center;"><b>CALL MODE</b></p> <ul style="list-style-type: none"> <li>● <b>Answering a Call:</b> Short press the Multi-Function Button to answer an incoming call, or answer the call normally via your mobile phone.</li> </ul> <p style="text-align: center;">④</p>	<ul style="list-style-type: none"> <li>● <b>Rejecting a Call:</b> Press and hold the Multi-Function Button for 2 seconds to reject the incoming call.</li> <li>● <b>Ending a Call:</b> Short press the Multi-Function Button to end the call or end the call directly from your mobile phone.</li> <li>● <b>Redialing a Call:</b> Double click the Multi-Function Button to redial the last dialed phone number on your mobile phone.</li> <li>● <b>Voice Assistant:</b> Once connected, press and hold the Multi-Function Button for 1 second to access voice assistant of your smart phone.</li> </ul> <p style="text-align: center;">⑤</p>	<p style="text-align: center;"><b>SPECIFICATIONS</b></p> <table border="1" data-bbox="817 869 1043 1137"> <tr><td>Dimensions</td><td>580*31*13mm</td></tr> <tr><td>Weight</td><td>20g</td></tr> <tr><td>Chipset</td><td>CSR 8670</td></tr> <tr><td>Bluetooth</td><td>V5.0</td></tr> <tr><td>Profile</td><td>A2DP, AVRCP, HSP, HFP</td></tr> <tr><td>Bluetooth range</td><td>10m</td></tr> <tr><td>Battery</td><td>60mAh*2 lithium-ion</td></tr> <tr><td>Charging time</td><td>about 2 hours</td></tr> <tr><td>Playtime</td><td>about 6 hours</td></tr> <tr><td>Speaker diameter</td><td>Φ6mm</td></tr> <tr><td>Frequency response</td><td>20Hz-20KHz</td></tr> <tr><td>Impedance</td><td>16Ω ±15%</td></tr> <tr><td>Sensibility</td><td>99dB±3dB at 1KHz</td></tr> <tr><td>MIC type</td><td>MEMS MIC</td></tr> </table> <p style="text-align: center;">⑥</p>	Dimensions	580*31*13mm	Weight	20g	Chipset	CSR 8670	Bluetooth	V5.0	Profile	A2DP, AVRCP, HSP, HFP	Bluetooth range	10m	Battery	60mAh*2 lithium-ion	Charging time	about 2 hours	Playtime	about 6 hours	Speaker diameter	Φ6mm	Frequency response	20Hz-20KHz	Impedance	16Ω ±15%	Sensibility	99dB±3dB at 1KHz	MIC type	MEMS MIC	<p style="text-align: center;"><b>LED INDICATOR</b></p> <table border="1" data-bbox="1088 869 1315 1025"> <thead> <tr> <th>STATUS</th> <th>INDICATOR</th> </tr> </thead> <tbody> <tr><td>Power On</td><td>Blue(slow flash)</td></tr> <tr><td>Power Off</td><td>Red(solid and out)</td></tr> <tr><td>Charging</td><td>Red(solid)</td></tr> <tr><td>Fully Charged</td><td>Blue(solid)</td></tr> <tr><td>Pairing</td><td>Blue/Red(quick flash)</td></tr> <tr><td>Connected</td><td>Blue(slow flash)</td></tr> <tr><td>Low Power</td><td>Red(quick flash)</td></tr> </tbody> </table> <p style="text-align: center;">⑦</p>	STATUS	INDICATOR	Power On	Blue(slow flash)	Power Off	Red(solid and out)	Charging	Red(solid)	Fully Charged	Blue(solid)	Pairing	Blue/Red(quick flash)	Connected	Blue(slow flash)	Low Power	Red(quick flash)
Dimensions	580*31*13mm																																														
Weight	20g																																														
Chipset	CSR 8670																																														
Bluetooth	V5.0																																														
Profile	A2DP, AVRCP, HSP, HFP																																														
Bluetooth range	10m																																														
Battery	60mAh*2 lithium-ion																																														
Charging time	about 2 hours																																														
Playtime	about 6 hours																																														
Speaker diameter	Φ6mm																																														
Frequency response	20Hz-20KHz																																														
Impedance	16Ω ±15%																																														
Sensibility	99dB±3dB at 1KHz																																														
MIC type	MEMS MIC																																														
STATUS	INDICATOR																																														
Power On	Blue(slow flash)																																														
Power Off	Red(solid and out)																																														
Charging	Red(solid)																																														
Fully Charged	Blue(solid)																																														
Pairing	Blue/Red(quick flash)																																														
Connected	Blue(slow flash)																																														
Low Power	Red(quick flash)																																														
<p><b>FCC Statement</b></p> <p>Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.</p> <p>This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:</p> <ul style="list-style-type: none"> <li>- Reorient or relocate the receiving antenna.</li> <li>- Increase the separation between the equipment and receiver.</li> <li>- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.</li> <li>- Consult the dealer or an experienced radio/TV technician for help.</li> </ul> <p>This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.</p> <p style="text-align: center;">⑧</p>																																															