

### GODOX设计文件图注

项目类型	<input type="checkbox"/> 彩盒 <input type="checkbox"/> 彩卡 <input type="checkbox"/> 白盒 <input type="checkbox"/> 贴纸 <input checked="" type="checkbox"/> 说明书 <input type="checkbox"/> 内托 <input type="checkbox"/> 胶盒 <input type="checkbox"/> 吸塑 <input type="checkbox"/> 其他:		
项目名称	LED摄影灯VL系列		
产品料号	705-VL0000-00	版本	A
展开尺寸(mm)		成品尺寸(mm)	142.5x210mm
尺寸公差	±2mm		
材质	80g书纸		
工艺说明	骑马钉		
备注/色值			
设计师	陈正丰	校对	杨入人

Godox 神牛

LED 摄影灯/LED Video Light  
VL150 VL200 VL300



深圳市神牛摄影器材有限公司  
GODOX Photo Equipment Co., Ltd.

地址/Add: 深圳市宝安区福海街道塘尾社区耀川工业区厂房2栋1层至4层、4栋1层至4层  
1st to 4th Floor, Building 2/ 1st to 4th Floor, Building 4, Yaochuan Industrial Zone, Tangwei Community,  
Fuhai Street, Bao'an District, Shenzhen, China

电话/Tel: +86-755-29609320(8062) 传真/Fax: +86-755-25723423

邮箱/E-mail: godox@godox.com http://www.godox.com

705-VL0000-00

Made In China



说明手册

INSTRUCTION MANUAL

## 前言

---

### 感谢您购买神牛产品！

LED摄影灯VL系列灯体轻巧便携，适配器、控制盒与灯体分离，操作方便。光源稳定，显色性好，功能强大，非常适用于儿童摄影、影棚拍摄、采访布光、静物拍摄以及视频拍摄等。配备专用遥控器，可无线分组调光，无线调节亮度。VL系列产品包括VL150、VL200、VL300。

### 主要特点：

- 功率强劲，光源稳定，亮度高且可自由调节
- V口锂电池供电或DC电源供电，室内室外两用
- 灯身体积小，重量轻，布灯更轻松，收纳更方便
- 适配器、控制盒、灯体分离，操控更便捷，散热性更佳
- 433MHz无线6组16频道分组控制&手机APP蓝牙无线控制
- U型支架设计，可吊装，调节各种角度更方便
- 保荣卡口，兼容各类光效附件
- 标配便携包，即拎即走

## 警告

---

- ▲ 请保持干燥：请勿用湿手接触产品，亦不可将产品浸入水中或暴露于雨中。
- ▲ 请勿私自拆卸产品，如产品出现故障须由本公司或授权的维修人员进行检查维修。
- ▲ 请勿让儿童接触本产品。
- ▲ 本产品不能防水，在雨天及潮湿环境下请注意防水。
- ▲ 请勿放置在超过50摄氏度的高温环境中。
- ▲ 请勿在化学品、可燃性气体或其他特殊物质附近使用闪光灯，这些物质在特殊情况下可能对闪光灯发出的瞬间强光敏感，有可能导致火灾或电磁干扰。在这些场合下，请注意相关警告标识。

## 部件名称

### 灯体



## 部件名称

### 控制器部件



### 标配物品

- 1、灯体 2、控制器 3、适配器 4、电源线 5、电源连接线  
6、遥控器 7、LED保荣反光罩 8、保护罩 9、便携包 10、说明书



## 接通电源

- 1、先将电源连接线两头分别插入控制器输出控制接口和灯体输入控制接口，听到咔声表示已经插好。



- 2、将适配器的连接线输出口端插入控制器电源输入端。




- 3、使用电源线，连接电源。


注：如果使用V口电池，直接插上V口电池，打开电源开关即可使用。

## 操作说明


- 1、**开关**：长按控制盒开关按键，LED灯亮，再次长按LED灯灭。



- 2、**无线组别/频道选择**：按一下GR/CH按钮，频道值被选中，旋转亮度调节旋钮可调整频道；再次按GR/CH按钮，组别值被选中，旋转亮度调节旋钮可调整组别（旋转时组别值循环出现）；再次按GR/CH按钮退出组别频道选择。



- 3、**亮度调节**：旋转亮度调节旋钮亮度改变，亮度调节范围0%-100%。



- 4、**功率选择**：按住GR/CH按钮开机进入功率选择模式，旋转亮度调节旋钮可选择300、250、200三种功率。功率默认为300W，进入功率模式5秒无操作自动退出此模式。

注：此功能适用于灯具大功率输出时，某些V口电池无法输出相应功率导致电池进入保护状态、不能继续使用该灯的情况。进入此模式，可降低灯的输出功率，让电池能带起负载避免出现电池保护(此功能只适用于VL300)。

## 无线控制：433MHz无线和手机APP蓝牙无线控制

- 1、VL系列LED灯具备**无线遥控功能**，使用433MHz无线技术，无视角限制，距离远，可同时分别控制6组LED灯。16组通道频率，抗干扰强。使用前请把LED控制盒和遥控器RC-A5II的频率与组别调至一致。



### 控制器频道/组别调整

- 在常态时，按GR/CH按钮，此时频道闪烁，旋转亮度调节可选择频道(1~16)；
- 在常态时，按GR/CH按钮2次，此时组别闪烁，旋转亮度调节可选择组别(A~F)。

### 遥控器频道/组别调整

- 在常态时，按CH/GR按钮，此时组别闪烁，按“-”“+”按钮可选择组别(A~F)；
- 在常态时，按CH/GR按钮2次，此时频道闪烁，按“-”“+”按钮可选择频道(1~16)。

### 遥控器亮度参数调节

- 在常态时，按“-”“+”按钮可对亮度调整。

注：控制器在开机状态下才可以接收无线信号。

- 2、神牛VL系列LED灯还具备**手机APP蓝牙无线控制功能**，可同时分别控制6组LED灯。16组通道频率，抗干扰强。



- **连接蓝牙**：在控制盒开机状态下，长按GR/CH按钮，控制器会显示蓝牙ID号。在手机上打开APP“GodoxPhoto”，点击蓝牙选择控制盒对应的蓝牙号，输入密码(原始密码“000000”)，蓝牙连接成功。

注：LED控制盒和APP显示的频道与组别需调至一致。



- **LED控制**：具体操作请看手机APP“GodoxPhoto”：设置---帮助---LED。

## 产品参数

VL系列LED灯		VI150	VI200	VI300
供电	DC电源供电	AC100V-240V(50/60HZ) /2A(DC16.8V 10A)	AC100V-240V(50/60HZ) /3.9A(DC33V 7A)	AC100V-240V(50/60HZ) /4.3A(DC33V 10A)
	锂电池供电	V口电池(另购)		
功率		150W	200W	300W
色温		5600 ± 200K		
100%光照度 (LUX,1米 距离)(≈) *注	标配 反光罩	61000	75000	77000
	裸灯	6400	7800	10800
CRI≈		96		
TLCI≈		95		
调光范围		0%-100%		
工作环境温度		-10°C ~ 40°C		
频道		16个		
组别		6组(A、B、C、D、E、F)		
产品尺寸		30x14x18cm	30x14x18cm	34x14x18cm
净量	灯:	1.97Kg	2.23Kg	2.64Kg
	控制盒:	0.86Kg	1.19Kg	1.26Kg
	适配器:	0.72Kg	0.96Kg	1.14Kg

注：配件不同，流明值也会有差异。

\*设计和规格如有变更，恕不另行通知。

## Foreword

### Thank you for purchasing this Godox Product!

LED Video Light VL series are portable and convenient due to the compact light and the separation design of main body, adapter and controller. It's excellent for children shooting, studio shooting, product shooting, photojournalistic and video recording, etc. VL series create stable light resource and even illumination for photography. With an included remote control and easy operation, VL series LED lights can be adjusted its light brightness in separate groups. Three models are available: VL150, VL200 and VL300.

### Main Features:

- With strong power, stable light source and adjustable light brightness
- Powered by V-port Lithium battery or DC power supply with wide application
- Small and portable light body provided with easy light arrangement
- Adapter and controller are separate from the main light body, which offers more convenient operation and better heat dissipation
- Achieving wireless control by 433MHz grouping system (6 groups & 16 channels) and smartphone APP through Bluetooth
- With U-type bracket to adjust different angles easily
- Bowens-mount enables to install various of accessories
- Included a carrying bag to pack the whole set

## ! Warning

- ▲ Always keep this product dry. Do not use in rain or in damp conditions.
- ▲ Do not disassemble. Should repairs become necessary, this product must be sent to an authorized maintenance center.
- ▲ Keep out of reach of children.
- ▲ As this product do not have waterproof function, please take measures of waterproof in rainy or damp environment.
- ▲ Do not use the flash unit in the presence of flammable gases, chemicals and other similar materials. In certain circumstance, these materials may be sensitive to the strong light emitting from this flash unit and fire or electromagnetic interference may result.
- ▲ As this product has built-in lithium battery, do not disassemble, impact, squeeze or put it into fire. If serious bulge occurs, please do not use. Do not use or store the product if the ambient temperature reads over 50°C. Please charge the product with specialized charger and correctly operate it within the defined voltage and working temperate according to the instruction manual.
- ▲ The light source of this luminaire is not replaceable; when the light source reaches its end of life the whole luminaire shall be replaced.
- ▲ Minimum distances from flammable materials: 10cm.