













































Maximum Power Spectral Density Level

Condition	Mode	Frequency (MHz)	Antenna	Conducted PSD (dBm)	Duty Factor (dB)	Total PSD (dBm)	MIMO PSD (dBm)	Limit (dBm)	Verdict
NVNT	ac20	5180	Ant1	-4.35	0.05	-4.3	2.33	5	Pass
NVNT	ac20	5180	Ant2	-11.88	0.05	-11.83			
NVNT	ac20	5180	Ant3	-11.29	0.05	-11.24			
NVNT	ac20	5180	Ant4	-10.37	0.05	-10.32			
NVNT	ac20	5180	Ant5	-4.25	0.05	-4.2			
NVNT	ac20	5180	Ant6	-6.53	0.05	-6.48			
NVNT	ac20	5180	Ant7	-6.25	0.05	-6.2			
NVNT	ac20	5180	Ant8	-5.89	0.05	-5.84			
NVNT	ac20	5200	Ant1	-5.17	0.05	-5.12	2.01	5	Pass
NVNT	ac20	5200	Ant2	-11.46	0.05	-11.41			
NVNT	ac20	5200	Ant3	-11.42	0.05	-11.37			
NVNT	ac20	5200	Ant4	-9.83	0.05	-9.78			
NVNT	ac20	5200	Ant5	-5.01	0.05	-4.96			
NVNT	ac20	5200	Ant6	-6.99	0.05	-6.94			
NVNT	ac20	5200	Ant7	-6.33	0.05	-6.28			
NVNT	ac20	5200	Ant8	-5.67	0.05	-5.62			
NVNT	ac20	5240	Ant1	-4.75	0.05	-4.7	1.90	5	Pass
NVNT	ac20	5240	Ant2	-11.74	0.05	-11.69			
NVNT	ac20	5240	Ant3	-10.86	0.05	-10.81			
NVNT	ac20	5240	Ant4	-9.57	0.05	-9.52			
NVNT	ac20	5240	Ant5	-5.89	0.05	-5.84			
NVNT	ac20	5240	Ant6	-7.25	0.05	-7.2			
NVNT	ac20	5240	Ant7	-6.4	0.05	-6.35			
NVNT	ac20	5240	Ant8	-5.77	0.05	-5.72			
NVNT	ac40	5190	Ant1	-5.15	0.1	-5.05	0.45	5	Pass
NVNT	ac40	5190	Ant2	-14.03	0.29	-13.74			
NVNT	ac40	5190	Ant3	-13.54	0.16	-13.38			
NVNT	ac40	5190	Ant4	-11.64	0.13	-11.51			
NVNT	ac40	5190	Ant5	-7.04	0.1	-6.94			
NVNT	ac40	5190	Ant6	-8.85	0.1	-8.75			
NVNT	ac40	5190	Ant7	-8.42	0.1	-8.32			
NVNT	ac40	5190	Ant8	-8.09	0.1	-7.99			
NVNT	ac40	5230	Ant1	-5.44	0.1	-5.34	0.13	5	Pass
NVNT	ac40	5230	Ant2	-13.89	0.32	-13.57			
NVNT	ac40	5230	Ant3	-13.43	0.15	-13.28			
NVNT	ac40	5230	Ant4	-11.68	0.14	-11.54			
NVNT	ac40	5230	Ant5	-8.13	0.1	-8.03			
NVNT	ac40	5230	Ant6	-9.4	0.1	-9.3			
NVNT	ac40	5230	Ant7	-8.9	0.11	-8.79			

NVNT	ac40	5230	Ant8	-7.71	0.1	-7.61			
NVNT	ac80	5210	Ant1	-6.95	0.79	-6.16	-2.44	5	Pass
NVNT	ac80	5210	Ant2	-18.24	0.21	-18.03			
NVNT	ac80	5210	Ant3	-18.07	0.21	-17.86			
NVNT	ac80	5210	Ant4	-13.45	0.21	-13.24			
NVNT	ac80	5210	Ant5	-11.42	0.25	-11.17			
NVNT	ac80	5210	Ant6	-13.6	0.25	-13.35			
NVNT	ac80	5210	Ant7	-13.08	0.24	-12.84			
NVNT	ac80	5210	Ant8	-12.32	0.25	-12.07			
NVNT	ac160	5250	Ant1	-9.61	0.39	-9.22	-5.85	5	Pass
NVNT	ac160	5250	Ant2	-18.63	0.39	-18.24			
NVNT	ac160	5250	Ant3	-21.75	0.39	-21.36			
NVNT	ac160	5250	Ant4	-15.34	0.39	-14.95			
NVNT	ac160	5250	Ant5	-15.4	0.39	-15.01			
NVNT	ac160	5250	Ant6	-18.58	0.39	-18.19			
NVNT	ac160	5250	Ant7	-17.33	0.38	-16.95			
NVNT	ac160	5250	Ant8	-16.91	0.39	-16.52			
NVNT	ax160	5250	Ant1	-9.26	0.43	-8.83	-6.02	5	Pass
NVNT	ax160	5250	Ant2	-19.86	0.44	-19.42			
NVNT	ax160	5250	Ant3	-22.08	0.44	-21.64			
NVNT	ax160	5250	Ant4	-16.96	0.43	-16.53			
NVNT	ax160	5250	Ant5	-16.31	0.43	-15.88			
NVNT	ax160	5250	Ant6	-18.94	0.44	-18.5			
NVNT	ax160	5250	Ant7	-17.72	0.43	-17.29			
NVNT	ax160	5250	Ant8	-17.18	0.43	-16.75			
NVNT	ax20	5180	Ant1	-4.65	0.06	-4.59	2.28	5	Pass
NVNT	ax20	5180	Ant2	-11.89	0.06	-11.83			
NVNT	ax20	5180	Ant3	-11.19	0.07	-11.12			
NVNT	ax20	5180	Ant4	-10.55	0.06	-10.49			
NVNT	ax20	5180	Ant5	-4.38	0.07	-4.31			
NVNT	ax20	5180	Ant6	-6.63	0.06	-6.57			
NVNT	ax20	5180	Ant7	-6.12	0.06	-6.06			
NVNT	ax20	5180	Ant8	-5.89	0.06	-5.83			
NVNT	ax20	5200	Ant1	-4.85	0.06	-4.79	2.12	5	Pass
NVNT	ax20	5200	Ant2	-11.68	0.06	-11.62			
NVNT	ax20	5200	Ant3	-11.22	0.06	-11.16			
NVNT	ax20	5200	Ant4	-10.18	0.06	-10.12			
NVNT	ax20	5200	Ant5	-5.07	0.06	-5.01			
NVNT	ax20	5200	Ant6	-6.82	0.06	-6.76			
NVNT	ax20	5200	Ant7	-6.01	0.06	-5.95			
NVNT	ax20	5200	Ant8	-5.8	0.06	-5.74			
NVNT	ax20	5240	Ant1	-5.1	0.06	-5.04	1.90	5	Pass
NVNT	ax20	5240	Ant2	-11.8	0.06	-11.74			
NVNT	ax20	5240	Ant3	-11.13	0.06	-11.07			

NVNT	ax20	5240	Ant4	-9.79	0.06	-9.73			
NVNT	ax20	5240	Ant5	-5.98	0.06	-5.92			
NVNT	ax20	5240	Ant6	-6.93	0.06	-6.87			
NVNT	ax20	5240	Ant7	-6.45	0.06	-6.39			
NVNT	ax20	5240	Ant8	-5.63	0.06	-5.57			
NVNT	ax40	5190	Ant1	-5.87	0.13	-5.74	0.13	5	Pass
NVNT	ax40	5190	Ant2	-14.67	0.58	-14.09			
NVNT	ax40	5190	Ant3	-14.32	0.3	-14.02			
NVNT	ax40	5190	Ant4	-12.11	0.16	-11.95			
NVNT	ax40	5190	Ant5	-7.12	0.12	-7			
NVNT	ax40	5190	Ant6	-9.33	0.12	-9.21			
NVNT	ax40	5190	Ant7	-8.91	0.12	-8.79			
NVNT	ax40	5190	Ant8	-7.94	0.12	-7.82			
NVNT	ax40	5230	Ant1	-5.52	0.12	-5.4	-0.09	5	Pass
NVNT	ax40	5230	Ant2	-14.29	0.5	-13.79			
NVNT	ax40	5230	Ant3	-14.09	0.25	-13.84			
NVNT	ax40	5230	Ant4	-11.58	0.16	-11.42			
NVNT	ax40	5230	Ant5	-8.52	0.12	-8.4			
NVNT	ax40	5230	Ant6	-9.46	0.12	-9.34			
NVNT	ax40	5230	Ant7	-9.07	0.12	-8.95			
NVNT	ax40	5230	Ant8	-8.46	0.12	-8.34			
NVNT	ax80	5210	Ant1	-7.18	0.58	-6.6	-2.92	5	Pass
NVNT	ax80	5210	Ant2	-18.38	0.24	-18.14			
NVNT	ax80	5210	Ant3	-18.67	0.24	-18.43			
NVNT	ax80	5210	Ant4	-14.2	0.24	-13.96			
NVNT	ax80	5210	Ant5	-12.06	0.28	-11.78			
NVNT	ax80	5210	Ant6	-13.8	0.28	-13.52			
NVNT	ax80	5210	Ant7	-13.58	0.28	-13.3			
NVNT	ax80	5210	Ant8	-12.42	0.28	-12.14			





























