

## RF EXPOSURE EVALUATION

According to FCC 1.1310: The criteria listed in the following table shall be used to evaluate the environment impact of human exposure to radio frequency(RF) Radiation as specified in §1.1307(b)

FCC ID: **2ACYP-YN360S**

### EUT Specification

EUT	Bluetooth Smart Switch
<b>Frequency band (Operating)</b>	<input type="checkbox"/> WLAN: 2.412GHz ~ 2.462GHz <input type="checkbox"/> WLAN: 5.18GHz ~ 5.24GHz <input checked="" type="checkbox"/> Others: 2.402GHz~2.480GHz (BT4.0)
<b>Device category</b>	<input type="checkbox"/> Portable (<20cm separation) <input checked="" type="checkbox"/> Mobile (>20cm separation) <input type="checkbox"/> Others ____
<b>Exposure classification</b>	<input type="checkbox"/> Occupational/Controlled exposure (S = 5mW/cm <sup>2</sup> ) <input checked="" type="checkbox"/> General Population/Uncontrolled exposure (S=1mW/cm <sup>2</sup> )
<b>Antenna diversity</b>	<input checked="" type="checkbox"/> Single antenna <input type="checkbox"/> Multiple antennas <input type="checkbox"/> Tx diversity <input type="checkbox"/> Rx diversity <input type="checkbox"/> Tx/Rx diversity
<b>Max. output power</b>	-4.865dBm (0.0003W)
<b>Antenna gain (Max)</b>	-4.49 dBi
<b>Evaluation applied</b>	<input checked="" type="checkbox"/> MPE Evaluation <input type="checkbox"/> SAR Evaluation

Limits for Maximum Permissible Exposure(MPE)

Frequency Range(MHz)	Electric Field Strength(V/m)	Magnetic Field Strength(A/m)	Power Density(mW/cm <sup>2</sup> )	Average Time
<b>(A) Limits for Occupational/Control Exposures</b>				
<b>300-1500</b>	--	--	<b>F/300</b>	<b>6</b>
<b>1500-100000</b>	--	--	<b>5</b>	<b>6</b>
<b>(B) Limits for General Population/Uncontrol Exposures</b>				
<b>300-1500</b>	--	--	<b>F/1500</b>	<b>6</b>
<b>1500-100000</b>	--	--	<b>1</b>	<b>30</b>

## Friis transmission formula: $Pd=(Pout * G) / (4 * \pi * R^2)$

Where

$Pd$ = Power density in  $mW/cm^2$

$Pout$ =output power to antenna in Mw

$G$ = gain of antenna in linear scale

$\pi=3.1416$

$R$ = distance between observation point and center of the radiator in cm

$Pd$  the limit of MPE,  $1mW/cm^2$ . If we know the maximum gain of the antenna and total power input to the antenna, through the calculation, we will know the distance where the MPE limit is reached.

## Measurement Result

Operating Mode	Channel Frequency	Measured Power	Tune up tolerance	Max. Tune up Power	Antenna Gain	Power density at 20cm	Power density Limits
	(MHz)	(dBm)	(dBm)	(dBm)	(dBi)	( $mW/cm^2$ )	( $mW/cm^2$ )
BLE	2402	-5.607	$-5.607 \pm 1$	-4.607	-4.49	0.00002	1
	2441	-5.530	$-5.530 \pm 1$	-4.530	-4.49	0.00002	1
	2480	-4.865	$-4.865 \pm 1$	-3.865	-4.49	0.00003	1