

Tune up procedure

Tune up procedure shall be over the power range or at specific operating power levels.

It must provide an operational voltage (DC 3.7V by battery) to turn on the device and on One certain channel in service mode by means of company proprietary software.

Spectrum analyzer (Agilent, 9020A) and Power meter

(R&S,NRVS)measures the 2.4G device specific RF characteristics.

The maximum gains of each individual device are adjusted until the target value met.

Maximum RF Conducted Output Power(Peak value)			
Frequency Bands	Service	PCL/Class	Target Value(dBm)
WIFI	802.11b	1Mbps	8.50 ± 0.5
	802.11g	6Mbps	8.00 ± 1.0
	802.11n(HT20)	6.5Mbps	6.00 ± 1.0
	802.11n(HT40)	13.5Mbps	5.00 ± 1.0
V3.0+EDR	GFSK	1M	3.5 ± 0.5
	π /4-DQPSK	2M	3.5 ± 0.5
	8-DPSK	3M	3.0 ± 0.5
BLE4.0	GFSK	1M	0.5 ± 0.5

Then these appropriate gain settings are stored in each device individually.

The user has no possibility to change these settings later on, and during manufacturing each device will be individual calibrated.

The measurement is done in fully calibrated setup, which is based on a Agilent 8960 base station simulator, spectrum analyzer(Agilent, 9020A) and Power meter. Furthermore, the highest power level is verified afterwards in a call measurement on three channels (low, middle and high).