



Operating Instructions

The Versa Panic was designed to transmit an emergency signal from any location within the range of the alarm system. Signals from the button

will be transmitted whether the system is armed or disarmed.

The button is small and lightweight enough to be placed in a shirt pocket or tucked away inside a purse. It can also be used with the supplied lanyard. It can also be permanently mounted to a convenient location.

To activate, press and hold the button for approximately 2 seconds. The LED located on the top of the unit will light up for approximately 1 second to confirm a signal has been sent.

Note: Signals will not be received if the button is not within range of the control panel.

Programming

This device is supervised. If the unit is removed from the coverage range, then a trouble will be indicated on the system. If this is not desired, the supervisory option for this zone must be disabled on the alarm control panel. For more details, please refer to the security panel manufacturer's installation & programming instructions.

Program the Versa Panic using the 6-digit number located on the device.

For ETL listed installations the supervisory bit in the alarm control panel must be enabled.

Testing

- Put the control panel into sensor test mode.
- Press and hold the button for approximately 2 seconds. The LED located on the top of the unit will light up for approximately 1 second to confirm a signal has been sent.
- Listen for siren or keypad beeps to determine appropriate response (refer to the control panel installation instructions).
- Exit sensor test mode.

Note: It is recommended that a system test be performed per the Operation & User's Guide at least once a year.

FCC Notice

This device complies with FCC Rules Part 15. Operation is subject to the following two conditions:

- This device may not cause harmful interference.
- This device must accept any interference that may be received, including interference that may cause undesired operation.¹

Changes or modifications not expressly approved by Versa Wireless Inc. can void the user's authority to operate the equipment. Le présent appareil est conforme aux CNR d'Industrie Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes : (1) l'appareil ne doit pas produire de brouillage, et (2) l'utilisateur de l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.

¹ For UL compliance the units are for residential use only.

Installation instructions **Rev 1**.

This Class [B] digital apparatus complies with Canadian ICES-003.

Cet appareil numérique de la classe [B] est conforme à la norme NMB-003 du Canada.

Statement: This device complies with RSS-210 and IC ES-003 of the Industry Canada Rules. Operation is subject to the following two conditions : (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation of this device.

Le présent appareil est conforme aux CNR d'Industrie Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes : (1) l'appareil ne doit pas produire de brouillage, et (2) l'utilisateur de l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.

Specifications

Wireless Signal Range	350 feet, open air, with 2GIG wireless alarm control panel
Code Output	Alarm, supervisory, low battery
Transmitter Frequency	345 MHz (crystal controlled)
Transmitter Frequency Tolerance	±15 kHz
Transmitter Bandwidth	24 kHz
Modulation Type	Amplitude shift keying — on/off keying
Unique ID Codes	Over 1 million
Supervisory Interval	70 minutes
Peak Field Strength	Typical 36,000 uV/m at 3m
LED	Red (when activated)
Dimensions	1.42" x 1.42" x 0.47"
Weight (including battery)	0.45 oz
Housing Material	ABS plastic
Color	White with blue button
Operating Temperature	32° to 120°F (0° to 49°C)
Relative Humidity	Water resistant
Battery Installed	1 CR2032 lithium battery (non-replaceable)
Regulatory Listing(s)	ETL, FCC Part 15, Industry Canada
Warranty	2 years
Included Accessories	Lanyard

FCC Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.