

2.4G Wireless Keyboard And Touchpad

NEO K1

Installation & User Manual

New product With
MULTI TOUCH

IN LINE WITH THE POLICY OF CONTINUED DEVELOPMENT THE MANUFACTURER RESERVES THE RIGHT TO AMEND THE SPECIFICATIONS WITHOUT PRIOR NOTIFICATION. THE PICTURES AND DATA IN THE STYLEBOOK ARE CONSULT ONLY, IF THERE IS FLUCTUATION, ACCORDING TO THE REAL OBJECT PLEASE

RoHS
Made in China

Overview

Thank you for purchasing the Wireless Mini QWERTY Keyboard & Touchpad Combo. You can use it for emails, chat, remote, type and games. It is compatible with PC, Laptop, Raspberry Pi 2, MacOS, Linux, HTPC, IPTV, Google Android Smart TV Box ,XBMC, Windows 2000 XP Vista 7 8 10. Use it with your android box or smart tv on your sofa or browse the internet in the most comfortable fashion.

Package contents

- Keyboard touchpad Combo
- USB Wireless Receiver
- User Manual
- USB Charging Cable

System Requirements

- HID compatible device
- Terminal with USB port
- Windows 2000
- Windows XP
- Windows Vista, Windows CE, Windows 7, Windows 8

- Linux (Debian-3.1, Redhat-9.0, Ubuntu-8.10, Fedora-7.0 tested)
- Android OS (With standard USB interface)

Please note:

1. It can work on Amazon Fire TV as follows: use an app called app2 fire on android. You can send any app to fire tv. Then run it so for example google chrome. the keyboard works as mouse and keyboard. Just note that it only works on sideloaded application's. for example google chrome, firefox, showbox. KODI is a native app on fire.
2. Not suitable for all smart tv. Some smart tv do not support external input device. before you place the order, please use a wired keyboard to check if it can work.

Specifications

Receiver(dongle): Nano style
Connection port : With USB2.0 above
Transmission mode : GFSK 2.4GHz wireless, up to 10 meters
Power supply: Rechargeable polymer Lithium-ion battery
Operation voltage: 3.7V
Recharge Voltage: DC 5V/300mA

Operating current: <15mA
Product weight: 110g
Product size: 146.8*97.5*19mm

Installation

1. Take off the USB receiver from back cover of the keyboard
2. Plug the USB Receiver into your device's USB port. Such as android tv box, smart tv
3. Turn on the keyboard.

A blue LED will stay on. That means the keyboard has paired with your device.

You can enjoy the keyboard now!

Note:

1. The three port extension USB cable can not only be used for battery charging but also solving signal interference! It can not be used as digital connection
2. If the blue LED does not stay on and orange light stay flashing, it means the keyboard need to be paired with your device handy. As for how to pair, please try following steps:

Step1: Keep your PC on, and be sure the keyboard is full of power.:
Step2: Press the "F1" without releasing.
Step3: Power on the keyboard and release the "F1" immediately.
Step4: Plug the USB receiver on the USB port of your PC.
Wait a moment. The keyboard will repair automatically.
When the yellow light stop flashing and blue led on, it means successful.

3. About the meaning of the three leds (orange, blue and red)
Red: means charge status. When start to charge, it will be on. When it is powerful, it will be off automatically.
Blue: means pair status. When it is on, it means keyboard is paired with your device successfully. If it is off, it means not be paired. You need to do the above 4 steps to repair it.
Orange: means sync. It will flashing whatever you type any button or touchpad. If it not flash, it means it has something wrong on keyboard or the compatibility.

4. About signal interference: special for android tv box and smart tv.
Large size monitor's device always has some signal interference. Signal interference may result to short distance and buttons do not work as well. When you press "a", "aaaaaa..." will appear. For this case, you can use the three port extension cable we shipped to you to solve it. please plug the extension cable to your smart tv, and plug usb receiver on the cable. then pair and use remote keyboard

5. Shortcut Keys:
FN+RF: enter into pair model
FN+F7: Screenshot
FN+F8: Turn on/off touchpad mouse
FN+F9: F11
FN+F10: F12

FN+ Back: Delete
FN+ PgUp: Home

6. Special keys use in special layout. such as @ in UK layout
This keyboard has different layout. Please know exactly which layout do you want. For example. If you want and buy UK layout. And you want to use @. You need to first change your device's system language to british English. Then it can work by shift+@.

7. Don't work all the time
This keyboard has auto sleep / wake up function. when customers do not use it in 3 mins, it will enter into sleep automaticly, this time the customers can press any button to make it wake up. also please let customers to charge the keyboard and make sure it is on enough power.

Using the Touchpad

The touchpad is activated together with the keyboard. When the keyboard is on, the keyboard is ready for use. FN+F8 can turn on / off touchpad function
You will enjoy more convenience and control on-screen menu easier.

Auto Sleep and Wake-up feature

The keyboard supports auto sleep and wake-up. Without operation around 3 minutes, the keyboard will enter sleep mode. In sleep status, all LED indicators are off. Pressing any key can wake it up.

Switching off the keyboard after use

After use, push the switch to the "OFF" position to turn it off. The USB receiver does not need to be pulled out from the terminal. You can use it next time directly.

Charging the battery

The device uses built-in lithium-ion battery. Please use only approved data cables and chargers.

Note: Fully charge the unit before initial operation. This device can be used when charging, but charging time will be extended.

When the battery is low, the low-voltage light will blink to warn the user. The unit will be automatically turned off if the battery has been depleted.

Multi-finger Functions Touchpad (Only for i8+ A/B versions)

This touchpad supports multi-finger functions.

- (1) When a single finger click, on behalf of the left mouse function keys
- (2) When two-finger click, on behalf of the right mouse function keys
- (3) When double finger drag up and down, on behalf of the Rolling screen
- (4) When a single finger sliding pointer can be controlled

Turn on/off the Backlit LED (Only for i8+ A/B versions)

Two Modes: Software Control and Manual Control
When the wireless connection is successful, the backlit LED will be automatically on 3 seconds, then off, to save power and lengthen standby time. You can click the backlit LED button to turn the LED on. Users can turn on the LED in dark environment for better operation.

Enabling the backlight (Only for i8+ A/B versions)

The backlight led will automatically turn on for three seconds after having pressed the power switch to the on position. If enabling backlight function, the backlight led will light for one minute. In a minute, if having no key is pressed, the backlight led will turn off. After backlight led turned off, the backlight led will turn on again if you press any key again. Enable/disable the backlight led through pressing Backlight control key.

Audio Feature (Only for i8+ A versions)

Audio feature configuration is available for this device. This device includes a MIC. Under some systems, the audio feature requires manual configuration.


Warning

- When charging finishes, pull out the charging cable.
- Never try to open or repair this product yourself.
- Keep this device away from fluids, such as water.

Maintenance

- Do not attempt to disassemble the device or replace the rechargeable battery. Doing so will void the warranty.
- The battery will discharge when it is stored for a long time without operation.
- Use the specified charger. Disconnect the device when the battery is fully charged. Overcharging will shorten the battery life.
- Do not expose the device in extreme heat or cold environment, which will shorten the battery life.

Disposal

 Always dispose the used appliance at a recycling centre. Do not dispose the used appliance together with the household waste.

Note:

Due to 2.4G wave technology adoption, the connection can be subject to interference from obstacles, like walls, metals, or other electronic devices. Please keep the space between the keyboard and USB receiver free of obstacle.

In line with the policy of continued development, the manufacturer reserves the right to amend. The specifications without prior notification. The illustrations in the user manual are for reference only. Please operate according to the real design.

FCC Warning:
This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- o Reorient or relocate the receiving antenna.
- o Increase the separation between the equipment and receiver.
- o Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- o Consult the dealer or an experienced radio/TV technician for help.

Caution: Any changes or modifications to this device not explicitly approved by manufacturer could void your authority to operate this equipment.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:
(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.