

RF EXPOSURE EVALUATION

According to FCC 1.1310: The criteria listed in the following table shall be used to evaluate the environment impact of human exposure to radio frequency(RF) Radiation as specified in §1.1307(b)

FCC ID: **2ADFS-R01**

EUT Specification

EUT	QuattroPod
Frequency band (Operating)	<input type="checkbox"/> WLAN: 2.412GHz ~ 2.462GHz <input checked="" type="checkbox"/> WLAN: 5.18GHz ~ 5.24GHz <input type="checkbox"/> WLAN: 5.745GHz ~ 5.825GHz <input type="checkbox"/> Others: 2.402GHz~2.480GHz
Device category	<input type="checkbox"/> Portable (<20cm separation) <input checked="" type="checkbox"/> Mobile (>20cm separation) <input type="checkbox"/> Others ____
Exposure classification	<input type="checkbox"/> Occupational/Controlled exposure (S = 5mW/cm ²) <input checked="" type="checkbox"/> General Population/Uncontrolled exposure (S=1mW/cm ²)
Antenna diversity	<input type="checkbox"/> Single antenna <input checked="" type="checkbox"/> Multiple antennas <input type="checkbox"/> Tx diversity <input type="checkbox"/> Rx diversity <input type="checkbox"/> Tx/Rx diversity
Max. output power	15.10dBm (0.0324W)
Antenna gain (Max)	ANT 1 & ANT 2: 4 dBi
Evaluation applied	<input checked="" type="checkbox"/> MPE Evaluation <input type="checkbox"/> SAR Evaluation

Limits for Maximum Permissible Exposure(MPE)

Frequency Range(MHz)	Electric Field Strength(V/m)	Magnetic Field Strength(A/m)	Power Density(mW/cm ²)	Average Time
(A) Limits for Occupational/Control Exposures				
300-1500	--	--	F/300	6
1500-100000	--	--	5	6
(B) Limits for General Population/Uncontrol Exposures				
300-1500	--	--	F/1500	6
1500-100000	--	--	1	30

Friis transmission formula: $P_d = \frac{P_{out} * G}{4 * \pi * R^2}$

Where

P_d = Power density in mW/cm^2

P_{out} = output power to antenna in Mw

G = gain of antenna in linear scale

$\pi = 3.1416$

R = distance between observation point and center of the radiator in cm

P_d the limit of MPE, $1mW/cm^2$. If we know the maximum gain of the antenna and total power input to the antenna, through the calculation, we will know the distance where the MPE limit is reached.

Measurement Result

ANT 1:

Operating Mode	Channel Frequency	Measured Power	Tune up tolerance	Max. Tune up Power	Antenna Gain	Power density at 20cm	Power density Limits
	(MHz)	(dBm)	(dBm)	(dBm)	(dBi)	(mW/cm^2)	(mW/cm^2)
802.11ac20	5180	14.83	14.83 ± 1	15.83	4	0.0191	1
	5200	14.52	14.52 ± 1	15.52	4	0.0178	1
	5240	15.07	15.07 ± 1	16.07	4	0.0202	1
802.11ac40	5190	14.67	14.67 ± 1	15.67	4	0.0184	1
	5230	14.98	14.98 ± 1	15.98	4	0.0198	1
802.11ac80	5210	14.53	14.53 ± 1	15.53	4	0.0179	1

ANT 2:

Operating Mode	Channel Frequency	Measured Power	Tune up tolerance	Max. Tune up Power	Antenna Gain	Power density at 20cm	Power density Limits
	(MHz)	(dBm)	(dBm)	(dBm)	(dBi)	(mW/cm^2)	(mW/cm^2)
802.11ac20	5180	14.90	14.90 ± 1	15.90	4	0.0194	1
	5200	14.67	14.67 ± 1	15.67	4	0.0184	1
	5240	15.10	15.10 ± 1	16.10	4	0.0204	1
802.11ac40	5190	14.92	14.92 ± 1	15.92	4	0.0195	1
	5230	15.23	15.23 ± 1	16.23	4	0.0210	1
802.11ac80	5210	14.92	14.92 ± 1	15.92	4	0.0195	1

ANT1+ANT2:

Operating Mode	Channel Frequency (MHz)	ANT 1 Power density at 20cm (mW/ cm ²)	ANT 2 Power density at 20cm (mW/ cm ²)	Power density at 20cm (mW/ cm ²)	Power density Limits (mW/cm ²)
802.11ac 80	5210	0.0179	0.0195	0.0374	1