

RF EXPOSURE EVALUATION METHOD

SAR Test Exclusion Thresholds for 100 MHz – 6 GHz and ≤ 50 mm

Approximate SAR Test Exclusion Power Thresholds at Selected Frequencies and Test Separation Distances are illustrated in the following Table.

MHz	5	10	15	20	25	mm
150	39	77	116	155	194	SAR Test Exclusion Threshold (mW)
300	27	55	82	110	137	
450	22	45	67	89	112	
835	16	33	49	66	82	
900	16	32	47	63	79	
1500	12	24	37	49	61	
1900	11	22	33	44	54	
2450	10	19	29	38	48	
3600	8	16	24	32	40	
5200	7	13	20	26	33	
5400	6	13	19	26	32	
5800	6	12	19	25	31	

The 1-g and 10-g SAR test exclusion thresholds for 100 MHz to 6 GHz at test separation distances ≤ 50 mm are determined by:

$[(\text{max. power of channel, including tune-up tolerance, mW}) / (\text{min. test separation distance, mm})] \cdot [\sqrt{f(\text{GHz})}] \leq 3.0$ for 1-g SAR and ≤ 7.5 for 10-g extremity SAR, where $f(\text{GHz})$ is the RF channel transmit frequency in GHz

Power and distance are rounded to the nearest mW and mm before calculation

The result is rounded to one decimal place for comparison

The test exclusions are applicable only when the minimum test separation distance is ≤ 50 mm and for transmission frequencies between 100 MHz and 6 GHz. When the minimum test separation distance is < 5 mm, a distance of 5 mm is applied to determine SAR test exclusion.

Maximum measured transmitter power.

2.4G WIFI The Worst Case

Mode	frequency	Maximum Peak Conducted Output Power	Tune up tolerance
	GHz	dBm	dBm
802.11b	2.412	8.27	8±1
802.11g	2.437	7.72	7±1
802.11n20	2.437	7.03	7±1
802.11n40	2.452	6.42	6±1

Remark: The worst case gain of the antenna is 1.5dBi.

1.5dBi logarithmic terms convert to numeric result is nearly 1.41

Tune up Power₍₂₄₁₂₎=7.943mw

Tune up Power₍₂₄₃₇₎=6.310mw

Tune up Power₍₂₄₃₇₎=6.310mw

Tune up Power₍₂₄₅₂₎=5.012mw

WIFI:

[(max. power of channel, including tune-up tolerance, mW)/802.11b test separation distance,mm)] • [√f(GHz)]= 7.943/5* √ 2.412=2.467≤3.0

[(max. power of channel, including tune-up tolerance, mW)/(802.11g test separation distance,mm)] • [√f(GHz)]= 6.310/5* √ 2.437=1.970≤3.0

[(max. power of channel, including tune-up tolerance, mW)/(802.11n20 test separation distance,mm)] • [√f(GHz)]= 6.310/5* √ 2.437=1.970≤3.0

[(max. power of channel, including tune-up tolerance, mW)/(802.11n40 test separation distance,mm)] • [√f(GHz)]= 5.012/5* √ 2.452=1.570≤3.0

Threshold at which no SAR required is 7.943≤ 3.0 for 1-g SAR, Separation distance is 5mm.

Maximum measured transmitter power.

5G WIFI The Worst Case

Mode	frequency	Maximum Peak Conducted Output Power	Tune up tolerance
	GHz	dBm	dBm
802.11a/n/ac(HT20)	5.180	7.32	7±0.5
802.11n/ac(HT40)	5.190	5.62	5±1
802.11 ac(HT80)	5.210	4.90	5±1

Remark: The worst case gain of the antenna is 1.5dBi.

1.5dBi logarithmic terms convert to numeric result is nearly 1.41

Tune up Power₍₅₁₈₀₎=5.623mw

Tune up Power₍₅₁₉₀₎=3.981mw

Tune up Power₍₅₂₁₀₎=3.981mw

WIFI:

[(max. power of channel, including tune-up tolerance, mW)/ 802.11a/n/ac(HT20) test separation distance,mm)] • [√ f(GHz)]= 5.623/5* √ 5.180=2.560 ≤ 3.0

[(max. power of channel, including tune-up tolerance, mW)/(802.11n/ac(HT40) test separation distance,mm)] • [√ f(GHz)]= 3.981/5* √ 5.190=1.814 ≤ 3.0

[(max. power of channel, including tune-up tolerance, mW)/(802.11 ac(HT80) test separation distance,mm)] • [√ f(GHz)]= 3.981/5* √ 5.210=1.817 ≤ 3.0

Threshold at which no SAR required is 2.560 ≤ 3.0 for 1-g SAR, Separation distance is 5mm.

Maximum measured transmitter power.

5G WIFI The Worst Case

Mode	frequency	Maximum Peak Conducted Output Power	Tune up tolerance
	GHz	dBm	dBm
802.11a/n/ac(HT20)	5.785	7.35	7±0.5
802.11n/ac(HT40)	5.795	6.46	6±0.5
802.11 ac(HT80)	5.775	5.93	6±0.5

Remark: The worst case gain of the antenna is 1.5dBi.

1.5dBi logarithmic terms convert to numeric result is nearly 1.41

Tune up Power₍₅₇₈₅₎=5.623mw

Tune up Power₍₅₇₉₅₎=4.467mw

Tune up Power₍₅₇₇₅₎=4.467mw

WIFI:

[(max. power of channel, including tune-up tolerance, mW)/ 802.11a/n/ac(HT20) test separation distance,mm)] • [√ f(GHz)]= 5.623/5* √ 5.785=2.705 ≤ 3.0

[(max. power of channel, including tune-up tolerance, mW)/(802.11n/ac(HT40) test separation distance,mm)] • [√ f(GHz)]= 4.467/5* √ 5.795=2.151 ≤ 3.0

[(max. power of channel, including tune-up tolerance, mW)/(802.11 ac(HT80) test separation distance,mm)] • [√ f(GHz)]= 4.467/5* √ 5.775=2.147 ≤ 3.0

Threshold at which no SAR required is 2.705 ≤ 3.0 for 1-g SAR, Separation distance is 5mm.