

Wireless Controller

Model:SMWireless

FCC ID:2AEYKSMWIRELESS

This mode will allow you to control the fogger using the optional wireless controller. This consists of the transmitter and the receiver. You may control up to 4 independent fog machines or many more if you run them simultaneously. See the below instructions on setting up your fogger to operate with the Wireless Remote Kit.

1. Plug the wires receiver into the fog machine 5-pin port labeled wireless Controller?
2. There are 4 buttons on the wireless remote transmitter which act as triggers. Each button can be assigned to a different fog machine. You may only choose 1 dipswitch on each receiver. See the below configuration for setting the receivers to operate with the transmitter remote.

Mode	Dipswitches
CH1	1 = On, 2-4 = Off
CH2	2 = On, 1,3,4 = Off
CH3	3 = On, 1,2,4 = Off
CH4	4 = On, 1,2,3 = Off

3. Press the fog button, and the fog machine will output fog momentarily for as long as you hold down the button.



Technical specification

The spec	Model:	SMWireless							
	Transmit mode :	wireless ASK transmit							
	Quiescent current:	$\leq 0.1\mu A$							
	Operating current :	$\leq 10mA$							
	Power supply:	12V/DC							
	Operating voltage:	9V-12.5V							
	Oscillation mode:	SAW resonance							
	Modulation mode:	ASK							
	Ground experiment:	Remote control without packaging , free from 60 cm above the ground three times, remote control electric property without exception and shell without damage							
	Transmitting power	$>50M$ (use with GD-RD5)	directivity	360°					
Description	Operating frequency:	433.92MHZ	frequency error	$\pm 75KHZ$ (MAX)					
	Size:	52*40*13 (mm)							
	Key :	4KEYS							
	Power :	12V/27A*1							
	Material:	plastic	Color : Plastic						
	Key pressure:	$180 \pm 40g$							
	Storage temperature	$-10^\circ C - +60^\circ C$							
	Ambient humidity:	60%-90%(RH)							
Approval standards:	More than PET 10times								
	ISO9001:2000 FCC								
Products good /bad :		Best	Quality						
Picture									

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions:

- (1) this device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

The device meets RF Exposure requirements without any restriction.