

## RF EXPOSURE EVALUATION

According to FCC 1.1310: The criteria listed in the following table shall be used to evaluate the environment impact of human exposure to radio frequency(RF) Radiation as specified in §1.1307(b)

FCC ID: 2AF2K-WM415

### EUT Specification

EUT	EZCast Pro
<b>Frequency band (Operating)</b>	<input checked="" type="checkbox"/> WLAN: 2.412GHz ~ 2.462GHz <input type="checkbox"/> WLAN: 5.18GHz ~ 5.32GHz / 5.50GHz ~ 5.70GHz <input type="checkbox"/> WLAN: 5.745GHz ~ 5825GHz <input type="checkbox"/> Others
<b>Device category</b>	<input type="checkbox"/> Portable (<20cm separation) <input checked="" type="checkbox"/> Mobile (>20cm separation) <input type="checkbox"/> Others ____
<b>Exposure classification</b>	<input type="checkbox"/> Occupational/Controlled exposure (S = 5mW/cm <sup>2</sup> ) <input checked="" type="checkbox"/> General Population/Uncontrolled exposure (S=1mW/cm <sup>2</sup> )
<b>Antenna diversity</b>	<input type="checkbox"/> Single antenna <input checked="" type="checkbox"/> Multiple antennas <input type="checkbox"/> Tx diversity <input type="checkbox"/> Rx diversity <input type="checkbox"/> Tx/Rx diversity
<b>Max. output power</b>	11.45dBm (0.014W)
<b>Antenna gain (Max)</b>	-1.78 dBi
<b>Evaluation applied</b>	<input checked="" type="checkbox"/> MPE Evaluation <input type="checkbox"/> SAR Evaluation

Limits for Maximum Permissible Exposure(MPE)

Frequency Range(MHz)	Electric Field Strength(V/m)	Magnetic Field Strength(A/m)	Power Density(mW/cm <sup>2</sup> )	Average Time
<b>(A) Limits for Occupational/Control Exposures</b>				
<b>300-1500</b>	--	--	<b>F/300</b>	<b>6</b>
<b>1500-100000</b>	--	--	<b>5</b>	<b>6</b>
<b>(B) Limits for General Population/Uncontrol Exposures</b>				
<b>300-1500</b>	--	--	<b>F/1500</b>	<b>6</b>
<b>1500-100000</b>	--	--	<b>1</b>	<b>30</b>

## Friis transmission formula: $P_d = \frac{P_{out} * G}{4 * \pi * R^2}$

Where

$P_d$  = Power density in mW/cm<sup>2</sup>

$P_{out}$  = output power to antenna in Mw

$G$  = gain of antenna in linear scale

$\pi$  = 3.1416

$R$  = distance between observation point and center of the radiator in cm

$P_d$  the limit of MPE, 1mW/cm<sup>2</sup>. If we know the maximum gain of the antenna and total power input to the antenna, through the calculation, we will know the distance where the MPE limit is reached.

## Measurement Result

### ANT A:

Operating Mode	Channel Frequency (MHz)	Measured Power (dBm)	Tune up tolerance (dBm)	Max. Tune up Power (dBm)	Antenna Gain (dBi)	Power density at 20cm (mW/ cm <sup>2</sup> )	Power density Limits (mW/cm <sup>2</sup> )
802.11b	2412	11.45	11.45±1	12.45	-1.78	0.00232	1
	2437	11.36	11.36±1	12.36	-1.78	0.00227	1
	2462	11.37	11.37±1	12.37	-1.78	0.00228	1
802.11g	2412	10.02	10.02±1	11.02	-1.78	0.00167	1
	2437	11.23	11.23±1	12.23	-1.78	0.00221	1
	2462	9.26	9.26±1	10.26	-1.78	0.00140	1
802.11n (HT20)	2412	9.65	9.65±1	10.65	-1.78	0.00153	1
	2437	10.08	10.08±1	11.08	-1.78	0.00169	1
	2462	8.66	8.66±1	9.66	-1.78	0.00122	1
802.11n (HT40)	2422	7.65	7.65±1	8.65	-1.78	0.00097	1
	2437	7.28	7.28±1	8.28	-1.78	0.00089	1
	2452	6.50	6.50±1	7.50	-1.78	0.00074	1

**ANT B:**

Operating Mode	Channel Frequency (MHz)	Measured Power (dBm)	Tune up tolerance (dBm)	Max. Tune up Power (dBm)	Antenna Gain (dBi)	Power density at 20cm (mW/ cm <sup>2</sup> )	Power density Limits (mW/cm <sup>2</sup> )
802.11b	2412	8.62	8.62±1	9.62	-1.78	0.00121	1
	2437	8.43	8.43±1	9.43	-1.78	0.00116	1
	2462	9.06	9.06±1	10.06	-1.78	0.00134	1
802.11g	2412	8.22	8.22±1	9.22	-1.78	0.00110	1
	2437	10.23	10.23±1	11.23	-1.78	0.00175	1
	2462	8.86	8.86±1	9.86	-1.78	0.00128	1
802.11n (HT20)	2412	6.96	6.96±1	7.96	-1.78	0.00083	1
	2437	9.09	9.09±1	10.09	-1.78	0.00135	1
	2462	7.81	7.81±1	8.81	-1.78	0.00100	1
802.11n (HT40)	2422	5.74	5.74±1	6.74	-1.78	0.00062	1
	2437	6.30	6.30±1	7.30	-1.78	0.00071	1
	2452	5.86	5.86±1	6.86	-1.78	0.00064	1

Antenna A Gain= -1.78 dBi

Antenna B Gain= -1.78 dBi

Array Gain= 1.23 dBi= GANT+10\*log(NANT)dBi

Operating Mode	Channel Frequency (MHz)	ANT A Power density at 20cm (mW/ cm <sup>2</sup> )	ANT B Power density at 20cm (mW/ cm <sup>2</sup> )	Power density at 20cm (mW/ cm <sup>2</sup> )	Power density Limits (mW/cm <sup>2</sup> )
802.11n (HT20)	2412	0.00153	0.00083	0.00236	1
	2437	0.00169	0.00135	0.00304	1
	2462	0.00122	0.00100	0.00222	1
802.11n (HT40)	2422	0.00097	0.00062	0.00159	1
	2437	0.00089	0.00071	0.00160	1
	2452	0.00074	0.00064	0.00138	1