



HB6351 说明书 (helllobaby)

说明书为折叠式
尺寸: 540*120MM
材质: 100g双胶纸 (彩色)
版本: V1.0
类型: 环保

 <p>HelloBaby® User Manual 2.4GHz Digital Wireless Video Baby Monitor</p> <p>Model: HB6351</p> <p>The pictures are for reference only, please subject to practicality.</p> <p>www.helllobaby.net.cn service@helllobaby.net.cn</p>	<p>120.00 mm</p> <p>540.00 mm</p> <p>Thank you for purchasing the HB6351 Baby Monitor. With our baby monitor, you could see and hear your baby sleeping or playing in their room anytime.</p> <p>Please retain your original dated sales receipt for your records. For warranty service of your product, you will need to provide a copy of your dated sales receipt to confirm warranty status. Registration is not required for warranty coverage.</p> <p>2. WARRANTY TERMS We offer one-year warranty from the original purchase date against defects in workmanship and materials. If you have warranty or support issues, please contact our after-sales service via email.</p> <p>3. SAFETY INSTRUCTIONS CAUTION: Keep the device away from children. The units do not appear to operate normally or exhibits a distinct change in performance. The units have been dropped or the enclosure damaged.</p> <p>4. READ AND KEEP INSTRUCTIONS All the safety and operating instructions for structures should be read before the baby monitor is operated. This product cannot replace responsible adult supervision.</p> <p>Water and moisture: This product is not designed to be exposed to water or moisture. Do not expose the baby monitor to rain or water. Do not drop the baby monitor into water. Do not allow liquid to get into the baby monitor. If liquid does get into the baby monitor, turn it off immediately and remove the battery. Do not use the baby monitor until it has completely dried.</p> <p>DO NOT: Use the appliance if the cord or plug is damaged. If your baby monitor is not working properly, do not attempt to repair or adjust any of the electrical or mechanical functions of the unit.</p> <p>Ventilation: This baby monitor should not be used on a bed, sofa, rug or similar surface that may block the ventilation openings, or be placed in an enclosed area such as a bookcase or closet. Keep away from sources of heat: This unit should not be exposed to direct heat sources such as a radiator, heater, stove or other appliance that emits heat. The unit must not be placed in direct sunlight.</p> <p>Power source: The power adapter can only be used with the AC power adapters included in this package (rated 5V DC 1A).</p> <p>Damaging require service: This unit should be serviced by qualified personnel only when: Objects have fallen or liquid has been spilled onto the product; The units have been exposed to rain;</p>	<p>5.3 INFRARED NIGHT VISION (AUTOMATIC) The infrared night vision function allows the camera to pick up images in dark or low light conditions. In this mode, only black and white images will be displayed on the screen. The infrared night vision range is 10m (32ft) away from object. The camera is in night vision mode, the wireless unit is 6ft (2m) away from object.</p> <p>6. PRODUCT OVERVIEW</p> <p>6.1 ICONS OVERVIEW:</p>  <p>6.2 PARENT UNIT OVERVIEW:</p>  <p>6.3 BABY UNIT OVERVIEW:</p>  <p>7. KEY OPERATION</p> <p>7.1 TURN ON THE BABY MONITOR 1. Press the power key and hold the power key for 3 seconds to turn on/off the parent unit. 2. Press the / / / key to enter the main menu; Press to select the camera icon is selected by red box; Press the key to enter the sub-menu; Then press key to select your desired camera.</p> <p>4. PRESS THE KEY TO SELECT THEN PRESS KEY</p> <p>5.2 TURN ON THE PARENT UNIT 1. Insert the DC power adapter into the DC jack in the side of the parent unit; 2. Insert the other end of the power adapter into a suitable electrical outlet; 3. Press and hold the power key 3 seconds on the side of the parent unit; 4. Once parent unit is on, the power LED will light and the image will display on the LCD screen.</p> <p>6. ONCE PAIRED, SUCCESSFUL PAIRING shows on the LCD screen; 7. Press the key above steps.</p> <p>8.1 ADD CAMERA 1. Press the key and the menu will pop up; 2. Press the / / key until the camera icon is selected by red box; 3. Press the key to enter into sub-menu; Then press key to select your desired camera;</p> <p>4. PRESS THE KEY TO SELECT THEN PRESS KEY</p> <p>5.3 DISPLAY BRIGHTNESS 1. Press the key then the menu will pop up; 2. Press the / / key until the volume icon is selected by red box; 3. Press the key to enter into sub-menu;</p> <p>4. PRESS THE KEY TO SELECT THE DESIRED BRIGHTNESS LEVEL FROM LEVEL 1 ~ 5.</p> <p>8.2 LANGUAGE SETTING 1. Press the key then the menu will pop up; 2. Press the / / key until the language icon is selected by red box; 3. Press the key to enter into sub-menu;</p> <p>4. PRESS THE / / key to select one of the 8 available lullabies, you can pick single language or all languages (playback JS or stop JS).</p> <p>5. PRESS KEY TO CONFIRM.</p> <p>8.3 DISPLAY VOLUME 1. Press the key then the menu will pop up; 2. Press the / / key until the brightness icon is selected by red box; 3. Press the key to enter into sub-menu;</p> <p>4. PRESS THE / / key to select the desired brightness level from level 1 ~ 5.</p> <p>8.4 TEMPERATURE SETTING 1. Press the key then the menu will pop up; 2. Press the / / key until the temperature icon is selected by red box; 3. Press the key to enter into sub-menu;</p> <p>4. PRESS THE / / key to select the or for setting temperature unit.</p> <p>5. PRESS KEY TO CONFIRM.</p> <p>Note: The detected temperature range is 0~40°C.</p>	<p>8.5 VOX SETTING 1. Press the key to control the sound activation of your baby unit. If there is no sound around the baby unit within 30 seconds, it will stop audio transmission and turn off the screen of the parent unit. When the baby unit detects any sounds louder than the sensitivity level, it will start transmitting the signal to the parent unit again and turn on the screen of the parent unit. To change the VOX level, please follow the below instructions: 1. Press the / / key to select for turning on alarm function; Press key to confirm; 2. Press the / / key to select for turning off alarm function; Press key to confirm; 3. Press the / / key to adjust the VOX level when is selected; 4. Press / / key to adjust the VOX level when is selected; 5. Press / / key to exit.</p> <p>Note: The high temperature alarm default setting is 35 °C, and the low temperature alarm default setting is 8 °C. When the temperature goes above or below the settings, the temperature icon will display on the screen. It will alert user by beeps. Press any key on the screen to stop the alarm and the screen will display again.</p> <p>8.6 LULLABY SETTING 1. You can switch the baby unit to play by selecting gentle lullaby from the Camera unit. 2. Press the key to enter into sub-menu; Then press key to select the language you need; 3. Press the key to enter into sub-menu; Then press key to select the language you need; 4. Press key to confirm;</p> <p>8.7 TECHNICAL DATA</p> <table border="1" style="width: 100%; border-collapse: collapse;"> <tr> <td style="width: 10%;">Frequency</td> <td style="width: 90%;">2412MHz~2460MHz</td> </tr> <tr> <td>Power Adapter</td> <td>Parent Unit: Input: 100-240VAC 50/60Hz Output: 5V DC 1A Camera Unit: Input: 100-240VAC 50/60Hz Output: 5V DC 1A</td> </tr> <tr> <td>Operating Range</td> <td>Up to 1000ft (300m) outdoor (line of sight) Up to 655ft (50m) indoor</td> </tr> <tr> <td>Display</td> <td>5.0" Diagonal TFT LCD</td> </tr> <tr> <td>Battery/Farent Unit</td> <td>Li-ion 3.7V 2000mAh (7.4Wh)</td> </tr> <tr> <td>Battery Life</td> <td>Up to 8 hours</td> </tr> <tr> <td>Maximum power</td> <td><10dBm</td> </tr> <tr> <td>Operation environment</td> <td>Operation Temperature: +32°F~+104°F (0°C~40°C) Battery Charging Temperature: +50°F~+104°F (10°C~40°C)</td> </tr> <tr> <td>Relative Humidity</td> <td>25%~85%</td> </tr> </table>	Frequency	2412MHz~2460MHz	Power Adapter	Parent Unit: Input: 100-240VAC 50/60Hz Output: 5V DC 1A Camera Unit: Input: 100-240VAC 50/60Hz Output: 5V DC 1A	Operating Range	Up to 1000ft (300m) outdoor (line of sight) Up to 655ft (50m) indoor	Display	5.0" Diagonal TFT LCD	Battery/Farent Unit	Li-ion 3.7V 2000mAh (7.4Wh)	Battery Life	Up to 8 hours	Maximum power	<10dBm	Operation environment	Operation Temperature: +32°F~+104°F (0°C~40°C) Battery Charging Temperature: +50°F~+104°F (10°C~40°C)	Relative Humidity	25%~85%	<p>10. TROUBLE SHOOTING</p> <p>No reception on the monitor</p> <ul style="list-style-type: none"> * The power adapters may not be properly connected; * Confirm that the camera and monitor are ON; * Camera may be far away from the monitor; * Camera and monitor are not paired. Please follow PAIRING instructions; * Move the monitor closer to the camera; * The camera or monitor may be placed too close to many metal objects; * Other electronic devices may be interfering with the signal; * Check the connection between the camera and monitor. <p>Interference or poor reception</p> <ul style="list-style-type: none"> * Move the monitor closer to the camera; * The camera or monitor may be placed too close to many metal objects; * Other electronic devices may be interfering with the signal; * Check the connection between the camera and monitor. <p>Audio feedback (high pitch noise)</p> <ul style="list-style-type: none"> * The camera or monitor may be placed too close; * The volume on the monitor may be set too high; <p>Frozen Picture on Screen</p> <ul style="list-style-type: none"> * Reboot the baby unit (plug out the adapter, then plug it into the back of the monitor again); * Press the RESET key at the back of parent unit. <p>11. MAINTENANCE</p> <p>Clean your baby monitor with a slightly damp or anti-static cloth.</p> <p>12. REPAIR OR REPAIR PRODUCT</p> <p>DO NOT TRY TO REPAIR OR ADJUST ANY OF THE ELECTRICAL OR MECHANICAL FUNCTIONS OF THE DEVICE.</p> <p>REMEMBER TO DISPOSE OF THE PRODUCT IN AN ENVIRONMENTALLY RESPONSIBLE WAY.</p> <p>FOR PROPER COLLECTION AND PROCESSING OF THESE PRODUCTS, PLEASE REFER TO THE COLLECTION POINTS DESIGNATED BY LOCAL AUTHORITIES. YOU CAN ALSO CONTACT THE STORE WHERE YOU PURCHASED THE PRODUCT.</p> <p>IMPROPER OR UNCORRECT USE OF BATTERIES MAY CAUSE CORROSION OR BATTERY LEAKAGE, WHICH COULD CAUSE PERSONAL INJURY OR DAMAGE TO PROPERTY. USE ONLY THE TYPES OF BATTERIES THAT ARE APPROVED FOR USE IN THIS DEVICE.</p> <p>CAUTION: RISK OF FIRE AND BURNS. DO NOT CRUSH, HEAT ABOVE 45°C OR INCINERATE.</p> <p>DISPOSAL OF BATTERIES: IF A BATTERY IS EXPOSED TO HIGH TEMPERATURE, IT MAY EXPLODE OR LEAK FLAMMABLE LIQUID OR GAS.</p> <p>THE DEVICE DOES NOT MEET THE EXISTING EMISSION LIMITS IN SECTION 2.5 OF RSS 102 AND COMPLIANCE WITH RSS 102 RF EXPOSURE USERS CAN OBTAIN CANADIAN INFORMATION ON RF EXPOSURE AND COMPLIANCE OF APPAREL AND ACCESSORIES WITH RSS 102 RF EXPOSURE. THE LATTER CAN BE FOUND AT THE WEBSITE: WWW.CTIA.CA.</p> <p>THE APPAREL AND ACCESSORIES COMPLY WITH INDUSTRY CANADA RADIATION EXPOSURE LIMITS SET FORTH FOR UNCONTROLLED ENVIRONMENTS.</p> <p>CERTIFICATION: THE DEVICE COMPLIES WITH INDUSTRY CANADA'S RADIATION EXPOSURE LIMITS FOR UNCONTROLLED ENVIRONMENTS.</p> <p>DISCLAIMER: THE DEVICE DOES NOT MEET THE EXISTING EMISSION LIMITS IN SECTION 2.5 OF RSS 102 RF EXPOSURE. THE LATTER CAN BE FOUND AT THE WEBSITE: WWW.CTIA.CA.</p> <p>RISK GROUP 1</p> <p>WARNING: Emitted from this product. Do not stare at operating lamp.</p> <p>Product tested against EN62471</p>
Frequency	2412MHz~2460MHz																					
Power Adapter	Parent Unit: Input: 100-240VAC 50/60Hz Output: 5V DC 1A Camera Unit: Input: 100-240VAC 50/60Hz Output: 5V DC 1A																					
Operating Range	Up to 1000ft (300m) outdoor (line of sight) Up to 655ft (50m) indoor																					
Display	5.0" Diagonal TFT LCD																					
Battery/Farent Unit	Li-ion 3.7V 2000mAh (7.4Wh)																					
Battery Life	Up to 8 hours																					
Maximum power	<10dBm																					
Operation environment	Operation Temperature: +32°F~+104°F (0°C~40°C) Battery Charging Temperature: +50°F~+104°F (10°C~40°C)																					
Relative Humidity	25%~85%																					