



KDP HMI 10  
PCBA Usage Guide

*Version 1.0, 8/2021*

i. REVISION HISTORY

---

V1.0	Initial Release based on internal specification	20210818
------	---	----------

## 1. INTRODUCTION / OVERVIEW

The KDP HMI 10 is a custom PCBA, based on a Quad-core Cortex-A53 with 1GB LPDDR2 DRAM for use as a human-machine interface (HMI) controller.

An HDMI-to-MIPI display circuit is added for display panel connection.

USB Hub provide 4 USB Type A ports, touchscreen, along with custom cellular and camera connections.

### 1.1. SPECIFICATIONS

#### PROCESSING CORE

- 64-Bit, Quad-core ARM A53 SoC
- Heat sink for passive heat dissipation
- 1GB LPDDR2 DRAM
- WiFi/BT, 2.4GHZ, 802.11bgn

#### INPUT POWER

- Voltage: 12V +/- 10% DC Input
- Power: 12W minimum, 18W recommended
- Minimum recommended wattage includes:
  - All onboard devices
  - 2.2W for the display
  - 2W for added peripheral devices installed onto the connectors

#### ENVIRONMENTAL

- Ambient Operating Temperature Range: -20°C to 70°C\*, non-condensing humidity
- Storage Temperature Range: -40°C to 85°C, non-condensing humidity

*\*Note: depending on processor workload, CPU throttling may occur above 50C ambient*

#### DIMENSIONING & MOUNTING

- PCBA Dimensions: 146mm W x 75mm D x 20mm H (mating cables will require additional height and depth)
- Designed to mount to plate attached to back of custom touchscreen display

#### BOOT IMAGE / STORAGE MEDIUM

- 16GB (minimum) eMMC onboard

#### LED INDICATORS

- Onboard Power / Activity LED
  - PWR: Green LED indicates valid power
  - ACT: Yellow flashing indicates disk activity by default, but configurable
- Onboard User LEDs
  - Green
  - Controlled from user code using GPIO (LED1 and LED2)

## USB 2.0

A USB 2.0 High-Speed Hub provides seven (7) downstream connections. All downstream ports share a single USB 2.0 High-Speed connection back to the processor. This limits maximum shared bandwidth of all USB devices to ~250Mbit/s. All USB connections include ESD protection.

## DISPLAY CONNECTION

The display connection consists of several separate circuits:

- HDMI-to-MIPI bridge chip provides the signaling for the display
- LED backlight driver with PWM brightness control
- USB touchscreen interface
- I2C interface for ambient light sensor (ALS) connection

## 2. REFERENCES

### 2.1. COMPLIANCE

#### FCC COMPLIANCE STATEMENT

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

#### ISED COMPLIANCE STATEMENT

This device contains licence-exempt transmitter(s)/receiver(s) that comply with Innovation, Science and Economic Development Canada's licence-exempt RSS(s). Operation is subject to the following two conditions:

- (1) This device may not cause interference.
- (2) This device must accept any interference, including interference that may cause undesired operation of the device.

L'émetteur/récepteur exempt de licence contenu dans le présent appareil est conforme aux CNR d'Innovation, Sciences et Développement économique Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes :

- (1) L'appareil ne doit pas produire de brouillage;
- (2) L'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.

#### RADIATION EXPOSURE STATEMENT

This equipment complies with FCC/IC RSS-102 radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with minimum distance 20 cm between the radiator and your body.

Cet équipement est conforme aux limites d'exposition aux radiations FCC/IC CNR-102 établies pour un environnement non contrôlé. Cet équipement doit être installé et utilisé avec une distance minimale de 20 cm entre le radiateur et votre corps.

## **2.2. TRADEMARKS & NOTICES**

### **NOTICES**

The provided software and firmware are subject to the following disclaimer.

DISCLAIMER. THIS SOFTWARE IS PROVIDED BY THE COPYRIGHT HOLDERS AND CONTRIBUTORS "AS IS" AND ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE ARE DISCLAIMED. IN NO EVENT SHALL THE COPYRIGHT OWNER OR CONTRIBUTORS BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.