

RF EXPOSURE EVALUATION METHOD

FCC ID: 2AFAX-BDSXR

SAR Test Exclusion Thresholds for 100 MHz $\,$ - $\,$ 6 GHz and \leq 50 mm

Approximate SAR Test Exclusion Power Thresholds at Selected Frequencies and Test Separation Distances are illustrated in the following Table.

The 1-g and 10-g SAR test exclusion thresholds for 100 MHz to 6 GHz at test separation distances \leq 50 mm are determined by:

[(max. power of channel, including tune-up tolerance, mW)/(min. test separation distance, mm)] • $[\sqrt{f(GHz)}] \leq 3.0$ for 1-g SAR and ≤ 7.5 for 10-g extremity SAR,where f(GHz) is the RF channel transmit frequency in GHz

Power and distance are rounded to the nearest mW and mm before calculation The result is rounded to one decimal place for comparison

The test exclusions are applicable only when the minimum test separation distance is ≤ 50 mm and for transmission frequencies between 100 MHz and 6 GHz. When the minimum test separation distance is < 5 mm, a distance of 5 mm is applied to determine SAR test exclusion.

Maximum measured transmitter power.

ΒT

| GFSK | | | | | | |
|--------------|-----------|-------------------|-------------------|--|--|--|
| Test Channel | Frequency | Peak Output Power | Peak Output Power | | | |
| | (MHz) | (dBm) | (mW) | | | |
| CH00 | 2402 | -6.209 | 0.239 | | | |
| CH39 | 2441 | -7.360 | 0.184 | | | |
| CH78 | 2480 | -6.997 | 0.200 | | | |
| π /4-DQPSK | | | | | | |
| Test Channel | Frequency | Peak Output Power | Peak Output Power | | | |
| | (MHz) | (dBm) | (mW) | | | |
| CH00 | 2402 | -8.284 | 0.148 | | | |
| CH39 | 2441 | -7.242 | 0.189 | | | |
| CH78 | 2480 | -6.385 | 0.230 | | | |
| | | 8DPSK | | | | |
| Test Channel | Frequency | Peak Output Power | Peak Output Power | | | |
| | (MHz) | (dBm) | (mW) | | | |
| CH00 | 2402 | -6.124 | 0.244 | | | |
| CH39 | 2441 | -6.134 | 0.244 | | | |
| CH78 | 2480 | -6.800 | 0.209 | | | |

Remark:

The 1-g and 10-g SAR test exclusion thresholds for 100 MHz to 6 GHz at test separation distances \leq 50 mm are determined by:

[(max. power of channel, including tune-up tolerance, mW)/(min. test

separation distance,mm)] • $[\sqrt{f(GHz)}]$



| Test Channel | [(max. power of channel, mW) | (min. test separation distance,mm)] | [f(GHz)] | Result | Limit | | | | |
|-----------------|---------------------------------------|-------------------------------------------|----------|--------|-------|--|--|--|--|
| GFSK | | | | | | | | | |
| CH00 | 0.239 | 5 | 2.402 | 0.074 | 3 | | | | |
| CH39 | 0.184 | 5 | 2.441 | 0.057 | 3 | | | | |
| CH78 | 0.200 | 5 | 2.480 | 0.063 | 3 | | | | |
| π /4-DQPSK | | | | | | | | | |
| CH00 | 0.148 | 5 | 2.402 | 0.046 | 3 | | | | |
| CH39 | 0.189 | 5 | 2.441 | 0.059 | 3 | | | | |
| CH78 | 0.230 | 5 | 2.480 | 0.072 | 3 | | | | |
| | 8DPSK | | | | | | | | |
| CH00 | 0.244 | 5 | 2.402 | 0.076 | 3 | | | | |
| CH39 | 0.244 | 5 | 2.441 | 0.076 | 3 | | | | |
| CH78 | 0.209 | 5 | 2.480 | 0.066 | 3 | | | | |

The test Result is less than 3.0 for 1-g SAR and \leq 7.5 for 10-g extremity SAR.

Conclusion: No SAR is required.