

FCC SAR Test Report

APPLICANT : Xiaomi Communications Co., Ltd.
EQUIPMENT : Mobile Phone
BRAND NAME : Xiaomi
MODEL NAME : 2306EPN60G
FCC ID : 2AFZZN60G
STANDARD : FCC 47 CFR Part 2 (2.1093)

We, Sporton International Inc. (Shenzhen), would like to declare that the tested sample has been evaluated in accordance with the test procedures given in 47 CFR Part 2.1093 and FCC KDB and has been in compliance with the applicable technical standards.

The test results in this report apply exclusively to the tested model / sample. Without written approval of Sporton International Inc. (Shenzhen), the test report shall not be reproduced except in full.



Approved by: Si Zhang

Sporton International Inc. (Shenzhen)
1/F, 2/F, Bldg 5, Shiling Industrial Zone, Xinwei Village, Xili, Nanshan, Shenzhen, 518055
People's Republic of China



Table of Contents

1. Statement of Compliance 4
2. Administration Data 6
3. Guidance Applied 6
4. Equipment Under Test (EUT) Information 7
4.1 General Information 7
4.2 General LTE SAR Test and Reporting Considerations 9
4.3 General 5G NR SAR Test and Reporting Considerations 13
5. Proximity Sensor Triggering Test 17
6. RF Exposure Limits 19
6.1 Uncontrolled Environment 19
6.2 Controlled Environment 19
7. Specific Absorption Rate (SAR) 20
7.1 Introduction 20
7.2 SAR Definition 20
8. System Description and Setup 21
8.1 E-Field Probe 22
8.2 Data Acquisition Electronics (DAE) 22
8.3 Phantom 23
8.4 Device Holder 24
9. Measurement Procedures 25
9.1 Spatial Peak SAR Evaluation 25
9.2 Power Reference Measurement 26
9.3 Area Scan 26
9.4 Zoom Scan 27
9.5 Volume Scan Procedures 27
9.6 Power Drift Monitoring 27
10. Test Equipment List 28
11. System Verification 29
11.1 Tissue Simulating Liquids 29
11.2 Tissue Verification 29
11.3 System Performance Check Results 31
12. RF Exposure Positions 33
12.1 Ear and handset reference point 33
12.2 Definition of the cheek position 34
12.3 Definition of the tilt position 35
12.4 Body Worn Accessory 36
12.5 Product Specific 10g SAR Exposure 37
12.6 Wireless Router 37
13. Conducted RF Output Power (Unit: dBm) 38
14. Antenna Location 55
15. SAR Test Results 56
15.1 Head SAR 59
15.2 Hotspot SAR 78
15.3 Body Worn Accessory SAR 94
15.4 Product specific 10g SAR 106
15.5 Repeated SAR Measurement 112
15.6 NR Linearity Data Analysis 113
16. Simultaneous Transmission Analysis 117
16.1 Head Exposure Conditions 118
16.2 Hotspot Exposure Conditions 124
16.3 Body-Worn Accessory Exposure Conditions 132
16.4 Product specific 10g SAR Exposure Conditions 136
17. Uncertainty Assessment 144
18. References 145
Appendix A. Plots of System Performance Check
Appendix B. Plots of High SAR Measurement
Appendix C. DASY Calibration Certificate
Appendix D. Test Setup Photos
Appendix E. Conducted RF Output Power Table

1. Statement of Compliance

The maximum results of Specific Absorption Rate (SAR) found during testing for **Xiaomi Communications Co., Ltd., Mobile Phone, 2306EPN60G**, are as follows.

Highest 1g SAR Summary						
Equipment Class	Frequency Band		Head (Separation 0mm)	Hotspot (Separation 10mm)	Body-worn (Separation 15mm)	Highest Simultaneous Transmission 1g SAR (W/kg)
			1g SAR (W/kg)			
Licensed	GSM	GSM850	1.06	0.52	0.31	1.59
		GSM1900	0.95	0.88	0.36	
	WCDMA	WCDMA V	1.01	0.54	0.34	
		WCDMA IV	1.08	1.09	0.70	
		WCDMA II	0.96	0.98	0.99	
	LTE	LTE Band 12/17	0.80	0.35	0.20	
		LTE Band 13	1.05	0.59	0.33	
		LTE Band 26/5	0.97	0.68	0.32	
		LTE Band 4	1.00	0.79	0.75	
		LTE Band 66	1.09	0.87	0.72	
		LTE Band 2	1.09	1.04	0.84	
		LTE Band 7	1.04	0.69	0.79	
		LTE Band 41/38	1.04	0.73	0.65	
	5G NR	FR1 n5	0.96	0.65	0.39	
		FR1 n66	1.08	0.70	0.84	
		FR1 n7	1.09	0.60	1.01	
		FR1 n41/38	1.03	0.53	1.09	
FR1 n77/78		1.09	0.68	0.86		
DTS	WLAN	2.4GHz WLAN	0.92	0.38	0.21	1.59
NII		5GHz WLAN	1.07	0.42	0.49	1.59
DSS	Bluetooth	2.4GHz Bluetooth	0.14	0.10	<0.10	1.59
Highest 10g SAR Summary						
Equipment Class	Frequency Band		Product Specific 10g SAR (W/kg) (Separation 0mm)			Highest Simultaneous Transmission 10g SAR (W/kg)
Licensed	WCDMA	WCDMA IV	2.42			3.96
		WCDMA II	2.53			
	LTE	LTE Band 4	2.44			
		LTE Band 66	2.45			
		LTE Band 2	2.43			
		LTE Band 7	2.27			
		LTE Band 41/38	2.19			
	5G NR	FR1 n66	2.54			
		FR1 n7	2.58			
		FR1 n41/38	2.54			
FR1 n77/78		1.66				
NII	WLAN	5GHz WLAN	2.51			3.96
Date of Testing:			2023/5/13 ~ 2023/6/13			



Remark:

1. This device supports LTE B5 / B17 / B38 and B26 / B12 / B41. Since the supported frequency span for LTE B5 / B17 / B38 falls completely within the supports frequency span for LTE B26 / B12 / B41, both LTE bands have the same target power, and both LTE bands share the same transmission path; therefore, SAR was only assessed for LTE B26 / B12 / B41.
2. This device supports 5GNR n38/n78 and n41/77. Since the supported frequency span for 5GNR n38/n78 falls completely within the supports frequency span for n41/n77, both 5GNR bands have the same target power, and both 5GNR bands share the same transmission path; therefore, SAR was only assessed for n41/n77.

Declaration of Conformity:

The test results with all measurement uncertainty excluded are presented in accordance with the regulation limits or requirements declared by manufacturers.

Comments and Explanations:

The declared of product specification for EUT presented in the report are provided by the manufacturer, and the manufacturer takes all the responsibilities for the accuracy of product specification.

This device is in compliance with Specific Absorption Rate (SAR) for general population/uncontrolled exposure limits (1.6 W/kg for Partial-Body 1g SAR, 4.0 W/kg for Product Specific 10g SAR) specified in FCC 47 CFR part 2 (2.1093) and ANSI/IEEE C95.1-1992, and had been tested in accordance with the measurement methods and procedures specified in IEEE 1528-2013 and FCC KDB publications.



2. Administration Data

Sporton International Inc. (Shenzhen) is accredited to ISO/IEC 17025:2017 by American Association for Laboratory Accreditation with Certificate Number 5145.01.

Table with 4 columns: Test Firm, Test Site Location, Test Site No., and FCC Test Firm Registration No. (with sub-columns for Sporton Site No., FCC Designation No., and FCC Test Firm Registration No.).

Table with 2 columns: Applicant Company Name and Address.

Table with 2 columns: Manufacturer Company Name and Address.

3. Guidance Applied

The Specific Absorption Rate (SAR) testing specification, method, and procedure for this device is in accordance with the following standards:

- List of standards including FCC 47 CFR Part 2 (2.1093), ANSI/IEEE C95.1-1992, IEEE 1528-2013, FCC KDB 865664 D01 SAR Measurement 100 MHz to 6 GHz v01r04, FCC KDB 865664 D02 SAR Reporting v01r02, FCC KDB 447498 D01 General RF Exposure Guidance v06, FCC KDB 648474 D04 SAR Evaluation Considerations for Wireless Handsets v01r03, FCC KDB 248227 D01 802.11 Wi-Fi SAR v02r02, FCC KDB 616217 D04 SAR for laptop and tablets v01r02, FCC KDB 941225 D01 3G SAR Procedures v03r01, FCC KDB 941225 D05 SAR for LTE Devices v02r05, FCC KDB 941225 D05A Rel.10 LTE SAR Test Guidance v01r02, FCC KDB 941225 D06 Hotspot Mode SAR v02r01

4. Equipment Under Test (EUT) Information

4.1 General Information

Product Feature & Specification	
Equipment Name	Mobile Phone
Brand Name	Xiaomi
Model Name	2306EPN60G
FCC ID	2AFZZN60G
IMEI Code	IMEI 1: 864825060086241 IMEI 2: 864825060086258
Wireless Technology and Frequency Range	GSM850: 824 MHz ~ 849 MHz GSM1900: 1850 MHz ~ 1910 MHz WCDMA Band II: 1850 MHz ~ 1910 MHz WCDMA Band IV: 1710 MHz ~ 1755 MHz WCDMA Band V: 824 MHz ~ 849 MHz LTE Band 2: 1850 MHz ~ 1910 MHz LTE Band 4: 1710 MHz ~ 1755 MHz LTE Band 5: 824 MHz ~ 849 MHz LTE Band 7: 2500 MHz ~ 2570 MHz LTE Band 12: 699 MHz ~ 716 MHz LTE Band 13: 777 MHz ~ 787 MHz LTE Band 17: 704 MHz ~ 716 MHz LTE Band 26: 814 MHz ~ 849 MHz LTE Band 38: 2570 MHz ~ 2620 MHz LTE Band 41: 2496 MHz ~ 2690 MHz LTE Band 66: 1710 MHz ~ 1780 MHz 5G NR n5: 824 MHz ~ 849 MHz 5G NR n7: 2500 MHz ~ 2570 MHz 5G NR n66: 1710 MHz ~ 1780 MHz 5G NR n38 : 2570 MHz ~ 2620 MHz 5G NR n41 : 2496 MHz ~ 2690 MHz 5G NR n77: 3450 MHz ~ 3550 MHz, 3700 MHz ~ 3980 MHz 5G NR n78: 3450 MHz ~ 3550 MHz, 3700 MHz ~ 3800 MHz WLAN 2.4GHz Band: 2412 MHz ~ 2462 MHz WLAN 5.2GHz Band: 5180 MHz ~ 5240 MHz WLAN 5.3GHz Band: 5260 MHz ~ 5320 MHz WLAN 5.5GHz Band: 5500 MHz ~ 5720 MHz WLAN 5.8GHz Band: 5745 MHz ~ 5825 MHz Bluetooth: 2402 MHz ~ 2480 MHz NFC: 13.56 MHz
Mode	GSM/GPRS/EGPRS RMC/AMR 12.2Kbps HSDPA HSUPA DC-HSDPA HSPA+(16QAM uplink is supported) LTE: QPSK, 16QAM, 64QAM, 256QAM 5G NR : CP-OFDM / DFT-s-OFDM, PI/2 BPSK, QPSK, 16QAM, 64QAM, 256QAM WLAN 2.4GHz 802.11b/g/n HT20 WLAN 2.4GHz 802.11ax HE20 WLAN 5GHz 802.11a/n HT20/HT40 WLAN 5GHz 802.11ac/ax VHT20/VHT40/VHT80/HE20/HE40/HE80 Bluetooth BR/EDR/LE NFC: ASK
HW Version	P2.0
SW Version	MIUI 14
GSM / (E)GPRS Transfer mode	Class B – EUT cannot support Packet Switched and Circuit Switched Network simultaneously but can automatically switch between Packet and Circuit Switched Network.
EUT Stage	Identical Prototype

Remark:

1. This device supports VoIP in GPRS, EGPRS, WCDMA and LTE (e.g. for 3rd-party VoIP), LTE supports VoLTE operation.
2. This device 2.4GHz WLAN support hotspot operation and Bluetooth support tethering applications.
3. This device 5.2GHz WLAN/5.8GHz WLAN support hotspot operation, and 5.2GHz WLAN/5.8GHz WLAN supports WiFi Direct (GC/GO), and 5.3GHz / 5.5GHz supports WiFi Direct (GC only).
4. The 2.4GHz/5GHz WLAN can transmit in SISO and MIMO antenna mode.
5. This device does not support DTM operation and supports GPRS/EGPRS mode up to multi-slot class 12.
6. For dual SIM card mobile has two SIM slots and supports dual SIM dual standby. The WWAN radio transmission will be enabled by either one SIM at a time (single active). After pre-scan two SIM cards power, we found test result of the SIM1 was the worse, so we chose SIM1 slot to perform all tests.
7. The device implements Proximity sensors/receiver detect mechanism/hotspot trigger reduced power for the power management for SAR compliance at different exposure conditions (head, body-worn, hotspot, extremity). The device will invoke corresponding work scenarios power level base on frequency bands/antennas, which can refer to appendix E. power table.
8. For WLAN when transmit simultaneous with WWAN, power reduction will be activated to head, Body, hotspot and extremity exposure conditions.
9. 5GNR n77/n78 supports HPUE mode, HPUE power and SAR testing performed separately.
10. 5GNR n77/n78 HPUE with higher power. For HPUE power is higher than power class 3 but with lower duty cycle, the maximum average power for class 2 and class 3 is almost the same, so we chose power class 3 full SAR testing and power class 2 verify the worst case of power class 3 SAR.
11. For 5GNR n77/n78 HPUE, 5GNR n77/n78 PC2 Maximum Duty Cycle is 50%, using FTM (Factory Test Mode) with 50% duty cycle is considered during SAR testing. For 5G NR other bands, using FTM to perform SAR with default 100% transmission.
12. 5G NR supports CP-OFDM and DFT-s-OFDM modulation, for DFT-s-OFDM power is higher than CP-OFDM, so only show DFT-s-OFDM power table and chose DFT-s-OFDM to perform SAR testing.
13. For DFT-s-OFDM and CP-OFDM output power measurement reduction, according to 38.101 maximum power reduction for the CP-OFDM mode will not higher than DFT-s-OFDM mode, therefore, CP-OFDM measurement is unnecessary.
14. NSA and SA mode should perform SAR separately. For the maximum power of NSA mode is the same as SA total power level, so SA SAR can represent NSA mode SAR.
15. 5GNR NSA mode, the power level is the same as 5GNR SA mode, so 5GNR NSA mode and SA mode power table only show one time.
16. For 5GNR EN-DC mode, standalone SAR performed for 5GNR NSA band with the maximum power, EN-DC SAR summed EN-DC mode 5GNR standalone SAR and LTE standalone SAR, the result of EN-DC SAR is more conservatively.
17. The device support DBS (Dual Band Simultaneous) function, when the device WLAN 2.4GHz and WLAN 5GHz transmit at the same time the module will limit different output power for simultaneous transmission compliance.
18. There are three samples under test, sample 1 is 8+256G memory & Battery 1 & glass back cover, sample 2 is 12+256G memory & Battery 2 & PU back cover, sample 3 is 8+256G memory & Battery 1 & PU back cover, according to the difference, so chose sample 1 to perform full test.
19. This device supports 5GNR FR1 bands as following table, including NSA mode and SA mode. NSA and SA mode performed SAR separately.
20. This device has NFC function and the NFC SAR report will be separately submitted.

<5G NR>

Mode	Band	Duplex	SCS(KHz)	Bandwidths(BW)
NSA	n5	FDD	15	5, 10, 15, 20
	n7	FDD	15	5, 10, 15, 20, 25, 30, 40, 50
	n66	FDD	15	5, 10, 15, 20, 25, 30, 40
	n38	TDD	30	10, 15, 20, 25, 30, 40
	n41	TDD	30	10, 15, 20, 30, 40, 50, 60, 80, 90, 100
	n78	TDD	30	10, 15, 20, 25, 30, 40, 50, 60, 70, 80, 90, 100
SA	n5	FDD	15	5, 10, 15, 20
	n7	FDD	15	5, 10, 15, 20, 25, 30, 40, 50
	n66	FDD	15	5, 10, 15, 20, 25, 30, 40
	n38	TDD	30	10, 15, 20, 25, 30, 40
	n41	TDD	30	10, 15, 20, 30, 40, 50, 60, 70, 80, 90, 100
	n77	TDD	30	10, 15, 20, 25, 30, 40, 50, 60, 70, 80, 90, 100
	n78	TDD	30	10, 15, 20, 25, 30, 40, 50, 60, 70, 80, 90, 100

4.2 General LTE SAR Test and Reporting Considerations

Summarized necessary items addressed in KDB 941225 D05 v02r05																																																															
FCC ID	2AFZZN60G																																																														
Equipment Name	Mobile Phone																																																														
Operating Frequency Range of each LTE transmission band	LTE Band 2: 1850 MHz ~ 1910 MHz LTE Band 4: 1710 MHz ~ 1755 MHz LTE Band 5: 824 MHz ~ 849 MHz LTE Band 7: 2500 MHz ~ 2570 MHz LTE Band 12: 699 MHz ~ 716 MHz LTE Band 13: 777 MHz ~ 787 MHz LTE Band 17: 704 MHz ~ 716 MHz LTE Band 26: 814 MHz ~ 849 MHz LTE Band 38: 2570 MHz ~ 2620 MHz LTE Band 41: 2496 MHz ~ 2690 MHz LTE Band 66: 1710 MHz ~ 1780 MHz																																																														
Channel Bandwidth	LTE Band 2: 1.4MHz, 3MHz, 5MHz, 10MHz, 15MHz, 20MHz LTE Band 4: 1.4MHz, 3MHz, 5MHz, 10MHz, 15MHz, 20MHz LTE Band 5: 1.4MHz, 3MHz, 5MHz, 10MHz LTE Band 7: 5MHz, 10MHz, 15MHz, 20MHz LTE Band 12: 1.4MHz, 3MHz, 5MHz, 10MHz LTE Band 13: 5MHz, 10MHz LTE Band 17: 5MHz, 10MHz LTE Band 26: 1.4MHz, 3MHz, 5MHz, 10MHz, 15MHz LTE Band 38: 5MHz, 10MHz, 15MHz, 20MHz LTE Band 41: 5MHz, 10MHz, 15MHz, 20MHz LTE Band 66: 1.4MHz, 3MHz, 5MHz, 10MHz, 15MHz, 20MHz																																																														
uplink modulations used	QPSK / 16QAM / 64QAM / 256QAM																																																														
LTE Voice / Data requirements	Voice and Data																																																														
LTE Release Version	R16, Cat18																																																														
CA Support	Supported, Uplink and Downlink																																																														
LTE MPR permanently built-in by design	<p>Table 6.2.3-1: Maximum Power Reduction (MPR) for Power Class 1, 2 and 3</p> <table border="1"> <thead> <tr> <th rowspan="2">Modulation</th> <th colspan="6">Channel bandwidth / Transmission bandwidth (N_{RB})</th> <th rowspan="2">MPR (dB)</th> </tr> <tr> <th>1.4 MHz</th> <th>3.0 MHz</th> <th>5 MHz</th> <th>10 MHz</th> <th>15 MHz</th> <th>20 MHz</th> </tr> </thead> <tbody> <tr> <td>QPSK</td> <td>> 5</td> <td>> 4</td> <td>> 8</td> <td>> 12</td> <td>> 16</td> <td>> 18</td> <td>≤ 1</td> </tr> <tr> <td>16 QAM</td> <td>≤ 5</td> <td>≤ 4</td> <td>≤ 8</td> <td>≤ 12</td> <td>≤ 16</td> <td>≤ 18</td> <td>≤ 1</td> </tr> <tr> <td>64 QAM</td> <td>> 5</td> <td>> 4</td> <td>> 8</td> <td>> 12</td> <td>> 16</td> <td>> 18</td> <td>≤ 2</td> </tr> <tr> <td>64 QAM</td> <td>≤ 5</td> <td>≤ 4</td> <td>≤ 8</td> <td>≤ 12</td> <td>≤ 16</td> <td>≤ 18</td> <td>≤ 2</td> </tr> <tr> <td>64 QAM</td> <td>> 5</td> <td>> 4</td> <td>> 8</td> <td>> 12</td> <td>> 16</td> <td>> 18</td> <td>≤ 3</td> </tr> <tr> <td>256 QAM</td> <td colspan="6">≥ 1</td> <td>≤ 5</td> </tr> </tbody> </table>	Modulation	Channel bandwidth / Transmission bandwidth (N _{RB})						MPR (dB)	1.4 MHz	3.0 MHz	5 MHz	10 MHz	15 MHz	20 MHz	QPSK	> 5	> 4	> 8	> 12	> 16	> 18	≤ 1	16 QAM	≤ 5	≤ 4	≤ 8	≤ 12	≤ 16	≤ 18	≤ 1	64 QAM	> 5	> 4	> 8	> 12	> 16	> 18	≤ 2	64 QAM	≤ 5	≤ 4	≤ 8	≤ 12	≤ 16	≤ 18	≤ 2	64 QAM	> 5	> 4	> 8	> 12	> 16	> 18	≤ 3	256 QAM	≥ 1						≤ 5
Modulation	Channel bandwidth / Transmission bandwidth (N _{RB})						MPR (dB)																																																								
	1.4 MHz	3.0 MHz	5 MHz	10 MHz	15 MHz	20 MHz																																																									
QPSK	> 5	> 4	> 8	> 12	> 16	> 18	≤ 1																																																								
16 QAM	≤ 5	≤ 4	≤ 8	≤ 12	≤ 16	≤ 18	≤ 1																																																								
64 QAM	> 5	> 4	> 8	> 12	> 16	> 18	≤ 2																																																								
64 QAM	≤ 5	≤ 4	≤ 8	≤ 12	≤ 16	≤ 18	≤ 2																																																								
64 QAM	> 5	> 4	> 8	> 12	> 16	> 18	≤ 3																																																								
256 QAM	≥ 1						≤ 5																																																								
LTE A-MPR	In the base station simulator configuration, Network Setting value is set to NS_01 to disable A-MPR during SAR testing and the LTE SAR tests was transmitting on all TTI frames (Maximum TTI)																																																														
Spectrum plots for RB configuration	A properly configured base station simulator was used for the SAR and power measurement; therefore, spectrum plots for each RB allocation and offset configuration are not included in the SAR report.																																																														
Power reduction applied to satisfy SAR compliance	Yes, when operating in Proximity sensors/receiver/hotspot detect mechanism, head/body -worn /hotspot/extremity will trigger reduced power for some bands applied to satisfy SAR compliance, the detail please referred to section 13.																																																														
LTE Carrier Aggregation Combinations	Inter-Band and Intra-Band possible combinations and the detail power verification please referred to section 13.																																																														
LTE Carrier Aggregation Additional Information	1. This device supports LTE Carrier Aggregation (CA) in the uplink for intra-band and inter-band with two component carriers in the uplink. SAR Measurements and conducted powers were evaluated per FCC Guidance. 2. This device supports maximum of 3 carriers in the downlink and 2 carriers in the uplink.																																																														



Transmission (H, M, L) channel numbers and frequencies in each LTE band												
LTE Band 2												
	Bandwidth 1.4 MHz		Bandwidth 3 MHz		Bandwidth 5 MHz		Bandwidth 10 MHz		Bandwidth 15 MHz		Bandwidth 20 MHz	
	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)
L	18607	1850.7	18615	1851.5	18625	1852.5	18650	1855	18675	1857.5	18700	1860
M	18900	1880	18900	1880	18900	1880	18900	1880	18900	1880	18900	1880
H	19193	1909.3	19185	1908.5	19175	1907.5	19150	1905	19125	1902.5	19100	1900
LTE Band 4												
	Bandwidth 1.4 MHz		Bandwidth 3 MHz		Bandwidth 5 MHz		Bandwidth 10 MHz		Bandwidth 15 MHz		Bandwidth 20 MHz	
	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)
L	19957	1710.7	19965	1711.5	19975	1712.5	20000	1715	20025	1717.5	20050	1720
M	20175	1732.5	20175	1732.5	20175	1732.5	20175	1732.5	20175	1732.5	20175	1732.5
H	20393	1754.3	20385	1753.5	20375	1752.5	20350	1750	20325	1747.5	20300	1745
LTE Band 5												
	Bandwidth 1.4 MHz		Bandwidth 3 MHz		Bandwidth 5 MHz		Bandwidth 10 MHz		Bandwidth 15 MHz		Bandwidth 20 MHz	
	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)
L	20407	824.7	20415	825.5	20425	826.5	20450	829	20450	829	20450	829
M	20525	836.5	20525	836.5	20525	836.5	20525	836.5	20525	836.5	20525	836.5
H	20643	848.3	20635	847.5	20625	846.5	20600	844	20600	844	20600	844
LTE Band 7												
	Bandwidth 5 MHz		Bandwidth 10 MHz		Bandwidth 15 MHz		Bandwidth 20 MHz		Bandwidth 15 MHz		Bandwidth 20 MHz	
	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)
L	20775	2502.5	20800	2505	20825	2507.5	20850	2510	20850	2510	20850	2510
M	21100	2535	21100	2535	21100	2535	21100	2535	21100	2535	21100	2535
H	21425	2567.5	21400	2565	21375	2562.5	21350	2560	21350	2560	21350	2560
LTE Band 12												
	Bandwidth 1.4 MHz		Bandwidth 3 MHz		Bandwidth 5 MHz		Bandwidth 10 MHz		Bandwidth 15 MHz		Bandwidth 20 MHz	
	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)
L	23017	699.7	23025	700.5	23035	701.5	23060	704	23060	704	23060	704
M	23095	707.5	23095	707.5	23095	707.5	23095	707.5	23095	707.5	23095	707.5
H	23173	715.3	23165	714.5	23155	713.5	23130	711	23130	711	23130	711
LTE Band 13												
	Bandwidth 5 MHz				Bandwidth 10 MHz				Bandwidth 10 MHz			
	Channel #	Freq.(MHz)			Channel #	Freq.(MHz)			Channel #	Freq.(MHz)		
L	23205	779.5			23230	782			23230	782		
M	23230	782				782						
H	23255	784.5				782						
LTE Band 17												
	Bandwidth 5 MHz				Bandwidth 10 MHz				Bandwidth 10 MHz			
	Channel #	Freq.(MHz)			Channel #	Freq.(MHz)			Channel #	Freq.(MHz)		
L	23755	706.5			23780	709			23780	709		
M	23790	710			23790	710			23790	710		
H	23825	713.5			23800	711			23800	711		
LTE Band 26												
	Bandwidth 1.4 MHz		Bandwidth 3 MHz		Bandwidth 5 MHz		Bandwidth 10 MHz		Bandwidth 15 MHz		Bandwidth 20 MHz	
	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)
L	26697	814.7	26705	815.5	26715	816.5	26740	819	26765	821.5	26765	821.5
M	26865	831.5	26865	831.5	26865	831.5	26865	831.5	26865	831.5	26865	831.5
H	27033	848.3	27025	847.5	27015	846.5	26990	844	26965	841.5	26965	841.5
LTE Band 38												
	Bandwidth 5 MHz		Bandwidth 10 MHz		Bandwidth 15 MHz		Bandwidth 20 MHz		Bandwidth 15 MHz		Bandwidth 20 MHz	
	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)
L	37775	2572.5	37800	2575	37825	2577.5	37850	2580	37850	2580	37850	2580
M	38000	2595	38000	2595	38000	2595	38000	2595	38000	2595	38000	2595
H	38225	2617.5	38200	2615	38175	2612.5	38150	2610	38150	2610	38150	2610

LTE Band 41												
	Bandwidth 5 MHz		Bandwidth 10 MHz		Bandwidth 15 MHz		Bandwidth 20 MHz					
	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)
L	39675	2498.5	39700	2501	39725	2503.5	39750	2506				
LM	40148	2545.8	40160	2547	40173	2548.3	40185	2549.5				
M	40620	2593	40620	2593	40620	2593	40620	2593				
HM	41093	2640.3	41080	2639	41068	2637.8	41055	2636.5				
H	41565	2687.5	41540	2685	41515	2682.5	41490	2680				

LTE Band 66												
	Bandwidth 1.4 MHz		Bandwidth 3 MHz		Bandwidth 5 MHz		Bandwidth 10 MHz		Bandwidth 15 MHz		Bandwidth 20 MHz	
	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)
L	131979	1710.7	131987	1711.5	131997	1712.5	132022	1715	132047	1717.5	132072	1720
M	132322	1745	132322	1745	132322	1745	132322	1745	132322	1745	132322	1745
H	132665	1779.3	132657	1778.5	132647	1777.5	132622	1775	132597	1772.5	132572	1770

<For LTE Overlap Bands Description>

1) LTE Bands BW

Band	1.4 MHz	3 MHz	5 MHz	10 MHz	15 MHz	20 MHz
LTE Band 4	Yes	Yes	Yes	Yes	Yes	Yes
LTE Band 66	Yes	Yes	Yes	Yes	Yes	Yes
LTE Band 5	Yes	Yes	Yes	Yes		
LTE Band 26	Yes	Yes	Yes	Yes	Yes	
LTE Band 12	Yes	Yes	Yes	Yes		
LTE Band 17			Yes	Yes		
LTE Band 38			Yes	Yes	Yes	Yes
LTE Band 41			Yes	Yes	Yes	Yes

2) LTE Bands tune up

Band	Antenna	Default	DSI 0	DSI 1	DSI 3	DSI 4
			Receiver on	Sensor on	Sensor off	Hotspot on
			Tune-up Limit	Tune-up Limit	Tune-up Limit	Tune-up Limit
LTE Band 4	Ant 1	25.0	18.0	22.0	25.0	18.0
LTE Band 66		24.0	18.0	21.0	24.0	18.0
LTE Band 5	Ant 0	25.50	25.50	25.50	25.50	25.50
LTE Band 26		25.50	25.50	25.50	25.50	25.50
LTE Band 5	Ant 1	25.50	24.00	25.50	25.50	24.00
LTE Band 26		25.50	24.00	25.50	25.50	24.00
LTE Band 12	Ant 0	25.50	25.50	25.50	25.50	25.50
LTE Band 17		25.50	25.50	25.50	25.50	25.50
LTE Band 12	Ant 1	25.50	25.50	25.50	25.50	25.50
LTE Band 17		25.50	25.50	25.50	25.50	25.50
LTE Band 38	Ant 1	24.50	20.00	23.50	24.50	20.00
LTE Band 41		24.50	20.00	23.50	24.50	20.00
LTE Band 38	Ant 2	25.70	25.70	23.20	25.70	23.20
LTE Band 41		25.70	25.70	23.20	25.70	23.20
LTE Band 38	Ant 3	24.50	22.00	23.50	24.50	22.00
LTE Band 41		24.50	22.00	23.50	24.50	22.00
LTE Band 38	Ant 4	25.70	21.20	23.70	23.70	21.20
LTE Band 41		25.70	21.20	23.70	23.70	21.20

Note: For some bands/antennas at some exposure conditions which cannot be covered were fully tested for RF exposure compliance.



3) ENDC_ LTE Bands tune up

Band	Antenna	Default	DSI 0	DSI 1	DSI 3	DSI 4
			Receiver on	Sensor on	Sensor off	Hotspot on
		Tune-up Limit	Tune-up Limit	Tune-up Limit	Tune-up Limit	Tune-up Limit
LTE Band 5	Ant 0	25.50	25.50	23.50	25.50	25.00
LTE Band 26		25.50	25.50	23.50	25.50	25.00
LTE Band 5	Ant 1	25.50	21.50	23.50	25.50	21.50
LTE Band 26		25.50	21.50	23.50	25.50	21.50
LTE Band 38	Ant 1	24.50	18.00	22.00	24.50	18.00
LTE Band 41		24.50	18.00	22.00	24.50	18.00
LTE Band 38	Ant 2	25.70	25.70	23.20	25.20	22.20
LTE Band 41		25.70	25.70	23.20	25.20	22.20
LTE Band 38	Ant 3	24.50	20.00	23.50	24.50	20.00
LTE Band 41		24.50	20.00	23.50	24.50	20.00
LTE Band 38	Ant 4	25.70	18.70	22.20	22.20	18.70
LTE Band 41		25.70	18.70	22.20	22.20	18.70

4.3 General 5G NR SAR Test and Reporting Considerations

5G NR Information	
Operating Frequency Range of each 5G NR transmission band	5G NR n5: 824 MHz ~ 849 MHz 5G NR n7: 2500 MHz ~ 2570 MHz 5G NR n66: 1710 MHz ~ 1780 MHz 5G NR n38 : 2570 MHz ~ 2620 MHz 5G NR n41 : 2496 MHz ~ 2690 MHz 5G NR n77: 3450 MHz ~ 3550 MHz, 3700 MHz ~ 3980 MHz 5G NR n78: 3450 MHz ~ 3550 MHz, 3700 MHz ~ 3800 MHz
Channel Bandwidth	The detail please refers to section 4.1 5GNR FR1 bands table.
SCS	FDD: SCS15KHz, TDD: SCS30KHz
uplink modulations used	DFT-s-OFDM: PI/2 BPSK / QPSK / 16QAM / 64QAM / 256QAM CP-OFDM: QPSK / 16QAM / 64QAM / 256QAM
A-MPR (Additional MPR) disabled for SAR Testing?	Yes
LTE Anchor Bands for n5	LTE B7
LTE Anchor Bands for n7	LTE B66
LTE Anchor Bands for n66	LTE B2/5/7/12/66
LTE Anchor Bands for n38	LTE B66
LTE Anchor Bands for n41	LTE B66
LTE Anchor Bands for n78	LTE B2/5/7/26/38/41/66

Transmission (H, M, L) channel numbers and frequencies in each 5G NR band								
NR Band 5								
	Bandwidth 5MHz		Bandwidth 10MHz		Bandwidth 15MHz		Bandwidth 20MHz	
	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)
L	165300	826.5	165800	829	166300	831.5	166800	834
M	167300	836.5	167300	836.5	167300	836.5	167300	836.5
H	169300	846.5	168800	844	168300	841.5	167800	839

NR Band 7																
	Bandwidth 5MHz		Bandwidth 10MHz		Bandwidth 15MHz		Bandwidth 20MHz		Bandwidth 25MHz		Bandwidth 30MHz		Bandwidth 40MHz		Bandwidth 50MHz	
	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)
L	500500	2502.5	501000	2505	501500	2507.5	502000	2510	502500	2512.5	503000	2515	504000	2520	505000	2525
M	507000	2535	507000	2535	507000	2535	507000	2535	507000	2535	507000	2535	507000	2535	507000	2535
H	513500	2567.5	513000	2565	512500	2562.5	512000	2560	511500	2557.5	511000	2555	510000	2550	509000	2545

NR Band 66														
	Bandwidth 5MHz		Bandwidth 10MHz		Bandwidth 15MHz		Bandwidth 20MHz		Bandwidth 25MHz		Bandwidth 30MHz		Bandwidth 40MHz	
	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)
L	342500	1712.5	343000	1715	343500	1717.5	344000	1720	344500	1722.5	345000	1725	346000	1730
M	349000	1745	349000	1745	349000	1745	349000	1745	349000	1745	349000	1745	349000	1745
H	355500	1777.5	355000	1775	354500	1772.5	354000	1770	353500	1767.5	353000	1765	352000	1760

NR Band 38												
	Bandwidth 10MHz		Bandwidth 15MHz		Bandwidth 20MHz		Bandwidth 25MHz		Bandwidth 30MHz		Bandwidth 40MHz	
	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)
L	515004	2575.02	515502	2577.51	516000	2580	516504	2582.52	517002	2585.01	518004	2590.02
M	519000	2595	519000	2595	519000	2595	519000	2595	519000	2595	519000	2595
H	522996	2614.98	522498	2612.49	522000	2610	521496	2607.48	520998	2604.99	519996	2599.98



NR Band 41																				
Bandwidth 10MHz		Bandwidth 15MHz		Bandwidth 20MHz		Bandwidth 30MHz		Bandwidth 40MHz		Bandwidth 50MHz		Bandwidth 60MHz		Bandwidth 80MHz		Bandwidth 90MHz		Bandwidth 100MHz		
Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	
L	500202	2501.01	500700	2503.5	501204	2506.02	502200	2511	503202	2516.01	504204	2521.02	505200	2526	507204	2536.02	508200	2541	509202	2546.01
M	518598	2592.99	518598	2592.99	518598	2592.99	518598	2592.99	518598	2592.99	518598	2592.99	518598	2592.99	518598	2592.99	518598	2592.99	518598	2592.99
H	537000	2685	536496	2682.48	535998	2679.99	534996	2674.98	534000	2670	532998	2664.99	531996	2659.98	529998	2649.99	528996	2644.98	528000	2640

NR Band 77 SCS30KHz																								
Bandwidth 10MHz		Bandwidth 15MHz		Bandwidth 20MHz		Bandwidth 25MHz		Bandwidth 30MHz		Bandwidth 40MHz		Bandwidth 50MHz		Bandwidth 60MHz		Bandwidth 70MHz		Bandwidth 80MHz		Bandwidth 90MHz		Bandwidth 100MHz		
Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	
L	647000	3705	647168	3707.52	647334	3710.01	647500	3712.5	647668	3715.02	648000	3720	648334	3725.01	648668	3730.02	649000	3735	649334	3740.01	649668	3745.02	650000	3750
M	656000	3840	656000	3840	656000	3840	656000	3840.00	656000	3840.00	656000	3840	656000	3840	656000	3840	656000	3840	656000	3840	656000	3840	656000	3840
H	665000	3975	664832	3972.48	664666	3969.99	664500	3967.50	664332	3964.98	664000	3960	663666	3954.99	663332	3949.98	663000	3945	662666	3939.99	662332	3934.98	662000	3930

NR Band 78 SCS30KHz																								
Bandwidth 10MHz		Bandwidth 15MHz		Bandwidth 20MHz		Bandwidth 25MHz		Bandwidth 30MHz		Bandwidth 40MHz		Bandwidth 50MHz		Bandwidth 60MHz		Bandwidth 70MHz		Bandwidth 80MHz		Bandwidth 90MHz		Bandwidth 100MHz		
Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	
L	647000	3705	647168	3707.52	647334	3710.01	647500	3712.5	647668	3715.02	648000	3720	648334	3725.01	648668	3730.02	649000	3735	649334	3740.01	649668	3745.02		
M	650000	3750	650000	3750	650000	3750	650000	3750	650000	3750	650000	3750	650000	3750	650000	3750	650000	3750	650000	3750	650000	3750	650000	3750
H	653000	3795	652832	3792.48	652666	3789.99	652500	3787.5	652332	3784.98	652000	3780	651666	3774.99	651332	3769.98	651000	3765	650666	3759.99	650332	3754.98		

For <3450 MHz ~ 3550 MHz >

NR Band 77 SCS30KHz																								
Bandwidth 10MHz		Bandwidth 15MHz		Bandwidth 20MHz		Bandwidth 25MHz		Bandwidth 30MHz		Bandwidth 40MHz		Bandwidth 50MHz		Bandwidth 60MHz		Bandwidth 70MHz		Bandwidth 80MHz		Bandwidth 90MHz		Bandwidth 100MHz		
Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	
L	630334	3455.01	630500	3457.5	630668	3460.02	630834	3462.51	631000	3465	631334	3470.01	631668	3475.02	632000	3480	632334	3485.01	632668	3490.02	633000	3495		
M	633332	3499.98	633332	3499.98	633332	3499.98	633332	3499.98	633332	3499.98	633332	3499.98	633332	3499.98	633332	3499.98	633332	3499.98	633332	3499.98	633332	3499.98	633332	3499.98
H	636332	3544.98	636166	3542.49	636000	3540	635832	3537.48	635666	3534.99	635332	3529.98	635000	3525	634666	3519.99	634332	3514.98	634000	3510	633666	3504.99		

NR Band 78 SCS30KHz																								
Bandwidth 10MHz		Bandwidth 15MHz		Bandwidth 20MHz		Bandwidth 25MHz		Bandwidth 30MHz		Bandwidth 40MHz		Bandwidth 50MHz		Bandwidth 60MHz		Bandwidth 70MHz		Bandwidth 80MHz		Bandwidth 90MHz		Bandwidth 100MHz		
Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	Ch. #	Freq. (MHz)	
L	630334	3455.01	630500	3457.5	630668	3460.02	630834	3462.51	631000	3465	631334	3470.01	631668	3475.02	632000	3480	632334	3485.01	632668	3490.02	633000	3495		
M	633332	3499.98	633332	3499.98	633332	3499.98	633332	3499.98	633332	3499.98	633332	3499.98	633332	3499.98	633332	3499.98	633332	3499.98	633332	3499.98	633332	3499.98	633332	3499.98
H	636332	3544.98	636166	3542.49	636000	3540	635832	3537.48	635666	3534.99	635332	3529.98	635000	3525	634666	3519.99	634332	3514.98	634000	3510	633666	3504.99		



<For NR Overlap Bands Description>

1) NR Bands BW

Mode	Band	Duplex	SCS(KHz)	Bandwidths(BW)
SA	n38	TDD	30	10, 15, 20, 25, 30, 40
	n41	TDD	30	10, 15, 20, 30, 40, 50, 60, 70, 80, 90, 100
	n77	TDD	30	10, 15, 20, 25, 30, 40, 50, 60, 70, 80, 90, 100
	n78	TDD	30	10, 15, 20, 25, 30, 40, 50, 60, 70, 80, 90, 100

2) NR Bands Tune up:

Band	Antenna	Default Tune-up Limit	DSI 0	DSI 1	DSI 3	DSI 4
			Receiver on	Sensor on	Sensor off	Hotspot on
			Tune-up Limit	Tune-up Limit	Tune-up Limit	Tune-up Limit
FR1 n38	Ant 1	25	18.5	21	25	18.5
FR1 n41		25	18.5	21	25	18.5
FR1 n38	Ant 2	25.7	25.7	20.2	25.7	20.2
FR1 n41		25.7	25.7	20.2	25.7	20.2
FR1 n38	Ant 3	25	19	21.5	25	19
FR1 n41		25	19	21.5	25	19
FR1 n38	Ant 4	25.7	17.7	21.2	21.2	17.7
FR1 n41		25.7	17.7	21.2	21.2	17.7
FR1 n77 Part 27Q_PC2	Ant 1	25.5	22.5	22	25.5	22
FR1 n77 Part 27O_PC2		26	23	22.5	26	22.5
FR1 n78 Part 27Q_PC2		26.5	22	22.5	26.5	22
FR1 n78 Part 27O_PC2		26.5	22	22.5	26.5	22
FR1 n77 Part 27Q_PC3	Ant 1	22.5	19.5	19	22.5	19
FR1 n77 Part 27O_PC3		23	20	19.5	23	19.5
FR1 n78 Part 27Q_PC3		23.5	19	19.5	23.5	19
FR1 n78 Part 27O_PC3		23.5	19	19.5	23.5	19
FR1 n77 Part 27Q_PC2	Ant 5	26	22.5	23	23	22.5
FR1 n77 Part 27O_PC2		26	22.5	23	23	22.5
FR1 n78 Part 27Q_PC2		27	22.5	23.5	23.5	22.5
FR1 n78 Part 27O_PC2		27	22.5	23.5	23.5	22.5
FR1 n77 Part 27Q_PC3	Ant 5	23	19.5	20	20	19.5
FR1 n77 Part 27O_PC3		23	19.5	20	20	19.5
FR1 n78 Part 27Q_PC3		24	19.5	20.5	20.5	19.5
FR1 n78 Part 27O_PC3		24	19.5	20.5	20.5	19.5
FR1 n77 Part 27Q_PC2	Ant 6	25.5	20.5	22.5	22.5	20.5
FR1 n77 Part 27O_PC2		26.5	21.5	23.5	23.5	21.5
FR1 n78 Part 27Q_PC2		26.5	20.5	22.5	22.5	20.5
FR1 n78 Part 27O_PC2		27	21	23	23	21
FR1 n77 Part 27Q_PC3	Ant 6	22.5	17.5	19.5	19.5	17.5
FR1 n77 Part 27O_PC3		23.5	18.5	20.5	20.5	18.5
FR1 n78 Part 27Q_PC3		23.5	17.5	19.5	19.5	17.5
FR1 n78 Part 27O_PC3		24	18	20	20	18
FR1 n77 Part 27Q_PC2	Ant 7	26	26	19.5	24	22.5
FR1 n77 Part 27O_PC2		26.5	26.5	20	24.5	23
FR1 n78 Part 27Q_PC2		27	27	20	21	23
FR1 n78 Part 27O_PC2		27.5	27.5	20.5	21.5	23.5
FR1 n77 Part 27Q_PC3	Ant 7	23	23	16.5	21	16.5
FR1 n77 Part 27O_PC3		23.5	23.5	17	21.5	17
FR1 n78 Part 27Q_PC3		24	24	17	18	16.5
FR1 n78 Part 27O_PC3		24.5	24.5	17.5	18.5	17

Note: For some bands/antennas at some exposure conditions which cannot be covered were fully tested for RF exposure compliance.

3) ENDC_NR Bands Tune up:


Band	Antenna	Default	DSI 0	DSI 1	DSI 3	DSI 4
			Receiver on	Sensor on	Sensor off	Hotspot on
		Tune-up Limit	Tune-up Limit	Tune-up Limit	Tune-up Limit	Tune-up Limit
FR1 n38	Ant 1	25	16	18	24	16
FR1 n41		25	16	18	24	16
FR1 n38	Ant 2	25.7	25.7	17.7	22.7	17.7
FR1 n41		25.7	25.7	17.7	22.7	17.7
FR1 n38	Ant 3	25	16	18.5	24	16
FR1 n41		25	16	18.5	24	16
FR1 n38	Ant 4	25.7	15.2	19.7	19.7	15.2
FR1 n41		25.7	15.2	19.7	19.7	15.2
FR1 n77 Part 27Q_PC2	Ant 1	25.5	19.5	22	25.5	19.5
FR1 n77 Part 27O_PC2		26	20	22.5	26	20
FR1 n78 Part 27Q_PC2		26.5	19.5	22.5	26.5	19.5
FR1 n78 Part 27O_PC2		26.5	19.5	22.5	26.5	19.5
FR1 n77 Part 27Q_PC3	Ant 1	22.5	16.5	19	25.5	16.5
FR1 n77 Part 27O_PC3		23	17	19.5	26	17
FR1 n78 Part 27Q_PC3		23.5	16.5	19.5	26.5	16.5
FR1 n78 Part 27O_PC3		23.5	16.5	19.5	26.5	16.5
FR1 n77 Part 27Q_PC2	Ant 5	26	19.5	22.5	22.5	19.5
FR1 n77 Part 27O_PC2		26	19.5	22.5	22.5	19.5
FR1 n78 Part 27Q_PC2		27	19.5	23.5	23.5	19.5
FR1 n78 Part 27O_PC2		27	19.5	23.5	23.5	19.5
FR1 n77 Part 27Q_PC3	Ant 5	23	16.5	19.5	19.5	16.5
FR1 n77 Part 27O_PC3		23	16.5	19.5	19.5	16.5
FR1 n78 Part 27Q_PC3		24	16.5	20.5	20.5	16.5
FR1 n78 Part 27O_PC3		24	16.5	20.5	20.5	16.5
FR1 n77 Part 27Q_PC2	Ant 6	25.5	18	22	22	18
FR1 n77 Part 27O_PC2		26.5	19	23	23	19
FR1 n78 Part 27Q_PC2		26.5	18	22	22	18
FR1 n78 Part 27O_PC2		27	18.5	22.5	22.5	18.5
FR1 n77 Part 27Q_PC3	Ant 6	22.5	15	19	19	15
FR1 n77 Part 27O_PC3		23.5	16	20	20	16
FR1 n78 Part 27Q_PC3		23.5	15	19	19	15
FR1 n78 Part 27O_PC3		24	15.5	19.5	19.5	15.5
FR1 n77 Part 27Q_PC2	Ant 7	26	26	19.5	22	18.5
FR1 n77 Part 27O_PC2		26.5	26.5	20	22.5	19
FR1 n78 Part 27Q_PC2		27	25	19.5	22	18.5
FR1 n78 Part 27O_PC2		27.5	25.5	20	22.5	19
FR1 n77 Part 27Q_PC3	Ant 7	23	23	16.5	19	15.5
FR1 n77 Part 27O_PC3		23.5	23.5	17	19.5	16
FR1 n78 Part 27Q_PC3		24	24	16.5	19	15.5
FR1 n78 Part 27O_PC3		24.5	24.5	17	19.5	16

Note: For some bands/antennas at some exposure conditions which cannot be covered were fully tested for RF exposure compliance.

5. Proximity Sensor Triggering Test

<Proximity Sensor Triggering Distance>:

1. Proximity sensor triggering distance testing was performed according to the procedures outlined in KDB 616217 D04 section 6.2, and EUT moving further away from the flat phantom and EUT moving toward the flat phantom were both assessed and the tissue-equivalent medium for highest frequency (3980MHz) and lowest (1750MHz) frequency was used for proximity sensor triggering testing.
2. Capacitive proximity sensors placed coincident with antenna elements at the top and bottom ends of the phone are utilized to determine when the device comes in proximity of the user's body or finger or hand at the front or back or bottom or left or right or top side of the device. There is no need to do sensor coverage testing for the proximity sensor is designed to support sufficient detection range and sensitivity to cover regions of the sensors in all applicable directions since the proximity sensor entirely covers the antenna.
3. The sensors can use to detect the proximity of the user's body or handheld states at the front or back or bottom or left or right or top side of the device use a detection threshold distance. When front/back/left/right/top/bottom sides of body or handheld condition is detected reduced power will be active. The trigger distance shown in the sections below.
4. For verification of compliance of power reduction scheme, additional SAR testing with EUT transmitting at full RF power at a conservative trigger distance -1mm was performed:





<P-Sensor>

< Sensor for Ant0/2 >

Proximity Sensor Triggering Distance (mm)								
Position	Front		Back		Right Side		Bottom Side	
	Moving towards	Moving away	Moving towards	Moving away	Moving towards	Moving away	Moving towards	Moving away
Minimum	16	16	16	16	16	16	16	16

< Sensor for Ant1/3/7 >

Proximity Sensor Triggering Distance (mm)								
Position	Front		Back		Left Side		Top Side	
	Moving towards	Moving away	Moving towards	Moving away	Moving towards	Moving away	Moving towards	Moving away
Minimum	6	6	6	6	6	6	6	6

6. RF Exposure Limits

6.1 Uncontrolled Environment

Uncontrolled Environments are defined as locations where there is the exposure of individuals who have no knowledge or control of their exposure. The general population/uncontrolled exposure limits are applicable to situations in which the general public may be exposed or in which persons who are exposed as a consequence of their employment may not be made fully aware of the potential for exposure or cannot exercise control over their exposure. Members of the general public would come under this category when exposure is not employment-related; for example, in the case of a wireless transmitter that exposes persons in its vicinity.

6.2 Controlled Environment

Controlled Environments are defined as locations where there is exposure that may be incurred by persons who are aware of the potential for exposure, (i.e. as a result of employment or occupation). In general, occupational/controlled exposure limits are applicable to situations in which persons are exposed as a consequence of their employment, who have been made fully aware of the potential for exposure and can exercise control over their exposure. The exposure category is also applicable when the exposure is of a transient nature due to incidental passage through a location where the exposure levels may be higher than the general population/uncontrolled limits, but the exposed person is fully aware of the potential for exposure and can exercise control over his or her exposure by leaving the area or by some other appropriate means.

Limits for Occupational/Controlled Exposure (W/kg)

Whole-Body	Partial-Body	Hands, Wrists, Feet and Ankles
0.4	8.0	20.0

Limits for General Population/Uncontrolled Exposure (W/kg)

Whole-Body	Partial-Body	Hands, Wrists, Feet and Ankles
0.08	1.6	4.0

Whole-Body SAR is averaged over the entire body, partial-body SAR is averaged over any 1gram of tissue defined as a tissue volume in the shape of a cube. SAR for hands, wrists, feet and ankles is averaged over any 10 grams of tissue defined as a tissue volume in the shape of a cube.

7. Specific Absorption Rate (SAR)

7.1 Introduction

SAR is related to the rate at which energy is absorbed per unit mass in an object exposed to a radio field. The SAR distribution in a biological body is complicated and is usually carried out by experimental techniques or numerical modeling. The standard recommends limits for two tiers of groups, occupational/controlled and general population/uncontrolled, based on a person's awareness and ability to exercise control over his or her exposure. In general, occupational/controlled exposure limits are higher than the limits for general population/uncontrolled.

7.2 SAR Definition

The SAR definition is the time derivative (rate) of the incremental energy (dW) absorbed by (dissipated in) an incremental mass (dm) contained in a volume element (dv) of a given density (ρ). The equation description is as below:

$$\text{SAR} = \frac{d}{dt} \left(\frac{dW}{dm} \right) = \frac{d}{dt} \left(\frac{dW}{\rho dv} \right)$$


SAR is expressed in units of Watts per kilogram (W/kg)

$$\text{SAR} = \frac{\sigma |E|^2}{\rho}$$

Where: σ is the conductivity of the tissue, ρ is the mass density of the tissue and E is the RMS electrical field strength.

8. System Description and Setup

The DASY5 system used for performing compliance tests consists of the following items:




- A standard high precision 6-axis robot with controller, teach pendant and software. An arm extension for accommodating the data acquisition electronics (DAE).
- An isotropic Field probe optimized and calibrated for the targeted measurement.
- A data acquisition electronics (DAE) which performs the signal amplification, signal multiplexing, AD-conversion, offset measurements, mechanical surface detection, collision detection, etc. The unit is battery powered with standard or rechargeable batteries. The signal is optically transmitted to the EOC.
- The Electro-optical converter (EOC) performs the conversion from optical to electrical signals for the digital communication to the DAE. To use optical surface detection, a special version of the EOC is required. The EOC signal is transmitted to the measurement server.
- The function of the measurement server is to perform the time critical tasks such as signal filtering, control of the robot operation and fast movement interrupts.
- The Light Beam used is for probe alignment. This improves the (absolute) accuracy of the probe positioning.
- A computer running WinXP or Win10 and the DASY5 software.
- Remote control and teach pendant as well as additional circuitry for robot safety such as warning lamps, etc.
- The phantom, the device holder and other accessories according to the targeted measurement.


8.1 E-Field Probe

The SAR measurement is conducted with the dosimetric probe (manufactured by SPEAG).The probe is specially designed and calibrated for use in liquid with high permittivity. The dosimetric probe has special calibration in liquid at different frequency. This probe has a built in optical surface detection system to prevent from collision with phantom.

<ES3DV3 Probe>

Construction	Symmetric design with triangular core Interleaved sensors Built-in shielding against static charges PEEK enclosure material (resistant to organic solvents, e.g., DGBE)	
Frequency	10 MHz – 4 GHz; Linearity: ±0.2 dB (30 MHz – 4 GHz)	
Directivity	±0.2 dB in TSL (rotation around probe axis) ±0.3 dB in TSL (rotation normal to probe axis)	
Dynamic Range	5 µW/g – >100 mW/g; Linearity: ±0.2 dB	
Dimensions	Overall length: 337 mm (tip: 20 mm) Tip diameter: 3.9 mm (body: 12 mm) Distance from probe tip to dipole centers: 3.0 mm	

<EX3DV4 Probe>

Construction	Symmetric design with triangular core Built-in shielding against static charges PEEK enclosure material (resistant to organic solvents, e.g., DGBE)	
Frequency	10 MHz – >6 GHz Linearity: ±0.2 dB (30 MHz – 6 GHz)	
Directivity	±0.3 dB in TSL (rotation around probe axis) ±0.5 dB in TSL (rotation normal to probe axis)	
Dynamic Range	10 µW/g – >100 mW/g Linearity: ±0.2 dB (noise: typically <1 µW/g)	
Dimensions	Overall length: 337 mm (tip: 20 mm) Tip diameter: 2.5 mm (body: 12 mm) Typical distance from probe tip to dipole centers: 1 mm	

8.2 Data Acquisition Electronics (DAE)

The data acquisition electronics (DAE) consists of a highly sensitive electrometer-grade preamplifier with auto-zeroing, a channel and gain-switching multiplexer, a fast 16 bit AD-converter and a command decoder and control logic unit. Transmission to the measurement server is accomplished through an optical downlink for data and status information as well as an optical uplink for commands and the clock.


The input impedance of the DAE is 200 MOhm; the inputs are symmetrical and floating. Common mode rejection is above 80 dB.



Photo of DAE


8.3 Phantom

<SAM Twin Phantom>

Shell Thickness	2 ± 0.2 mm; Center ear point: 6 ± 0.2 mm	
Filling Volume	Approx. 25 liters	
Dimensions	Length: 1000 mm; Width: 500 mm; Height: adjustable feet	
Measurement Areas	Left Hand, Right Hand, Flat Phantom	

The bottom plate contains three pair of bolts for locking the device holder. The device holder positions are adjusted to the standard measurement positions in the three sections. A white cover is provided to tap the phantom during off-periods to prevent water evaporation and changes in the liquid parameters. On the phantom top, three reference markers are provided to identify the phantom position with respect to the robot.

<ELI Phantom>

Shell Thickness	2 ± 0.2 mm (sagging: <1%)	
Filling Volume	Approx. 30 liters	
Dimensions	Major ellipse axis: 600 mm Minor axis: 400 mm	

The ELI phantom is intended for compliance testing of handheld and body-mounted wireless devices or for evaluating transmitters operating at low frequencies. ELI is fully compatible with standard and all known tissue simulating liquids.

8.4 Device Holder

<Mounting Device for Hand-Held Transmitter>

In combination with the Twin SAM V5.0/V5.0c or ELI phantoms, the Mounting Device for Hand-Held Transmitters enables rotation of the mounted transmitter device to specified spherical coordinates. At the heads, the rotation axis is at the ear opening. Transmitter devices can be easily and accurately positioned according to IEC 62209-1, IEEE 1528, FCC, or other specifications. The device holder can be locked for positioning at different phantom sections (left head, right head, flat). And upgrade kit to Mounting Device to enable easy mounting of wider devices like big smart-phones, e-books, small tablets, etc. It holds devices with width up to 140 mm.



Mounting Device for Hand-Held Transmitters



Mounting Device Adaptor for Wide-Phones

<Mounting Device for Laptops and other Body-Worn Transmitters>

The extension is lightweight and made of POM, acrylic glass and foam. It fits easily on the upper part of the mounting device in place of the phone positioned. The extension is fully compatible with the SAM Twin and ELI phantoms.



Mounting Device for Laptops

9. Measurement Procedures

The measurement procedures are as follows:

<Conducted power measurement>

- (a) For WWAN power measurement, use base station simulator to configure EUT WWAN transmission in conducted connection with RF cable, at maximum power in each supported wireless interface and frequency band.
- (b) Read the WWAN RF power level from the base station simulator.
- (c) For WLAN/BT power measurement, use engineering software to configure EUT WLAN/BT continuously transmission, at maximum RF power in each supported wireless interface and frequency band
- (d) Connect EUT RF port through RF cable to the power meter, and measure WLAN/BT output power

<SAR measurement>

- (a) Use base station simulator to configure EUT WWAN transmission in radiated connection, and engineering software to configure EUT WLAN/BT continuously transmission, at maximum RF power, in the highest power channel.
- (b) Place the EUT in the positions as Appendix D demonstrates.
- (c) Set scan area, grid size and other setting on the DASY software.
- (d) Measure SAR results for the highest power channel on each testing position.
- (e) Find out the largest SAR result on these testing positions of each band
- (f) Measure SAR results for other channels in worst SAR testing position if the reported SAR of highest power channel is larger than 0.8 W/kg

According to the test standard, the recommended procedure for assessing the peak spatial-average SAR value consists of the following steps:

- (a) Power reference measurement
- (b) Area scan
- (c) Zoom scan
- (d) Power drift measurement

9.1 Spatial Peak SAR Evaluation

The procedure for spatial peak SAR evaluation has been implemented according to the test standard. It can be conducted for 1g and 10g, as well as for user-specific masses. The DASY software includes all numerical procedures necessary to evaluate the spatial peak SAR value.

The base for the evaluation is a "cube" measurement. The measured volume must include the 1g and 10g cubes with the highest averaged SAR values. For that purpose, the center of the measured volume is aligned to the interpolated peak SAR value of a previously performed area scan.

The entire evaluation of the spatial peak values is performed within the post-processing engine (SEMCAD). The system always gives the maximum values for the 1g and 10g cubes. The algorithm to find the cube with highest averaged SAR is divided into the following stages:

- (a) Extraction of the measured data (grid and values) from the Zoom Scan
- (b) Calculation of the SAR value at every measurement point based on all stored data (A/D values and measurement parameters)
- (c) Generation of a high-resolution mesh within the measured volume
- (d) Interpolation of all measured values from the measurement grid to the high-resolution grid
- (e) Extrapolation of the entire 3-D field distribution to the phantom surface over the distance from sensor to surface
- (f) Calculation of the averaged SAR within masses of 1g and 10g

9.2 Power Reference Measurement

The Power Reference Measurement and Power Drift Measurements are for monitoring the power drift of the device under test in the batch process. The minimum distance of probe sensors to surface determines the closest measurement point to phantom surface. This distance cannot be smaller than the distance of sensor calibration points to probe tip as defined in the probe properties.

9.3 Area Scan

The area scan is used as a fast scan in two dimensions to find the area of high field values, before doing a fine measurement around the hot spot. The sophisticated interpolation routines implemented in DASY software can find the maximum found in the scanned area, within a range of the global maximum. The range (in dB0 is specified in the standards for compliance testing. For example, a 2 dB range is required in IEEE standard 1528 and IEC 62209 standards, whereby 3 dB is a requirement when compliance is assessed in accordance with the ARIB standard (Japan), if only one zoom scan follows the area scan, then only the absolute maximum will be taken as reference. For cases where multiple maximums are detected, the number of zoom scans has to be increased accordingly.

Area scan parameters extracted from FCC KDB 865664 D01v01r04 SAR measurement 100 MHz to 6 GHz.

	≤ 3 GHz	> 3 GHz
Maximum distance from closest measurement point (geometric center of probe sensors) to phantom surface	5 ± 1 mm	$\frac{1}{2} \cdot \delta \cdot \ln(2) \pm 0.5$ mm
Maximum probe angle from probe axis to phantom surface normal at the measurement location	$30^\circ \pm 1^\circ$	$20^\circ \pm 1^\circ$
Maximum area scan spatial resolution: $\Delta x_{Area}, \Delta y_{Area}$	≤ 2 GHz: ≤ 15 mm $2 - 3$ GHz: ≤ 12 mm	$3 - 4$ GHz: ≤ 12 mm $4 - 6$ GHz: ≤ 10 mm
	When the x or y dimension of the test device, in the measurement plane orientation, is smaller than the above, the measurement resolution must be \leq the corresponding x or y dimension of the test device with at least one measurement point on the test device.	

9.4 Zoom Scan

Zoom scans are used to assess the peak spatial SAR values within a cubic averaging volume containing 1 gram and 10 gram of simulated tissue. The zoom scan measures points (refer to table below) within a cube whose base faces are centered on the maxima found in a preceding area scan job within the same procedure. When the measurement is done, the zoom scan evaluates the averaged SAR for 1 gram and 10 gram and displays these values next to the job's label.

Zoom scan parameters extracted from FCC KDB 865664 D01v01r04 SAR measurement 100 MHz to 6 GHz.

			≤ 3 GHz	> 3 GHz
Maximum zoom scan spatial resolution: $\Delta x_{Zoom}, \Delta y_{Zoom}$			≤ 2 GHz: ≤ 8 mm $2 - 3$ GHz: ≤ 5 mm*	$3 - 4$ GHz: ≤ 5 mm* $4 - 6$ GHz: ≤ 4 mm*
Maximum zoom scan spatial resolution, normal to phantom surface	uniform grid: $\Delta z_{Zoom}(n)$		≤ 5 mm	$3 - 4$ GHz: ≤ 4 mm $4 - 5$ GHz: ≤ 3 mm $5 - 6$ GHz: ≤ 2 mm
	graded grid	$\Delta z_{Zoom}(1)$: between 1 st two points closest to phantom surface	≤ 4 mm	$3 - 4$ GHz: ≤ 3 mm $4 - 5$ GHz: ≤ 2.5 mm $5 - 6$ GHz: ≤ 2 mm
		$\Delta z_{Zoom}(n>1)$: between subsequent points	$\leq 1.5 \cdot \Delta z_{Zoom}(n-1)$	
Minimum zoom scan volume	x, y, z		≥ 30 mm	$3 - 4$ GHz: ≥ 28 mm $4 - 5$ GHz: ≥ 25 mm $5 - 6$ GHz: ≥ 22 mm
Note: δ is the penetration depth of a plane-wave at normal incidence to the tissue medium; see draft standard IEEE P1528-2011 for details. * When zoom scan is required and the <u>reported</u> SAR from the <u>area scan based 1-g SAR estimation</u> procedures of KDB 447498 is ≤ 1.4 W/kg, ≤ 8 mm, ≤ 7 mm and ≤ 5 mm zoom scan resolution may be applied, respectively, for 2 GHz to 3 GHz, 3 GHz to 4 GHz and 4 GHz to 6 GHz.				

9.5 Volume Scan Procedures

The volume scan is used to assess overlapping SAR distributions for antennas transmitting in different frequency bands. It is equivalent to an oversized zoom scan used in standalone measurements. The measurement volume will be used to enclose all the simultaneous transmitting antennas. For antennas transmitting simultaneously in different frequency bands, the volume scan is measured separately in each frequency band. In order to sum correctly to compute the 1g aggregate SAR, the EUT remain in the same test position for all measurements and all volume scan use the same spatial resolution and grid spacing. When all volume scan were completed, the software, SEMCAD postprocessor can combine and subsequently superpose these measurement data to calculating the multiband SAR.

9.6 Power Drift Monitoring

All SAR testing is under the EUT install full charged battery and transmit maximum output power. In DASY measurement software, the power reference measurement and power drift measurement procedures are used for monitoring the power drift of EUT during SAR test. Both these procedures measure the field at a specified reference position before and after the SAR testing. The software will calculate the field difference in dB. If the power drifts more than 5%, the SAR will be retested.

10. Test Equipment List

Manufacturer	Name of Equipment	Type/Model	Serial Number	Calibration	
				Last Cal.	Due Date
SPEAG	750MHz System Validation Kit	D750V3	1099	Dec. 15, 2021	Dec. 14, 2024
SPEAG	835MHz System Validation Kit	D835V2	4d162	Dec. 17, 2021	Dec. 16, 2024
SPEAG	1750MHz System Validation Kit	D1750V2	1137	Oct. 19, 2021	Oct. 18, 2024
SPEAG	1900MHz System Validation Kit	D1900V2	5d182	Dec. 20, 2021	Dec. 19, 2024
SPEAG	2450MHz System Validation Kit	D2450V2	924	Sep. 02, 2020	Aug. 31, 2023
SPEAG	2600MHz System Validation Kit	D2600V2	1070	Dec. 20, 2021	Dec. 19, 2024
SPEAG	3500MHz System Validation Kit	D3500V2	1037	Nov. 25, 2020	Nov. 23, 2023
SPEAG	3700MHz System Validation Kit	D3700V2	1008	Nov. 25, 2020	Nov. 23, 2023
SPEAG	3900MHz System Validation Kit	D3900V2	1022	Aug. 18, 2022	Aug. 17, 2023
SPEAG	5000MHz System Validation Kit	D5GHzV2	1341	Dec. 13, 2021	Dec. 12, 2024
SPEAG	Data Acquisition Electronics	DAE4	1437	Nov. 23, 2022	Nov. 22, 2023
SPEAG	Data Acquisition Electronics	DAE4	679	Jun. 06, 2022	Jun. 05, 2023
SPEAG	Dosimetric E-Field Probe	ES3DV3	3191	Feb. 17, 2023	Feb. 16, 2024
SPEAG	Dosimetric E-Field Probe	EX3DV4	3887	Oct. 28, 2022	Oct. 27, 2023
SPEAG	SAM Twin Phantom	QD 000 P40 CD	1795	NCR	NCR
SPEAG	Phone Positioner	N/A	N/A	NCR	NCR
Anritsu	Radio communication analyzer	MT8820C	6201563813	Dec. 27, 2022	Dec. 26, 2023
Anritsu	Radio communication analyzer	MT8821C	6262314715	Jun. 27, 2022	Jun. 26, 2023
Agilent	Wireless Communication Test Set	E5515C	MY50267224	Jul. 07, 2022	Jul. 06, 2023
Keysight	Network Analyzer	E5071C	MY46523671	Oct. 17, 2022	Oct. 16, 2023
Speag	Dielectric Assessment KIT	DAK-3.5	1071	Feb. 20, 2023	Feb. 19, 2024
Agilent	Signal Generator	N5181A	MY50145381	Dec. 27, 2022	Dec. 26, 2023
Anritsu	Power Sensor	MA2411B	1306099	Oct. 17, 2022	Oct. 16, 2023
Anritsu	Power Meter	ML2495A	1349001	Oct. 17, 2022	Oct. 16, 2023
R&S	CBT BLUETOOTH TESTER	CBT	100963	Dec. 27, 2022	Dec. 26, 2023
R&S	Spectrum Analyzer	FSP7	100818	Jul. 07, 2022	Jul. 06, 2023
TES	Hygrometer	1310	200505600	Jul. 12, 2022	Jul. 11, 2023
Anymetre	Thermo-Hygrometer	JR593	2020062101	Jul. 12, 2022	Jul. 11, 2023
SPEAG	Device Holder	N/A	N/A	N/A	N/A
Mini-Circuits	Amplifier	ZVE-3W-83+	599201528	Note 1	
ARRA	Power Divider	A3200-2	N/A	Note 1	
ET Industries	Dual Directional Coupler	C-058-10	N/A	Note 1	
Weinschel	Attenuator 1	3M-10	N/A	Note 1	
Weinschel	Attenuator 2	3M-20	N/A	Note 1	

Note:

1. Prior to system verification and validation, the path loss from the signal generator to the system check source and the power meter, which includes the amplifier, cable, attenuator and directional coupler, was measured by the network analyzer. The reading of the power meter was offset by the path loss difference between the path to the power meter and the path to the system check source to monitor the actual power level fed to the system check.
2. Referring to KDB 865664 D01v01r04, the dipole calibration interval can be extended to 3 years with justification. The dipoles are also not physically damaged, or repaired during the interval.
3. The justification data of dipole can be found in appendix C. The return loss is < -20dB, within 20% of prior calibration, the impedance is within 5 ohm of prior calibration.

11. System Verification

11.1 Tissue Simulating Liquids

For the measurement of the field distribution inside the SAM phantom with DASY, the phantom must be filled with around 25 liters of homogeneous body tissue simulating liquid. For head SAR testing, the liquid height from the ear reference point (ERP) of the phantom to the liquid top surface is larger than 15 cm, which is shown in Fig. 11.1. For body SAR testing, the liquid height from the center of the flat phantom to the liquid top surface is larger than 15 cm, which is shown in Fig. 11.2.




Fig 11.1 Photo of Liquid Height for Head SAR




Fig 11.2 Photo of Liquid Height for Body SAR

11.2 Tissue Verification

The following tissue formulations are provided for reference only as some of the parameters have not been thoroughly verified. The composition of ingredients may be modified accordingly to achieve the desired target tissue parameters required for routine SAR evaluation.

Frequency (MHz)	Water (%)	Sugar (%)	Cellulose (%)	Salt (%)	Preventol (%)	DGBE (%)	Conductivity (σ)	Permittivity (ϵ_r)
For Head								
750	41.1	57.0	0.2	1.4	0.2	0	0.89	41.9
835	40.3	57.9	0.2	1.4	0.2	0	0.90	41.5
1800, 1900, 2000	55.2	0	0	0.3	0	44.5	1.40	40.0
2450	55.0	0	0	0	0	45.0	1.80	39.2
2600	54.8	0	0	0.1	0	45.1	1.96	39.0

Simulating Liquid for 5GHz, Manufactured by SPEAG

Ingredients	(% by weight)
Water	64~78%
Mineral oil	11~18%
Emulsifiers	9~15%
Additives and Salt	2~3%

<Tissue Dielectric Parameter Check Results>

Frequency (MHz)	Tissue Type	Liquid Temp. (°C)	Conductivity (σ)	Permittivity (ε _r)	Conductivity Target (σ)	Permittivity Target (ε _r)	Delta (σ) (%)	Delta (ε _r) (%)	Limit (%)	Date
750	Head	22.4	0.888	40.879	0.89	41.90	-0.22	-2.44	±5	2023/5/13
750	Head	22.6	0.878	40.673	0.89	41.90	-1.35	-2.93	±5	2023/5/23
835	Head	22.3	0.911	42.404	0.90	41.50	1.22	2.18	±5	2023/5/14
835	Head	22.4	0.908	41.378	0.90	41.50	0.89	-0.29	±5	2023/5/24
1750	Head	22.3	1.383	41.300	1.37	40.10	0.95	2.99	±5	2023/5/15
1750	Head	22.5	1.362	41.482	1.37	40.10	-0.58	3.45	±5	2023/5/25
1900	Head	22.3	1.412	38.427	1.40	40.00	0.86	-3.93	±5	2023/5/16
1900	Head	22.4	1.428	41.216	1.40	40.00	2.00	3.04	±5	2023/5/26
2450	Head	22.5	1.823	37.961	1.80	39.20	1.28	-3.16	±5	2023/5/20
2450	Head	22.3	1.804	37.483	1.80	39.20	0.22	-4.38	±5	2023/5/27
2600	Head	22.4	1.934	37.621	1.96	39.00	-1.33	-3.54	±5	2023/5/16
2600	Head	22.2	1.915	39.536	1.96	39.00	-2.30	1.37	±5	2023/5/28
3500	Head	22.6	2.933	39.225	2.91	37.90	0.79	3.50	±5	2023/5/17
3500	Head	22.3	2.935	39.303	2.91	37.90	0.86	3.70	±5	2023/5/29
3700	Head	22.2	3.031	39.117	3.12	37.70	-2.85	3.76	±5	2023/5/18
3700	Head	22.7	3.041	36.377	3.12	37.70	-2.53	-3.51	±5	2023/5/30
3900	Head	22.4	3.214	39.072	3.33	37.51	-3.48	4.16	±5	2023/5/19
3900	Head	22.5	3.199	36.160	3.33	37.51	-3.93	-3.60	±5	2023/5/31
5250	Head	22.3	4.841	35.356	4.71	35.95	2.78	-1.65	±5	2023/5/19
5250	Head	22.4	4.554	37.035	4.71	35.95	-3.31	3.02	±5	2023/6/1
5600	Head	22.5	5.002	36.115	5.07	35.50	-1.34	1.73	±5	2023/5/22
5600	Head	22.3	4.856	36.517	5.07	35.50	-4.22	2.86	±5	2023/6/2
5750	Head	22.6	5.358	34.497	5.22	35.35	2.64	-2.41	±5	2023/5/23
5750	Head	22.6	5.014	36.603	5.22	35.35	-3.95	3.54	±5	2023/6/3
3500	Head	22.4	2.868	36.972	2.91	37.90	-1.44	-2.45	±5	2023/6/12
3700	Head	22.5	3.011	36.767	3.12	37.70	-3.49	-2.47	±5	2023/6/12
3900	Head	22.6	3.165	36.566	3.33	37.51	-4.95	-2.52	±5	2023/6/13



11.3 System Performance Check Results

Comparing to the original SAR value provided by SPEAG, the verification data should be within its specification of 10 %. Below table shows the target SAR and measured SAR after normalized to 1W input power. The table below indicates the system performance check can meet the variation criterion and the plots can be referred to Appendix A of this report.

<1g SAR>

Table with 11 columns: Date, Frequency (MHz), Tissue Type, Input Power (mW), Dipole S/N, Probe S/N, DAE S/N, Measured 1g SAR (W/kg), Targeted 1g SAR (W/kg), Normalized 1g SAR (W/kg), Deviation (%). Rows contain test data from 2023/5/13 to 2023/6/13.

<10g SAR>

Date	Frequency (MHz)	Tissue Type	Input Power (mW)	Dipole S/N	Probe S/N	DAE S/N	Measured 10g SAR (W/kg)	Targeted 10g SAR (W/kg)	Normalized 10g SAR (W/kg)	Deviation (%)
2023/5/13	750	Head	250	1099	3191	1437	1.450	5.650	5.8	2.65
2023/5/23	750	Head	250	1099	3191	1437	1.370	5.650	5.48	-3.01
2023/5/14	835	Head	250	4d162	3191	1437	1.670	6.260	6.68	6.71
2023/5/24	835	Head	250	4d162	3191	1437	1.570	6.260	6.28	0.32
2023/5/15	1750	Head	250	1137	3191	1437	5.080	19.200	20.32	5.83
2023/5/25	1750	Head	250	1137	3191	1437	4.820	19.200	19.28	0.42
2023/5/16	1900	Head	250	5d182	3191	1437	5.410	20.200	21.64	7.13
2023/5/26	1900	Head	250	5d182	3191	1437	5.030	20.200	20.12	-0.40
2023/5/20	2450	Head	250	924	3191	1437	5.870	24.000	23.48	-2.17
2023/5/27	2450	Head	250	924	3191	1437	6.140	24.000	24.56	2.33
2023/5/16	2600	Head	250	1070	3191	1437	5.790	24.600	23.16	-5.85
2023/5/28	2600	Head	250	1070	3191	1437	6.090	24.600	24.36	-0.98
2023/5/17	3500	Head	100	1037	3887	679	2.530	25.400	25.3	-0.39
2023/5/29	3500	Head	100	1037	3887	679	2.710	25.400	27.1	6.69
2023/5/18	3700	Head	100	1008	3887	679	2.390	24.400	23.9	-2.05
2023/5/30	3700	Head	100	1008	3887	679	2.520	24.400	25.2	3.28
2023/5/19	3900	Head	100	1022	3887	679	2.240	23.700	22.4	-5.49
2023/5/31	3900	Head	100	1022	3887	679	2.330	23.700	23.3	-1.69
2023/5/19	5250	Head	100	1341	3887	679	2.400	23.100	24	3.90
2023/6/1	5250	Head	100	1341	3887	679	2.410	23.100	24.1	4.33
2023/5/22	5600	Head	100	1341	3887	679	2.550	24.000	25.5	6.25
2023/6/2	5600	Head	100	1341	3887	679	2.480	24.000	24.8	3.33
2023/5/23	5750	Head	100	1341	3887	679	2.150	22.700	21.5	-5.29
2023/6/3	5750	Head	100	1341	3887	679	2.320	22.700	23.2	2.20
2023/6/12	3500	Head	100	1037	3887	1437	2.440	25.400	24.4	-3.94
2023/6/12	3700	Head	100	1008	3887	1437	2.370	24.400	23.7	-2.87
2023/6/13	3900	Head	100	1022	3887	1437	2.230	23.700	22.3	-5.91




Fig 11.3.1 System Performance Check Setup



Fig 11.3.2 Setup Photo

12. RF Exposure Positions

12.1 Ear and handset reference point

Figure 12.1.1 shows the front, back, and side views of the SAM phantom. The center-of-mouth reference point is labeled “M,” the left ear reference point (ERP) is marked “LE,” and the right ERP is marked “RE.” Each ERP is 15 mm along the B-M (back-mouth) line behind the entrance-to-ear-canal (EEC) point, as shown in Figure 12.1.2 The Reference Plane is defined as passing through the two ear reference points and point M. The line N-F (neck-front), also called the reference pivoting line, is normal to the Reference Plane and perpendicular to both a line passing through RE and LE and the B-M line (see Figure 12.1.3). Both N-F and B-M lines should be marked on the exterior of the phantom shell to facilitate handset positioning. Posterior to the N-F line the ear shape is a flat surface with 6 mm thickness at each ERP, and forward of the N-F line the ear is truncated, as illustrated in Figure 12.1.2. The ear truncation is introduced to preclude the ear lobe from interfering with handset tilt, which could lead to unstable positioning at the cheek.




Fig 12.1.1 Front, back, and side views of SAM twin phantom




Fig 12.1.2 Close-up side view of phantom showing the ear region.




Fig 12.1.3 Side view of the phantom showing relevant markings and seven cross-sectional plane locations

12.2 Definition of the cheek position

1. Ready the handset for talk operation, if necessary. For example, for handsets with a cover piece (flip cover), open the cover. If the handset can transmit with the cover closed, both configurations must be tested.
2. Define two imaginary lines on the handset—the vertical centerline and the horizontal line. The vertical centerline passes through two points on the front side of the handset—the midpoint of the width w_t of the handset at the level of the acoustic output (point A in Figure 12.2.1 and Figure 12.2.2), and the midpoint of the width w_b of the bottom of the handset (point B). The horizontal line is perpendicular to the vertical centerline and passes through the center of the acoustic output (see Figure 12.2.1). The two lines intersect at point A. Note that for many handsets, point A coincides with the center of the acoustic output; however, the acoustic output may be located elsewhere on the horizontal line. Also note that the vertical centerline is not necessarily parallel to the front face of the handset (see Figure 12.2.2), especially for clamshell handsets, handsets with flip covers, and other irregularly-shaped handsets.
3. Position the handset close to the surface of the phantom such that point A is on the (virtual) extension of the line passing through points RE and LE on the phantom (see Figure 12.2.3), such that the plane defined by the vertical centerline and the horizontal line of the handset is approximately parallel to the sagittal plane of the phantom.
4. Translate the handset towards the phantom along the line passing through RE and LE until handset point A touches the pinna at the ERP.
5. While maintaining the handset in this plane, rotate it around the LE-RE line until the vertical centerline is in the plane normal to the plane containing B-M and N-F lines, i.e., the Reference Plane.
6. Rotate the handset around the vertical centerline until the handset (horizontal line) is parallel to the N-F line.
7. While maintaining the vertical centerline in the Reference Plane, keeping point A on the line passing through RE and LE, and maintaining the handset contact with the pinna, rotate the handset about the N-F line until any point on the handset is in contact with a phantom point below the pinna on the cheek. See Figure 12.2.3. The actual rotation angles should be documented in the test report.




Fig 12.2.1 Handset vertical and horizontal reference lines—“fixed case”




Fig 12.2.2 Handset vertical and horizontal reference lines—“clam-shell case”




Fig 12.2.3 cheek or touch position. The reference points for the right ear (RE), left ear (LE), and mouth (M), which establish the Reference Plane for handset positioning, are indicated.

12.3 Definition of the tilt position

1. Ready the handset for talk operation, if necessary. For example, for handsets with a cover piece (flip cover), open the cover. If the handset can transmit with the cover closed, both configurations must be tested.
2. While maintaining the orientation of the handset, move the handset away from the pinna along the line passing through RE and LE far enough to allow a rotation of the handset away from the cheek by 15°.
3. Rotate the handset around the horizontal line by 15°.
4. While maintaining the orientation of the handset, move the handset towards the phantom on the line passing through RE and LE until any part of the handset touches the ear. The tilt position is obtained when the contact point is on the pinna. See Figure 12.3.1. If contact occurs at any location other than the pinna, e.g., the antenna at the back of the phantom head, the angle of the handset should be reduced. In this case, the tilt position is obtained if any point on the handset is in contact with the pinna and a second point




Fig 12.3.1 Tilt position. The reference points for the right ear (RE), left ear (LE), and mouth (M), which define the Reference Plane for handset positioning, are indicated.

12.4 Body Worn Accessory

Body-worn operating configurations are tested with the belt-clips and holsters attached to the device and positioned against a flat phantom in a normal use configuration (see Figure 11.4). Per KDB648474 D04v01r03, body-worn accessory exposure is typically related to voice mode operations when handsets are carried in body-worn accessories. The body-worn accessory procedures in FCC KDB 447498 D01v06 should be used to test for body-worn accessory SAR compliance, without a headset connected to it. This enables the test results for such configuration to be compatible with that required for hotspot mode when the body-worn accessory test separation distance is greater than or equal to that required for hotspot mode, when applicable. When the reported SAR for body-worn accessory, measured without a headset connected to the handset is $> 1.2 \text{ W/kg}$, the highest reported SAR configuration for that wireless mode and frequency band should be repeated for that body-worn accessory with a headset attached to the handset.

Accessories for body-worn operation configurations are divided into two categories: those that do not contain metallic components and those that do contain metallic components. When multiple accessories that do not contain metallic components are supplied with the device, the device is tested with only the accessory that dictates the closest spacing to the body. Then multiple accessories that contain metallic components are test with the device with each accessory. If multiple accessories share an identical metallic component (i.e. the same metallic belt-chip used with different holsters with no other metallic components) only the accessory that dictates the closest spacing to the body is tested.




Fig 12.4 Body Worn Position

12.5 Product Specific 10g SAR Exposure

For smart phones with a display diagonal dimension > 15.0 cm or an overall diagonal dimension > 16.0 cm, that can provide similar mobile web access and multimedia support found in mini-tablets or UMPC mini-tablets and support voice calls next to the ear, According to KDB648474 D04v01r03, the following phablet procedures should be applied to evaluate SAR compliance for each applicable wireless modes and frequency band. Devices marketed as phablets, regardless of form factors and operating characteristics must be tested as a phablet to determine SAR compliance

1. The normally required head and body-worn accessory SAR test procedures for handsets, including hotspot mode, must be applied.
2. The UMPC mini-tablet procedures must also be applied to test the SAR of all surfaces and edges with an antenna located at ≤ 25 mm from that surface or edge, in direct contact with a flat phantom, for 10-g extremity SAR according to the body-equivalent tissue dielectric parameters in KDB 865664 to address interactive hand use exposure conditions.6 The UMPC mini-tablet 1-g SAR at 5 mm is not required. When hotspot mode applies, 10-g extremity SAR is required only for the surfaces and edges with hotspot mode 1-g reported SAR > 1.2 W/kg.

12.6 Wireless Router

Some battery-operated handsets have the capability to transmit and receive user through simultaneous transmission of WIFI simultaneously with a separate licensed transmitter. The FCC has provided guidance in FCC KDB Publication 941225 D06 v02r01 where SAR test considerations for handsets ($L \times W \geq 9$ cm x 5 cm) are based on a composite test separation distance of 10mm from the front, back and edges of the device containing transmitting antennas within 2.5cm of their edges, determined from general mixed use conditions for this type of devices. Since the hotspot SAR results may overlap with the body-worn accessory SAR requirements, the more conservative configurations can be considered, thus excluding some body-worn accessory SAR tests.

When the user enables the personal wireless router functions for the handset, actual operations include simultaneous transmission of both the WIFI transmitter and another licensed transmitter. Both transmitters often do not transmit at the same transmitting frequency and thus cannot be evaluated for SAR under actual use conditions due to the limitations of the SAR assessment probes. Therefore, SAR must be evaluated for each frequency transmission and mode separately and spatially summed with the WIFI transmitter according to FCC KDB Publication 447498 D01v06 publication procedures. The "Portable Hotspot" feature on the handset was NOT activated during SAR assessments, to ensure the SAR measurements were evaluated for a single transmission frequency RF signal at a time.

13. Conducted RF Output Power (Unit: dBm)

The detailed conducted power table can refer to Appendix E.

<GSM Conducted Power>

1. Per KDB 447498 D01v06, the maximum output power channel is used for SAR testing and for further SAR test reduction.
2. Per KDB 941225 D01v03r01, for SAR test reduction for GSM / GPRS / EDGE modes is determined by the source-based time-averaged output power including tune-up tolerance. The mode with highest specified time-averaged output power should be tested for SAR compliance in the applicable exposure conditions. For modes with the same specified maximum output power and tolerance, the higher number time-slot configuration should be tested.
3. Other configurations of GSM / GPRS / EDGE are considered as secondary modes. The 3G SAR test reduction procedure is applied, when the maximum output power and tune-up tolerance specified for production units in a secondary mode is $\leq \frac{1}{4}$ dB higher than the primary mode, SAR measurement is not required for the secondary mode.

<WCDMA Conducted Power>

1. The following tests were conducted according to the test requirements outlines in 3GPP TS 34.121 specification.
2. The procedures in KDB 941225 D01v03r01 are applied for 3GPP Rel. 6 HSPA to configure the device in the required sub-test mode(s) to determine SAR test exclusion.
3. For HSPA+ devices supporting 16 QAM in the uplink, power measurements procedure is according to the configurations in Table C.11.1.4 of 3GPP TS 34.121-1.
4. For DC-HSDPA, the device was configured according to the H-Set 12, Fixed Reference Channel (FRC) configuration in Table C.8.1.12 of 3GPP TS 34.121-1, with the primary and the secondary serving HS-DSCH Cell enabled during the power measurement.

A summary of these settings are illustrated below:

HSDPA Setup Configuration:

- a. The EUT was connected to Base Station Agilent E5515C referred to the Setup Configuration.
- b. The RF path losses were compensated into the measurements.
- c. A call was established between EUT and Base Station with following setting:
 - i. Set Gain Factors (β_c and β_d) and parameters were set according to each
 - ii. Specific sub-test in the following table, C10.1.4, quoted from the TS 34.121
 - iii. Set RMC 12.2Kbps + HSDPA mode.
 - iv. Set Cell Power = -86 dBm
 - v. Set HS-DSCH Configuration Type to FRC (H-set 1, QPSK)
 - vi. Select HSDPA Uplink Parameters
 - vii. Set Delta ACK, Delta NACK and Delta CQI = 8
 - viii. Set Ack-Nack Repetition Factor to 3
 - ix. Set CQI Feedback Cycle (k) to 4 ms
 - x. Set CQI Repetition Factor to 2
 - xi. Power Ctrl Mode = All Up bits
- d. The transmitted maximum output power was recorded.

Table C.10.1.4: β values for transmitter characteristics tests with HS-DPCCH

Sub-test	β_c	β_d	β_d (SF)	β_o/β_d	β_{HS} (Note 1, Note 2)	CM (dB) (Note 3)	MPR (dB) (Note 3)
1	2/15	15/15	64	2/15	4/15	0.0	0.0
2	12/15 (Note 4)	15/15 (Note 4)	64	12/15 (Note 4)	24/15	1.0	0.0
3	15/15	8/15	64	15/8	30/15	1.5	0.5
4	15/15	4/15	64	15/4	30/15	1.5	0.5

Note 1: $\Delta_{ACK}, \Delta_{NACK}$ and $\Delta_{CQI} = 30/15$ with $\beta_{HS} = 30/15 * \beta_c$.

Note 2: For the HS-DPCCH power mask requirement test in clause 5.2C, 5.7A, and the Error Vector Magnitude (EVM) with HS-DPCCH test in clause 5.13.1A, and HSDPA EVM with phase discontinuity in clause 5.13.1AA, Δ_{ACK} and $\Delta_{NACK} = 30/15$ with $\beta_{HS} = 30/15 * \beta_c$, and $\Delta_{CQI} = 24/15$ with $\beta_{HS} = 24/15 * \beta_c$.

Note 3: CM = 1 for $\beta_o/\beta_d = 12/15, \beta_{HS}/\beta_c = 24/15$. For all other combinations of DPDCH, DPCCH and HS-DPCCH the MPR is based on the relative CM difference. This is applicable for only UEs that support HSDPA in release 6 and later releases.

Note 4: For subtest 2 the β_o/β_d ratio of 12/15 for the TFC during the measurement period (TF1, TF0) is achieved by setting the signalled gain factors for the reference TFC (TF1, TF1) to $\beta_c = 11/15$ and $\beta_d = 15/15$.

Setup Configuration

HSUPA Setup Configuration:

- a. The EUT was connected to Base Station Agilent E5515C referred to the Setup Configuration.
- b. The RF path losses were compensated into the measurements.
- c. A call was established between EUT and Base Station with following setting * :
 - i. Call Configs = 5.2B, 5.9B, 5.10B, and 5.13.2B with QPSK
 - ii. Set the Gain Factors (β_c and β_d) and parameters (AG Index) were set according to each specific sub-test in the following table, C11.1.3, quoted from the TS 34.121
 - iii. Set Cell Power = -86 dBm
 - iv. Set Channel Type = 12.2k + HSPA
 - v. Set UE Target Power
 - vi. Power Ctrl Mode= Alternating bits
 - vii. Set and observe the E-TFCI
 - viii. Confirm that E-TFCI is equal to the target E-TFCI of 75 for sub-test 1, and other subtest's E-TFCI
- d. The transmitted maximum output power was recorded.

Table C.11.1.3: β values for transmitter characteristics tests with HS-DPCCH and E-DCH

Sub-test	β_c	β_d	β_d (SF)	β_c/β_d	β_{HS} (Note1)	β_{ec}	β_{ed} (Note 4) (Note 5)	β_{ed} (SF)	β_{ed} (Codes)	CM (dB) (Note 2)	MPR (dB) (Note 2) (Note 6)	AG Index (Note 5)	E-TFCI
1	11/15 (Note 3)	15/15 (Note 3)	64	11/15 (Note 3)	22/15	209/25	1309/225	4	1	1.0	0.0	20	75
2	6/15	15/15	64	6/15	12/15	12/15	94/75	4	1	3.0	2.0	12	67
3	15/15	9/15	64	15/9	30/15	30/15	$\beta_{ed1}: 47/15$ $\beta_{ed2}: 47/15$	4	2	2.0	1.0	15	92
4	2/15	15/15	64	2/15	4/15	2/15	56/75	4	1	3.0	2.0	17	71
5	15/15	0	-	-	5/15	5/15	47/15	4	1	1.0	0.0	12	67

Note 1: For sub-test 1 to 4, Δ_{ACK} , Δ_{NACK} and $\Delta_{CQI} = 30/15$ with $\beta_{hs} = 30/15 * \beta_c$. For sub-test 5, Δ_{ACK} , Δ_{NACK} and $\Delta_{CQI} = 5/15$ with $\beta_{hs} = 5/15 * \beta_c$.

Note 2: CM = 1 for $\beta_c/\beta_d = 12/15$, $\beta_{hs}/\beta_c = 24/15$. For all other combinations of DPDCH, DPCCH, HS-DPCCH, E-DPDCH and E-DPCCH the MPR is based on the relative CM difference.

Note 3: For subtest 1 the β_c/β_d ratio of 11/15 for the TFC during the measurement period (TF1, TF0) is achieved by setting the signalled gain factors for the reference TFC (TF1, TF0) to $\beta_c = 10/15$ and $\beta_d = 15/15$.

Note 4: In case of testing by UE using E-DPDCH Physical Layer category 1, Sub-test 3 is omitted according to TS25.306 Table 5.1g.

Note 5: β_{ed} can not be set directly; it is set by Absolute Grant Value.

Note 6: For subtests 2, 3 and 4, UE may perform E-DPDCH power scaling at max power which could results in slightly smaller MPR values.

Setup Configuration

DC-HSDPA 3GPP release 8 Setup Configuration:

- a. The EUT was connected to Base Station referred to the Setup Configuration below
- b. The RF path losses were compensated into the measurements.
- c. A call was established between EUT and Base Station with following setting:
 - i. Set RMC 12.2Kbps + HSDPA mode.
 - ii. Set Cell Power = -25 dBm
 - iii. Set HS-DSCH Configuration Type to FRC (H-set 12, QPSK)
 - iv. Select HSDPA Uplink Parameters
 - v. Set Gain Factors (β_c and β_d) and parameters were set according to each Specific sub-test in the following table, C10.1.4, quoted from the TS 34.121
 - a). Subtest 1: $\beta_c/\beta_d=2/15$
 - b). Subtest 2: $\beta_c/\beta_d=12/15$
 - c). Subtest 3: $\beta_c/\beta_d=15/8$
 - d). Subtest 4: $\beta_c/\beta_d=15/4$
 - vi. Set Delta ACK, Delta NACK and Delta CQI = 8
 - vii. Set Ack-Nack Repetition Factor to 3
 - viii. Set CQI Feedback Cycle (k) to 4 ms
 - ix. Set CQI Repetition Factor to 2
 - x. Power Ctrl Mode = All Up bits
- d. The transmitted maximum output power was recorded.

The following tests were conducted according to the test requirements outlines in 3GPP TS 34.121 specification. A summary of these settings are illustrated below:

C.8.1.12 Fixed Reference Channel Definition H-Set 12

Table C.8.1.12: Fixed Reference Channel H-Set 12

Parameter	Unit	Value
Nominal Avg. Inf. Bit Rate	kbps	60
Inter-TTI Distance	TTI's	1
Number of HARQ Processes	Processes	6
Information Bit Payload (N_{INF})	Bits	120
Number Code Blocks	Blocks	1
Binary Channel Bits Per TTI	Bits	960
Total Available SML's in UE	SML's	19200
Number of SML's per HARQ Proc.	SML's	3200
Coding Rate		0.15
Number of Physical Channel Codes	Codes	1
Modulation		QPSK
Note 1: The RMC is intended to be used for DC-HSDPA mode and both cells shall transmit with identical parameters as listed in the table. Note 2: Maximum number of transmission is limited to 1, i.e., retransmission is not allowed. The redundancy and constellation version 0 shall be used.		




Figure C.8.19: Coding rate for Fixed reference Channel H-Set 12 (QPSK) Setup Configuration

HSPA+ 3GPP release 7 (uplink category 7) 16QAM, Setup Configuration:

1. The EUT was connected to Base Station Agilent E5515C referred to the Setup Configuration.
2. The RF path losses were compensated into the measurements.
3. A call was established between EUT and Base Station with following setting * :
 - i. Call Configs = 5.2E:HSPA+:UL with 16QAM
 - ii. Set the Gain Factors (β_c and β_d) and parameters (AG Index) were set according to each specific sub-test in the following table, C11.1.4, quoted from the TS 34.121-1 s5.2E
 - iii. Set Channel Parms
 - iv. Set Cell Power = -86 dBm
 - v. Set Channel Type = HSPA
 - vi. Set UE Target Power =21 dBm
 - vii. Power Ctrl Mode= All Up Bits
 - viii. Set Manual Uplink DPCH Bc/Bd = Manual
 - ix. Set Manual Uplink DPCH Bc and Bd=15,15(for 34.121-1 v8.10.0 table C11.1.4 sub-test 1)
 - x. Set HSPA Conn DL Channel Levels
 - xi. Set HS-SCCH Configs
 - xii. Set RB Test Mode Setup
 - xiii. Set Common HSUPA Parameters
 - xiv. Set Serving Grant
 - xv. Confirm that E-TFCl is equal to the target E-TFCl of 105 for sub-test 1, and other subtest's E-TFCl
4. The transmitted maximum output power was recorded.

Table C.11.1.4: β values for transmitter characteristics tests with HS-DPCCH and E-DCH with 16QAM

Sub-test	β_c (Note3)	β_d	β_{HS} (Note1)	β_{ec}	β_{ed} (2xSF2) (Note 4)	β_{ed} (2xSF4) (Note 4)	CM (dB) (Note 2)	MPR (dB) (Note 2)	AG Index (Note 4)	E-TFCl (Note 5)	E-TFCl (boost)
1	1	0	30/15	30/15	β_{ed1} : 30/15 β_{ed2} : 30/15	β_{ed3} : 24/15 β_{ed4} : 24/15	3.5	2.5	14	105	105

Note 1: $\Delta_{ACK}, \Delta_{NACK}$ and $\Delta_{CQI} = 30/15$ with $\beta_{fs} = 30/15 * \beta_c$.

Note 2: CM = 3.5 and the MPR is based on the relative CM difference, MPR = MAX(CM-1,0).

Note 3: DPDCH is not configured, therefore the β_c is set to 1 and $\beta_d = 0$ by default.

Note 4: β_{ed} can not be set directly; it is set by Absolute Grant Value.

Note 5: All the sub-tests require the UE to transmit 2SF2+2SF4 16QAM EDCH and they apply for UE using E-DPDCH category 7. E-DCH TTI is set to 2ms TTI and E-DCH table index = 2. To support these E-DCH configurations DPDCH is not allocated. The UE is signaled to use the extrapolation algorithm.

Setup Configuration

<WCDMA Conducted Power>


General Note:

1. Per KDB 941225 D01v03r01, for SAR testing is measured using a 12.2 kbps RMC with TPC bits configured to all "1's".
2. Per KDB 941225 D01v03r01, RMC 12.2kbps setting is used to evaluate SAR. The maximum output power and tune-up tolerance specified for production units in HSDPA / HSUPA / DC-HSDPA / HSPA+ is $\leq 1/4$ dB higher than RMC 12.2Kbps or when the highest reported SAR of the RMC12.2Kbps is scaled by the ratio of specified maximum output power and tune-up tolerance of HSDPA / HSUPA / DC-HSDPA / HSPA+ to RMC12.2Kbps and the adjusted SAR is ≤ 1.2 W/kg, SAR measurement is not required for HSDPA / HSUPA / DC-HSDPA / HSPA+, and according to the following RF output power, the output power results of the secondary modes (HSDPA / HSUPA / DC-HSDPA / HSPA+) are less than $1/4$ dB higher than the primary modes; therefore, SAR measurement is not required for HSDPA / HSUPA / DC-HSDPA / HSPA+.

<LTE Conducted Power>

General Note:

1. Anritsu MT8820C base station simulator was used to setup the connection with EUT; the frequency band, channel bandwidth, RB allocation configuration, modulation type are set in the base station simulator to configure EUT transmitting at maximum power and at different configurations which are requested to be reported to FCC, for conducted power measurement and SAR testing.
2. Per KDB 941225 D05v02r05, when a properly configured base station simulator is used for the SAR and power measurements, spectrum plots for each RB allocation and offset configuration is not required.
3. Per KDB 941225 D05v02r05, start with the largest channel bandwidth and measure SAR for QPSK with 1 RB allocation, using the RB offset and required test channel combination with the highest maximum output power for RB offsets at the upper edge, middle and lower edge of each required test channel.
4. Per KDB 941225 D05v02r05, 50% RB allocation for QPSK SAR testing follows 1RB QPSK allocation procedure.
5. Per KDB 941225 D05v02r05, for QPSK with 100% RB allocation, SAR is not required when the highest maximum output power for 100 % RB allocation is less than the highest maximum output power in 50% and 1 RB allocations and the highest reported SAR for 1 RB and 50% RB allocation are ≤ 0.8 W/kg. Otherwise, SAR is measured for the highest output power channel; and if the reported SAR is > 1.45 W/kg, the remaining required test channels must also be tested.
6. Per KDB 941225 D05v02r05, 16QAM/64QAM/256QAM output power for each RB allocation configuration is $>$ not $\frac{1}{2}$ dB higher than the same configuration in QPSK and the reported SAR for the QPSK configuration is ≤ 1.45 W/kg; Per KDB 941225 D05v02r05, 16QAM/64QAM/256QAM SAR testing is not required.
7. Per KDB 941225 D05v02r05, smaller bandwidth output power for each RB allocation configuration is $>$ not $\frac{1}{2}$ dB higher than the same configuration in the largest supported bandwidth, and the reported SAR for the largest supported bandwidth is ≤ 1.45 W/kg; Per KDB 941225 D05v02r05, smaller bandwidth SAR testing is not required.
8. For LTE B4 / B5 / B12 / B17 / B26 / B38 the maximum bandwidth does not support three non-overlapping channels, per KDB 941225 D05v02r05, when a device supports overlapping channel assignment in a channel bandwidth configuration, the middle channel of the group of overlapping channels should be selected for testing.
9. LTE B4 / B5 / B17 / B38 SAR test was covered by B66 / B26 / B12 / B41; according to April 2015 TCB workshop, SAR test for overlapping LTE bands can be reduced if
 - a. the maximum output power, including tolerance, for the smaller band is \leq the larger band to qualify for the SAR test exclusion
 - b. the channel bandwidth and other operating parameters for the smaller band are fully supported by the larger band
10. According to May 2017 TCB workshop, for 16QAM and 64QAM, 256QAM should be verified by checking the signal constellation with a call box to avoid incorrect maximum power levels due to MPR and other requirements associated with signal modulation, and the following figure is taken from the "Fundamental Measurement >> Modulation Analysis >> constellation" mode of the device connect to the MT8821C base station, therefore, the device 256QAM, 64QAM and 16QAM signal modulation are correct.



<TDD LTE SAR Measurement>

TDD LTE configuration setup for SAR measurement

SAR was tested with a fixed periodic duty factor according to the highest transmission duty factor implemented for the device and supported by 3GPP.

- a. 3GPP TS 36.211 section 4.2 for Type 2 Frame Structure and Table 4.2-2 for uplink-downlink configurations
- b. "special subframe S" contains both uplink and downlink transmissions, it has been taken into consideration to determine the transmission duty factor according to the worst case uplink and downlink cyclic prefix requirements for UpPTS
- c. Establishing connections with base station simulators ensure a consistent means for testing SAR and recommended for evaluating SAR. The Anritsu MT8820C (firmware: #22.52#004) was used for LTE output power measurements and SAR testing.




Figure 4.2-1: Frame structure type 2 (for 5 ms switch-point periodicity).

Table 4.2-2: Uplink-downlink configurations.

Uplink-downlink configuration	Downlink-to-Uplink Switch-point periodicity	Subframe number									
		0	1	2	3	4	5	6	7	8	9
0	5 ms	D	S	U	U	U	D	S	U	U	U
1	5 ms	D	S	U	U	D	D	S	U	U	D
2	5 ms	D	S	U	D	D	D	S	U	D	D
3	10 ms	D	S	U	U	U	D	D	D	D	D
4	10 ms	D	S	U	U	D	D	D	D	D	D
5	10 ms	D	S	U	D	D	D	D	D	D	D
6	5 ms	D	S	U	U	D	S	U	U	D	

Table 4.2-1: Configuration of special subframe (lengths of DwPTS/GP/UpPTS).

Special subframe configuration	Normal cyclic prefix in downlink				Extended cyclic prefix in downlink		
	DwPTS	UpPTS		DwPTS	UpPTS		
		Normal cyclic prefix in uplink	Extended cyclic prefix in uplink		Normal cyclic prefix in uplink	Extended cyclic prefix in uplink	
0	6592 · Ts	2192 · Ts	2560 · Ts	7680 · Ts	2192 · Ts	2560 · Ts	
1	19760 · Ts			20480 · Ts			
2	21952 · Ts			23040 · Ts			
3	24144 · Ts			25600 · Ts			
4	26336 · Ts			7680 · Ts	4384 · Ts	5120 · Ts	
5	6592 · Ts	4384 · Ts	5120 · Ts	20480 · Ts			
6	19760 · Ts			23040 · Ts			
7	21952 · Ts			12800 · Ts			
8	24144 · Ts			-	-	-	
9	13168 · Ts			-	-	-	

Special subframe (30720·T_s): Normal cyclic prefix in downlink (UpPTS)			
	Special subframe configuration	Normal cyclic prefix in uplink	Extended cyclic prefix in uplink
Uplink duty factor in one special subframe	0~4	7.13%	8.33%
	5~9	14.3%	16.7%

Special subframe(30720·T_s): Extended cyclic prefix in downlink (UpPTS)			
	Special subframe configuration	Normal cyclic prefix in uplink	Extended cyclic prefix in uplink
Uplink duty factor in one special subframe	0~3	7.13%	8.33%
	4~7	14.3%	16.7%

The highest duty factor is resulted from:

- i. Uplink-downlink configuration: 0. In a half-frame consisted of 5 subframes, uplink operation is in 3 uplink subframes and 1 special subframe.
- ii. special subframe configuration: 5-9 for normal cyclic prefix in downlink, 4-7 for extended cyclic prefix in downlink
- iii. for special subframe with extended cyclic prefix in uplink, the total uplink duty factor in one half-frame is: $(3+0.167)/5 = 63.3\%$
- iv. for special subframe with normal cyclic prefix in uplink, the total uplink duty factor in one half-frame is: $(3+0.143)/5 = 62.9\%$
- v. For TDD LTE SAR measurement, the duty cycle 1:1.59 (62.9 %) was used perform testing and considering the theoretical duty cycle of 63.3% for extended cyclic prefix in the uplink, and the theoretical duty cycle of 62.9% for normal cyclic prefix in uplink, a scaling factor of extended cyclic prefix $63.3\%/62.9\% = 1.006$ is applied to scale-up the measured SAR result. The scaled TDD LTE SAR = measured SAR (W/kg)* Tune-up Scaling Factor* scaling factor for extended cyclic prefix.



<LTE Carrier Aggregation>

General Note:

1. This device supports Carrier Aggregation on downlink for inter and intra band. For the device supports bands and bandwidths and configurations are provided as follow table was according to 3GPP.
2. In applying the existing power measurement procedures of KDB 941225 D05A for DL CA SAR test exclusion, only the subset with the largest number of combinations of frequency bands and CCs in each row need combination, and for this device that all the configurations were choose to power measurement.
3. All permutations exist. No restrictions on Pcell & Scell combinations.
4. The gray color table is covered by other combinations and no need to verify power

2CC Downlink Carrier Aggregation					3CC Downlink Carrier Aggregation				
Number	Combination	4X4 MIMO	Restriction	Covered by Measurement Superset	Number	Combination	4X4 MIMO	Restriction	Covered by Measurement Superset
1	CA_12A-66A	66A			1	CA_2A-4A-5A			
2	CA_2A-4A			3CC-1	2	CA_2A-7A-66A	66A		
3	CA_2A-5A			3CC-1	3	CA_2A-7A-7A			
4	CA_2A-7A			3CC-2	4	CA_2A-7C			
5	CA_2C				5	CA_41A-41A-41A	41A-41A-41A		
6	CA_38C	38C			6	CA_41D	41D		
7	CA_41A-41A	41A-41A		3CC-5	7	CA_4A-7C	4A-7C		
8	CA_41C	41C			8	CA_5A-7C	7C		
9	CA_4A-5A	4A		3CC-1	9	CA_7A-66A-66A	7A,66A-66A		
10	CA_4A-7A	4A-7A		3CC-11	10	CA_5A-7A-7A	7A-7A		
11	CA_5A-7A	7A		3CC-10	11	CA_2A-4A-7A			
12	CA_66A-66A	66A-66A		3CC-9	12	CA_2A-5A-66A	66A		
13	CA_38C	38C			13	CA_2A-5A-7A			
14	CA_7A-7A	7A-7A		3CC-3	14	CA_5A-66A-66A	66A-66A		
15	CA_7C	7C		3CC-4	15				
16	CA_66C	66C			16				
17	CA_66B	66B			17				
18	CA_2A-2A				18				
19	CA_2A-66A	66A		3CC-2	19				
20	CA_7A-66A	7A,66A		3CC-2	20				
21	CA_5A-66A	66A		3CC-12	21				
22	CA_4A-4A	4A-4A			22				
23	CA_7A-26A	7A			23				
24	CA_26A-38A	38A			24				
25	CA_26A-41A	41A			25				
26	CA_2A-26A				26				
27	CA_2A-38A				27				

LTE Carrier Aggregation Conducted Power (Downlink)

- i. According to KDB941225 D05A v01r02, Uplink maximum output power measurement with downlink carrier aggregation active should be measured, using the highest output channel measured without downlink carrier aggregation, to confirm that uplink maximum output power with downlink carrier aggregation active remains within the specified tune-up tolerance limits and not more than ¼ dB higher than the maximum output measured without downlink carrier aggregation active.
- ii. Uplink maximum output power with downlink carrier aggregation active does not show more than ¼ dB higher than the maximum output power without downlink carrier aggregation active, therefore SAR evaluation with downlink carrier aggregation active can be excluded.
- iii. The device supports downlink three carrier aggregation. For power measurement were control and acknowledge data is sent on uplink channels that operate identical to specifications when downlink carrier aggregation is inactive.
- iv. Selected highest measured power when downlink carrier aggregation is inactive for conducted power comparison with downlink carrier aggregation is active, to confirm that when downlink carrier aggregation is active uplink maximum output power remains within the specified tune-up tolerance limits and not more than ¼ dB higher than the maximum output power measured when downlink carrier aggregation inactive.
- v. For inter-band CA, the SCC selected highest bandwidth and near the middle of its transmission band. For SCC DL RB size and offset will base on the PCC corresponding RB allocation.
- vi. For non-contiguous intra-band CA, the SCC selected to provide maximum separation from the PCC and must remain fully within the downlink transmission band.
- vii. For Intra-band, contiguous CA, the downlink channels selected to perform the uplink power measurement must satisfy 3GPP channel spacing (5.4.1A of 3GPP TS 36.521 or equivalent) and channel bandwidth (5.4.2A) requirements.

$$\text{Nominal channel spacing} = \left\lceil \frac{BW_{\text{Channel}(1)} + BW_{\text{Channel}(2)} - 0.1|BW_{\text{Channel}(1)} - BW_{\text{Channel}(2)}|}{0.6} \right\rceil 0.3 \text{ [MHz]}$$

LTE 4x4 MIMO (Downlink)

This device supports downlink 4x4 MIMO operations for LTE Band 4/7/66/38/41 only. Uplink transmission is limited to a single output stream. Power measurements were performed with downlink 4x4 MIMO active for the configuration with highest measured maximum conducted power with 4x4 downlink MIMO inactive measured among the channel bandwidth, modulation, and RB combinations in each frequency band.

Per FCC Guidance, SAR for downlink 4x4 MIMO was not needed since the maximum average output power in 4x4 downlink MIMO mode was not > 0.25 dB higher than the maximum output power with downlink 4x4 MIMO inactive. When carrier aggregation is applicable, power measurements were performed with the downlink carrier aggregation and 4x4 DL MIMO active for the configuration with highest measured maximum conducted power with downlink carrier aggregation inactive measured among the channel bandwidth, modulation, and RB combinations in each frequency band.

4X4 MIMO	Band
	LTE Band 4/7/66/38/41

LTE Carrier Aggregation Conducted Power (Uplink)

LTE Uplink CA	2CC Uplink Carrier Aggregation
Intra-band	Antenna Tx
CA_7C	Ant1/2/3/4
CA_38C	Ant1/2/3/4

<Intra-band>

General Note:

- i. The device supports intra-band uplink carrier aggregation for LTE B7/38 with a maximum of two uplink component carriers. For intra band contiguous carrier aggregation scenarios, 3GPP 36.101 table 6.2.2A-1 specifies that the aggregate maximum allowed output power is equivalent to the single carrier scenario. 3GPP 36.101 6.2.3A allows for several dB of MPR to be applied when not-contiguous RB allocation is implemented. The conducted power and MPR setting in this device are permanently implemented pre 3GPP requirement.
- ii. The device supports uplink carrier aggregation with a maximum of two uplink component carriers. For intra band contiguous carrier aggregation scenarios, 3GPP 36.101 table 6.2.2A-1 specifies that the aggregate maximum allowed output power is equivalent to the single carrier scenario. 3GPP 36.101 6.2.3A allows for several dB of MPR to be applied when not-contiguous RB allocation is implemented. The conducted power and MPR setting in this device are permanently implemented pre the 3GPP requirement.
- iii. According Nov. 2017 TCB workshop, the output power with uplink CA active was measured for the configuration with the highest reported SAR with single carrier for each exposure condition. The power was measured with wideband signal integration over both component carriers.
- iv. Additional SAR measurement for LTE UL CA with other DL CA combinations active were not required since the maximum output power for this configuration was not > 0.25dB higher than the maximum output power for UL CA active.

<Inter-band uplink carrier aggregation consideration>

LTE Uplink CA	2CC Uplink Carrier Aggregation	
Inter-band	Antenna Tx	Antenna Tx
CA_2A-4A	B2: Ant2/4	B4: Ant1/3
CA_4A-7A	B4: Ant1/2/3/4	B7: Ant1/2/3/4

General Note:

1. In inter-band UL CA operation, the each PCC TX power level will be less than or same as the standalone LTE operation. For Inter-band CA co-located SAR analysis is performed using standalone SAR summed together and they are more conservatively for inter band CA.

5G NR Output Power (Unit: dBm)

General Note:

1. 5G NR n5/n7/n66/n38/n41/n78 is NSA mode.
2. 5G NR n5/n7/n66/n38/n41/n77/n78 is SA mode.
3. For 5G NR test procedure was following step similar FCC KDB 941225 D05:
 - a. For DFT-OFDM and CP-OFDM output power measurement reduction, according to 38.101 maximum power reduction for power class2 and 3, the CP-OFDM mode will not higher than DFT-OFDM mode, therefore, similar FCC KDB 941225 D05 procedure for other modulation output power for each RB allocation configuration is > not ½ dB higher than the same configuration in DFT-s QPSK and the reported SAR for the DFT-s QPSK configuration is ≤ 1.45 W/kg; CP-OFDM testing is not required.
 - b. For DFT-OFDM output power measurement reduction, according to 38.101 maximum power reduction for power class2 and 3, for 16QAM/64QAM/256QAM and smaller bandwidth output power will spot check largest channel bandwidth worst RB configuration to ensure the 16QAM/64QAM/256QAM and smaller bandwidth output power will not ½ dB higher than the same configuration in the largest supported bandwidth.
 - c. SAR testing start with the largest channel bandwidth and measure SAR for QPSK with 1 RB allocation, using the RB offset and required test channel combination with the highest maximum output power for RB offsets at the upper edge, middle and lower edge of each required test channel
 - d. 50% RB allocation for QPSK SAR testing follows 1RB QPSK allocation procedure
 - e. QPSK with 100% RB allocation, SAR is not required when the highest maximum output power for 100 % RB allocation is less than the highest maximum output power in 50% and 1 RB allocations and the highest reported SAR for 1 RB and 50% RB allocation are ≤ 0.8 W/kg. Otherwise, SAR is measured for the highest output power channel; and if the reported SAR is > 1.45 W/kg, the remaining required test channels must also be tested
 - f. PI/2 BPSK/16QAM/64QAM/256QAM output powers according to 3GPP MPR will not ½ dB higher than the same configuration in QPSK, also reported SAR for the QPSK configuration is less than 1.45 W/kg, PI/2 BPSK /16QAM/64QAM/256QAM SAR testing are not required.
 - g. Smaller bandwidth output power for each RB allocation configuration for this device will not ½ dB higher than the same configuration in the largest supported bandwidth, and the reported SAR for the largest supported bandwidth is ≤ 1.45 W/kg, smaller bandwidth SAR testing is not required for this device
4. For 5G NR n77/n78 HPUE, 5G NR n77/n78 PC2 Maximum Duty Cycle is 50%, using FTM (Factory Test Mode) with 50% duty cycle is considered during SAR testing. For 5G NR other bands, using FTM to perform SAR with default 100% transmission.
5. For 5G NR, the simultaneous transmission analysis is used standalone SAR at total power level to show compliance.
6. NSA and SA mode should perform SAR separately. For the maximum power of NSA mode is the same as SA total power level, so SA SAR can represent NSA mode SAR.
7. 5G NR NSA mode, the power level is the same as 5G NR SA mode, so 5G NR NSA mode and SA mode power table only show one time.
8. 5G NR supports CP-OFDM and DFT-s-OFDM modulation, for DFT-s-OFDM power is higher than CP-OFDM, so only show DFT-s-OFDM power table and chose DFT-s-OFDM to perform SAR testing.
9. For DFT-s-OFDM and CP-OFDM output power measurement reduction, according to 38.101 maximum power reduction for the CP-OFDM mode will not higher than DFT-s-OFDM mode, therefore, CP-OFDM measurement is unnecessary.
10. 5G NR n77/n78 supports HPUE, HPUE power and SAR testing performed separately.
11. For 5G NR EN-DC mode, standalone SAR performed for 5G NR NSA band with the maximum power, EN-DC SAR summed EN-DC mode 5G NR standalone SAR and LTE standalone SAR, the result of EN-DC SAR is more conservatively.

<3GPP 38.101 MPR for EN-DC>

Table 6.2.2-1 Maximum power reduction (MPR) for power class 3

Modulation		MPR (dB)		
		Edge RB allocations	Outer RB allocations	Inner RB allocations
DFT-s-OFDM	Pi/2 BPSK	$\leq 3.5^1$	$\leq 1.2^1$	$\leq 0.2^1$
		$\leq 0.5^2$	$\leq 0.5^2$	0 ²
	QPSK		≤ 1	0
	16 QAM		≤ 2	≤ 1
	64 QAM		≤ 2.5	
CP-OFDM	256 QAM		≤ 4.5	
	QPSK	≤ 3		≤ 1.5
	16 QAM	≤ 3		≤ 2
	64 QAM		≤ 3.5	
	256 QAM		≤ 6.5	

NOTE 1: Applicable for UE operating in TDD mode with Pi/2 BPSK modulation and UE indicates support for UE capability *powerBoosting-pi2BPSK* and if the IE *powerBoostPi2BPSK* is set to 1 and 40 % or less slots in radio frame are used for UL transmission for bands n40, n41, n77, n78 and n79. The reference power of 0 dB MPR is 26 dBm.

NOTE 2: Applicable for UE operating in FDD mode, or in TDD mode in bands other than n40, n41, n77, n78 and n79 with Pi/2 BPSK modulation and if the IE *powerBoostPi2BPSK* is set to 0 and if more than 40 % of slots in radio frame are used for UL transmission for bands n40, n41, n77, n78 and n79.

Table 6.2.2-2 Maximum power reduction (MPR) for power class 2

Modulation		MPR (dB)		
		Edge RB allocations	Outer RB allocations	Inner RB allocations
DFT-s-OFDM	Pi/2 BPSK	≤ 3.5	≤ 0.5	0
	QPSK	≤ 3.5	≤ 1	0
	16 QAM	≤ 3.5	≤ 2	≤ 1
	64 QAM	≤ 3.5		≤ 2.5
	256 QAM		≤ 4.5	
CP-OFDM	QPSK	≤ 3.5	≤ 3	≤ 1.5
	16 QAM	≤ 3.5	≤ 3	≤ 2
	64 QAM		≤ 3.5	
	256 QAM		≤ 6.5	



<EN-DC combination>

ENDC	Band	Antenna Tx
DC_7A_n5A	N5	Ant 0
		Ant 1
	B7	Ant 1
		Ant 2
		Ant 3
DC_66A_n7A	N7	Ant 4
		Ant 1
		Ant 2
		Ant 3
	B66	Ant 4
DC_66A_n38A	N38	Ant 1
		Ant 3
		Ant 4
	B66	Ant 1
		Ant 3
DC_12A_n66A	N66	Ant 1
		Ant 2
		Ant 3
		Ant 4
	B12	Ant 0
DC_2A_n66A	N66	Ant 1
		Ant 2
		Ant 3
		Ant 4
	B2	Ant 2
DC_5A_n66A	N66	Ant 4
		Ant 1
		Ant 2
		Ant 3
	B5	Ant 4
DC_66A_n66A	N66	ANT0
		ANT1
		Ant 1
		Ant 2
	B66	Ant 3
Ant 4		
Ant 1		
Ant 2		
DC_7A_n66A	N66	Ant 3
		Ant 4
	B7	Ant 1
		Ant 2
		Ant 3
DC_2A_n78A	N78	Ant 4
		Ant 1
		Ant 5
		Ant 6



		Ant 7
	B2	Ant 2
		Ant 4
DC_66A_n41A	N41	Ant 1
		Ant 2
		Ant 3
	B66	Ant 4
		Ant 1
		Ant 3
DC_38A_n78A	N78	Ant 1
		Ant 5
		Ant 6
		Ant 7
	B38	Ant 1
		Ant 2
		Ant 3
		Ant 4
DC_41A_n78A	N78	Ant 1
		Ant 5
		Ant 6
		Ant 7
	B41	Ant 1
		Ant 2
		Ant 3
		Ant 4
DC_5A_n78A	N78	Ant 1
		Ant 5
		Ant 6
	B5	Ant 7
		Ant 0
		Ant 1
DC_66A_n78A	N78	Ant 1
		Ant 5
		Ant 6
		Ant 7
	B66	Ant 1
		Ant 2
		Ant 3
		Ant 4
DC_7A_n78A	N78	Ant 1
		Ant 5
		Ant 6
		Ant 7
	B7	Ant 1
		Ant 2
		Ant 3
		Ant 4
DC_26A_n78A	N78	Ant 1
		Ant 5
		Ant 6
	B26	Ant 7
		Ant 0
		Ant 1

<WLAN Conducted Power>


General Note:

1. The maximum output power specified for production units are determined for all applicable 802.11 transmission modes in each standalone and aggregated frequency band. Maximum output power is measured for the highest maximum output power configuration(s) in each frequency band according to the default power measurement procedures. For "Not required", SAR Test reduction was applied from KDB 248227 guidance, Sec. 2.1, b), 1) when the same maximum power is specified for multiple transmission modes in a frequency band, the largest channel bandwidth, lowest order modulation, lowest data rate and lowest order 802.11a/g/n/ac mode is used for SAR measurement, on the highest measured output power channel in the initial test configuration. Additional output power measurements were not necessary.
2. Per KDB 248227 D01v02r02, SAR test reduction is determined according to 802.11 transmission mode configurations and certain exposure conditions with multiple test positions. In the 2.4 GHz band, separate SAR procedures are applied to DSSS and OFDM configurations to simplify DSSS test requirements. For OFDM, in both 2.4 and 5 GHz bands, an initial test configuration must be determined for each standalone and aggregated frequency band, according to the transmission mode configuration with the highest maximum output power specified for production units to perform SAR measurements. If the same highest maximum output power applies to different combinations of channel bandwidths, modulations and data rates, additional procedures are applied to determine which test configurations require SAR measurement. When applicable, an initial test position may be applied to reduce the number of SAR measurements required for next to the ear, UMPC mini-tablet or hotspot mode configurations with multiple test positions.
3. For 2.4 GHz 802.11b DSSS, either the initial test position procedure for multiple exposure test positions or the DSSS procedure for fixed exposure position is applied; these are mutually exclusive. For 2.4 GHz and 5 GHz OFDM configurations, the initial test configuration is applied to measure SAR using either the initial test position procedure for multiple exposure test position configurations or the initial test configuration procedures for fixed exposure test conditions. Based on the reported SAR of the measured configurations and maximum output power of the transmission mode configurations that are not included in the initial test configuration, the subsequent test configuration and initial test position procedures are applied to determine if SAR measurements are required for the remaining OFDM transmission configurations. In general, the number of test channels that require SAR measurement is minimized based on maximum output power measured for the test sample(s).
4. For OFDM transmission configurations in the 2.4 GHz and 5 GHz bands, When the same maximum power is specified for multiple transmission modes in a frequency band, the largest channel bandwidth, lowest order modulation, lowest data rate and lowest order 802.11a/g/n/ac mode is used for SAR measurement, on the highest measured output power channel for each frequency band.
5. DSSS and OFDM configurations are considered separately according to the required SAR procedures. SAR is measured in the initial test position using the 802.11 transmission mode configuration required by the DSSS procedure or initial test configuration and subsequent test configuration(s) according to the OFDM procedures.18 The initial test position procedure is described in the following:
 - a. When the reported SAR of the initial test position is ≤ 0.4 W/kg, further SAR measurement is not required for the other test positions in that exposure configuration and 802.11 transmission mode combinations within the frequency band or aggregated band.
 - b. When the reported SAR of the test position is > 0.4 W/kg, SAR is repeated for the 802.11 transmission mode configuration tested in the initial test position to measure the subsequent next closet/smallest test separation distance and maximum coupling test position on the highest maximum output power channel, until the report SAR is ≤ 0.8 W/kg or all required test position are tested.
 - c. For all positions/configurations, when the reported SAR is > 0.8 W/kg, SAR is measured for these test positions/configurations on the subsequent next highest measured output power channel(s) until the reported SAR is ≤ 1.2 W/kg or all required channels are tested.
6. 802.11ax full tone and partial tone supported for WLAN2.4GHz/WLAN5GHz, after verification for the partial tone power level is far less than full tone power level, so we chose full tone power to be measured in this report.
7. The 2.4GHz/5GHz WLAN can transmit in SISO and MIMO antenna mode.
8. SISO and MIMO all supported by WLAN2.4GHz/WLAN5GHz, for SISO mode power is less than per chain power of MIMO mode. For WLAN SISO & MIMO mode, the whole testing has assessed only MIMO mode by referring to their higher conducted power, so only chose MIMO mode to perform SAR testing. However, in order to do SISO simultaneous transmission, we tested the WLAN 2.4G SISO antenna 17 and WLAN 5G SISO antenna 18.
9. For the conducted power measurement is MIMO chains transmitting simultaneously and measured the separately conducted power for both chains and then based on the conducted power of two antennas respectively to calculate sum of the power for MIMO mode.

<2.4GHz Bluetooth>

General Note:

1. For 2.4GHz Bluetooth SAR testing was selected 1Mbps, due to its highest average power.
2. The Bluetooth duty cycle is 76.4 % as following figure, according to Oct. 2016 TCB workshop for Bluetooth SAR scaling need further consideration and the maximum duty cycle is 100%, therefore the actual duty cycle will be scaled up to 100% for Bluetooth reported SAR calculation.





14. Antenna Location

The detailed antenna location information can refer to SAR Test Setup Photos.

15. SAR Test Results

General Note:

1. Per KDB 447498 D01v06, the reported SAR is the measured SAR value adjusted for maximum tune-up tolerance.
 - a. Tune-up scaling Factor = tune-up limit power (mW) / EUT RF power (mW), where tune-up limit is the maximum rated power among all production units.
 - b. For SAR testing of WLAN signal with non-100% duty cycle, the measured SAR is scaled-up by the duty cycle scaling factor which is equal to "1/(duty cycle)"
 - c. For SAR testing of Bluetooth signal with 83.3% theoretical duty cycle, the measured SAR is scaled-up by the duty cycle scaling factor which is equal to "1/(duty cycle) *83.3%".
 - d. For WWAN: Reported SAR(W/kg)= Measured SAR(W/kg)*Tune-up Scaling Factor
 - e. For BT/WLAN: Reported SAR(W/kg)= Measured SAR(W/kg)* Duty Cycle scaling factor * Tune-up scaling factor
 - f. For TDD LTE SAR measurement of power class 3, the duty cycle 1:1.59 (62.9 %) was used perform testing and considering the theoretical duty cycle of 63.3% for extended cyclic prefix in the uplink, and the theoretical duty cycle of 62.9% for normal cyclic prefix in uplink, a scaling factor of extended cyclic prefix 63.3%/62.9% = 1.006 is applied to scale-up the measured SAR result. The reported TDD LTE SAR (W/kg) = Measured SAR (W/kg)* Tune-up Scaling Factor* scaling factor for extended cyclic prefix.
2. Per KDB 447498 D01v06, for each exposure position, testing of other required channels within the operating mode of a frequency band is not required when the *reported* 1-g or 10-g SAR for the mid-band or highest output power channel is:
 - ≤ 0.8 W/kg or 2.0 W/kg, for 1-g or 10-g respectively, when the transmission band is ≤ 100 MHz
 - ≤ 0.6 W/kg or 1.5 W/kg, for 1-g or 10-g respectively, when the transmission band is between 100 MHz and 200 MHz
 - ≤ 0.4 W/kg or 1.0 W/kg, for 1-g or 10-g respectively, when the transmission band is ≥ 200 MHz
3. Per KDB 865664 D01v01r04, for each frequency band, repeated SAR measurement is required when the measured SAR is ≥ 0.8W/kg. Per KDB 865664 D01v01r04, if the extremity repeated SAR is necessary, the same procedures should be adapted for measurements according to extremity and occupational exposure limits by applying a factor of 2.5 for extremity exposure and a factor of 5 for occupational exposure to the corresponding SAR thresholds.
4. The device implements Proximity sensors/receiver detect mechanism/hotspot trigger reduced power for the power management for SAR compliance at different exposure conditions (head, body-worn, hotspot, extremity). The device will invoke corresponding work scenarios power level base on frequency bands/antennas, which can refer to appendix E. power table.
5. For WLAN when transmit simultaneous with WWAN, power reduction will be activated to head, Body, hotspot and extremity exposure conditions.
6. 5G NR n77/n78 supports HPUE mode, HPUE power and SAR testing performed separately.
7. For 5G NR n77/n78 HPUE, 5G NR n77/n78 PC2 Maximum Duty Cycle is 50%, using FTM (Factory Test Mode) with 50% duty cycle is considered during SAR testing. For 5G NR other bands, using FTM to perform SAR with default 100% transmission.
8. 5G NR n77/n78 HPUE with higher power. For HPUE power is higher than power class 3 but with lower duty cycle, the maximum average power for class 2 and class 3 is almost the same, so we chose power class 3 full SAR testing and power class 2 verify the worst case of power class 3 SAR.
9. For 5G NR EN-DC mode, standalone SAR performed for 5G NR NSA band with the maximum power, EN-DC SAR summed EN-DC mode 5G NR standalone SAR and LTE standalone SAR, the result of EN-DC SAR is more conservatively.
10. Per KDB648474 D04v01r03, for smart phones with a display diagonal dimension > 15.0 cm or an overall diagonal dimension > 16.0 cm, when hotspot mode applies, 10-g extremity SAR is required only for the surfaces and edges with hotspot mode 1-g reported SAR > 1.2 W/kg, however, when power reduction applies to hotspot mode the measured SAR must be scaled to the maximum output power (for handheld on state, the maximum full power means reduced power), including tolerance, allowed for phablet modes to compare with the 1.2 W/kg SAR test reduction threshold.
 - a. For this device SAR for WWAN/WLAN transmitter scaled to maximum output power mode for product specific 10g SAR is higher than 1.2W/kg of WCDMA Band II/IV, LTE Band 2/4/7/66/38/41, 5G NR n7/n38/n66/n41/n77/n78, WLAN5.8GHz, therefore product specific 10g SAR is necessary.
 - b. WLAN 5.3/5.5GHz tested the product specific 10g SAR since it has no hotspot mode.
 - c. When 10-g product specific 10g SAR is considered, SAR thresholds is specified in the procedures for SAR test reduction and exclusion should be multiplied by 2.5.
11. For distance SAR and non-distance SAR, always chose higher SAR to do co-located analysis.
12. LTE B5 at ant0/1 and LTE B4/66 at ant1/2/3/4, 5G NR n5 at ant0/1 and 5G NR n66 at ant1/2/3/4 support different PAs for

some antennas. For LTE B5 at ant0/1, LTE B1/3 at ant1/2/3/4, 5GNR n5 at ant0/1 and 5GNR n66 at ant2/4, the maximum power of Main PA is higher than and very close to the other PA, for RF exposure, after verification all PAs in a same position, so choose the worst case of the main PA to perform full SAR tested to ensure the RF exposure is compliance. For 5GNR n66 at ant1/3, the maximum power of Main PA is less than and very close to the other PA, for RF exposure, after verification all PAs in a same position, so choose the other PA to perform full SAR tested to ensure the RF exposure is compliance.

GSM Note:

1. Per KDB 941225 D01v03r01, for SAR test reduction for GSM / GPRS / EDGE modes is determined by the source-based time-averaged output power including tune-up tolerance. The mode with highest specified time-averaged output power should be tested for SAR compliance in the applicable exposure conditions. For modes with the same specified maximum output power and tolerance, the higher number time-slot configuration should be tested.
2. Other configurations of GSM / GPRS / EDGE are considered as secondary modes. The 3G SAR test reduction procedure is applied, when the maximum output power and tune-up tolerance specified for production units in a secondary mode is \leq ¼ dB higher than the primary mode, SAR measurement is not required for the secondary mode.

WCDMA Note:

1. Per KDB 941225 D01v03r01, for SAR testing is measured using a 12.2 kbps RMC with TPC bits configured to all "1's".
2. Per KDB 941225 D01v03r01, RMC 12.2kbps setting is used to evaluate SAR. The maximum output power and tune-up tolerance specified for production units in HSDPA / HSUPA / DC-HSDPA / HSPA+ is \leq ¼ dB higher than RMC 12.2Kbps or when the highest reported SAR of the RMC12.2Kbps is scaled by the ratio of specified maximum output power and tune-up tolerance of HSDPA / HSUPA / DC-HSDPA / HSPA+ to RMC12.2Kbps and the adjusted SAR is \leq 1.2 W/kg, SAR measurement is not required for HSDPA / HSUPA / DC-HSDPA / HSPA+, and according to the following RF output power, the output power results of the secondary modes (HSDPA / HSUPA / DC-HSDPA / HSPA+) are less than ¼ dB higher than the primary modes; therefore, SAR measurement is not required for HSDPA / HSUPA / DC-HSDPA / HSPA+ .

LTE Note:

1. Per KDB 941225 D05v02r05, start with the largest channel bandwidth and measure SAR for QPSK with 1 RB allocation, using the RB offset and required test channel combination with the highest maximum output power for RB offsets at the upper edge, middle and lower edge of each required test channel.
2. Per KDB 941225 D05v02r05, 50% RB allocation for QPSK SAR testing follows 1RB QPSK allocation procedure.
3. Per KDB 941225 D05v02r05, for QPSK with 100% RB allocation, SAR is not required when the highest maximum output power for 100 % RB allocation is less than the highest maximum output power in 50% and 1 RB allocations and the highest reported SAR for 1 RB and 50% RB allocation are \leq 0.8 W/kg. Otherwise, SAR is measured for the highest output power channel; and if the reported SAR is $>$ 1.45 W/kg, the remaining required test channels must also be tested.
4. Per KDB 941225 D05v02r05, 16QAM/64QAM/256QAM output power for each RB allocation configuration is $>$ not ½ dB higher than the same configuration in QPSK and the reported SAR for the QPSK configuration is \leq 1.45 W/kg; Per KDB 941225 D05v02r05, 16QAM/64QAM/256QAM SAR testing is not required.
5. Per KDB 941225 D05v02r05, smaller bandwidth output power for each RB allocation configuration is $>$ not ½ dB higher than the same configuration in the largest supported bandwidth, and the reported SAR for the largest supported bandwidth is \leq 1.45 W/kg; Per KDB 941225 D05v02r05, smaller bandwidth SAR testing is not required.
6. For LTE B4 / B5 / B12 / B17 / B26 / B38 the maximum bandwidth does not support three non-overlapping channels, per KDB 941225 D05v02r05, when a device supports overlapping channel assignment in a channel bandwidth configuration, the middle channel of the group of overlapping channels should be selected for testing.
7. LTE B4 / B5 / B17 / B38 SAR test was covered by B66 / B26 / B12 / B41; according to April 2015 TCB workshop, SAR test for overlapping LTE bands can be reduced if
 - a. the maximum output power, including tolerance, for the smaller band is \leq the larger band to qualify for the SAR test exclusion
 - b. the channel bandwidth and other operating parameters for the smaller band are fully supported by the larger band

5G NR Note:

1. For 5G NR test procedure was following step similar FCC KDB 941225 D05:
 - a. SAR testing start with the largest channel bandwidth and measure SAR for QPSK with 1 RB allocation, using the RB offset and required test channel combination with the highest maximum output power for RB offsets at the upper edge, middle and lower edge of each required test channel.
 - b. 50% RB allocation for QPSK SAR testing follows 1RB QPSK allocation procedure
 - c. QPSK with 100% RB allocation, SAR is not required when the highest maximum output power for 100 % RB allocation is less than the highest maximum output power in 50% and 1 RB allocations and the highest reported SAR for 1 RB and 50% RB allocation are ≤ 0.8 W/kg. Otherwise, SAR is measured for the highest output power channel; and if the reported SAR is > 1.45 W/kg, the remaining required test channels must also be tested.
 - d. PI/2 BPSK/16QAM/64QAM/256QAM output powers according to 3GPP MPR will not $\frac{1}{2}$ dB higher than the same configuration in QPSK, also reported SAR for the QPSK configuration is less than 1.45 W/kg, PI/2 BPSK /16QAM/64QAM/256QAM SAR testing are not required.
 - e. Smaller bandwidth output power for each RB allocation configuration for this device will not $\frac{1}{2}$ dB higher than the same configuration in the largest supported bandwidth, and the reported SAR for the largest supported bandwidth is ≤ 1.45 W/kg, smaller bandwidth SAR testing is not required for this device
 - f. For 5G FR1 n5 /n7/n66/n38/n41/n77 the maximum bandwidth does not support three non-overlapping channels, when a device supports overlapping channel assignment in a channel bandwidth configuration, the middle channel of the group of overlapping channels should be selected for testing.

WLAN/Bluetooth Note:

1. Per KDB 248227 D01v02r02, for 2.4GHz 802.11g/n SAR testing is not required when the highest reported SAR for DSSS is adjusted by the ratio of OFDM to DSSS specified maximum output power and the adjusted SAR is ≤ 1.2 W/kg.
2. Per KDB 248227 D01v02r02, U-NII-1 SAR testing is not required when the U-NII-2A band highest reported SAR for a test configuration is ≤ 1.2 W/kg, SAR is not required for U-NII-1 band.
3. When the reported SAR of the test position is > 0.4 W/kg, SAR is repeated for the 802.11 transmission mode configuration tested in the initial test position to measure the subsequent next closet/smallest test separation distance and maximum coupling test position on the highest maximum output power channel, until the report SAR is ≤ 0.8 W/kg or all required test position are tested.
4. For all positions / configurations, when the reported SAR is > 0.8 W/kg, SAR is measured for these test positions / configurations on the subsequent next highest measured output power channel(s) until the reported SAR is ≤ 1.2 W/kg or all required channels are tested.
5. During SAR testing the WLAN transmission was verified using a spectrum analyzer.
6. The 2.4GHz/5GHz WLAN can transmit in SISO and MIMO antenna mode.
7. SISO and MIMO all supported by WLAN2.4GHz/WLAN5GHz, for SISO mode power is less than per chain power of MIMO mode. For WLAN SISO & MIMO mode, the whole testing has assessed only MIMO mode by referring to their higher conducted power, so only chose MIMO mode to perform SAR testing. However, in order to do SISO simultaneous transmission, we tested the WLAN 2.4G SISO antenna 17 and WLAN 5G SISO antenna 18.
8. For the conducted power measurement is MIMO chains transmitting simultaneously and measured the separately conducted power for both chains and then based on the conducted power of two antennas respectively to calculate sum of the power for MIMO mode.

DSI status description:

The device has the following DSI state which used at different exposure condition.

Exposure Condition	DSI	Trigger conditions
Head SAR	DSI 0	Earpiece On
Hotspot Mode SAR	DSI 4	Hotspot On
Body worn/ Extremity Mode SAR	DSI 3	Sensor Off/ receiver off
Body worn/ Extremity Mode SAR	DSI 1	Sensor On



15.1 Head SAR

Plot No.	Band	BW (MHz)	Modulation	RB Size	RB offset	Mode	Test Position	Gap (mm)	Antenna	Power State	Ch.	Freq. (MHz)	Average Power (dBm)	Tune-Up Limit (dBm)	Tune-up Scaling Factor	Duty Cycle %	Duty Cycle Scaling Factor	Power Drift (dB)	Measured 1g SAR (W/kg)	Reported 1g SAR (W/kg)
750MHz																				
	LTE Band 12	10M	QPSK	1	0	-	Right Cheek	0mm	Ant 0	DSI 0	23095	707.5	24.67	25.50	1.211	-	-	-0.13	0.085	0.103
	LTE Band 12	10M	QPSK	1	0	-	Right Tilted	0mm	Ant 0	DSI 0	23095	707.5	24.67	25.50	1.211	-	-	-0.02	0.067	0.081
	LTE Band 12	10M	QPSK	1	0	-	Left Cheek	0mm	Ant 0	DSI 0	23095	707.5	24.67	25.50	1.211	-	-	-0.14	0.092	0.111
	LTE Band 12	10M	QPSK	1	0	-	Left Tilted	0mm	Ant 0	DSI 0	23095	707.5	24.67	25.50	1.211	-	-	0.09	0.064	0.077
	LTE Band 12	10M	QPSK	25	0	-	Right Cheek	0mm	Ant 0	DSI 0	23095	707.5	23.61	24.50	1.227	-	-	0.02	0.067	0.082
	LTE Band 12	10M	QPSK	25	0	-	Right Tilted	0mm	Ant 0	DSI 0	23095	707.5	23.61	24.50	1.227	-	-	-0.09	0.053	0.065
	LTE Band 12	10M	QPSK	25	0	-	Left Cheek	0mm	Ant 0	DSI 0	23095	707.5	23.61	24.50	1.227	-	-	0.19	0.073	0.090
	LTE Band 12	10M	QPSK	25	0	-	Left Tilted	0mm	Ant 0	DSI 0	23095	707.5	23.61	24.50	1.227	-	-	-0.1	0.050	0.061
01	LTE Band 12	10M	QPSK	1	0	-	Right Cheek	0mm	Ant 1	DSI 0	23095	707.5	23.88	25.50	1.452	-	-	0.15	0.551	0.800
	LTE Band 12	10M	QPSK	1	0	-	Right Tilted	0mm	Ant 1	DSI 0	23095	707.5	23.88	25.50	1.452	-	-	0.11	0.331	0.481
	LTE Band 12	10M	QPSK	1	0	-	Left Cheek	0mm	Ant 1	DSI 0	23095	707.5	23.88	25.50	1.452	-	-	0.05	0.195	0.283
	LTE Band 12	10M	QPSK	1	0	-	Left Tilted	0mm	Ant 1	DSI 0	23095	707.5	23.88	25.50	1.452	-	-	-0.02	0.184	0.267
	LTE Band 12	10M	QPSK	25	0	-	Right Cheek	0mm	Ant 1	DSI 0	23095	707.5	22.84	24.50	1.466	-	-	-0.06	0.457	0.670
	LTE Band 12	10M	QPSK	25	0	-	Right Tilted	0mm	Ant 1	DSI 0	23095	707.5	22.84	24.50	1.466	-	-	-0.09	0.286	0.419
	LTE Band 12	10M	QPSK	25	0	-	Left Cheek	0mm	Ant 1	DSI 0	23095	707.5	22.84	24.50	1.466	-	-	-0.1	0.179	0.262
	LTE Band 12	10M	QPSK	25	0	-	Left Tilted	0mm	Ant 1	DSI 0	23095	707.5	22.84	24.50	1.466	-	-	0.08	0.160	0.234
	LTE Band 12	10M	QPSK	50	0	-	Right Cheek	0mm	Ant 1	DSI 0	23095	707.5	22.83	24.50	1.469	-	-	0.06	0.451	0.662
	LTE Band 13	10M	QPSK	1	0	-	Right Cheek	0mm	Ant 0	DSI 0	23230	782	24.58	25.50	1.236	-	-	0.03	0.148	0.183
	LTE Band 13	10M	QPSK	1	0	-	Right Tilted	0mm	Ant 0	DSI 0	23230	782	24.58	25.50	1.236	-	-	-0.17	0.101	0.125
	LTE Band 13	10M	QPSK	1	0	-	Left Cheek	0mm	Ant 0	DSI 0	23230	782	24.58	25.50	1.236	-	-	0.14	0.165	0.204
	LTE Band 13	10M	QPSK	1	0	-	Left Tilted	0mm	Ant 0	DSI 0	23230	782	24.58	25.50	1.236	-	-	0.14	0.091	0.112
	LTE Band 13	10M	QPSK	25	0	-	Right Cheek	0mm	Ant 0	DSI 0	23230	782	23.62	24.50	1.225	-	-	-0.01	0.118	0.145
	LTE Band 13	10M	QPSK	25	0	-	Right Tilted	0mm	Ant 0	DSI 0	23230	782	23.62	24.50	1.225	-	-	0.06	0.080	0.098
	LTE Band 13	10M	QPSK	25	0	-	Left Cheek	0mm	Ant 0	DSI 0	23230	782	23.62	24.50	1.225	-	-	-0.11	0.128	0.157
	LTE Band 13	10M	QPSK	25	0	-	Left Tilted	0mm	Ant 0	DSI 0	23230	782	23.62	24.50	1.225	-	-	-0.04	0.075	0.092
02	LTE Band 13	10M	QPSK	1	0	-	Right Cheek	0mm	Ant 1	DSI 0	23230	782	22.69	24.50	1.517	-	-	0.06	0.691	1.048
	LTE Band 13	10M	QPSK	1	0	-	Right Tilted	0mm	Ant 1	DSI 0	23230	782	22.69	24.50	1.517	-	-	0.16	0.514	0.780
	LTE Band 13	10M	QPSK	1	0	-	Left Cheek	0mm	Ant 1	DSI 0	23230	782	22.69	24.50	1.517	-	-	-0.05	0.349	0.529
	LTE Band 13	10M	QPSK	1	0	-	Left Tilted	0mm	Ant 1	DSI 0	23230	782	22.69	24.50	1.517	-	-	-0.12	0.327	0.496
	LTE Band 13	10M	QPSK	25	0	-	Right Cheek	0mm	Ant 1	DSI 0	23230	782	22.65	24.50	1.531	-	-	-0.07	0.650	0.995
	LTE Band 13	10M	QPSK	25	0	-	Right Tilted	0mm	Ant 1	DSI 0	23230	782	22.65	24.50	1.531	-	-	-0.08	0.477	0.730
	LTE Band 13	10M	QPSK	25	0	-	Left Cheek	0mm	Ant 1	DSI 0	23230	782	22.65	24.50	1.531	-	-	0.07	0.335	0.513
	LTE Band 13	10M	QPSK	25	0	-	Left Tilted	0mm	Ant 1	DSI 0	23230	782	22.65	24.50	1.531	-	-	0.16	0.310	0.475
	LTE Band 13	10M	QPSK	50	0	-	Right Cheek	0mm	Ant 1	DSI 0	23230	782	22.63	24.50	1.538	-	-	-0.15	0.629	0.967
835MHz																				
	GSM850	-	-	-	-	GPRS (4 Tx slots)	Right Cheek	0mm	Ant 0	DSI 0	189	836.4	27.15	28.00	1.216	-	-	-0.06	0.165	0.201
	GSM850	-	-	-	-	GPRS (4 Tx slots)	Right Tilted	0mm	Ant 0	DSI 0	189	836.4	27.15	28.00	1.216	-	-	-0.02	0.109	0.133
	GSM850	-	-	-	-	GPRS (4 Tx slots)	Left Cheek	0mm	Ant 0	DSI 0	189	836.4	27.15	28.00	1.216	-	-	-0.01	0.202	0.246
	GSM850	-	-	-	-	GPRS (4 Tx slots)	Left Tilted	0mm	Ant 0	DSI 0	189	836.4	27.15	28.00	1.216	-	-	-0.12	0.099	0.120
	GSM850	-	-	-	-	GPRS (4 Tx slots)	Right Cheek	0mm	Ant 1	DSI 0	189	836.4	25.35	26.50	1.303	-	-	0.13	0.788	1.027
	GSM850	-	-	-	-	GPRS (4 Tx slots)	Right Tilted	0mm	Ant 1	DSI 0	189	836.4	25.35	26.50	1.303	-	-	0.06	0.628	0.818
	GSM850	-	-	-	-	GPRS (4 Tx slots)	Left Cheek	0mm	Ant 1	DSI 0	189	836.4	25.35	26.50	1.303	-	-	-0.14	0.418	0.545
	GSM850	-	-	-	-	GPRS (4 Tx slots)	Left Tilted	0mm	Ant 1	DSI 0	189	836.4	25.35	26.50	1.303	-	-	0.12	0.387	0.504
	GSM850	-	-	-	-	GPRS (4 Tx slots)	Right Cheek	0mm	Ant 1	DSI 0	128	824.2	25.10	26.50	1.380	-	-	0.08	0.690	0.952
03	GSM850	-	-	-	-	GPRS (4 Tx slots)	Right Cheek	0mm	Ant 1	DSI 0	251	848.8	25.34	26.50	1.306	-	-	-0.06	0.812	1.061
	GSM850	-	-	-	-	GPRS (4 Tx slots)	Right Tilted	0mm	Ant 1	DSI 0	128	824.2	25.10	26.50	1.380	-	-	0.01	0.548	0.756
	GSM850	-	-	-	-	GPRS (4 Tx slots)	Right Tilted	0mm	Ant 1	DSI 0	251	848.8	25.34	26.50	1.306	-	-	0.05	0.645	0.842
	WCDMA V	-	-	-	-	RMC 12.2Kbps	Right Cheek	0mm	Ant 0	DSI 0	4182	836.4	24.40	25.00	1.148	-	-	-0.06	0.202	0.232
	WCDMA V	-	-	-	-	RMC 12.2Kbps	Right Tilted	0mm	Ant 0	DSI 0	4182	836.4	24.40	25.00	1.148	-	-	-0.03	0.135	0.155
	WCDMA V	-	-	-	-	RMC 12.2Kbps	Left Cheek	0mm	Ant 0	DSI 0	4182	836.4	24.40	25.00	1.148	-	-	0.01	0.237	0.272



FCC SAR Test Report

Report No. : FA350505

	WCDMA V	-	-	-	-	RMC 12.2Kbps	Left Tilted	0mm	Ant 0	DSI 0	4182	836.4	24.40	25.00	1.148	-	-	-0.11	0.121	0.139
	WCDMA V	-	-	-	-	RMC 12.2Kbps	Right Cheek	0mm	Ant 1	DSI 0	4182	836.4	21.35	23.00	1.462	-	-	-0.08	0.653	0.955
	WCDMA V	-	-	-	-	RMC 12.2Kbps	Right Tilted	0mm	Ant 1	DSI 0	4182	836.4	21.35	23.00	1.462	-	-	0.16	0.440	0.643
	WCDMA V	-	-	-	-	RMC 12.2Kbps	Left Cheek	0mm	Ant 1	DSI 0	4182	836.4	21.35	23.00	1.462	-	-	-0.18	0.308	0.450
	WCDMA V	-	-	-	-	RMC 12.2Kbps	Left Tilted	0mm	Ant 1	DSI 0	4182	836.4	21.35	23.00	1.462	-	-	-0.01	0.305	0.446
	WCDMA V	-	-	-	-	RMC 12.2Kbps	Right Cheek	0mm	Ant 1	DSI 0	4132	826.4	21.29	23.00	1.483	-	-	-0.12	0.602	0.892
04	WCDMA V	-	-	-	-	RMC 12.2Kbps	Right Cheek	0mm	Ant 1	DSI 0	4233	846.6	21.23	23.00	1.503	-	-	0.08	0.673	1.012
	LTE Band 26	15M	QPSK	1	0	-	Right Cheek	0mm	Ant 0	DSI 0	26865	831.5	24.69	25.50	1.205	-	-	-0.12	0.229	0.276
	LTE Band 26	15M	QPSK	1	0	-	Right Tilted	0mm	Ant 0	DSI 0	26865	831.5	24.69	25.50	1.205	-	-	-0.11	0.130	0.157
	LTE Band 26	15M	QPSK	1	0	-	Left Cheek	0mm	Ant 0	DSI 0	26865	831.5	24.69	25.50	1.205	-	-	-0.06	0.257	0.310
	LTE Band 26	15M	QPSK	1	0	-	Left Tilted	0mm	Ant 0	DSI 0	26865	831.5	24.69	25.50	1.205	-	-	-0.19	0.127	0.153
	LTE Band 26	15M	QPSK	36	0	-	Right Cheek	0mm	Ant 0	DSI 0	26865	831.5	23.66	24.50	1.213	-	-	0.07	0.181	0.220
	LTE Band 26	15M	QPSK	36	0	-	Right Tilted	0mm	Ant 0	DSI 0	26865	831.5	23.66	24.50	1.213	-	-	-0.14	0.096	0.116
	LTE Band 26	15M	QPSK	36	0	-	Left Cheek	0mm	Ant 0	DSI 0	26865	831.5	23.66	24.50	1.213	-	-	0.12	0.206	0.250
	LTE Band 26	15M	QPSK	36	0	-	Left Tilted	0mm	Ant 0	DSI 0	26865	831.5	23.66	24.50	1.213	-	-	0.02	0.092	0.112
05	LTE Band 26	15M	QPSK	1	0	-	Right Cheek	0mm	Ant 1	DSI 0	26865	831.5	22.39	24.00	1.449	-	-	0.13	0.672	0.974
	LTE Band 26	15M	QPSK	1	0	-	Right Tilted	0mm	Ant 1	DSI 0	26865	831.5	22.39	24.00	1.449	-	-	0.16	0.519	0.752
	LTE Band 26	15M	QPSK	1	0	-	Left Cheek	0mm	Ant 1	DSI 0	26865	831.5	22.39	24.00	1.449	-	-	0.01	0.361	0.523
	LTE Band 26	15M	QPSK	1	0	-	Left Tilted	0mm	Ant 1	DSI 0	26865	831.5	22.39	24.00	1.449	-	-	0.11	0.340	0.493
	LTE Band 26	15M	QPSK	36	0	-	Right Cheek	0mm	Ant 1	DSI 0	26865	831.5	22.37	24.00	1.455	-	-	0	0.658	0.958
	LTE Band 26	15M	QPSK	36	0	-	Right Tilted	0mm	Ant 1	DSI 0	26865	831.5	22.37	24.00	1.455	-	-	-0.02	0.511	0.744
	LTE Band 26	15M	QPSK	36	0	-	Left Cheek	0mm	Ant 1	DSI 0	26865	831.5	22.37	24.00	1.455	-	-	-0.14	0.351	0.511
	LTE Band 26	15M	QPSK	36	0	-	Left Tilted	0mm	Ant 1	DSI 0	26865	831.5	22.37	24.00	1.455	-	-	-0.02	0.334	0.486
	LTE Band 26	15M	QPSK	75	0	-	Right Cheek	0mm	Ant 1	DSI 0	26865	831.5	22.35	24.00	1.462	-	-	-0.18	0.659	0.964
	FR1 n5	20M	QPSK	1	1	DFT-15	Right Cheek	0mm	Ant 0	DSI 0	167300	836.5	24.39	25.50	1.291	-	-	-0.17	0.182	0.235
	FR1 n5	20M	QPSK	1	1	DFT-15	Right Tilted	0mm	Ant 0	DSI 0	167300	836.5	24.39	25.50	1.291	-	-	0	0.118	0.152
	FR1 n5	20M	QPSK	1	1	DFT-15	Left Cheek	0mm	Ant 0	DSI 0	167300	836.5	24.39	25.50	1.291	-	-	-0.04	0.204	0.263
	FR1 n5	20M	QPSK	1	1	DFT-15	Left Tilted	0mm	Ant 0	DSI 0	167300	836.5	24.39	25.50	1.291	-	-	0.14	0.104	0.134
	FR1 n5	20M	QPSK	50	28	DFT-15	Right Cheek	0mm	Ant 0	DSI 0	167300	836.5	24.31	25.50	1.315	-	-	-0.06	0.184	0.242
	FR1 n5	20M	QPSK	50	28	DFT-15	Right Tilted	0mm	Ant 0	DSI 0	167300	836.5	24.31	25.50	1.315	-	-	-0.18	0.119	0.157
	FR1 n5	20M	QPSK	50	28	DFT-15	Left Cheek	0mm	Ant 0	DSI 0	167300	836.5	24.31	25.50	1.315	-	-	0.12	0.227	0.299
	FR1 n5	20M	QPSK	50	28	DFT-15	Left Tilted	0mm	Ant 0	DSI 0	167300	836.5	24.31	25.50	1.315	-	-	-0.14	0.108	0.142
	FR1 n5	20M	QPSK	1	1	DFT-15	Right Cheek	0mm	Ant 1	DSI 0	167300	836.5	20.71	22.50	1.510	-	-	-0.15	0.567	0.856
	FR1 n5	20M	QPSK	1	1	DFT-15	Right Tilted	0mm	Ant 1	DSI 0	167300	836.5	20.71	22.50	1.510	-	-	-0.01	0.491	0.741
	FR1 n5	20M	QPSK	1	1	DFT-15	Left Cheek	0mm	Ant 1	DSI 0	167300	836.5	20.71	22.50	1.510	-	-	0.02	0.311	0.470
	FR1 n5	20M	QPSK	1	1	DFT-15	Left Tilted	0mm	Ant 1	DSI 0	167300	836.5	20.71	22.50	1.510	-	-	-0.04	0.158	0.239
06	FR1 n5	20M	QPSK	50	28	DFT-15	Right Cheek	0mm	Ant 1	DSI 0	167300	836.5	20.69	22.50	1.517	-	-	0.01	0.631	0.957
	FR1 n5	20M	QPSK	50	28	DFT-15	Right Tilted	0mm	Ant 1	DSI 0	167300	836.5	20.69	22.50	1.517	-	-	-0.09	0.560	0.850
	FR1 n5	20M	QPSK	50	28	DFT-15	Left Cheek	0mm	Ant 1	DSI 0	167300	836.5	20.69	22.50	1.517	-	-	0.02	0.339	0.514
	FR1 n5	20M	QPSK	50	28	DFT-15	Left Tilted	0mm	Ant 1	DSI 0	167300	836.5	20.69	22.50	1.517	-	-	-0.04	0.199	0.302
	FR1 n5	20M	QPSK	100	0	DFT-15	Right Cheek	0mm	Ant 1	DSI 0	167300	836.5	20.66	22.50	1.528	-	-	0.19	0.608	0.929
	FR1 n5	20M	QPSK	100	0	DFT-15	Right Tilted	0mm	Ant 1	DSI 0	167300	836.5	20.66	22.50	1.528	-	-	0.01	0.502	0.767
1750MHz																				
07	WCDMA IV	-	-	-	-	RMC 12.2Kbps	Right Cheek	0mm	Ant 1	DSI 0	1413	1732.6	16.49	18.00	1.416	-	-	0.09	0.763	1.080
	WCDMA IV	-	-	-	-	RMC 12.2Kbps	Right Tilted	0mm	Ant 1	DSI 0	1413	1732.6	16.49	18.00	1.416	-	-	-0.16	0.483	0.684
	WCDMA IV	-	-	-	-	RMC 12.2Kbps	Left Cheek	0mm	Ant 1	DSI 0	1413	1732.6	16.49	18.00	1.416	-	-	0.17	0.359	0.508
	WCDMA IV	-	-	-	-	RMC 12.2Kbps	Left Tilted	0mm	Ant 1	DSI 0	1413	1732.6	16.49	18.00	1.416	-	-	0.02	0.443	0.627
	WCDMA IV	-	-	-	-	RMC 12.2Kbps	Right Cheek	0mm	Ant 1	DSI 0	1312	1712.4	16.34	18.00	1.466	-	-	0.11	0.715	1.048
	WCDMA IV	-	-	-	-	RMC 12.2Kbps	Right Cheek	0mm	Ant 1	DSI 0	1513	1752.6	16.46	18.00	1.426	-	-	0.09	0.739	1.054
	WCDMA IV	-	-	-	-	RMC 12.2Kbps	Right Cheek	0mm	Ant 2	DSI 0	1413	1732.6	24.67	25.00	1.079	-	-	-0.1	0.191	0.206
	WCDMA IV	-	-	-	-	RMC 12.2Kbps	Right Tilted	0mm	Ant 2	DSI 0	1413	1732.6	24.67	25.00	1.079	-	-	-0.13	0.072	0.078
	WCDMA IV	-	-	-	-	RMC 12.2Kbps	Left Cheek	0mm	Ant 2	DSI 0	1413	1732.6	24.67	25.00	1.079	-	-	-0.02	0.168	0.181
	WCDMA IV	-	-	-	-	RMC 12.2Kbps	Left Tilted	0mm	Ant 2	DSI 0	1413	1732.6	24.67	25.00	1.079	-	-	-0.04	0.123	0.133
	LTE Band 4	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 2	DSI 0	20175	1732.5	24.96	25.70	1.186	-	-	0.04	0.279	0.331
	LTE Band 4	20M	QPSK	1	0	-	Right Tilted	0mm	Ant 2	DSI 0	20175	1732.5	24.96	25.70	1.186	-	-	-0.16	0.093	0.110
	LTE Band 4	20M	QPSK	1	0	-	Left Cheek	0mm	Ant 2	DSI 0	20175	1732.5	24.96	25.70	1.186	-	-	-0.06	0.187	0.222



FCC SAR Test Report

Report No. : FA350505

	LTE Band 4	20M	QPSK	1	0	-	Left Tilted	0mm	Ant 2	DSI 0	20175	1732.5	24.96	25.70	1.186	-	-	-0.15	0.123	0.146
	LTE Band 4	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 2	DSI 0	20175	1732.5	24.01	24.70	1.172	-	-	-0.13	0.224	0.263
	LTE Band 4	20M	QPSK	50	0	-	Right Tilted	0mm	Ant 2	DSI 0	20175	1732.5	24.01	24.70	1.172	-	-	0.12	0.075	0.088
	LTE Band 4	20M	QPSK	50	0	-	Left Cheek	0mm	Ant 2	DSI 0	20175	1732.5	24.01	24.70	1.172	-	-	-0.11	0.154	0.181
	LTE Band 4	20M	QPSK	50	0	-	Left Tilted	0mm	Ant 2	DSI 0	20175	1732.5	24.01	24.70	1.172	-	-	0.08	0.098	0.115
08	LTE Band 4	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 3	DSI 0	20175	1732.5	21.65	23.00	1.365	-	-	-0.04	0.736	1.004
	LTE Band 4	20M	QPSK	1	0	-	Right Tilted	0mm	Ant 3	DSI 0	20175	1732.5	21.65	23.00	1.365	-	-	-0.1	0.236	0.322
	LTE Band 4	20M	QPSK	1	0	-	Left Cheek	0mm	Ant 3	DSI 0	20175	1732.5	21.65	23.00	1.365	-	-	-0.17	0.648	0.884
	LTE Band 4	20M	QPSK	1	0	-	Left Tilted	0mm	Ant 3	DSI 0	20175	1732.5	21.65	23.00	1.365	-	-	-0.16	0.172	0.235
	LTE Band 4	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 3	DSI 0	20175	1732.5	21.61	23.00	1.377	-	-	-0.06	0.710	0.978
	LTE Band 4	20M	QPSK	50	0	-	Right Tilted	0mm	Ant 3	DSI 0	20175	1732.5	21.61	23.00	1.377	-	-	-0.07	0.218	0.300
	LTE Band 4	20M	QPSK	50	0	-	Left Cheek	0mm	Ant 3	DSI 0	20175	1732.5	21.61	23.00	1.377	-	-	0.15	0.634	0.873
	LTE Band 4	20M	QPSK	50	0	-	Left Tilted	0mm	Ant 3	DSI 0	20175	1732.5	21.61	23.00	1.377	-	-	-0.04	0.147	0.202
	LTE Band 4	20M	QPSK	100	0	-	Right Cheek	0mm	Ant 3	DSI 0	20175	1732.5	21.55	23.00	1.396	-	-	-0.08	0.711	0.993
	LTE Band 4	20M	QPSK	100	0	-	Left Cheek	0mm	Ant 3	DSI 0	20175	1732.5	21.55	23.00	1.396	-	-	0.06	0.611	0.853
	LTE Band 4	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 4	DSI 0	20175	1732.5	24.69	25.50	1.205	-	-	-0.11	0.027	0.033
	LTE Band 4	20M	QPSK	1	0	-	Right Tilted	0mm	Ant 4	DSI 0	20175	1732.5	24.69	25.50	1.205	-	-	-0.1	0.022	0.027
	LTE Band 4	20M	QPSK	1	0	-	Left Cheek	0mm	Ant 4	DSI 0	20175	1732.5	24.69	25.50	1.205	-	-	-0.11	0.057	0.069
	LTE Band 4	20M	QPSK	1	0	-	Left Tilted	0mm	Ant 4	DSI 0	20175	1732.5	24.69	25.50	1.205	-	-	0.09	0.050	0.060
	LTE Band 4	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 4	DSI 0	20175	1732.5	23.73	24.50	1.194	-	-	0	0.023	0.027
	LTE Band 4	20M	QPSK	50	0	-	Right Tilted	0mm	Ant 4	DSI 0	20175	1732.5	23.73	24.50	1.194	-	-	0	0.018	0.021
	LTE Band 4	20M	QPSK	50	0	-	Left Cheek	0mm	Ant 4	DSI 0	20175	1732.5	23.73	24.50	1.194	-	-	0.09	0.048	0.057
	LTE Band 4	20M	QPSK	50	0	-	Left Tilted	0mm	Ant 4	DSI 0	20175	1732.5	23.73	24.50	1.194	-	-	-0.04	0.041	0.049
	LTE Band 66	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 1	DSI 0	132322	1745	16.73	18.00	1.340	-	-	-0.12	0.628	0.841
	LTE Band 66	20M	QPSK	1	0	-	Right Tilted	0mm	Ant 1	DSI 0	132322	1745	16.73	18.00	1.340	-	-	-0.19	0.314	0.421
	LTE Band 66	20M	QPSK	1	0	-	Left Cheek	0mm	Ant 1	DSI 0	132322	1745	16.73	18.00	1.340	-	-	0.18	0.218	0.292
	LTE Band 66	20M	QPSK	1	0	-	Left Tilted	0mm	Ant 1	DSI 0	132322	1745	16.73	18.00	1.340	-	-	-0.12	0.271	0.363
	LTE Band 66	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 1	DSI 0	132072	1720	16.57	18.00	1.390	-	-	-0.07	0.648	0.901
	LTE Band 66	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 1	DSI 0	132572	1770	16.68	18.00	1.355	-	-	0.18	0.636	0.862
	LTE Band 66	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 1	DSI 0	132322	1745	16.70	18.00	1.349	-	-	-0.01	0.600	0.809
	LTE Band 66	20M	QPSK	50	0	-	Right Tilted	0mm	Ant 1	DSI 0	132322	1745	16.70	18.00	1.349	-	-	0.03	0.300	0.405
	LTE Band 66	20M	QPSK	50	0	-	Left Cheek	0mm	Ant 1	DSI 0	132322	1745	16.70	18.00	1.349	-	-	0.17	0.208	0.281
	LTE Band 66	20M	QPSK	50	0	-	Left Tilted	0mm	Ant 1	DSI 0	132322	1745	16.70	18.00	1.349	-	-	-0.08	0.259	0.349
	LTE Band 66	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 1	DSI 0	132072	1720	16.66	18.00	1.361	-	-	-0.09	0.619	0.843
	LTE Band 66	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 1	DSI 0	132572	1770	16.67	18.00	1.358	-	-	0.12	0.607	0.824
	LTE Band 66	20M	QPSK	100	0	-	Right Cheek	0mm	Ant 1	DSI 0	132322	1745	16.67	18.00	1.358	-	-	-0.14	0.595	0.808
	LTE Band 66	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 2	DSI 0	132322	1745	24.14	25.50	1.368	-	-	0.02	0.186	0.254
	LTE Band 66	20M	QPSK	1	0	-	Right Tilted	0mm	Ant 2	DSI 0	132322	1745	24.14	25.50	1.368	-	-	-0.05	0.072	0.098
	LTE Band 66	20M	QPSK	1	0	-	Left Cheek	0mm	Ant 2	DSI 0	132322	1745	24.14	25.50	1.368	-	-	0.06	0.154	0.211
	LTE Band 66	20M	QPSK	1	0	-	Left Tilted	0mm	Ant 2	DSI 0	132322	1745	24.14	25.50	1.368	-	-	-0.07	0.119	0.163
	LTE Band 66	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 2	DSI 0	132322	1745	23.12	24.50	1.374	-	-	-0.16	0.142	0.195
	LTE Band 66	20M	QPSK	50	0	-	Right Tilted	0mm	Ant 2	DSI 0	132322	1745	23.12	24.50	1.374	-	-	0.07	0.058	0.080
	LTE Band 66	20M	QPSK	50	0	-	Left Cheek	0mm	Ant 2	DSI 0	132322	1745	23.12	24.50	1.374	-	-	-0.13	0.125	0.172
	LTE Band 66	20M	QPSK	50	0	-	Left Tilted	0mm	Ant 2	DSI 0	132322	1745	23.12	24.50	1.374	-	-	0.18	0.092	0.126
	LTE Band 66	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 3	DSI 0	132322	1745	21.11	22.50	1.377	-	-	0.06	0.728	1.003
	LTE Band 66	20M	QPSK	1	0	-	Right Tilted	0mm	Ant 3	DSI 0	132322	1745	21.11	22.50	1.377	-	-	0.15	0.117	0.161
	LTE Band 66	20M	QPSK	1	0	-	Left Cheek	0mm	Ant 3	DSI 0	132322	1745	21.11	22.50	1.377	-	-	-0.12	0.424	0.584
	LTE Band 66	20M	QPSK	1	0	-	Left Tilted	0mm	Ant 3	DSI 0	132322	1745	21.11	22.50	1.377	-	-	-0.15	0.070	0.096
	LTE Band 66	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 3	DSI 0	132072	1720	20.93	22.50	1.435	-	-	0.05	0.575	0.825
	LTE Band 66	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 3	DSI 0	132572	1770	21.08	22.50	1.387	-	-	0.1	0.731	1.014
	LTE Band 66	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 3	DSI 0	132322	1745	21.04	22.50	1.400	-	-	0.1	0.725	1.015
	LTE Band 66	20M	QPSK	50	0	-	Right Tilted	0mm	Ant 3	DSI 0	132322	1745	21.04	22.50	1.400	-	-	-0.14	0.119	0.167
	LTE Band 66	20M	QPSK	50	0	-	Left Cheek	0mm	Ant 3	DSI 0	132322	1745	21.04	22.50	1.400	-	-	0.16	0.439	0.614
	LTE Band 66	20M	QPSK	50	0	-	Left Tilted	0mm	Ant 3	DSI 0	132322	1745	21.04	22.50	1.400	-	-	0.01	0.075	0.105
	LTE Band 66	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 3	DSI 0	132072	1720	20.85	22.50	1.462	-	-	0.05	0.609	0.890
09	LTE Band 66	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 3	DSI 0	132572	1770	21.00	22.50	1.413	-	-	0.12	0.769	1.086



FCC SAR Test Report

Report No. : FA350505

	LTE Band 66	20M	QPSK	100	0	-	Right Cheek	0mm	Ant 3	DSI 0	132322	1745	21.02	22.50	1.406	-	-	0.01	0.713	1.003
	LTE Band 66	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 4	DSI 0	132322	1745	23.80	24.50	1.175	-	-	0.07	0.034	0.040
	LTE Band 66	20M	QPSK	1	0	-	Right Tilted	0mm	Ant 4	DSI 0	132322	1745	23.80	24.50	1.175	-	-	0.04	0.027	0.032
	LTE Band 66	20M	QPSK	1	0	-	Left Cheek	0mm	Ant 4	DSI 0	132322	1745	23.80	24.50	1.175	-	-	-0.12	0.053	0.062
	LTE Band 66	20M	QPSK	1	0	-	Left Tilted	0mm	Ant 4	DSI 0	132322	1745	23.80	24.50	1.175	-	-	-0.08	0.045	0.053
	LTE Band 66	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 4	DSI 0	132322	1745	22.88	23.50	1.153	-	-	-0.16	0.030	0.035
	LTE Band 66	20M	QPSK	50	0	-	Right Tilted	0mm	Ant 4	DSI 0	132322	1745	22.88	23.50	1.153	-	-	-0.13	0.023	0.027
	LTE Band 66	20M	QPSK	50	0	-	Left Cheek	0mm	Ant 4	DSI 0	132322	1745	22.88	23.50	1.153	-	-	0.05	0.042	0.048
	LTE Band 66	20M	QPSK	50	0	-	Left Tilted	0mm	Ant 4	DSI 0	132322	1745	22.88	23.50	1.153	-	-	-0.08	0.037	0.043
	FR1 n66_Other PA	40M	QPSK	1	1	DFT-15	Right Cheek	0mm	Ant 1	DSI 0	349000	1745	17.02	18.00	1.253	-	-	-0.12	0.811	1.016
	FR1 n66_Other PA	40M	QPSK	1	1	DFT-15	Right Tilted	0mm	Ant 1	DSI 0	349000	1745	17.02	18.00	1.253	-	-	0.12	0.459	0.575
	FR1 n66_Other PA	40M	QPSK	1	1	DFT-15	Left Cheek	0mm	Ant 1	DSI 0	349000	1745	17.02	18.00	1.253	-	-	-0.05	0.351	0.440
	FR1 n66_Other PA	40M	QPSK	1	1	DFT-15	Left Tilted	0mm	Ant 1	DSI 0	349000	1745	17.02	18.00	1.253	-	-	-0.19	0.365	0.457
	FR1 n66_Other PA	40M	QPSK	108	54	DFT-15	Right Cheek	0mm	Ant 1	DSI 0	349000	1745	17.00	18.00	1.259	-	-	0.05	0.842	1.060
	FR1 n66_Main PA	40M	QPSK	108	54	DFT-15	Right Cheek	0mm	Ant 1	DSI 0	349000	1745	14.83	16.50	1.469	-	-	-0.1	0.672	0.987
	FR1 n66_Other PA	40M	QPSK	108	54	DFT-15	Right Tilted	0mm	Ant 1	DSI 0	349000	1745	17.00	18.00	1.259	-	-	-0.13	0.473	0.595
	FR1 n66_Other PA	40M	QPSK	108	54	DFT-15	Left Cheek	0mm	Ant 1	DSI 0	349000	1745	17.00	18.00	1.259	-	-	-0.15	0.355	0.447
	FR1 n66_Other PA	40M	QPSK	108	54	DFT-15	Left Tilted	0mm	Ant 1	DSI 0	349000	1745	17.00	18.00	1.259	-	-	-0.17	0.384	0.483
	FR1 n66_Other PA	40M	QPSK	216	0	DFT-15	Right Cheek	0mm	Ant 1	DSI 0	349000	1745	16.98	18.00	1.265	-	-	-0.03	0.644	0.814
	FR1 n66	40M	QPSK	1	1	DFT-15	Right Cheek	0mm	Ant 2	DSI 0	349000	1745	23.65	25.00	1.365	-	-	-0.15	0.190	0.259
	FR1 n66	40M	QPSK	1	1	DFT-15	Right Tilted	0mm	Ant 2	DSI 0	349000	1745	23.65	25.00	1.365	-	-	0.09	0.076	0.104
	FR1 n66	40M	QPSK	1	1	DFT-15	Left Cheek	0mm	Ant 2	DSI 0	349000	1745	23.65	25.00	1.365	-	-	-0.06	0.173	0.236
	FR1 n66	40M	QPSK	1	1	DFT-15	Left Tilted	0mm	Ant 2	DSI 0	349000	1745	23.65	25.00	1.365	-	-	0.09	0.130	0.177
	FR1 n66	40M	QPSK	108	54	DFT-15	Right Cheek	0mm	Ant 2	DSI 0	349000	1745	23.51	25.00	1.409	-	-	0.15	0.181	0.255
	FR1 n66	40M	QPSK	108	54	DFT-15	Right Tilted	0mm	Ant 2	DSI 0	349000	1745	23.51	25.00	1.409	-	-	-0.18	0.070	0.099
	FR1 n66	40M	QPSK	108	54	DFT-15	Left Cheek	0mm	Ant 2	DSI 0	349000	1745	23.51	25.00	1.409	-	-	-0.01	0.166	0.234
	FR1 n66	40M	QPSK	108	54	DFT-15	Left Tilted	0mm	Ant 2	DSI 0	349000	1745	23.51	25.00	1.409	-	-	0.19	0.125	0.176
	FR1 n66_Other PA	40M	QPSK	1	1	DFT-15	Right Cheek	0mm	Ant 3	DSI 0	349000	1745	20.33	22.00	1.469	-	-	-0.05	0.711	1.044
	FR1 n66_Other PA	40M	QPSK	1	1	DFT-15	Right Tilted	0mm	Ant 3	DSI 0	349000	1745	20.33	22.00	1.469	-	-	0.13	0.105	0.154
	FR1 n66_Other PA	40M	QPSK	1	1	DFT-15	Left Cheek	0mm	Ant 3	DSI 0	349000	1745	20.33	22.00	1.469	-	-	-0.09	0.459	0.674
	FR1 n66_Other PA	40M	QPSK	1	1	DFT-15	Left Tilted	0mm	Ant 3	DSI 0	349000	1745	20.33	22.00	1.469	-	-	-0.01	0.070	0.103
10	FR1 n66_Other PA	40M	QPSK	108	54	DFT-15	Right Cheek	0mm	Ant 3	DSI 0	349000	1745	20.30	22.00	1.479	-	-	0.01	0.728	1.077
	FR1 n66_Main PA	40M	QPSK	108	54	DFT-15	Right Cheek	0mm	Ant 3	DSI 0	349000	1745	18.15	20.00	1.531	-	-	-0.09	0.640	0.980
	FR1 n66_Other PA	40M	QPSK	108	54	DFT-15	Right Tilted	0mm	Ant 3	DSI 0	349000	1745	20.30	22.00	1.479	-	-	-0.16	0.107	0.158
	FR1 n66_Other PA	40M	QPSK	108	54	DFT-15	Left Cheek	0mm	Ant 3	DSI 0	349000	1745	20.30	22.00	1.479	-	-	0.11	0.489	0.723
	FR1 n66_Other PA	40M	QPSK	108	54	DFT-15	Left Tilted	0mm	Ant 3	DSI 0	349000	1745	20.30	22.00	1.479	-	-	0.16	0.077	0.114
	FR1 n66_Other PA	40M	QPSK	216	0	DFT-15	Right Cheek	0mm	Ant 3	DSI 0	349000	1745	20.28	22.00	1.486	-	-	-0.09	0.611	0.908
	FR1 n66	40M	QPSK	1	1	DFT-15	Right Cheek	0mm	Ant 4	DSI 0	349000	1745	23.43	24.50	1.279	-	-	0.16	0.035	0.045
	FR1 n66	40M	QPSK	1	1	DFT-15	Right Tilted	0mm	Ant 4	DSI 0	349000	1745	23.43	24.50	1.279	-	-	0.03	0.033	0.042
	FR1 n66	40M	QPSK	1	1	DFT-15	Left Cheek	0mm	Ant 4	DSI 0	349000	1745	23.43	24.50	1.279	-	-	-0.06	0.061	0.078
	FR1 n66	40M	QPSK	1	1	DFT-15	Left Tilted	0mm	Ant 4	DSI 0	349000	1745	23.43	24.50	1.279	-	-	-0.04	0.050	0.064
	FR1 n66	40M	QPSK	108	54	DFT-15	Right Cheek	0mm	Ant 4	DSI 0	349000	1745	23.38	24.50	1.294	-	-	-0.04	0.040	0.052
	FR1 n66	40M	QPSK	108	54	DFT-15	Right Tilted	0mm	Ant 4	DSI 0	349000	1745	23.38	24.50	1.294	-	-	0.15	0.037	0.048
	FR1 n66	40M	QPSK	108	54	DFT-15	Left Cheek	0mm	Ant 4	DSI 0	349000	1745	23.38	24.50	1.294	-	-	-0.19	0.068	0.088
	FR1 n66	40M	QPSK	108	54	DFT-15	Left Tilted	0mm	Ant 4	DSI 0	349000	1745	23.38	24.50	1.294	-	-	0.02	0.055	0.071
1900MHz																				
11	GSM1900	-	-	-	-	GPRS (4 Tx slots)	Right Cheek	0mm	Ant 1	DSI 0	661	1880	20.07	21.00	1.239	-	-	-0.08	0.764	0.946
	GSM1900	-	-	-	-	GPRS (4 Tx slots)	Right Tilted	0mm	Ant 1	DSI 0	661	1880	20.07	21.00	1.239	-	-	-0.14	0.626	0.775
	GSM1900	-	-	-	-	GPRS (4 Tx slots)	Left Cheek	0mm	Ant 1	DSI 0	661	1880	20.07	21.00	1.239	-	-	-0.06	0.271	0.336
	GSM1900	-	-	-	-	GPRS (4 Tx slots)	Left Tilted	0mm	Ant 1	DSI 0	661	1880	20.07	21.00	1.239	-	-	0.14	0.277	0.343
	GSM1900	-	-	-	-	GPRS (4 Tx slots)	Right Cheek	0mm	Ant 1	DSI 0	512	1850.2	19.93	21.00	1.279	-	-	-0.15	0.722	0.924
	GSM1900	-	-	-	-	GPRS (4 Tx slots)	Right Cheek	0mm	Ant 1	DSI 0	810	1909.8	19.95	21.00	1.274	-	-	0.05	0.730	0.930
	GSM1900	-	-	-	-	GPRS (4 Tx slots)	Right Cheek	0mm	Ant 2	DSI 0	661	1880	24.36	25.00	1.159	-	-	-0.05	0.081	0.094
	GSM1900	-	-	-	-	GPRS (4 Tx slots)	Right Tilted	0mm	Ant 2	DSI 0	661	1880	24.36	25.00	1.159	-	-	-0.02	0.047	0.054
	GSM1900	-	-	-	-	GPRS (4 Tx slots)	Left Cheek	0mm	Ant 2	DSI 0	661	1880	24.36	25.00	1.159	-	-	0.09	0.082	0.095
	GSM1900	-	-	-	-	GPRS (4 Tx slots)	Left Tilted	0mm	Ant 2	DSI 0	661	1880	24.36	25.00	1.159	-	-	-0.04	0.055	0.064



FCC SAR Test Report

Report No. : FA350505

	WCDMA II	-	-	-	-	RMC 12.2Kbps	Right Cheek	0mm	Ant 1	DSI 0	9400	1880	16.09	17.50	1.384	-	-	-0.07	0.587	0.812
	WCDMA II	-	-	-	-	RMC 12.2Kbps	Right Tilted	0mm	Ant 1	DSI 0	9400	1880	16.09	17.50	1.384	-	-	0.06	0.504	0.697
	WCDMA II	-	-	-	-	RMC 12.2Kbps	Left Cheek	0mm	Ant 1	DSI 0	9400	1880	16.09	17.50	1.384	-	-	0.08	0.248	0.343
	WCDMA II	-	-	-	-	RMC 12.2Kbps	Left Tilted	0mm	Ant 1	DSI 0	9400	1880	16.09	17.50	1.384	-	-	-0.17	0.249	0.345
	WCDMA II	-	-	-	-	RMC 12.2Kbps	Right Cheek	0mm	Ant 1	DSI 0	9262	1852.4	16.08	17.50	1.387	-	-	0.07	0.553	0.767
12	WCDMA II	-	-	-	-	RMC 12.2Kbps	Right Cheek	0mm	Ant 1	DSI 0	9538	1907.6	15.74	17.50	1.500	-	-	0.17	0.642	0.963
	WCDMA II	-	-	-	-	RMC 12.2Kbps	Right Cheek	0mm	Ant 2	DSI 0	9400	1880	24.59	25.00	1.099	-	-	0.04	0.212	0.233
	WCDMA II	-	-	-	-	RMC 12.2Kbps	Right Tilted	0mm	Ant 2	DSI 0	9400	1880	24.59	25.00	1.099	-	-	-0.04	0.144	0.158
	WCDMA II	-	-	-	-	RMC 12.2Kbps	Left Cheek	0mm	Ant 2	DSI 0	9400	1880	24.59	25.00	1.099	-	-	-0.11	0.223	0.245
	WCDMA II	-	-	-	-	RMC 12.2Kbps	Left Tilted	0mm	Ant 2	DSI 0	9400	1880	24.59	25.00	1.099	-	-	0.04	0.189	0.208
	LTE Band 2	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 2	DSI 0	18900	1880	23.96	25.00	1.271	-	-	-0.18	0.178	0.226
	LTE Band 2	20M	QPSK	1	0	-	Right Tilted	0mm	Ant 2	DSI 0	18900	1880	23.96	25.00	1.271	-	-	-0.05	0.100	0.127
	LTE Band 2	20M	QPSK	1	0	-	Left Cheek	0mm	Ant 2	DSI 0	18900	1880	23.96	25.00	1.271	-	-	-0.02	0.183	0.233
	LTE Band 2	20M	QPSK	1	0	-	Left Tilted	0mm	Ant 2	DSI 0	18900	1880	23.96	25.00	1.271	-	-	-0.03	0.139	0.177
	LTE Band 2	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 2	DSI 0	18900	1880	22.94	24.00	1.276	-	-	-0.18	0.137	0.175
	LTE Band 2	20M	QPSK	50	0	-	Right Tilted	0mm	Ant 2	DSI 0	18900	1880	22.94	24.00	1.276	-	-	-0.12	0.079	0.101
	LTE Band 2	20M	QPSK	50	0	-	Left Cheek	0mm	Ant 2	DSI 0	18900	1880	22.94	24.00	1.276	-	-	0.18	0.147	0.188
	LTE Band 2	20M	QPSK	50	0	-	Left Tilted	0mm	Ant 2	DSI 0	18900	1880	22.94	24.00	1.276	-	-	0.05	0.108	0.138
	LTE Band 2	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 4	DSI 0	18900	1880	22.14	23.00	1.219	-	-	-0.14	0.682	0.831
	LTE Band 2	20M	QPSK	1	0	-	Right Tilted	0mm	Ant 4	DSI 0	18900	1880	22.14	23.00	1.219	-	-	0.17	0.135	0.165
	LTE Band 2	20M	QPSK	1	0	-	Left Cheek	0mm	Ant 4	DSI 0	18900	1880	22.14	23.00	1.219	-	-	-0.06	0.847	1.032
	LTE Band 2	20M	QPSK	1	0	-	Left Tilted	0mm	Ant 4	DSI 0	18900	1880	22.14	23.00	1.219	-	-	0.04	0.225	0.274
	LTE Band 2	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 4	DSI 0	18700	1860	21.96	23.00	1.271	-	-	0.17	0.618	0.785
	LTE Band 2	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 4	DSI 0	19100	1900	22.03	23.00	1.250	-	-	-0.16	0.705	0.881
	LTE Band 2	20M	QPSK	1	0	-	Left Cheek	0mm	Ant 4	DSI 0	18700	1860	21.96	23.00	1.271	-	-	-0.06	0.767	0.975
13	LTE Band 2	20M	QPSK	1	0	-	Left Cheek	0mm	Ant 4	DSI 0	19100	1900	22.03	23.00	1.250	-	-	-0.16	0.875	1.094
	LTE Band 2	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 4	DSI 0	18900	1880	22.05	23.00	1.245	-	-	0.13	0.651	0.810
	LTE Band 2	20M	QPSK	50	0	-	Right Tilted	0mm	Ant 4	DSI 0	18900	1880	22.05	23.00	1.245	-	-	-0.04	0.132	0.164
	LTE Band 2	20M	QPSK	50	0	-	Left Cheek	0mm	Ant 4	DSI 0	18900	1880	22.05	23.00	1.245	-	-	0.01	0.815	1.014
	LTE Band 2	20M	QPSK	50	0	-	Left Tilted	0mm	Ant 4	DSI 0	18900	1880	22.05	23.00	1.245	-	-	0.18	0.218	0.271
	LTE Band 2	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 4	DSI 0	18700	1860	21.83	23.00	1.309	-	-	-0.13	0.577	0.755
	LTE Band 2	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 4	DSI 0	19100	1900	21.95	23.00	1.274	-	-	0.05	0.666	0.848
	LTE Band 2	20M	QPSK	50	0	-	Left Cheek	0mm	Ant 4	DSI 0	18700	1860	21.83	23.00	1.309	-	-	-0.13	0.717	0.939
	LTE Band 2	20M	QPSK	50	0	-	Left Cheek	0mm	Ant 4	DSI 0	19100	1900	21.95	23.00	1.274	-	-	-0.17	0.827	1.053
	LTE Band 2	20M	QPSK	100	0	-	Right Cheek	0mm	Ant 4	DSI 0	18900	1880	21.97	23.00	1.268	-	-	-0.01	0.608	0.771
	LTE Band 2	20M	QPSK	100	0	-	Left Cheek	0mm	Ant 4	DSI 0	18900	1880	21.97	23.00	1.268	-	-	-0.16	0.803	1.018
2600MHz																				
	LTE Band 7	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 1	DSI 0	21100	2535	16.87	18.00	1.297	-	-	-0.13	0.668	0.867
	LTE Band 7	20M	QPSK	1	0	-	Right Tilted	0mm	Ant 1	DSI 0	21100	2535	16.87	18.00	1.297	-	-	0.03	0.590	0.765
	LTE Band 7	20M	QPSK	1	0	-	Left Cheek	0mm	Ant 1	DSI 0	21100	2535	16.87	18.00	1.297	-	-	-0.04	0.311	0.403
	LTE Band 7	20M	QPSK	1	0	-	Left Tilted	0mm	Ant 1	DSI 0	21100	2535	16.87	18.00	1.297	-	-	-0.06	0.274	0.355
	LTE Band 7	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 1	DSI 0	20850	2510	16.80	18.00	1.318	-	-	0.07	0.700	0.923
	LTE Band 7C	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 1	DSI 0	20850+21048	2510+2529.8	16.48	18.00	1.419	-	-	0.06	0.560	0.795
	LTE Band 7	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 1	DSI 0	21350	2560	16.83	18.00	1.309	-	-	0.09	0.643	0.842
	LTE Band 7	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 1	DSI 0	21100	2535	16.72	18.00	1.343	-	-	-0.04	0.638	0.857
	LTE Band 7	20M	QPSK	50	0	-	Right Tilted	0mm	Ant 1	DSI 0	21100	2535	16.72	18.00	1.343	-	-	-0.18	0.563	0.756
	LTE Band 7	20M	QPSK	50	0	-	Left Cheek	0mm	Ant 1	DSI 0	21100	2535	16.72	18.00	1.343	-	-	-0.11	0.296	0.397
	LTE Band 7	20M	QPSK	50	0	-	Left Tilted	0mm	Ant 1	DSI 0	21100	2535	16.72	18.00	1.343	-	-	0.13	0.261	0.350
	LTE Band 7	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 1	DSI 0	20850	2510	16.71	18.00	1.346	-	-	0.12	0.668	0.899
	LTE Band 7	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 1	DSI 0	21350	2560	16.68	18.00	1.355	-	-	0.12	0.614	0.832
	LTE Band 7	20M	QPSK	100	0	-	Right Cheek	0mm	Ant 1	DSI 0	21100	2535	16.65	18.00	1.365	-	-	0.06	0.624	0.851
	LTE Band 7	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 2	DSI 0	21100	2535	24.41	25.50	1.285	-	-	0.15	0.166	0.213
	LTE Band 7	20M	QPSK	1	0	-	Right Tilted	0mm	Ant 2	DSI 0	21100	2535	24.41	25.50	1.285	-	-	-0.1	0.151	0.194
	LTE Band 7	20M	QPSK	1	0	-	Left Cheek	0mm	Ant 2	DSI 0	21100	2535	24.41	25.50	1.285	-	-	0.18	0.328	0.422
	LTE Band 7C	20M	QPSK	1	0	-	Left Cheek	0mm	Ant 2	DSI 0	21100+21298	2535+2554.8	24.20	25.50	1.349	-	-	0.07	0.258	0.348



FCC SAR Test Report

Report No. : FA350505

	LTE Band 7	20M	QPSK	1	0	-	Left Tilted	0mm	Ant 2	DSI 0	21100	2535	24.41	25.50	1.285	-	-	-0.02	0.080	0.103
	LTE Band 7	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 2	DSI 0	21100	2535	23.44	24.50	1.276	-	-	0.16	0.148	0.189
	LTE Band 7	20M	QPSK	50	0	-	Right Tilted	0mm	Ant 2	DSI 0	21100	2535	23.44	24.50	1.276	-	-	0.08	0.135	0.172
	LTE Band 7	20M	QPSK	50	0	-	Left Cheek	0mm	Ant 2	DSI 0	21100	2535	23.44	24.50	1.276	-	-	0.12	0.292	0.373
	LTE Band 7	20M	QPSK	50	0	-	Left Tilted	0mm	Ant 2	DSI 0	21100	2535	23.44	24.50	1.276	-	-	0.03	0.061	0.078
	LTE Band 7	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 3	DSI 0	21100	2535	18.57	19.50	1.239	-	-	-0.03	0.720	0.892
	LTE Band 7	20M	QPSK	1	0	-	Right Tilted	0mm	Ant 3	DSI 0	21100	2535	18.57	19.50	1.239	-	-	0.03	0.268	0.332
	LTE Band 7	20M	QPSK	1	0	-	Left Cheek	0mm	Ant 3	DSI 0	21100	2535	18.57	19.50	1.239	-	-	0.18	0.501	0.621
	LTE Band 7	20M	QPSK	1	0	-	Left Tilted	0mm	Ant 3	DSI 0	21100	2535	18.57	19.50	1.239	-	-	-0.11	0.135	0.167
	LTE Band 7	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 3	DSI 0	20850	2510	18.49	19.50	1.262	-	-	0.17	0.646	0.815
	LTE Band 7	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 3	DSI 0	21350	2560	18.44	19.50	1.276	-	-	0.04	0.752	0.960
	LTE Band 7C	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 3	DSI 0	21350+21152	2560+2540.2	17.83	19.50	1.469	-	-	0.01	0.605	0.889
	LTE Band 7	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 3	DSI 0	21100	2535	18.55	19.50	1.245	-	-	-0.17	0.687	0.855
	LTE Band 7	20M	QPSK	50	0	-	Right Tilted	0mm	Ant 3	DSI 0	21100	2535	18.55	19.50	1.245	-	-	-0.05	0.255	0.317
	LTE Band 7	20M	QPSK	50	0	-	Left Cheek	0mm	Ant 3	DSI 0	21100	2535	18.55	19.50	1.245	-	-	-0.09	0.478	0.595
	LTE Band 7	20M	QPSK	50	0	-	Left Tilted	0mm	Ant 3	DSI 0	21100	2535	18.55	19.50	1.245	-	-	0.14	0.129	0.161
	LTE Band 7	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 3	DSI 0	20850	2510	18.48	19.50	1.265	-	-	-0.14	0.618	0.782
	LTE Band 7	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 3	DSI 0	21350	2560	18.41	19.50	1.285	-	-	-0.12	0.734	0.943
	LTE Band 7	20M	QPSK	100	0	-	Right Cheek	0mm	Ant 3	DSI 0	21100	2535	18.50	19.50	1.259	-	-	0.05	0.655	0.825
	LTE Band 7	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 4	DSI 0	21100	2535	18.59	19.50	1.233	-	-	-0.17	0.690	0.851
	LTE Band 7	20M	QPSK	1	0	-	Right Tilted	0mm	Ant 4	DSI 0	21100	2535	18.59	19.50	1.233	-	-	-0.12	0.129	0.159
	LTE Band 7	20M	QPSK	1	0	-	Left Cheek	0mm	Ant 4	DSI 0	21100	2535	18.59	19.50	1.233	-	-	0.06	0.436	0.538
	LTE Band 7	20M	QPSK	1	0	-	Left Tilted	0mm	Ant 4	DSI 0	21100	2535	18.59	19.50	1.233	-	-	0.08	0.210	0.259
	LTE Band 7	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 4	DSI 0	20850	2510	18.40	19.50	1.288	-	-	0.14	0.663	0.854
14	LTE Band 7	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 4	DSI 0	21350	2560	18.42	19.50	1.282	-	-	0.09	0.809	1.037
	LTE Band 7C	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 4	DSI 0	21350+21152	2560+2540.2	18.25	19.50	1.334	-	-	0.07	0.572	0.763
	LTE Band 7	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 4	DSI 0	21100	2535	18.45	19.50	1.274	-	-	0.09	0.660	0.841
	LTE Band 7	20M	QPSK	50	0	-	Right Tilted	0mm	Ant 4	DSI 0	21100	2535	18.45	19.50	1.274	-	-	0.13	0.123	0.157
	LTE Band 7	20M	QPSK	50	0	-	Left Cheek	0mm	Ant 4	DSI 0	21100	2535	18.45	19.50	1.274	-	-	-0.16	0.416	0.530
	LTE Band 7	20M	QPSK	50	0	-	Left Tilted	0mm	Ant 4	DSI 0	21100	2535	18.45	19.50	1.274	-	-	0.15	0.201	0.256
	LTE Band 7	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 4	DSI 0	20850	2510	18.36	19.50	1.300	-	-	0.13	0.638	0.830
	LTE Band 7	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 4	DSI 0	21350	2560	18.37	19.50	1.297	-	-	0.03	0.772	1.001
	LTE Band 7	20M	QPSK	100	0	-	Right Cheek	0mm	Ant 4	DSI 0	21100	2535	18.31	19.50	1.315	-	-	-0.17	0.625	0.822
	LTE Band 41	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 1	DSI 0	40620	2593	19.17	20.00	1.211	62.9	1.006	0	0.691	0.842
	LTE Band 41	20M	QPSK	1	0	-	Right Tilted	0mm	Ant 1	DSI 0	40620	2593	19.17	20.00	1.211	62.9	1.006	-0.15	0.665	0.810
	LTE Band 41	20M	QPSK	1	0	-	Left Cheek	0mm	Ant 1	DSI 0	40620	2593	19.17	20.00	1.211	62.9	1.006	0.11	0.329	0.401
	LTE Band 41	20M	QPSK	1	0	-	Left Tilted	0mm	Ant 1	DSI 0	40620	2593	19.17	20.00	1.211	62.9	1.006	-0.17	0.292	0.356
	LTE Band 41	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 1	DSI 0	39750	2506	19.01	20.00	1.256	62.9	1.006	-0.01	0.808	1.021
	LTE Band 38C	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 1	DSI 0	37901+38099	2585.1+2604.9	18.74	20.00	1.337	62.9	1.006	-0.06	0.484	0.651
	LTE Band 41	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 1	DSI 0	40185	2549.5	19.08	20.00	1.236	62.9	1.006	0.08	0.708	0.880
	LTE Band 41	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 1	DSI 0	41055	2636.5	19.10	20.00	1.230	62.9	1.006	0.17	0.589	0.729
	LTE Band 41	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 1	DSI 0	41490	2680	19.14	20.00	1.219	62.9	1.006	0.1	0.592	0.726
	LTE Band 41	20M	QPSK	1	0	-	Right Tilted	0mm	Ant 1	DSI 0	39750	2506	19.01	20.00	1.256	62.9	1.006	0.1	0.772	0.975
	LTE Band 41	20M	QPSK	1	0	-	Right Tilted	0mm	Ant 1	DSI 0	40185	2549.5	19.08	20.00	1.236	62.9	1.006	-0.05	0.676	0.841
	LTE Band 41	20M	QPSK	1	0	-	Right Tilted	0mm	Ant 1	DSI 0	41055	2636.5	19.10	20.00	1.230	62.9	1.006	0.06	0.562	0.696
	LTE Band 41	20M	QPSK	1	0	-	Right Tilted	0mm	Ant 1	DSI 0	41490	2680	19.14	20.00	1.219	62.9	1.006	0.1	0.565	0.693
	LTE Band 41	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 1	DSI 0	40620	2593	19.10	20.00	1.230	62.9	1.006	0.03	0.673	0.833
	LTE Band 41	20M	QPSK	50	0	-	Right Tilted	0mm	Ant 1	DSI 0	40620	2593	19.10	20.00	1.230	62.9	1.006	-0.07	0.647	0.801
	LTE Band 41	20M	QPSK	50	0	-	Left Cheek	0mm	Ant 1	DSI 0	40620	2593	19.10	20.00	1.230	62.9	1.006	0.18	0.315	0.390
	LTE Band 41	20M	QPSK	50	0	-	Left Tilted	0mm	Ant 1	DSI 0	40620	2593	19.10	20.00	1.230	62.9	1.006	0.17	0.281	0.348
	LTE Band 41	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 1	DSI 0	39750	2506	18.93	20.00	1.279	62.9	1.006	0.09	0.776	0.999
	LTE Band 41	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 1	DSI 0	40185	2549.5	19.00	20.00	1.259	62.9	1.006	0.04	0.687	0.870
	LTE Band 41	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 1	DSI 0	41055	2636.5	19.07	20.00	1.239	62.9	1.006	-0.14	0.569	0.709
	LTE Band 41	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 1	DSI 0	41490	2680	19.08	20.00	1.236	62.9	1.006	0.05	0.569	0.707
	LTE Band 41	20M	QPSK	50	0	-	Right Tilted	0mm	Ant 1	DSI 0	39750	2506	18.93	20.00	1.279	62.9	1.006	-0.03	0.741	0.954



FCC SAR Test Report

Report No. : FA350505

Table with columns for LTE Band, Modulation, Power, Frequency, Location, Antenna, DSI, SAR values, etc. Includes a highlighted row with SAR value 1.035.



FCC SAR Test Report

Report No. : FA350505

	LTE Band 41	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 4	DSI 0	41055	2636.5	20.52	21.20	1.169	62.9	1.006	0.04	0.764	0.899
	LTE Band 41	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 4	DSI 0	41490	2680	20.56	21.20	1.159	62.9	1.006	-0.04	0.701	0.817
	LTE Band 41	20M	QPSK	100	0	-	Right Cheek	0mm	Ant 4	DSI 0	40620	2593	20.76	21.20	1.107	62.9	1.006	0.14	0.816	0.908
	FR1 n7	50M	QPSK	1	1	DFT-15	Right Cheek	0mm	Ant 1	DSI 0	507000	2535	16.89	18.50	1.449	-	-	0.01	0.658	0.953
	FR1 n7	50M	QPSK	1	1	DFT-15	Right Tilted	0mm	Ant 1	DSI 0	507000	2535	16.89	18.50	1.449	-	-	0.08	0.494	0.716
	FR1 n7	50M	QPSK	1	1	DFT-15	Left Cheek	0mm	Ant 1	DSI 0	507000	2535	16.89	18.50	1.449	-	-	0.01	0.291	0.422
	FR1 n7	50M	QPSK	1	1	DFT-15	Left Tilted	0mm	Ant 1	DSI 0	507000	2535	16.89	18.50	1.449	-	-	0.08	0.253	0.367
	FR1 n7	50M	QPSK	135	68	DFT-15	Right Cheek	0mm	Ant 1	DSI 0	507000	2535	16.82	18.50	1.472	-	-	0.17	0.617	0.908
	FR1 n7	50M	QPSK	135	68	DFT-15	Right Tilted	0mm	Ant 1	DSI 0	507000	2535	16.82	18.50	1.472	-	-	0.03	0.430	0.633
	FR1 n7	50M	QPSK	135	68	DFT-15	Left Cheek	0mm	Ant 1	DSI 0	507000	2535	16.82	18.50	1.472	-	-	0	0.268	0.395
	FR1 n7	50M	QPSK	135	68	DFT-15	Left Tilted	0mm	Ant 1	DSI 0	507000	2535	16.82	18.50	1.472	-	-	-0.01	0.233	0.343
	FR1 n7	50M	QPSK	270	0	DFT-15	Right Cheek	0mm	Ant 1	DSI 0	507000	2535	16.78	18.50	1.486	-	-	0.01	0.605	0.899
	FR1 n7	50M	QPSK	1	1	DFT-15	Right Cheek	0mm	Ant 2	DSI 0	507000	2535	24.56	25.50	1.242	-	-	-0.09	0.147	0.183
	FR1 n7	50M	QPSK	1	1	DFT-15	Right Tilted	0mm	Ant 2	DSI 0	507000	2535	24.56	25.50	1.242	-	-	-0.02	0.105	0.130
	FR1 n7	50M	QPSK	1	1	DFT-15	Left Cheek	0mm	Ant 2	DSI 0	507000	2535	24.56	25.50	1.242	-	-	-0.09	0.304	0.377
	FR1 n7	50M	QPSK	1	1	DFT-15	Left Tilted	0mm	Ant 2	DSI 0	507000	2535	24.56	25.50	1.242	-	-	0.01	0.058	0.072
	FR1 n7	50M	QPSK	135	68	DFT-15	Right Cheek	0mm	Ant 2	DSI 0	507000	2535	24.51	25.50	1.256	-	-	-0.18	0.148	0.186
	FR1 n7	50M	QPSK	135	68	DFT-15	Right Tilted	0mm	Ant 2	DSI 0	507000	2535	24.51	25.50	1.256	-	-	0.15	0.110	0.138
	FR1 n7	50M	QPSK	135	68	DFT-15	Left Cheek	0mm	Ant 2	DSI 0	507000	2535	24.51	25.50	1.256	-	-	-0.11	0.326	0.409
	FR1 n7	50M	QPSK	135	68	DFT-15	Left Tilted	0mm	Ant 2	DSI 0	507000	2535	24.51	25.50	1.256	-	-	0.07	0.062	0.078
	FR1 n7	50M	QPSK	1	1	DFT-15	Right Cheek	0mm	Ant 3	DSI 0	507000	2535	17.98	19.50	1.419	-	-	0.18	0.636	0.903
	FR1 n7	50M	QPSK	1	1	DFT-15	Right Tilted	0mm	Ant 3	DSI 0	507000	2535	17.98	19.50	1.419	-	-	-0.04	0.170	0.241
	FR1 n7	50M	QPSK	1	1	DFT-15	Left Cheek	0mm	Ant 3	DSI 0	507000	2535	17.98	19.50	1.419	-	-	0.08	0.521	0.739
	FR1 n7	50M	QPSK	1	1	DFT-15	Left Tilted	0mm	Ant 3	DSI 0	507000	2535	17.98	19.50	1.419	-	-	-0.06	0.093	0.132
16	FR1 n7	50M	QPSK	135	68	DFT-15	Right Cheek	0mm	Ant 3	DSI 0	507000	2535	17.95	19.50	1.429	-	-	0.08	0.764	1.092
	FR1 n7	50M	QPSK	135	68	DFT-15	Right Tilted	0mm	Ant 3	DSI 0	507000	2535	17.95	19.50	1.429	-	-	0.12	0.178	0.254
	FR1 n7	50M	QPSK	135	68	DFT-15	Left Cheek	0mm	Ant 3	DSI 0	507000	2535	17.95	19.50	1.429	-	-	-0.12	0.576	0.823
	FR1 n7	50M	QPSK	135	68	DFT-15	Left Tilted	0mm	Ant 3	DSI 0	507000	2535	17.95	19.50	1.429	-	-	0.17	0.115	0.164
	FR1 n7	50M	QPSK	270	0	DFT-15	Right Cheek	0mm	Ant 3	DSI 0	507000	2535	17.89	19.50	1.449	-	-	0.13	0.599	0.868
	FR1 n7	50M	QPSK	270	0	DFT-15	Left Cheek	0mm	Ant 3	DSI 0	507000	2535	17.89	19.50	1.449	-	-	-0.16	0.483	0.700
	FR1 n7	50M	QPSK	1	1	DFT-15	Right Cheek	0mm	Ant 4	DSI 0	507000	2535	18.50	19.50	1.259	-	-	0.04	0.723	0.910
	FR1 n7	50M	QPSK	1	1	DFT-15	Right Tilted	0mm	Ant 4	DSI 0	507000	2535	18.50	19.50	1.259	-	-	-0.19	0.119	0.150
	FR1 n7	50M	QPSK	1	1	DFT-15	Left Cheek	0mm	Ant 4	DSI 0	507000	2535	18.50	19.50	1.259	-	-	0.03	0.482	0.607
	FR1 n7	50M	QPSK	1	1	DFT-15	Left Tilted	0mm	Ant 4	DSI 0	507000	2535	18.50	19.50	1.259	-	-	0.19	0.173	0.218
	FR1 n7	50M	QPSK	135	68	DFT-15	Right Cheek	0mm	Ant 4	DSI 0	507000	2535	18.47	19.50	1.268	-	-	0.02	0.859	1.089
	FR1 n7	50M	QPSK	135	68	DFT-15	Right Tilted	0mm	Ant 4	DSI 0	507000	2535	18.47	19.50	1.268	-	-	0.15	0.134	0.170
	FR1 n7	50M	QPSK	135	68	DFT-15	Left Cheek	0mm	Ant 4	DSI 0	507000	2535	18.47	19.50	1.268	-	-	-0.17	0.549	0.696
	FR1 n7	50M	QPSK	135	68	DFT-15	Left Tilted	0mm	Ant 4	DSI 0	507000	2535	18.47	19.50	1.268	-	-	-0.19	0.200	0.254
	FR1 n7	50M	QPSK	270	0	DFT-15	Right Cheek	0mm	Ant 4	DSI 0	507000	2535	18.40	19.50	1.288	-	-	0.1	0.688	0.886
	FR1 n41	100M	QPSK	1	1	DFT-30	Right Cheek	0mm	Ant 1	DSI 0	518598	2592.99	17.19	18.50	1.352	-	-	0.07	0.736	0.995
	FR1 n41	100M	QPSK	1	1	DFT-30	Right Tilted	0mm	Ant 1	DSI 0	518598	2592.99	17.19	18.50	1.352	-	-	0.17	0.711	0.961
	FR1 n41	100M	QPSK	1	1	DFT-30	Left Cheek	0mm	Ant 1	DSI 0	518598	2592.99	17.19	18.50	1.352	-	-	0.11	0.394	0.533
	FR1 n41	100M	QPSK	1	1	DFT-30	Left Tilted	0mm	Ant 1	DSI 0	518598	2592.99	17.19	18.50	1.352	-	-	0.14	0.334	0.452
	FR1 n41	100M	QPSK	135	69	DFT-30	Right Cheek	0mm	Ant 1	DSI 0	518598	2592.99	17.18	18.50	1.355	-	-	0.01	0.705	0.955
	FR1 n41	100M	QPSK	135	69	DFT-30	Right Tilted	0mm	Ant 1	DSI 0	518598	2592.99	17.18	18.50	1.355	-	-	-0.09	0.659	0.893
	FR1 n41	100M	QPSK	135	69	DFT-30	Left Cheek	0mm	Ant 1	DSI 0	518598	2592.99	17.18	18.50	1.355	-	-	-0.18	0.363	0.492
	FR1 n41	100M	QPSK	135	69	DFT-30	Left Tilted	0mm	Ant 1	DSI 0	518598	2592.99	17.18	18.50	1.355	-	-	0.07	0.323	0.438
	FR1 n41	100M	QPSK	270	0	DFT-30	Right Cheek	0mm	Ant 1	DSI 0	518598	2592.99	17.16	18.50	1.361	-	-	0.15	0.703	0.957
	FR1 n41	100M	QPSK	270	0	DFT-30	Right Tilted	0mm	Ant 1	DSI 0	518598	2592.99	17.16	18.50	1.361	-	-	-0.07	0.673	0.916
	FR1 n41	100M	QPSK	1	1	DFT-30	Right Cheek	0mm	Ant 2	DSI 0	518598	2592.99	24.62	25.70	1.282	-	-	-0.02	0.173	0.222
	FR1 n41	100M	QPSK	1	1	DFT-30	Right Tilted	0mm	Ant 2	DSI 0	518598	2592.99	24.62	25.70	1.282	-	-	0.16	0.135	0.173
	FR1 n41	100M	QPSK	1	1	DFT-30	Left Cheek	0mm	Ant 2	DSI 0	518598	2592.99	24.62	25.70	1.282	-	-	-0.06	0.304	0.390
	FR1 n41	100M	QPSK	1	1	DFT-30	Left Tilted	0mm	Ant 2	DSI 0	518598	2592.99	24.62	25.70	1.282	-	-	0.18	0.084	0.108
	FR1 n41	100M	QPSK	135	69	DFT-30	Right Cheek	0mm	Ant 2	DSI 0	518598	2592.99	24.52	25.70	1.312	-	-	-0.12	0.148	0.194
	FR1 n41	100M	QPSK	135	69	DFT-30	Right Tilted	0mm	Ant 2	DSI 0	518598	2592.99	24.52	25.70	1.312	-	-	0.11	0.116	0.152
	FR1 n41	100M	QPSK	135	69	DFT-30	Left Cheek	0mm	Ant 2	DSI 0	518598	2592.99	24.52	25.70	1.312	-	-	0.11	0.290	0.381



FCC SAR Test Report

Report No. : FA350505

	FR1 n41	100M	QPSK	135	69	DFT-30	Left Tilted	0mm	Ant 2	DSI 0	518598	2592.99	24.52	25.70	1.312	-	-	0.08	0.075	0.098
17	FR1 n41	100M	QPSK	1	1	DFT-30	Right Cheek	0mm	Ant 3	DSI 0	518598	2592.99	17.36	19.00	1.459	-	-	-0.17	0.707	1.031
	FR1 n41	100M	QPSK	1	1	DFT-30	Right Tilted	0mm	Ant 3	DSI 0	518598	2592.99	17.36	19.00	1.459	-	-	-0.06	0.229	0.334
	FR1 n41	100M	QPSK	1	1	DFT-30	Left Cheek	0mm	Ant 3	DSI 0	518598	2592.99	17.36	19.00	1.459	-	-	-0.16	0.488	0.712
	FR1 n41	100M	QPSK	1	1	DFT-30	Left Tilted	0mm	Ant 3	DSI 0	518598	2592.99	17.36	19.00	1.459	-	-	-0.09	0.122	0.178
	FR1 n41	100M	QPSK	135	69	DFT-30	Right Cheek	0mm	Ant 3	DSI 0	518598	2592.99	17.20	19.00	1.514	-	-	-0.15	0.636	0.963
	FR1 n41	100M	QPSK	135	69	DFT-30	Right Tilted	0mm	Ant 3	DSI 0	518598	2592.99	17.20	19.00	1.514	-	-	0.1	0.200	0.303
	FR1 n41	100M	QPSK	135	69	DFT-30	Left Cheek	0mm	Ant 3	DSI 0	518598	2592.99	17.20	19.00	1.514	-	-	0	0.451	0.683
	FR1 n41	100M	QPSK	135	69	DFT-30	Left Tilted	0mm	Ant 3	DSI 0	518598	2592.99	17.20	19.00	1.514	-	-	0.08	0.111	0.168
	FR1 n41	100M	QPSK	270	0	DFT-30	Right Cheek	0mm	Ant 3	DSI 0	518598	2592.99	17.19	19.00	1.517	-	-	0.1	0.629	0.954
	FR1 n41	100M	QPSK	270	0	DFT-30	Left Cheek	0mm	Ant 3	DSI 0	518598	2592.99	17.19	19.00	1.517	-	-	0.1	0.452	0.686
	FR1 n41	100M	QPSK	1	1	DFT-30	Right Cheek	0mm	Ant 4	DSI 0	518598	2592.99	17.13	17.70	1.140	-	-	-0.07	0.811	0.925
	FR1 n41	100M	QPSK	1	1	DFT-30	Right Tilted	0mm	Ant 4	DSI 0	518598	2592.99	17.13	17.70	1.140	-	-	0.12	0.099	0.113
	FR1 n41	100M	QPSK	1	1	DFT-30	Left Cheek	0mm	Ant 4	DSI 0	518598	2592.99	17.13	17.70	1.140	-	-	0.16	0.341	0.389
	FR1 n41	100M	QPSK	1	1	DFT-30	Left Tilted	0mm	Ant 4	DSI 0	518598	2592.99	17.13	17.70	1.140	-	-	0.08	0.157	0.179
	FR1 n41	100M	QPSK	135	69	DFT-30	Right Cheek	0mm	Ant 4	DSI 0	518598	2592.99	17.09	17.70	1.151	-	-	-0.18	0.839	0.966
	FR1 n41	100M	QPSK	135	69	DFT-30	Right Tilted	0mm	Ant 4	DSI 0	518598	2592.99	17.09	17.70	1.151	-	-	-0.1	0.108	0.124
	FR1 n41	100M	QPSK	135	69	DFT-30	Left Cheek	0mm	Ant 4	DSI 0	518598	2592.99	17.09	17.70	1.151	-	-	0.08	0.356	0.410
	FR1 n41	100M	QPSK	135	69	DFT-30	Left Tilted	0mm	Ant 4	DSI 0	518598	2592.99	17.09	17.70	1.151	-	-	0.05	0.177	0.204
	FR1 n41	100M	QPSK	270	0	DFT-30	Right Cheek	0mm	Ant 4	DSI 0	518598	2592.99	17.06	17.70	1.159	-	-	0.07	0.779	0.903
3500MHz																				
	FR1 n77 Part27Q	100M	QPSK	1	137	DFT-30	Right Cheek	0mm	Ant 1	DSI 0	633332	3499.98	18.12	19.50	1.374	-	-	0.17	0.421	0.578
	FR1 n77 Part27Q	100M	QPSK	1	137	DFT-30	Right Tilted	0mm	Ant 1	DSI 0	633332	3499.98	18.12	19.50	1.374	-	-	-0.1	0.517	0.710
	FR1 n77 Part27Q	100M	QPSK	1	137	DFT-30	Left Cheek	0mm	Ant 1	DSI 0	633332	3499.98	18.12	19.50	1.374	-	-	0.13	0.208	0.286
	FR1 n77 Part27Q	100M	QPSK	1	137	DFT-30	Left Tilted	0mm	Ant 1	DSI 0	633332	3499.98	18.12	19.50	1.374	-	-	-0.1	0.242	0.333
	FR1 n77 Part27Q	100M	QPSK	135	69	DFT-30	Right Cheek	0mm	Ant 1	DSI 0	633332	3499.98	18.09	19.50	1.384	-	-	-0.03	0.408	0.564
	FR1 n77 Part27Q	100M	QPSK	135	69	DFT-30	Right Tilted	0mm	Ant 1	DSI 0	633332	3499.98	18.09	19.50	1.384	-	-	-0.03	0.492	0.681
	FR1 n77 Part27Q	100M	QPSK	135	69	DFT-30	Left Cheek	0mm	Ant 1	DSI 0	633332	3499.98	18.09	19.50	1.384	-	-	-0.14	0.200	0.277
	FR1 n77 Part27Q	100M	QPSK	135	69	DFT-30	Left Tilted	0mm	Ant 1	DSI 0	633332	3499.98	18.09	19.50	1.384	-	-	-0.06	0.231	0.320
	FR1 n77 Part27Q	100M	QPSK	1	137	DFT-30	Right Cheek	0mm	Ant 1	DSI 0	656000	3840	18.51	20.00	1.409	-	-	-0.17	0.615	0.867
	FR1 n77 Part27Q	100M	QPSK	1	137	DFT-30	Right Tilted	0mm	Ant 1	DSI 0	656000	3840	18.51	20.00	1.409	-	-	0.02	0.734	1.034
	FR1 n77 Part27Q	100M	QPSK	1	137	DFT-30	Left Cheek	0mm	Ant 1	DSI 0	656000	3840	18.51	20.00	1.409	-	-	-0.04	0.347	0.489
	FR1 n77 Part27Q	100M	QPSK	1	137	DFT-30	Left Tilted	0mm	Ant 1	DSI 0	656000	3840	18.51	20.00	1.409	-	-	-0.01	0.400	0.564
	FR1 n77 Part27Q	100M	QPSK	135	69	DFT-30	Right Cheek	0mm	Ant 1	DSI 0	656000	3840	18.48	20.00	1.419	-	-	0.01	0.634	0.900
	FR1 n77 Part27Q	100M	QPSK	135	69	DFT-30	Right Tilted	0mm	Ant 1	DSI 0	656000	3840	18.48	20.00	1.419	-	-	0.05	0.754	1.070
	FR1 n77 Part27Q	100M	QPSK	135	69	DFT-30	Left Cheek	0mm	Ant 1	DSI 0	656000	3840	18.48	20.00	1.419	-	-	-0.12	0.353	0.501
	FR1 n77 Part27Q	100M	QPSK	135	69	DFT-30	Left Tilted	0mm	Ant 1	DSI 0	656000	3840	18.48	20.00	1.419	-	-	-0.13	0.417	0.592
	FR1 n77 Part27Q PC2	100M	QPSK	135	69	DFT-30	Right Tilted	0mm	Ant 1	DSI 0	656000	3840	21.77	23.00	1.327	50	1.000	-0.14	0.765	1.015
	FR1 n77 Part27Q	100M	QPSK	270	0	DFT-30	Right Cheek	0mm	Ant 1	DSI 0	656000	3840	18.46	20.00	1.426	-	-	-0.09	0.611	0.871
	FR1 n77 Part27Q	100M	QPSK	270	0	DFT-30	Right Tilted	0mm	Ant 1	DSI 0	656000	3840	18.46	20.00	1.426	-	-	0.08	0.708	1.009
	FR1 n77 Part27Q	100M	QPSK	1	137	DFT-30	Right Cheek	0mm	Ant 5	DSI 0	633332	3499.98	17.98	19.50	1.419	-	-	0.16	0.261	0.371
	FR1 n77 Part27Q	100M	QPSK	1	137	DFT-30	Right Tilted	0mm	Ant 5	DSI 0	633332	3499.98	17.98	19.50	1.419	-	-	0.12	0.329	0.467
	FR1 n77 Part27Q	100M	QPSK	1	137	DFT-30	Left Cheek	0mm	Ant 5	DSI 0	633332	3499.98	17.98	19.50	1.419	-	-	0.15	0.439	0.623
18	FR1 n77 Part27Q	100M	QPSK	1	137	DFT-30	Left Tilted	0mm	Ant 5	DSI 0	633332	3499.98	17.98	19.50	1.419	-	-	0.09	0.766	1.087
	FR1 n77 Part27Q PC2	100M	QPSK	1	137	DFT-30	Left Tilted	0mm	Ant 5	DSI 0	633332	3499.98	20.86	22.50	1.459	50	1.000	0.04	0.731	1.066
	FR1 n77 Part27Q	100M	QPSK	135	69	DFT-30	Right Cheek	0mm	Ant 5	DSI 0	633332	3499.98	17.97	19.50	1.422	-	-	-0.15	0.249	0.354
	FR1 n77 Part27Q	100M	QPSK	135	69	DFT-30	Right Tilted	0mm	Ant 5	DSI 0	633332	3499.98	17.97	19.50	1.422	-	-	0.11	0.297	0.422
	FR1 n77 Part27Q	100M	QPSK	135	69	DFT-30	Left Cheek	0mm	Ant 5	DSI 0	633332	3499.98	17.97	19.50	1.422	-	-	0.08	0.422	0.600
	FR1 n77 Part27Q	100M	QPSK	135	69	DFT-30	Left Tilted	0mm	Ant 5	DSI 0	633332	3499.98	17.97	19.50	1.422	-	-	0.12	0.733	1.043
	FR1 n77 Part27Q	100M	QPSK	270	0	DFT-30	Left Tilted	0mm	Ant 5	DSI 0	633332	3499.98	17.79	19.50	1.483	-	-	0.04	0.704	1.044
	FR1 n77 Part27Q	100M	QPSK	1	137	DFT-30	Right Cheek	0mm	Ant 5	DSI 0	656000	3840	17.77	19.50	1.489	-	-	-0.03	0.238	0.354
	FR1 n77 Part27Q	100M	QPSK	1	137	DFT-30	Right Tilted	0mm	Ant 5	DSI 0	656000	3840	17.77	19.50	1.489	-	-	0.07	0.288	0.429
	FR1 n77 Part27Q	100M	QPSK	1	137	DFT-30	Left Cheek	0mm	Ant 5	DSI 0	656000	3840	17.77	19.50	1.489	-	-	0	0.388	0.578
	FR1 n77 Part27Q	100M	QPSK	1	137	DFT-30	Left Tilted	0mm	Ant 5	DSI 0	656000	3840	17.77	19.50	1.489	-	-	0.11	0.476	0.709
	FR1 n77 Part27Q	100M	QPSK	135	69	DFT-30	Right Cheek	0mm	Ant 5	DSI 0	656000	3840	17.69	19.50	1.517	-	-	-0.09	0.258	0.391
	FR1 n77 Part27Q	100M	QPSK	135	69	DFT-30	Right Tilted	0mm	Ant 5	DSI 0	656000	3840	17.69	19.50	1.517	-	-	-0.14	0.331	0.502



FCC SAR Test Report

Report No. : FA350505

	FR1 n77 Part27O	100M	QPSK	135	69	DFT-30	Left Cheek	0mm	Ant 5	DSI 0	656000	3840	17.69	19.50	1.517	-	-	0.09	0.405	0.614
	FR1 n77 Part27O	100M	QPSK	135	69	DFT-30	Left Tilted	0mm	Ant 5	DSI 0	656000	3840	17.69	19.50	1.517	-	-	-0.13	0.481	0.730
	FR1 n77 Part27O	100M	QPSK	270	0	DFT-30	Left Cheek	0mm	Ant 5	DSI 0	656000	3840	17.67	19.50	1.524	-	-	0.05	0.389	0.593
	FR1 n77 Part27O	100M	QPSK	270	0	DFT-30	Left Tilted	0mm	Ant 5	DSI 0	656000	3840	17.67	19.50	1.524	-	-	0.14	0.457	0.696
	FR1 n77 Part27Q	100M	QPSK	1	137	DFT-30	Right Cheek	0mm	Ant 6	DSI 0	633332	3499.98	16.19	17.50	1.352	-	-	0.16	0.124	0.168
	FR1 n77 Part27Q	100M	QPSK	1	137	DFT-30	Right Tilted	0mm	Ant 6	DSI 0	633332	3499.98	16.19	17.50	1.352	-	-	-0.02	0.068	0.092
	FR1 n77 Part27Q	100M	QPSK	1	137	DFT-30	Left Cheek	0mm	Ant 6	DSI 0	633332	3499.98	16.19	17.50	1.352	-	-	0.05	0.675	0.913
	FR1 n77 Part27Q	100M	QPSK	1	137	DFT-30	Left Tilted	0mm	Ant 6	DSI 0	633332	3499.98	16.19	17.50	1.352	-	-	-0.01	0.229	0.310
	FR1 n77 Part27Q	100M	QPSK	135	69	DFT-30	Right Cheek	0mm	Ant 6	DSI 0	633332	3499.98	16.06	17.50	1.393	-	-	0.15	0.125	0.174
	FR1 n77 Part27Q	100M	QPSK	135	69	DFT-30	Right Tilted	0mm	Ant 6	DSI 0	633332	3499.98	16.06	17.50	1.393	-	-	-0.16	0.085	0.118
	FR1 n77 Part27Q	100M	QPSK	135	69	DFT-30	Left Cheek	0mm	Ant 6	DSI 0	633332	3499.98	16.06	17.50	1.393	-	-	0.15	0.705	0.982
	FR1 n77 Part27Q	100M	QPSK	135	69	DFT-30	Left Tilted	0mm	Ant 6	DSI 0	633332	3499.98	16.06	17.50	1.393	-	-	0.17	0.242	0.337
	FR1 n77 Part27Q PC2	100M	QPSK	135	69	DFT-30	Left Cheek	0mm	Ant 6	DSI 0	633332	3499.98	19.21	20.50	1.346	50	1.000	0.15	0.721	0.970
	FR1 n77 Part27Q	100M	QPSK	270	0	DFT-30	Left Cheek	0mm	Ant 6	DSI 0	633332	3499.98	16.00	17.50	1.413	-	-	-0.03	0.644	0.910
	FR1 n77 Part27O	100M	QPSK	1	137	DFT-30	Right Cheek	0mm	Ant 6	DSI 0	656000	3840	17.07	18.50	1.390	-	-	-0.05	0.091	0.126
	FR1 n77 Part27O	100M	QPSK	1	137	DFT-30	Right Tilted	0mm	Ant 6	DSI 0	656000	3840	17.07	18.50	1.390	-	-	-0.13	0.050	0.069
	FR1 n77 Part27O	100M	QPSK	1	137	DFT-30	Left Cheek	0mm	Ant 6	DSI 0	656000	3840	17.07	18.50	1.390	-	-	0.08	0.410	0.570
	FR1 n77 Part27O	100M	QPSK	1	137	DFT-30	Left Tilted	0mm	Ant 6	DSI 0	656000	3840	17.07	18.50	1.390	-	-	-0.17	0.171	0.238
	FR1 n77 Part27O	100M	QPSK	135	69	DFT-30	Right Cheek	0mm	Ant 6	DSI 0	656000	3840	17.03	18.50	1.403	-	-	0.16	0.113	0.159
	FR1 n77 Part27O	100M	QPSK	135	69	DFT-30	Right Tilted	0mm	Ant 6	DSI 0	656000	3840	17.03	18.50	1.403	-	-	0.1	0.071	0.100
	FR1 n77 Part27O	100M	QPSK	135	69	DFT-30	Left Cheek	0mm	Ant 6	DSI 0	656000	3840	17.03	18.50	1.403	-	-	-0.1	0.430	0.603
	FR1 n77 Part27O	100M	QPSK	135	69	DFT-30	Left Tilted	0mm	Ant 6	DSI 0	656000	3840	17.03	18.50	1.403	-	-	-0.11	0.197	0.276
	FR1 n77 Part27O	100M	QPSK	270	0	DFT-30	Left Cheek	0mm	Ant 6	DSI 0	656000	3840	17.01	18.50	1.409	-	-	-0.01	0.405	0.571
	FR1 n77 Part27Q	100M	QPSK	1	137	DFT-30	Right Cheek	0mm	Ant 7	DSI 0	633332	3499.98	21.97	23.00	1.268	-	-	-0.07	0.330	0.418
	FR1 n77 Part27Q	100M	QPSK	1	137	DFT-30	Right Tilted	0mm	Ant 7	DSI 0	633332	3499.98	21.97	23.00	1.268	-	-	0.04	0.093	0.118
	FR1 n77 Part27Q	100M	QPSK	1	137	DFT-30	Left Cheek	0mm	Ant 7	DSI 0	633332	3499.98	21.97	23.00	1.268	-	-	-0.16	0.235	0.298
	FR1 n77 Part27Q	100M	QPSK	1	137	DFT-30	Left Tilted	0mm	Ant 7	DSI 0	633332	3499.98	21.97	23.00	1.268	-	-	0.19	0.054	0.068
	FR1 n77 Part27Q PC2	100M	QPSK	1	137	DFT-30	Right Cheek	0mm	Ant 7	DSI 0	633332	3499.98	24.97	26.00	1.268	50	1.000	-0.07	0.330	0.418
	FR1 n77 Part27Q	100M	QPSK	135	69	DFT-30	Right Cheek	0mm	Ant 7	DSI 0	633332	3499.98	21.95	23.00	1.274	-	-	0.13	0.313	0.399
	FR1 n77 Part27Q	100M	QPSK	135	69	DFT-30	Right Tilted	0mm	Ant 7	DSI 0	633332	3499.98	21.95	23.00	1.274	-	-	0.06	0.086	0.110
	FR1 n77 Part27Q	100M	QPSK	135	69	DFT-30	Left Cheek	0mm	Ant 7	DSI 0	633332	3499.98	21.95	23.00	1.274	-	-	0.11	0.203	0.259
	FR1 n77 Part27Q	100M	QPSK	135	69	DFT-30	Left Tilted	0mm	Ant 7	DSI 0	633332	3499.98	21.95	23.00	1.274	-	-	0.15	0.051	0.065
	FR1 n77 Part27O	100M	QPSK	1	137	DFT-30	Right Cheek	0mm	Ant 7	DSI 0	656000	3840	22.23	23.50	1.340	-	-	0.1	0.280	0.375
	FR1 n77 Part27O	100M	QPSK	1	137	DFT-30	Right Tilted	0mm	Ant 7	DSI 0	656000	3840	22.23	23.50	1.340	-	-	0.06	0.198	0.265
	FR1 n77 Part27O	100M	QPSK	1	137	DFT-30	Left Cheek	0mm	Ant 7	DSI 0	656000	3840	22.23	23.50	1.340	-	-	0.13	0.150	0.201
	FR1 n77 Part27O	100M	QPSK	1	137	DFT-30	Left Tilted	0mm	Ant 7	DSI 0	656000	3840	22.23	23.50	1.340	-	-	-0.06	0.108	0.145
	FR1 n77 Part27O	100M	QPSK	135	69	DFT-30	Right Cheek	0mm	Ant 7	DSI 0	656000	3840	22.20	23.50	1.349	-	-	-0.16	0.222	0.299
	FR1 n77 Part27O	100M	QPSK	135	69	DFT-30	Right Tilted	0mm	Ant 7	DSI 0	656000	3840	22.20	23.50	1.349	-	-	0.1	0.155	0.209
	FR1 n77 Part27O	100M	QPSK	135	69	DFT-30	Left Cheek	0mm	Ant 7	DSI 0	656000	3840	22.20	23.50	1.349	-	-	-0.16	0.122	0.165
	FR1 n77 Part27O	100M	QPSK	135	69	DFT-30	Left Tilted	0mm	Ant 7	DSI 0	656000	3840	22.20	23.50	1.349	-	-	-0.04	0.091	0.123
	FR1 n78 Part27Q	100M	QPSK	1	137	DFT-30	Right Cheek	0mm	Ant 7	DSI 0	633332	3499.98	22.59	24.00	1.384	-	-	0	0.585	0.809
	FR1 n78 Part27Q	100M	QPSK	1	137	DFT-30	Right Tilted	0mm	Ant 7	DSI 0	633332	3499.98	22.59	24.00	1.384	-	-	0.09	0.146	0.202
	FR1 n78 Part27Q	100M	QPSK	1	137	DFT-30	Left Cheek	0mm	Ant 7	DSI 0	633332	3499.98	22.59	24.00	1.384	-	-	-0.14	0.384	0.531
	FR1 n78 Part27Q	100M	QPSK	1	137	DFT-30	Left Tilted	0mm	Ant 7	DSI 0	633332	3499.98	22.59	24.00	1.384	-	-	0.18	0.089	0.123
	FR1 n78 Part27Q	100M	QPSK	135	69	DFT-30	Right Cheek	0mm	Ant 7	DSI 0	633332	3499.98	22.52	24.00	1.406	-	-	-0.13	0.553	0.778
	FR1 n78 Part27Q	100M	QPSK	135	69	DFT-30	Right Tilted	0mm	Ant 7	DSI 0	633332	3499.98	22.52	24.00	1.406	-	-	-0.19	0.126	0.177
	FR1 n78 Part27Q	100M	QPSK	135	69	DFT-30	Left Cheek	0mm	Ant 7	DSI 0	633332	3499.98	22.52	24.00	1.406	-	-	-0.15	0.346	0.486
	FR1 n78 Part27Q	100M	QPSK	135	69	DFT-30	Left Tilted	0mm	Ant 7	DSI 0	633332	3499.98	22.52	24.00	1.406	-	-	0.16	0.080	0.112
	FR1 n78 Part27Q	100M	QPSK	270	0	DFT-30	Right Cheek	0mm	Ant 7	DSI 0	633332	3499.98	22.48	24.00	1.419	-	-	0.04	0.538	0.763
	FR1 n78 Part27O	100M	QPSK	1	137	DFT-30	Right Cheek	0mm	Ant 7	DSI 0	650000	3750	23.04	24.50	1.400	-	-	0.02	0.634	0.887
	FR1 n78 Part27O	100M	QPSK	1	137	DFT-30	Right Tilted	0mm	Ant 7	DSI 0	650000	3750	23.04	24.50	1.400	-	-	-0.1	0.093	0.130
	FR1 n78 Part27O	100M	QPSK	1	137	DFT-30	Left Cheek	0mm	Ant 7	DSI 0	650000	3750	23.04	24.50	1.400	-	-	0.17	0.229	0.321
	FR1 n78 Part27O	100M	QPSK	1	137	DFT-30	Left Tilted	0mm	Ant 7	DSI 0	650000	3750	23.04	24.50	1.400	-	-	-0.11	0.044	0.062
19	FR1 n78 Part27O	100M	QPSK	1	137	DFT-30	Right Cheek	0mm	Ant 7	DSI 0	650000	3750	26.11	27.50	1.377	50	1.000	0.06	0.646	0.890
	FR1 n78 Part27O	100M	QPSK	135	69	DFT-30	Right Cheek	0mm	Ant 7	DSI 0	650000	3750	22.96	24.50	1.426	-	-	0.02	0.558	0.795
	FR1 n78 Part27O	100M	QPSK	135	69	DFT-30	Right Tilted	0mm	Ant 7	DSI 0	650000	3750	22.96	24.50	1.426	-	-	-0.02	0.051	0.073



FCC SAR Test Report

Report No. : FA350505

FR1 n78 Part270	100M	QPSK	135	69	DFT-30	Left Cheek	0mm	Ant 7	DSI 0	650000	3750	22.96	24.50	1.426	-	-	-0.17	0.139	0.198
FR1 n78 Part270	100M	QPSK	135	69	DFT-30	Left Tilted	0mm	Ant 7	DSI 0	650000	3750	22.96	24.50	1.426	-	-	0	0.041	0.058
FR1 n78 Part270	100M	QPSK	270	0	DFT-30	Right Cheek	0mm	Ant 7	DSI 0	650000	3750	22.95	24.50	1.429	-	-	0.08	0.585	0.836

Plot No.	Band	Mode	Test Position	Gap (mm)	Antenna	Power State	Ch.	Freq. (MHz)	Average Power (dBm)	Tune-Up Limit (dBm)	Tune-up Scaling Factor	Duty Cycle %	Duty Cycle Scaling Factor	Power Drift (dB)	Measured 1g SAR (W/kg)	Reported 1g SAR (W/kg)
2450MHz																
	Bluetooth	DH5 1Mbps	Right Cheek	0mm	Ant 17	Full power	0	2402	16.33	17.50	1.309	76.4	1.309	0.18	0.065	0.111
20	Bluetooth	DH5 1Mbps	Right Tilted	0mm	Ant 17	Full power	0	2402	16.33	17.50	1.309	76.4	1.309	-0.16	0.082	0.140
	Bluetooth	DH5 1Mbps	Left Cheek	0mm	Ant 17	Full power	0	2402	16.33	17.50	1.309	76.4	1.309	0.01	0.049	0.084
	Bluetooth	DH5 1Mbps	Left Tilted	0mm	Ant 17	Full power	0	2402	16.33	17.50	1.309	76.4	1.309	0.05	0.042	0.072
	WLAN2.4GHz	802.11b 1Mbps	Right Cheek	0mm	Ant 6+17	Standalone	6	2437	20.37	21.00	1.157	100	1.000	0.16	0.642	0.743
	WLAN2.4GHz	802.11b 1Mbps	Right Tilted	0mm	Ant 6+17	Standalone	6	2437	20.37	21.00	1.157	100	1.000	0.02	0.717	0.829
21	WLAN2.4GHz	802.11b 1Mbps	Left Cheek	0mm	Ant 6+17	Standalone	6	2437	20.37	21.00	1.157	100	1.000	0.15	0.794	0.918
	WLAN2.4GHz	802.11b 1Mbps	Left Tilted	0mm	Ant 6+17	Standalone	6	2437	20.37	21.00	1.157	100	1.000	0.17	0.725	0.839
	WLAN2.4GHz	802.11b 1Mbps	Right Tilted	0mm	Ant 6+17	Standalone	1	2412	19.98	21.00	1.265	100	1.000	0.07	0.628	0.795
	WLAN2.4GHz	802.11b 1Mbps	Left Cheek	0mm	Ant 6+17	Standalone	1	2412	19.98	21.00	1.265	100	1.000	0.15	0.673	0.852
	WLAN2.4GHz	802.11b 1Mbps	Left Tilted	0mm	Ant 6+17	Standalone	1	2412	19.98	21.00	1.265	100	1.000	0.02	0.644	0.815
	WLAN2.4GHz	802.11b 1Mbps	Right Cheek	0mm	Ant 6+17	Simultaneous	6	2437	16.53	17.50	1.250	100	1.000	-0.03	0.268	0.335
	WLAN2.4GHz	802.11b 1Mbps	Right Tilted	0mm	Ant 6+17	Simultaneous	6	2437	16.53	17.50	1.250	100	1.000	-0.15	0.289	0.361
	WLAN2.4GHz	802.11b 1Mbps	Left Cheek	0mm	Ant 6+17	Simultaneous	6	2437	16.53	17.50	1.250	100	1.000	-0.07	0.331	0.414
	WLAN2.4GHz	802.11b 1Mbps	Left Tilted	0mm	Ant 6+17	Simultaneous	6	2437	16.53	17.50	1.250	100	1.000	-0.11	0.302	0.378
	WLAN2.4GHz	802.11b 1Mbps	Right Cheek	0mm	Ant 17	Standalone DBS	6	2437	17.61	18.00	1.094	100	1.000	0.07	0.382	0.418
	WLAN2.4GHz	802.11b 1Mbps	Right Tilted	0mm	Ant 17	Standalone DBS	6	2437	17.61	18.00	1.094	100	1.000	0.03	0.453	0.496
	WLAN2.4GHz	802.11b 1Mbps	Left Cheek	0mm	Ant 17	Standalone DBS	6	2437	17.61	18.00	1.094	100	1.000	0.08	0.340	0.372
	WLAN2.4GHz	802.11b 1Mbps	Left Tilted	0mm	Ant 17	Standalone DBS	6	2437	17.61	18.00	1.094	100	1.000	0	0.424	0.464
	WLAN2.4GHz	802.11b 1Mbps	Right Cheek	0mm	Ant 17	Simultaneous DBS	1	2412	14.59	15.00	1.099	100	1.000	-0.18	0.191	0.210
	WLAN2.4GHz	802.11b 1Mbps	Right Tilted	0mm	Ant 17	Simultaneous DBS	1	2412	14.59	15.00	1.099	100	1.000	-0.03	0.227	0.249
	WLAN2.4GHz	802.11b 1Mbps	Left Cheek	0mm	Ant 17	Simultaneous DBS	1	2412	14.59	15.00	1.099	100	1.000	0.14	0.170	0.187
	WLAN2.4GHz	802.11b 1Mbps	Left Tilted	0mm	Ant 17	Simultaneous DBS	1	2412	14.59	15.00	1.099	100	1.000	-0.15	0.213	0.234
5000MHz																
	WLAN5.3GHz	802.11ac-VHT80 MCS0	Right Cheek	0mm	Ant 5+18	Standalone	58	5290	16.95	18.50	1.429	88.14	1.135	0	0.286	0.464
	WLAN5.3GHz	802.11ac-VHT80 MCS0	Right Tilted	0mm	Ant 5+18	Standalone	58	5290	16.95	18.50	1.429	88.14	1.135	0.03	0.343	0.556
	WLAN5.3GHz	802.11ac-VHT80 MCS0	Left Cheek	0mm	Ant 5+18	Standalone	58	5290	16.95	18.50	1.429	88.14	1.135	0.06	0.486	0.788
22	WLAN5.3GHz	802.11ac-VHT80 MCS0	Left Tilted	0mm	Ant 5+18	Standalone	58	5290	16.95	18.50	1.429	88.14	1.135	-0.03	0.640	1.038
	WLAN5.3GHz	802.11ac-VHT80 MCS0	Right Cheek	0mm	Ant 5+18	Simultaneous	58	5290	13.44	15.00	1.431	88.14	1.135	0.04	0.119	0.193
	WLAN5.3GHz	802.11ac-VHT80 MCS0	Right Tilted	0mm	Ant 5+18	Simultaneous	58	5290	13.44	15.00	1.431	88.14	1.135	-0.13	0.143	0.232
	WLAN5.3GHz	802.11ac-VHT80 MCS0	Left Cheek	0mm	Ant 5+18	Simultaneous	58	5290	13.44	15.00	1.431	88.14	1.135	0.13	0.202	0.328
	WLAN5.3GHz	802.11ac-VHT80 MCS0	Left Tilted	0mm	Ant 5+18	Simultaneous	58	5290	13.44	15.00	1.431	88.14	1.135	0.12	0.267	0.434
	WLAN5.3GHz	802.11n-HT40 MCS0	Right Cheek	0mm	Ant 18	Standalone	54	5270	16.02	17.50	1.406	93.68	1.067	0.06	0.134	0.201
	WLAN5.3GHz	802.11n-HT40 MCS0	Right Tilted	0mm	Ant 18	Standalone	54	5270	16.02	17.50	1.406	93.68	1.067	-0.14	0.068	0.102
	WLAN5.3GHz	802.11n-HT40 MCS0	Left Cheek	0mm	Ant 18	Standalone	54	5270	16.02	17.50	1.406	93.68	1.067	-0.01	0.636	0.954
	WLAN5.3GHz	802.11n-HT40 MCS0	Left Tilted	0mm	Ant 18	Standalone	54	5270	16.02	17.50	1.406	93.68	1.067	0.08	0.179	0.269
	WLAN5.3GHz	802.11n-HT40 MCS0	Left Cheek	0mm	Ant 18	Standalone	62	5310	15.10	16.50	1.379	93.68	1.067	0.1	0.428	0.630
	WLAN5.3GHz	802.11ac-VHT80 MCS0	Right Cheek	0mm	Ant 18	Simultaneous DBS	58	5290	11.05	12.50	1.396	88.14	1.135	0.18	0.041	0.065
	WLAN5.3GHz	802.11ac-VHT80 MCS0	Right Tilted	0mm	Ant 18	Simultaneous DBS	58	5290	11.05	12.50	1.396	88.14	1.135	0.19	0.018	0.029
	WLAN5.3GHz	802.11ac-VHT80 MCS0	Left Cheek	0mm	Ant 18	Simultaneous DBS	58	5290	11.05	12.50	1.396	88.14	1.135	0.09	0.146	0.231
	WLAN5.3GHz	802.11ac-VHT80 MCS0	Left Tilted	0mm	Ant 18	Simultaneous DBS	58	5290	11.05	12.50	1.396	88.14	1.135	0.04	0.118	0.187
	WLAN5.5GHz	802.11ac-VHT80 MCS0	Right Cheek	0mm	Ant 5+18	Standalone	138	5690	16.00	17.50	1.413	88.14	1.135	0.02	0.206	0.330
	WLAN5.5GHz	802.11ac-VHT80 MCS0	Right Tilted	0mm	Ant 5+18	Standalone	138	5690	16.00	17.50	1.413	88.14	1.135	-0.05	0.228	0.366
	WLAN5.5GHz	802.11ac-VHT80 MCS0	Left Cheek	0mm	Ant 5+18	Standalone	138	5690	16.00	17.50	1.413	88.14	1.135	0.15	0.621	0.996
23	WLAN5.5GHz	802.11ac-VHT80 MCS0	Left Tilted	0mm	Ant 5+18	Standalone	138	5690	16.00	17.50	1.413	88.14	1.135	0.18	0.630	1.010
	WLAN5.5GHz	802.11ac-VHT80 MCS0	Left Cheek	0mm	Ant 5+18	Standalone	122	5610	15.98	17.50	1.419	88.14	1.135	0.04	0.573	0.923
	WLAN5.5GHz	802.11ac-VHT80 MCS0	Left Tilted	0mm	Ant 5+18	Standalone	122	5610	15.98	17.50	1.419	88.14	1.135	0.05	0.596	0.960
	WLAN5.5GHz	802.11ac-VHT80 MCS0	Right Cheek	0mm	Ant 5+18	Simultaneous	138	5690	12.11	14.00	1.546	88.14	1.135	0.02	0.082	0.144



FCC SAR Test Report

Report No. : FA350505

	WLAN5.5GHz	802.11ac-VHT80 MCS0	Right Tilted	0mm	Ant 5+18	Simultaneous	138	5690	12.11	14.00	1.546	88.14	1.135	0.11	0.091	0.160
	WLAN5.5GHz	802.11ac-VHT80 MCS0	Left Cheek	0mm	Ant 5+18	Simultaneous	138	5690	12.11	14.00	1.546	88.14	1.135	0.19	0.231	0.405
	WLAN5.5GHz	802.11ac-VHT80 MCS0	Left Tilted	0mm	Ant 5+18	Simultaneous	138	5690	12.11	14.00	1.546	88.14	1.135	-0.04	0.241	0.423
	WLAN5.5GHz	802.11ac-VHT80 MCS0	Right Cheek	0mm	Ant 18	Standalone DBS	122	5610	12.94	14.50	1.432	88.14	1.135	0.01	0.211	0.343
	WLAN5.5GHz	802.11ac-VHT80 MCS0	Right Tilted	0mm	Ant 18	Standalone DBS	122	5610	12.94	14.50	1.432	88.14	1.135	-0.13	0.147	0.239
	WLAN5.5GHz	802.11ac-VHT80 MCS0	Left Cheek	0mm	Ant 18	Standalone DBS	122	5610	12.94	14.50	1.432	88.14	1.135	0.18	0.589	0.957
	WLAN5.5GHz	802.11ac-VHT80 MCS0	Left Tilted	0mm	Ant 18	Standalone DBS	122	5610	12.94	14.50	1.432	88.14	1.135	-0.03	0.482	0.784
	WLAN5.5GHz	802.11ac-VHT80 MCS0	Left Cheek	0mm	Ant 18	Standalone DBS	138	5690	12.93	14.50	1.436	88.14	1.135	0.03	0.485	0.791
	WLAN5.5GHz	802.11ac-VHT80 MCS0	Right Cheek	0mm	Ant 18	Simultaneous DBS	122	5610	7.13	9.00	1.538	88.14	1.135	-0.04	0.053	0.093
	WLAN5.5GHz	802.11ac-VHT80 MCS0	Right Tilted	0mm	Ant 18	Simultaneous DBS	122	5610	7.13	9.00	1.538	88.14	1.135	0.17	0.037	0.065
	WLAN5.5GHz	802.11ac-VHT80 MCS0	Left Cheek	0mm	Ant 18	Simultaneous DBS	122	5610	7.13	9.00	1.538	88.14	1.135	0	0.148	0.258
	WLAN5.5GHz	802.11ac-VHT80 MCS0	Left Tilted	0mm	Ant 18	Simultaneous DBS	122	5610	7.13	9.00	1.538	88.14	1.135	-0.18	0.121	0.211
	WLAN5.8GHz	802.11ac-VHT80 MCS0	Right Cheek	0mm	Ant 5+18	Standalone	155	5775	16.98	18.00	1.265	88.14	1.135	-0.14	0.276	0.396
	WLAN5.8GHz	802.11ac-VHT80 MCS0	Right Tilted	0mm	Ant 5+18	Standalone	155	5775	16.98	18.00	1.265	88.14	1.135	-0.05	0.295	0.423
	WLAN5.8GHz	802.11ac-VHT80 MCS0	Left Cheek	0mm	Ant 5+18	Standalone	155	5775	16.98	18.00	1.265	88.14	1.135	0.11	0.685	0.983
24	WLAN5.8GHz	802.11ac-VHT80 MCS0	Left Tilted	0mm	Ant 5+18	Standalone	155	5775	16.98	18.00	1.265	88.14	1.135	-0.07	0.742	1.065
	WLAN5.8GHz	802.11ac-VHT80 MCS0	Right Cheek	0mm	Ant 5+18	Simultaneous	155	5775	13.01	14.00	1.257	88.14	1.135	0.12	0.110	0.157
	WLAN5.8GHz	802.11ac-VHT80 MCS0	Right Tilted	0mm	Ant 5+18	Simultaneous	155	5775	13.01	14.00	1.257	88.14	1.135	0.1	0.117	0.167
	WLAN5.8GHz	802.11ac-VHT80 MCS0	Left Cheek	0mm	Ant 5+18	Simultaneous	155	5775	13.01	14.00	1.257	88.14	1.135	-0.04	0.258	0.368
	WLAN5.8GHz	802.11ac-VHT80 MCS0	Left Tilted	0mm	Ant 5+18	Simultaneous	155	5775	13.01	14.00	1.257	88.14	1.135	-0.07	0.295	0.421
	WLAN5.8GHz	802.11ac-VHT80 MCS0	Right Cheek	0mm	Ant 18	Standalone DBS	155	5775	13.57	15.00	1.390	88.14	1.135	0.07	0.151	0.238
	WLAN5.8GHz	802.11ac-VHT80 MCS0	Right Tilted	0mm	Ant 18	Standalone DBS	155	5775	13.57	15.00	1.390	88.14	1.135	-0.17	0.123	0.194
	WLAN5.8GHz	802.11ac-VHT80 MCS0	Left Cheek	0mm	Ant 18	Standalone DBS	155	5775	13.57	15.00	1.390	88.14	1.135	-0.1	0.617	0.973
	WLAN5.8GHz	802.11ac-VHT80 MCS0	Left Tilted	0mm	Ant 18	Standalone DBS	155	5775	13.57	15.00	1.390	88.14	1.135	-0.19	0.506	0.798
	WLAN5.8GHz	802.11ac-VHT80 MCS0	Right Cheek	0mm	Ant 18	Simultaneous DBS	155	5775	8.08	9.50	1.387	88.14	1.135	0.09	0.038	0.060
	WLAN5.8GHz	802.11ac-VHT80 MCS0	Right Tilted	0mm	Ant 18	Simultaneous DBS	155	5775	8.08	9.50	1.387	88.14	1.135	-0.09	0.031	0.049
	WLAN5.8GHz	802.11ac-VHT80 MCS0	Left Cheek	0mm	Ant 18	Simultaneous DBS	155	5775	8.08	9.50	1.387	88.14	1.135	0.03	0.155	0.244
	WLAN5.8GHz	802.11ac-VHT80 MCS0	Left Tilted	0mm	Ant 18	Simultaneous DBS	155	5775	8.08	9.50	1.387	88.14	1.135	0.01	0.127	0.200

<Inter CA&ENDC>

Plot No.	Band	BW (MHz)	Modulation	RB Size	RB offset	Mode	Test Position	Gap (mm)	Antenna	Power State	Ch.	Freq. (MHz)	Average Power (dBm)	Tune-Up Limit (dBm)	Tune-up Scaling Factor	Duty Cycle %	Duty Cycle Scaling Factor	Power Drift (dB)	Measured 1g SAR (W/kg)	Reported 1g SAR (W/kg)
750MHz																				
	LTE Band 12	10M	QPSK	1	0	-	Right Cheek	0mm	Ant 0	DSI 0	23095	707.5	24.67	25.50	1.211	-	-	0.08	0.085	0.103
	LTE Band 12	10M	QPSK	1	0	-	Right Tilted	0mm	Ant 0	DSI 0	23095	707.5	24.67	25.50	1.211	-	-	-0.13	0.067	0.081
	LTE Band 12	10M	QPSK	1	0	-	Left Cheek	0mm	Ant 0	DSI 0	23095	707.5	24.67	25.50	1.211	-	-	-0.07	0.092	0.111
	LTE Band 12	10M	QPSK	1	0	-	Left Tilted	0mm	Ant 0	DSI 0	23095	707.5	24.67	25.50	1.211	-	-	0.07	0.064	0.077
	LTE Band 12	10M	QPSK	25	0	-	Right Cheek	0mm	Ant 0	DSI 0	23095	707.5	23.61	24.50	1.227	-	-	-0.11	0.067	0.082
	LTE Band 12	10M	QPSK	25	0	-	Right Tilted	0mm	Ant 0	DSI 0	23095	707.5	23.61	24.50	1.227	-	-	-0.04	0.053	0.065
	LTE Band 12	10M	QPSK	25	0	-	Left Cheek	0mm	Ant 0	DSI 0	23095	707.5	23.61	24.50	1.227	-	-	0.05	0.073	0.090
	LTE Band 12	10M	QPSK	25	0	-	Left Tilted	0mm	Ant 0	DSI 0	23095	707.5	23.61	24.50	1.227	-	-	-0.07	0.050	0.061
	LTE Band 12	10M	QPSK	1	0	-	Right Cheek	0mm	Ant 1	DSI 0	23095	707.5	22.35	24.00	1.462	-	-	0.17	0.353	0.516
	LTE Band 12	10M	QPSK	1	0	-	Right Tilted	0mm	Ant 1	DSI 0	23095	707.5	22.35	24.00	1.462	-	-	0.03	0.245	0.358
	LTE Band 12	10M	QPSK	1	0	-	Left Cheek	0mm	Ant 1	DSI 0	23095	707.5	22.35	24.00	1.462	-	-	0.11	0.145	0.212
	LTE Band 12	10M	QPSK	1	0	-	Left Tilted	0mm	Ant 1	DSI 0	23095	707.5	22.35	24.00	1.462	-	-	0.01	0.137	0.200
	LTE Band 12	10M	QPSK	25	0	-	Right Cheek	0mm	Ant 1	DSI 0	23095	707.5	22.31	24.00	1.476	-	-	0.16	0.274	0.404
	LTE Band 12	10M	QPSK	25	0	-	Right Tilted	0mm	Ant 1	DSI 0	23095	707.5	22.31	24.00	1.476	-	-	-0.15	0.192	0.283
	LTE Band 12	10M	QPSK	25	0	-	Left Cheek	0mm	Ant 1	DSI 0	23095	707.5	22.31	24.00	1.476	-	-	0.14	0.121	0.179
	LTE Band 12	10M	QPSK	25	0	-	Left Tilted	0mm	Ant 1	DSI 0	23095	707.5	22.31	24.00	1.476	-	-	0.11	0.108	0.159
835MHz																				
	FR1 n5_Other PA	20M	QPSK	1	1	DFT-15	Right Cheek	0mm	Ant 0	DSI 0	167300	836.5	24.39	25.50	1.291	-	-	-0.17	0.182	0.235
	FR1 n5_Other PA	20M	QPSK	1	1	DFT-15	Right Tilted	0mm	Ant 0	DSI 0	167300	836.5	24.39	25.50	1.291	-	-	0	0.118	0.152
	FR1 n5_Other PA	20M	QPSK	1	1	DFT-15	Left Cheek	0mm	Ant 0	DSI 0	167300	836.5	24.39	25.50	1.291	-	-	-0.04	0.204	0.263
	FR1 n5_Other PA	20M	QPSK	1	1	DFT-15	Left Tilted	0mm	Ant 0	DSI 0	167300	836.5	24.39	25.50	1.291	-	-	0.14	0.104	0.134
	FR1 n5_Other PA	20M	QPSK	50	28	DFT-15	Right Cheek	0mm	Ant 0	DSI 0	167300	836.5	24.31	25.50	1.315	-	-	-0.06	0.184	0.242



FCC SAR Test Report

Report No. : FA350505

Table with columns for test parameters (e.g., FR1 n5_Other PA, 20M, QPSK, 50, 28, DFT-15, Right Tilted, 0mm, Ant 0, DSI 0, 167300, 836.5, 24.31, 25.50, 1.315, -0.18, 0.119, 0.157) and rows for various frequency bands and antenna configurations.

1750MHz

Table with columns for test parameters (e.g., LTE Band 4_Other PA Inter CA, 20M, QPSK, 1, 0, -, Right Cheek, 0mm, Ant 1, DSI 0, 20175, 1732.5, 14.53, 15.50, 1.250, 0.01, 0.433, 0.541) and rows for various antenna configurations.



FCC SAR Test Report

Report No. : FA350505

LTE Band 4_Other PA Inter CA	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 4	DSI 0	20175	1732.5	22.38	23.00	1.153	-	-	-0.1	0.023	0.027
LTE Band 4_Other PA Inter CA	20M	QPSK	50	0	-	Right Tilted	0mm	Ant 4	DSI 0	20175	1732.5	22.38	23.00	1.153	-	-	-0.14	0.018	0.021
LTE Band 4_Other PA Inter CA	20M	QPSK	50	0	-	Left Cheek	0mm	Ant 4	DSI 0	20175	1732.5	22.38	23.00	1.153	-	-	0.05	0.048	0.055
LTE Band 4_Other PA Inter CA	20M	QPSK	50	0	-	Left Tilted	0mm	Ant 4	DSI 0	20175	1732.5	22.38	23.00	1.153	-	-	0.16	0.041	0.047
LTE Band 66_Other PA	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 1	DSI 0	132322	1745	14.47	15.50	1.268	-	-	-0.18	0.441	0.559
LTE Band 66_Main PA	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 1	DSI 0	132322	1745	12.62	14.00	1.374	-	-	-0.13	0.396	0.544
LTE Band 66_Other PA	20M	QPSK	1	0	-	Right Tilted	0mm	Ant 1	DSI 0	132322	1745	14.47	15.50	1.268	-	-	-0.07	0.326	0.413
LTE Band 66_Other PA	20M	QPSK	1	0	-	Left Cheek	0mm	Ant 1	DSI 0	132322	1745	14.47	15.50	1.268	-	-	0.08	0.249	0.316
LTE Band 66_Other PA	20M	QPSK	1	0	-	Left Tilted	0mm	Ant 1	DSI 0	132322	1745	14.47	15.50	1.268	-	-	-0.02	0.288	0.365
LTE Band 66_Other PA	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 1	DSI 0	132322	1745	14.39	15.50	1.291	-	-	-0.16	0.372	0.480
LTE Band 66_Other PA	20M	QPSK	50	0	-	Right Tilted	0mm	Ant 1	DSI 0	132322	1745	14.39	15.50	1.291	-	-	0.1	0.258	0.333
LTE Band 66_Other PA	20M	QPSK	50	0	-	Left Cheek	0mm	Ant 1	DSI 0	132322	1745	14.39	15.50	1.291	-	-	0.09	0.198	0.256
LTE Band 66_Other PA	20M	QPSK	50	0	-	Left Tilted	0mm	Ant 1	DSI 0	132322	1745	14.39	15.50	1.291	-	-	-0.19	0.229	0.296
LTE Band 66_Other PA	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 3	DSI 0	132322	1745	18.54	20.00	1.400	-	-	0.05	0.388	0.543
LTE Band 66_Main PA	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 3	DSI 0	132322	1745	16.57	18.00	1.390	-	-	0.07	0.385	0.535
LTE Band 66_Other PA	20M	QPSK	1	0	-	Right Tilted	0mm	Ant 3	DSI 0	132322	1745	18.54	20.00	1.400	-	-	-0.09	0.046	0.064
LTE Band 66_Other PA	20M	QPSK	1	0	-	Left Cheek	0mm	Ant 3	DSI 0	132322	1745	18.54	20.00	1.400	-	-	0.02	0.163	0.228
LTE Band 66_Other PA	20M	QPSK	1	0	-	Left Tilted	0mm	Ant 3	DSI 0	132322	1745	18.54	20.00	1.400	-	-	0.12	0.027	0.038
LTE Band 66_Other PA	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 3	DSI 0	132322	1745	18.50	20.00	1.413	-	-	0.07	0.340	0.480
LTE Band 66_Other PA	20M	QPSK	50	0	-	Right Tilted	0mm	Ant 3	DSI 0	132322	1745	18.50	20.00	1.413	-	-	-0.09	0.039	0.055
LTE Band 66_Other PA	20M	QPSK	50	0	-	Left Cheek	0mm	Ant 3	DSI 0	132322	1745	18.50	20.00	1.413	-	-	-0.13	0.136	0.192
LTE Band 66_Other PA	20M	QPSK	50	0	-	Left Tilted	0mm	Ant 3	DSI 0	132322	1745	18.50	20.00	1.413	-	-	-0.12	0.023	0.032
LTE Band 66_Main PA	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 2	DSI 0	132322	1745	24.14	25.50	1.368	-	-	0.02	0.186	0.254
LTE Band 66_Main PA	20M	QPSK	1	0	-	Right Tilted	0mm	Ant 2	DSI 0	132322	1745	24.14	25.50	1.368	-	-	-0.05	0.072	0.098
LTE Band 66_Main PA	20M	QPSK	1	0	-	Left Cheek	0mm	Ant 2	DSI 0	132322	1745	24.14	25.50	1.368	-	-	0.06	0.154	0.211
LTE Band 66_Main PA	20M	QPSK	1	0	-	Left Tilted	0mm	Ant 2	DSI 0	132322	1745	24.14	25.50	1.368	-	-	-0.07	0.119	0.163
LTE Band 66_Main PA	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 2	DSI 0	132322	1745	23.12	24.50	1.374	-	-	-0.16	0.142	0.195
LTE Band 66_Main PA	20M	QPSK	50	0	-	Right Tilted	0mm	Ant 2	DSI 0	132322	1745	23.12	24.50	1.374	-	-	0.07	0.058	0.080
LTE Band 66_Main PA	20M	QPSK	50	0	-	Left Cheek	0mm	Ant 2	DSI 0	132322	1745	23.12	24.50	1.374	-	-	-0.13	0.125	0.172
LTE Band 66_Main PA	20M	QPSK	50	0	-	Left Tilted	0mm	Ant 2	DSI 0	132322	1745	23.12	24.50	1.374	-	-	0.18	0.092	0.126
LTE Band 66_Main PA	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 4	DSI 0	132322	1745	23.80	24.50	1.175	-	-	0.07	0.034	0.040
LTE Band 66_Main PA	20M	QPSK	1	0	-	Right Tilted	0mm	Ant 4	DSI 0	132322	1745	23.80	24.50	1.175	-	-	0.04	0.027	0.032
LTE Band 66_Main PA	20M	QPSK	1	0	-	Left Cheek	0mm	Ant 4	DSI 0	132322	1745	23.80	24.50	1.175	-	-	-0.12	0.053	0.062
LTE Band 66_Main PA	20M	QPSK	1	0	-	Left Tilted	0mm	Ant 4	DSI 0	132322	1745	23.80	24.50	1.175	-	-	-0.08	0.045	0.053
LTE Band 66_Main PA	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 4	DSI 0	132322	1745	22.88	23.50	1.153	-	-	-0.16	0.030	0.035
LTE Band 66_Main PA	20M	QPSK	50	0	-	Right Tilted	0mm	Ant 4	DSI 0	132322	1745	22.88	23.50	1.153	-	-	-0.13	0.023	0.027
LTE Band 66_Main PA	20M	QPSK	50	0	-	Left Cheek	0mm	Ant 4	DSI 0	132322	1745	22.88	23.50	1.153	-	-	0.05	0.042	0.048
LTE Band 66_Main PA	20M	QPSK	50	0	-	Left Tilted	0mm	Ant 4	DSI 0	132322	1745	22.88	23.50	1.153	-	-	-0.08	0.037	0.043
FR1 n66_Other PA	40M	QPSK	1	1	DFT-15	Right Cheek	0mm	Ant 1	DSI 0	349000	1745	14.50	15.50	1.259	-	-	-0.08	0.423	0.533
FR1 n66_Other PA	40M	QPSK	1	1	DFT-15	Right Tilted	0mm	Ant 1	DSI 0	349000	1745	14.50	15.50	1.259	-	-	0.15	0.227	0.286
FR1 n66_Other PA	40M	QPSK	1	1	DFT-15	Left Cheek	0mm	Ant 1	DSI 0	349000	1745	14.50	15.50	1.259	-	-	0.14	0.177	0.223
FR1 n66_Other PA	40M	QPSK	1	1	DFT-15	Left Tilted	0mm	Ant 1	DSI 0	349000	1745	14.50	15.50	1.259	-	-	-0.17	0.192	0.242
FR1 n66_Other PA	40M	QPSK	108	54	DFT-15	Right Cheek	0mm	Ant 1	DSI 0	349000	1745	14.47	15.50	1.268	-	-	0.16	0.432	0.548
FR1 n66_Main PA	40M	QPSK	108	54	DFT-15	Right Cheek	0mm	Ant 1	DSI 0	349000	1745	12.48	14.00	1.419	-	-	-0.1	0.378	0.536
FR1 n66_Other PA	40M	QPSK	108	54	DFT-15	Right Tilted	0mm	Ant 1	DSI 0	349000	1745	14.47	15.50	1.268	-	-	-0.02	0.222	0.281
FR1 n66_Other PA	40M	QPSK	108	54	DFT-15	Left Cheek	0mm	Ant 1	DSI 0	349000	1745	14.47	15.50	1.268	-	-	-0.13	0.166	0.210
FR1 n66_Other PA	40M	QPSK	108	54	DFT-15	Left Tilted	0mm	Ant 1	DSI 0	349000	1745	14.47	15.50	1.268	-	-	0.05	0.190	0.241
FR1 n66_Main PA	40M	QPSK	1	1	DFT-15	Right Cheek	0mm	Ant 2	DSI 0	349000	1745	23.65	25.00	1.365	-	-	-0.15	0.190	0.259
FR1 n66_Other PA	40M	QPSK	1	1	DFT-15	Right Cheek	0mm	Ant 2	DSI 0	349000	1745	23.65	24.50	1.216	-	-	-0.15	0.178	0.216
FR1 n66_Main PA	40M	QPSK	1	1	DFT-15	Right Tilted	0mm	Ant 2	DSI 0	349000	1745	23.65	25.00	1.365	-	-	0.09	0.076	0.104
FR1 n66_Main PA	40M	QPSK	1	1	DFT-15	Left Cheek	0mm	Ant 2	DSI 0	349000	1745	23.65	25.00	1.365	-	-	-0.06	0.173	0.236
FR1 n66_Main PA	40M	QPSK	1	1	DFT-15	Left Tilted	0mm	Ant 2	DSI 0	349000	1745	23.65	25.00	1.365	-	-	0.09	0.130	0.177
FR1 n66_Main PA	40M	QPSK	108	54	DFT-15	Right Cheek	0mm	Ant 2	DSI 0	349000	1745	23.51	25.00	1.409	-	-	0.15	0.181	0.255
FR1 n66_Main PA	40M	QPSK	108	54	DFT-15	Right Tilted	0mm	Ant 2	DSI 0	349000	1745	23.51	25.00	1.409	-	-	-0.18	0.070	0.099
FR1 n66_Main PA	40M	QPSK	108	54	DFT-15	Left Cheek	0mm	Ant 2	DSI 0	349000	1745	23.51	25.00	1.409	-	-	-0.01	0.166	0.234
FR1 n66_Main PA	40M	QPSK	108	54	DFT-15	Left Tilted	0mm	Ant 2	DSI 0	349000	1745	23.51	25.00	1.409	-	-	0.19	0.125	0.176



FCC SAR Test Report

Report No. : FA350505

FR1 n66_Other PA	40M	QPSK	1	1	DFT-15	Right Cheek	0mm	Ant 3	DSI 0	349000	1745	17.87	19.50	1.455	-	-	0.11	0.352	0.512
FR1 n66_Other PA	40M	QPSK	1	1	DFT-15	Right Tilted	0mm	Ant 3	DSI 0	349000	1745	17.87	19.50	1.455	-	-	-0.1	0.048	0.070
FR1 n66_Other PA	40M	QPSK	1	1	DFT-15	Left Cheek	0mm	Ant 3	DSI 0	349000	1745	17.87	19.50	1.455	-	-	-0.04	0.187	0.272
FR1 n66_Other PA	40M	QPSK	1	1	DFT-15	Left Tilted	0mm	Ant 3	DSI 0	349000	1745	17.87	19.50	1.455	-	-	-0.15	0.030	0.044
FR1 n66_Other PA	40M	QPSK	108	54	DFT-15	Right Cheek	0mm	Ant 3	DSI 0	349000	1745	17.84	19.50	1.466	-	-	0.06	0.371	0.544
FR1 n66_Main PA	40M	QPSK	108	54	DFT-15	Right Cheek	0mm	Ant 3	DSI 0	349000	1745	15.72	17.50	1.507	-	-	-0.09	0.360	0.542
FR1 n66_Other PA	40M	QPSK	108	54	DFT-15	Right Tilted	0mm	Ant 3	DSI 0	349000	1745	17.84	19.50	1.466	-	-	0.17	0.061	0.089
FR1 n66_Other PA	40M	QPSK	108	54	DFT-15	Left Cheek	0mm	Ant 3	DSI 0	349000	1745	17.84	19.50	1.466	-	-	0	0.238	0.349
FR1 n66_Other PA	40M	QPSK	108	54	DFT-15	Left Tilted	0mm	Ant 3	DSI 0	349000	1745	17.84	19.50	1.466	-	-	-0.18	0.038	0.056
FR1 n66_Main PA	40M	QPSK	1	1	DFT-15	Right Cheek	0mm	Ant 4	DSI 0	349000	1745	23.43	24.50	1.279	-	-	0.16	0.035	0.045
FR1 n66_Main PA	40M	QPSK	1	1	DFT-15	Right Tilted	0mm	Ant 4	DSI 0	349000	1745	23.43	24.50	1.279	-	-	0.03	0.033	0.042
FR1 n66_Main PA	40M	QPSK	1	1	DFT-15	Left Cheek	0mm	Ant 4	DSI 0	349000	1745	23.43	24.50	1.279	-	-	-0.06	0.061	0.078
FR1 n66_Main PA	40M	QPSK	1	1	DFT-15	Left Tilted	0mm	Ant 4	DSI 0	349000	1745	23.43	24.50	1.279	-	-	-0.04	0.050	0.064
FR1 n66_Main PA	40M	QPSK	108	54	DFT-15	Right Cheek	0mm	Ant 4	DSI 0	349000	1745	23.38	24.50	1.294	-	-	-0.04	0.040	0.052
FR1 n66_Main PA	40M	QPSK	108	54	DFT-15	Right Tilted	0mm	Ant 4	DSI 0	349000	1745	23.38	24.50	1.294	-	-	0.15	0.037	0.048
FR1 n66_Main PA	40M	QPSK	108	54	DFT-15	Left Cheek	0mm	Ant 4	DSI 0	349000	1745	23.38	24.50	1.294	-	-	-0.19	0.068	0.088
FR1 n66_Other PA	40M	QPSK	108	54	DFT-15	Left Cheek	0mm	Ant 4	DSI 0	349000	1745	23.32	24.50	1.312	-	-	-0.19	0.056	0.073
FR1 n66_Main PA	40M	QPSK	108	54	DFT-15	Left Tilted	0mm	Ant 4	DSI 0	349000	1745	23.38	24.50	1.294	-	-	0.02	0.055	0.071

1900MHz

LTE Band 2_Main PA	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 2	DSI 0	18900	1880	23.96	25.00	1.271	-	-	-0.18	0.178	0.226
LTE Band 2_Main PA	20M	QPSK	1	0	-	Right Tilted	0mm	Ant 2	DSI 0	18900	1880	23.96	25.00	1.271	-	-	-0.05	0.100	0.127
LTE Band 2_Main PA	20M	QPSK	1	0	-	Left Cheek	0mm	Ant 2	DSI 0	18900	1880	23.96	25.00	1.271	-	-	-0.02	0.183	0.233
LTE Band 2_Main PA	20M	QPSK	1	0	-	Left Tilted	0mm	Ant 2	DSI 0	18900	1880	23.96	25.00	1.271	-	-	-0.03	0.139	0.177
LTE Band 2_Main PA	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 2	DSI 0	18900	1880	22.94	24.00	1.276	-	-	-0.18	0.137	0.175
LTE Band 2_Main PA	20M	QPSK	50	0	-	Right Tilted	0mm	Ant 2	DSI 0	18900	1880	22.94	24.00	1.276	-	-	-0.12	0.079	0.101
LTE Band 2_Main PA	20M	QPSK	50	0	-	Left Cheek	0mm	Ant 2	DSI 0	18900	1880	22.94	24.00	1.276	-	-	0.18	0.147	0.188
LTE Band 2_Main PA	20M	QPSK	50	0	-	Left Tilted	0mm	Ant 2	DSI 0	18900	1880	22.94	24.00	1.276	-	-	0.05	0.108	0.138
LTE Band 2_Main PA	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 4	DSI 0	18900	1880	19.02	20.00	1.253	-	-	-0.11	0.358	0.449
LTE Band 2_Main PA	20M	QPSK	1	0	-	Right Tilted	0mm	Ant 4	DSI 0	18900	1880	19.02	20.00	1.253	-	-	0.17	0.071	0.089
LTE Band 2_Main PA	20M	QPSK	1	0	-	Left Cheek	0mm	Ant 4	DSI 0	18900	1880	19.02	20.00	1.253	-	-	0.04	0.435	0.545
LTE Band 2_Main PA	20M	QPSK	1	0	-	Left Tilted	0mm	Ant 4	DSI 0	18900	1880	19.02	20.00	1.253	-	-	-0.11	0.118	0.148
LTE Band 2_Main PA	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 4	DSI 0	18900	1880	18.95	20.00	1.274	-	-	0.05	0.342	0.436
LTE Band 2_Main PA	20M	QPSK	50	0	-	Right Tilted	0mm	Ant 4	DSI 0	18900	1880	18.95	20.00	1.274	-	-	0.04	0.069	0.088
LTE Band 2_Main PA	20M	QPSK	50	0	-	Left Cheek	0mm	Ant 4	DSI 0	18900	1880	18.95	20.00	1.274	-	-	0.02	0.423	0.539
LTE Band 2_Main PA	20M	QPSK	50	0	-	Left Tilted	0mm	Ant 4	DSI 0	18900	1880	18.95	20.00	1.274	-	-	-0.19	0.114	0.145

2600MHz

LTE Band 7_Main PA	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 1	DSI 0	21100	2535	14.85	16.00	1.303	-	-	0.08	0.421	0.549
LTE Band 7_Main PA	20M	QPSK	1	0	-	Right Tilted	0mm	Ant 1	DSI 0	21100	2535	14.85	16.00	1.303	-	-	0.06	0.372	0.485
LTE Band 7_Main PA	20M	QPSK	1	0	-	Left Cheek	0mm	Ant 1	DSI 0	21100	2535	14.85	16.00	1.303	-	-	-0.18	0.196	0.255
LTE Band 7_Main PA	20M	QPSK	1	0	-	Left Tilted	0mm	Ant 1	DSI 0	21100	2535	14.85	16.00	1.303	-	-	0.04	0.173	0.225
LTE Band 7_Main PA	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 1	DSI 0	21100	2535	14.80	16.00	1.318	-	-	0.11	0.403	0.531
LTE Band 7_Main PA	20M	QPSK	50	0	-	Right Tilted	0mm	Ant 1	DSI 0	21100	2535	14.80	16.00	1.318	-	-	-0.09	0.355	0.468
LTE Band 7_Main PA	20M	QPSK	50	0	-	Left Cheek	0mm	Ant 1	DSI 0	21100	2535	14.80	16.00	1.318	-	-	0.06	0.187	0.247
LTE Band 7_Main PA	20M	QPSK	50	0	-	Left Tilted	0mm	Ant 1	DSI 0	21100	2535	14.80	16.00	1.318	-	-	-0.13	0.165	0.218
LTE Band 7_Main PA	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 2	DSI 0	21100	2535	24.41	25.50	1.285	-	-	0.15	0.166	0.213
LTE Band 7_Main PA	20M	QPSK	1	0	-	Right Tilted	0mm	Ant 2	DSI 0	21100	2535	24.41	25.50	1.285	-	-	-0.1	0.151	0.194
LTE Band 7_Main PA	20M	QPSK	1	0	-	Left Cheek	0mm	Ant 2	DSI 0	21100	2535	24.41	25.50	1.285	-	-	0.18	0.328	0.422
LTE Band 7_Main PA	20M	QPSK	1	0	-	Left Tilted	0mm	Ant 2	DSI 0	21100	2535	24.41	25.50	1.285	-	-	-0.02	0.080	0.103
LTE Band 7_Main PA	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 2	DSI 0	21100	2535	23.44	24.50	1.276	-	-	0.16	0.148	0.189
LTE Band 7_Main PA	20M	QPSK	50	0	-	Right Tilted	0mm	Ant 2	DSI 0	21100	2535	23.44	24.50	1.276	-	-	0.08	0.135	0.172
LTE Band 7_Main PA	20M	QPSK	50	0	-	Left Cheek	0mm	Ant 2	DSI 0	21100	2535	23.44	24.50	1.276	-	-	0.12	0.292	0.373
LTE Band 7_Main PA	20M	QPSK	50	0	-	Left Tilted	0mm	Ant 2	DSI 0	21100	2535	23.44	24.50	1.276	-	-	0.03	0.061	0.078
LTE Band 7_Main PA	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 3	DSI 0	21100	2535	16.47	17.50	1.268	-	-	0.08	0.450	0.570
LTE Band 7_Main PA	20M	QPSK	1	0	-	Right Tilted	0mm	Ant 3	DSI 0	21100	2535	16.47	17.50	1.268	-	-	0.09	0.168	0.213
LTE Band 7_Main PA	20M	QPSK	1	0	-	Left Cheek	0mm	Ant 3	DSI 0	21100	2535	16.47	17.50	1.268	-	-	0.01	0.315	0.399
LTE Band 7_Main PA	20M	QPSK	1	0	-	Left Tilted	0mm	Ant 3	DSI 0	21100	2535	16.47	17.50	1.268	-	-	-0.19	0.085	0.108



FCC SAR Test Report

Report No. : FA350505

LTE Band 7_Main PA	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 3	DSI 0	21100	2535	16.38	17.50	1.294	-	-	0.06	0.432	0.559
LTE Band 7_Main PA	20M	QPSK	50	0	-	Right Tilted	0mm	Ant 3	DSI 0	21100	2535	16.38	17.50	1.294	-	-	-0.05	0.160	0.207
LTE Band 7_Main PA	20M	QPSK	50	0	-	Left Cheek	0mm	Ant 3	DSI 0	21100	2535	16.38	17.50	1.294	-	-	0.19	0.300	0.388
LTE Band 7_Main PA	20M	QPSK	50	0	-	Left Tilted	0mm	Ant 3	DSI 0	21100	2535	16.38	17.50	1.294	-	-	-0.09	0.081	0.105
LTE Band 7_Main PA	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 4	DSI 0	21100	2535	16.64	17.50	1.219	-	-	0.04	0.435	0.530
LTE Band 7_Main PA	20M	QPSK	1	0	-	Right Tilted	0mm	Ant 4	DSI 0	21100	2535	16.64	17.50	1.219	-	-	-0.18	0.081	0.099
LTE Band 7_Main PA	20M	QPSK	1	0	-	Left Cheek	0mm	Ant 4	DSI 0	21100	2535	16.64	17.50	1.219	-	-	-0.1	0.275	0.335
LTE Band 7_Main PA	20M	QPSK	1	0	-	Left Tilted	0mm	Ant 4	DSI 0	21100	2535	16.64	17.50	1.219	-	-	0.1	0.133	0.162
LTE Band 7_Main PA	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 4	DSI 0	21100	2535	16.50	17.50	1.259	-	-	0	0.416	0.524
LTE Band 7_Main PA	20M	QPSK	50	0	-	Right Tilted	0mm	Ant 4	DSI 0	21100	2535	16.50	17.50	1.259	-	-	0.18	0.078	0.098
LTE Band 7_Main PA	20M	QPSK	50	0	-	Left Cheek	0mm	Ant 4	DSI 0	21100	2535	16.50	17.50	1.259	-	-	0.09	0.262	0.330
LTE Band 7_Main PA	20M	QPSK	50	0	-	Left Tilted	0mm	Ant 4	DSI 0	21100	2535	16.50	17.50	1.259	-	-	-0.02	0.127	0.160
LTE Band 41_Main PA	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 1	DSI 0	40620	2593	17.13	18.00	1.222	62.9	1.006	-0.1	0.436	0.536
LTE Band 41_Main PA	20M	QPSK	1	0	-	Right Tilted	0mm	Ant 1	DSI 0	40620	2593	17.13	18.00	1.222	62.9	1.006	0.05	0.420	0.516
LTE Band 41_Main PA	20M	QPSK	1	0	-	Left Cheek	0mm	Ant 1	DSI 0	40620	2593	17.13	18.00	1.222	62.9	1.006	-0.16	0.208	0.256
LTE Band 41_Main PA	20M	QPSK	1	0	-	Left Tilted	0mm	Ant 1	DSI 0	40620	2593	17.13	18.00	1.222	62.9	1.006	0.14	0.184	0.226
LTE Band 41_Main PA	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 1	DSI 0	40620	2593	17.06	18.00	1.242	62.9	1.006	0.15	0.425	0.531
LTE Band 41_Main PA	20M	QPSK	50	0	-	Right Tilted	0mm	Ant 1	DSI 0	40620	2593	17.06	18.00	1.242	62.9	1.006	0.12	0.408	0.510
LTE Band 41_Main PA	20M	QPSK	50	0	-	Left Cheek	0mm	Ant 1	DSI 0	40620	2593	17.06	18.00	1.242	62.9	1.006	0.13	0.199	0.249
LTE Band 41_Main PA	20M	QPSK	50	0	-	Left Tilted	0mm	Ant 1	DSI 0	40620	2593	17.06	18.00	1.242	62.9	1.006	-0.07	0.177	0.221
LTE Band 41_Main PA	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 2	DSI 0	40620	2593	24.89	25.70	1.205	62.9	1.006	-0.09	0.114	0.138
LTE Band 41_Main PA	20M	QPSK	1	0	-	Right Tilted	0mm	Ant 2	DSI 0	40620	2593	24.89	25.70	1.205	62.9	1.006	-0.1	0.092	0.112
LTE Band 41_Main PA	20M	QPSK	1	0	-	Left Cheek	0mm	Ant 2	DSI 0	40620	2593	24.89	25.70	1.205	62.9	1.006	0.12	0.222	0.269
LTE Band 41_Main PA	20M	QPSK	1	0	-	Left Tilted	0mm	Ant 2	DSI 0	40620	2593	24.89	25.70	1.205	62.9	1.006	-0.02	0.065	0.079
LTE Band 41_Main PA	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 2	DSI 0	40620	2593	24.12	24.70	1.143	62.9	1.006	0.02	0.092	0.106
LTE Band 41_Main PA	20M	QPSK	50	0	-	Right Tilted	0mm	Ant 2	DSI 0	40620	2593	24.12	24.70	1.143	62.9	1.006	-0.07	0.076	0.087
LTE Band 41_Main PA	20M	QPSK	50	0	-	Left Cheek	0mm	Ant 2	DSI 0	40620	2593	24.12	24.70	1.143	62.9	1.006	-0.01	0.180	0.207
LTE Band 41_Main PA	20M	QPSK	50	0	-	Left Tilted	0mm	Ant 2	DSI 0	40620	2593	24.12	24.70	1.143	62.9	1.006	-0.17	0.056	0.064
LTE Band 41_Main PA	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 3	DSI 0	40620	2593	19.33	20.00	1.167	62.9	1.006	0.18	0.449	0.527
LTE Band 41_Main PA	20M	QPSK	1	0	-	Right Tilted	0mm	Ant 3	DSI 0	40620	2593	19.33	20.00	1.167	62.9	1.006	-0.19	0.170	0.200
LTE Band 41_Main PA	20M	QPSK	1	0	-	Left Cheek	0mm	Ant 3	DSI 0	40620	2593	19.33	20.00	1.167	62.9	1.006	-0.04	0.380	0.446
LTE Band 41_Main PA	20M	QPSK	1	0	-	Left Tilted	0mm	Ant 3	DSI 0	40620	2593	19.33	20.00	1.167	62.9	1.006	0.06	0.083	0.097
LTE Band 41_Main PA	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 3	DSI 0	40620	2593	19.30	20.00	1.175	62.9	1.006	0.04	0.449	0.531
LTE Band 41_Main PA	20M	QPSK	50	0	-	Right Tilted	0mm	Ant 3	DSI 0	40620	2593	19.30	20.00	1.175	62.9	1.006	-0.09	0.174	0.206
LTE Band 41_Main PA	20M	QPSK	50	0	-	Left Cheek	0mm	Ant 3	DSI 0	40620	2593	19.30	20.00	1.175	62.9	1.006	0.04	0.380	0.449
LTE Band 41_Main PA	20M	QPSK	50	0	-	Left Tilted	0mm	Ant 3	DSI 0	40620	2593	19.30	20.00	1.175	62.9	1.006	-0.08	0.086	0.102
LTE Band 41_Main PA	20M	QPSK	1	0	-	Right Cheek	0mm	Ant 4	DSI 0	40620	2593	18.20	18.70	1.122	62.9	1.006	-0.18	0.481	0.543
LTE Band 41_Main PA	20M	QPSK	1	0	-	Right Tilted	0mm	Ant 4	DSI 0	40620	2593	18.20	18.70	1.122	62.9	1.006	0.04	0.068	0.077
LTE Band 41_Main PA	20M	QPSK	1	0	-	Left Cheek	0mm	Ant 4	DSI 0	40620	2593	18.20	18.70	1.122	62.9	1.006	0.08	0.209	0.236
LTE Band 41_Main PA	20M	QPSK	1	0	-	Left Tilted	0mm	Ant 4	DSI 0	40620	2593	18.20	18.70	1.122	62.9	1.006	-0.19	0.083	0.094
LTE Band 41_Main PA	20M	QPSK	50	0	-	Right Cheek	0mm	Ant 4	DSI 0	40620	2593	18.16	18.70	1.132	62.9	1.006	0.14	0.489	0.557
LTE Band 41_Main PA	20M	QPSK	50	0	-	Right Tilted	0mm	Ant 4	DSI 0	40620	2593	18.16	18.70	1.132	62.9	1.006	0.1	0.069	0.079
LTE Band 41_Main PA	20M	QPSK	50	0	-	Left Cheek	0mm	Ant 4	DSI 0	40620	2593	18.16	18.70	1.132	62.9	1.006	-0.17	0.211	0.240
LTE Band 41_Main PA	20M	QPSK	50	0	-	Left Tilted	0mm	Ant 4	DSI 0	40620	2593	18.16	18.70	1.132	62.9	1.006	0	0.087	0.099
FR1 n7_Main PA	50M	QPSK	1	1	DFT-15	Right Cheek	0mm	Ant 1	DSI 0	507000	2535	14.42	16.00	1.439	-	-	-0.08	0.370	0.532
FR1 n7_Main PA	50M	QPSK	1	1	DFT-15	Right Tilted	0mm	Ant 1	DSI 0	507000	2535	14.42	16.00	1.439	-	-	-0.09	0.278	0.400
FR1 n7_Main PA	50M	QPSK	1	1	DFT-15	Left Cheek	0mm	Ant 1	DSI 0	507000	2535	14.42	16.00	1.439	-	-	-0.11	0.164	0.236
FR1 n7_Main PA	50M	QPSK	1	1	DFT-15	Left Tilted	0mm	Ant 1	DSI 0	507000	2535	14.42	16.00	1.439	-	-	0.11	0.142	0.204
FR1 n7_Main PA	50M	QPSK	135	68	DFT-15	Right Cheek	0mm	Ant 1	DSI 0	507000	2535	14.40	16.00	1.445	-	-	-0.16	0.347	0.502
FR1 n7_Main PA	50M	QPSK	135	68	DFT-15	Right Tilted	0mm	Ant 1	DSI 0	507000	2535	14.40	16.00	1.445	-	-	0.17	0.242	0.350
FR1 n7_Main PA	50M	QPSK	135	68	DFT-15	Left Cheek	0mm	Ant 1	DSI 0	507000	2535	14.40	16.00	1.445	-	-	0.07	0.151	0.218
FR1 n7_Main PA	50M	QPSK	135	68	DFT-15	Left Tilted	0mm	Ant 1	DSI 0	507000	2535	14.40	16.00	1.445	-	-	-0.08	0.131	0.189
FR1 n7_Main PA	50M	QPSK	1	1	DFT-15	Right Cheek	0mm	Ant 2	DSI 0	507000	2535	24.56	25.50	1.242	-	-	-0.04	0.147	0.183
FR1 n7_Main PA	50M	QPSK	1	1	DFT-15	Right Tilted	0mm	Ant 2	DSI 0	507000	2535	24.56	25.50	1.242	-	-	-0.1	0.105	0.130
FR1 n7_Main PA	50M	QPSK	1	1	DFT-15	Left Cheek	0mm	Ant 2	DSI 0	507000	2535	24.56	25.50	1.242	-	-	-0.07	0.304	0.377
FR1 n7_Main PA	50M	QPSK	1	1	DFT-15	Left Tilted	0mm	Ant 2	DSI 0	507000	2535	24.56	25.50	1.242	-	-	-0.02	0.058	0.072



FCC SAR Test Report

Report No. : FA350505

FR1 n7_Main PA	50M	QPSK	135	68	DFT-15	Right Cheek	0mm	Ant 2	DSI 0	507000	2535	24.51	25.50	1.256	-	-	-0.08	0.148	0.186
FR1 n7_Main PA	50M	QPSK	135	68	DFT-15	Right Tilted	0mm	Ant 2	DSI 0	507000	2535	24.51	25.50	1.256	-	-	0.04	0.110	0.138
FR1 n7_Main PA	50M	QPSK	135	68	DFT-15	Left Cheek	0mm	Ant 2	DSI 0	507000	2535	24.51	25.50	1.256	-	-	-0.13	0.326	0.409
FR1 n7_Main PA	50M	QPSK	135	68	DFT-15	Left Tilted	0mm	Ant 2	DSI 0	507000	2535	24.51	25.50	1.256	-	-	0.09	0.062	0.078
FR1 n7_Main PA	50M	QPSK	1	1	DFT-15	Right Cheek	0mm	Ant 3	DSI 0	507000	2535	14.98	16.50	1.419	-	-	-0.18	0.319	0.453
FR1 n7_Main PA	50M	QPSK	1	1	DFT-15	Right Tilted	0mm	Ant 3	DSI 0	507000	2535	14.98	16.50	1.419	-	-	0.18	0.085	0.121
FR1 n7_Main PA	50M	QPSK	1	1	DFT-15	Left Cheek	0mm	Ant 3	DSI 0	507000	2535	14.98	16.50	1.419	-	-	-0.12	0.261	0.370
FR1 n7_Main PA	50M	QPSK	1	1	DFT-15	Left Tilted	0mm	Ant 3	DSI 0	507000	2535	14.98	16.50	1.419	-	-	0.02	0.047	0.067
FR1 n7_Main PA	50M	QPSK	135	68	DFT-15	Right Cheek	0mm	Ant 3	DSI 0	507000	2535	14.92	16.50	1.439	-	-	-0.03	0.383	0.551
FR1 n7_Main PA	50M	QPSK	135	68	DFT-15	Right Tilted	0mm	Ant 3	DSI 0	507000	2535	14.92	16.50	1.439	-	-	0	0.089	0.128
FR1 n7_Main PA	50M	QPSK	135	68	DFT-15	Left Cheek	0mm	Ant 3	DSI 0	507000	2535	14.92	16.50	1.439	-	-	0.05	0.289	0.416
FR1 n7_Main PA	50M	QPSK	135	68	DFT-15	Left Tilted	0mm	Ant 3	DSI 0	507000	2535	14.92	16.50	1.439	-	-	-0.03	0.058	0.083
FR1 n7_Main PA	50M	QPSK	1	1	DFT-15	Right Cheek	0mm	Ant 4	DSI 0	507000	2535	15.36	16.50	1.300	-	-	0.1	0.362	0.471
FR1 n7_Main PA	50M	QPSK	1	1	DFT-15	Right Tilted	0mm	Ant 4	DSI 0	507000	2535	15.36	16.50	1.300	-	-	-0.12	0.060	0.078
FR1 n7_Main PA	50M	QPSK	1	1	DFT-15	Left Cheek	0mm	Ant 4	DSI 0	507000	2535	15.36	16.50	1.300	-	-	0.05	0.242	0.315
FR1 n7_Main PA	50M	QPSK	1	1	DFT-15	Left Tilted	0mm	Ant 4	DSI 0	507000	2535	15.36	16.50	1.300	-	-	0.16	0.087	0.113
FR1 n7_Main PA	50M	QPSK	135	68	DFT-15	Right Cheek	0mm	Ant 4	DSI 0	507000	2535	15.34	16.50	1.306	-	-	0.19	0.421	0.550
FR1 n7_Main PA	50M	QPSK	135	68	DFT-15	Right Tilted	0mm	Ant 4	DSI 0	507000	2535	15.34	16.50	1.306	-	-	0.01	0.067	0.088
FR1 n7_Main PA	50M	QPSK	135	68	DFT-15	Left Cheek	0mm	Ant 4	DSI 0	507000	2535	15.34	16.50	1.306	-	-	-0.04	0.275	0.359
FR1 n7_Main PA	50M	QPSK	135	68	DFT-15	Left Tilted	0mm	Ant 4	DSI 0	507000	2535	15.34	16.50	1.306	-	-	-0.17	0.100	0.131
FR1 n41_Main PA	100M	QPSK	1	1	DFT-30	Right Cheek	0mm	Ant 1	DSI 0	518598	2592.99	14.69	16.00	1.352	-	-	-0.15	0.406	0.549
FR1 n41_Main PA	100M	QPSK	1	1	DFT-30	Right Tilted	0mm	Ant 1	DSI 0	518598	2592.99	14.69	16.00	1.352	-	-	0.19	0.395	0.534
FR1 n41_Main PA	100M	QPSK	1	1	DFT-30	Left Cheek	0mm	Ant 1	DSI 0	518598	2592.99	14.69	16.00	1.352	-	-	0.08	0.219	0.296
FR1 n41_Main PA	100M	QPSK	1	1	DFT-30	Left Tilted	0mm	Ant 1	DSI 0	518598	2592.99	14.69	16.00	1.352	-	-	-0.1	0.186	0.251
FR1 n41_Main PA	100M	QPSK	135	69	DFT-30	Right Cheek	0mm	Ant 1	DSI 0	518598	2592.99	14.63	16.00	1.371	-	-	-0.18	0.392	0.537
FR1 n41_Main PA	100M	QPSK	135	69	DFT-30	Right Tilted	0mm	Ant 1	DSI 0	518598	2592.99	14.63	16.00	1.371	-	-	-0.1	0.366	0.502
FR1 n41_Main PA	100M	QPSK	135	69	DFT-30	Left Cheek	0mm	Ant 1	DSI 0	518598	2592.99	14.63	16.00	1.371	-	-	0.06	0.202	0.277
FR1 n41_Main PA	100M	QPSK	135	69	DFT-30	Left Tilted	0mm	Ant 1	DSI 0	518598	2592.99	14.63	16.00	1.371	-	-	0.13	0.180	0.247
FR1 n41_Main PA	100M	QPSK	1	1	DFT-30	Right Cheek	0mm	Ant 2	DSI 0	518598	2592.99	24.62	25.70	1.282	-	-	-0.02	0.173	0.222
FR1 n41_Main PA	100M	QPSK	1	1	DFT-30	Right Tilted	0mm	Ant 2	DSI 0	518598	2592.99	24.62	25.70	1.282	-	-	0.16	0.135	0.173
FR1 n41_Main PA	100M	QPSK	1	1	DFT-30	Left Cheek	0mm	Ant 2	DSI 0	518598	2592.99	24.62	25.70	1.282	-	-	-0.06	0.304	0.390
FR1 n41_Main PA	100M	QPSK	1	1	DFT-30	Left Tilted	0mm	Ant 2	DSI 0	518598	2592.99	24.62	25.70	1.282	-	-	0.18	0.084	0.108
FR1 n41_Main PA	100M	QPSK	135	69	DFT-30	Right Cheek	0mm	Ant 2	DSI 0	518598	2592.99	24.52	25.70	1.312	-	-	-0.12	0.148	0.194
FR1 n41_Main PA	100M	QPSK	135	69	DFT-30	Right Tilted	0mm	Ant 2	DSI 0	518598	2592.99	24.52	25.70	1.312	-	-	0.11	0.116	0.152
FR1 n41_Main PA	100M	QPSK	135	69	DFT-30	Left Cheek	0mm	Ant 2	DSI 0	518598	2592.99	24.52	25.70	1.312	-	-	0.11	0.290	0.381
FR1 n41_Main PA	100M	QPSK	135	69	DFT-30	Left Tilted	0mm	Ant 2	DSI 0	518598	2592.99	24.52	25.70	1.312	-	-	0.08	0.075	0.098
FR1 n41_Main PA	100M	QPSK	1	1	DFT-30	Right Cheek	0mm	Ant 3	DSI 0	518598	2592.99	14.33	16.00	1.469	-	-	-0.1	0.354	0.520
FR1 n41_Main PA	100M	QPSK	1	1	DFT-30	Right Tilted	0mm	Ant 3	DSI 0	518598	2592.99	14.33	16.00	1.469	-	-	-0.14	0.115	0.169
FR1 n41_Main PA	100M	QPSK	1	1	DFT-30	Left Cheek	0mm	Ant 3	DSI 0	518598	2592.99	14.33	16.00	1.469	-	-	0.12	0.245	0.360
FR1 n41_Main PA	100M	QPSK	1	1	DFT-30	Left Tilted	0mm	Ant 3	DSI 0	518598	2592.99	14.33	16.00	1.469	-	-	0.17	0.061	0.090
FR1 n41_Main PA	100M	QPSK	135	69	DFT-30	Right Cheek	0mm	Ant 3	DSI 0	518598	2592.99	14.29	16.00	1.483	-	-	0.12	0.319	0.473
FR1 n41_Main PA	100M	QPSK	135	69	DFT-30	Right Tilted	0mm	Ant 3	DSI 0	518598	2592.99	14.29	16.00	1.483	-	-	0.06	0.100	0.148
FR1 n41_Main PA	100M	QPSK	135	69	DFT-30	Left Cheek	0mm	Ant 3	DSI 0	518598	2592.99	14.29	16.00	1.483	-	-	-0.06	0.226	0.335
FR1 n41_Main PA	100M	QPSK	135	69	DFT-30	Left Tilted	0mm	Ant 3	DSI 0	518598	2592.99	14.29	16.00	1.483	-	-	-0.17	0.056	0.083
FR1 n41_Main PA	100M	QPSK	1	1	DFT-30	Right Cheek	0mm	Ant 4	DSI 0	518598	2592.99	14.50	15.20	1.175	-	-	0.04	0.456	0.536
FR1 n41_Main PA	100M	QPSK	1	1	DFT-30	Right Tilted	0mm	Ant 4	DSI 0	518598	2592.99	14.50	15.20	1.175	-	-	-0.15	0.056	0.066
FR1 n41_Main PA	100M	QPSK	1	1	DFT-30	Left Cheek	0mm	Ant 4	DSI 0	518598	2592.99	14.50	15.20	1.175	-	-	-0.01	0.192	0.226
FR1 n41_Main PA	100M	QPSK	1	1	DFT-30	Left Tilted	0mm	Ant 4	DSI 0	518598	2592.99	14.50	15.20	1.175	-	-	0.08	0.088	0.103
FR1 n41_Main PA	100M	QPSK	135	69	DFT-30	Right Cheek	0mm	Ant 4	DSI 0	518598	2592.99	14.46	15.20	1.186	-	-	0.11	0.462	0.548
FR1 n41_Main PA	100M	QPSK	135	69	DFT-30	Right Tilted	0mm	Ant 4	DSI 0	518598	2592.99	14.46	15.20	1.186	-	-	0.18	0.061	0.072
FR1 n41_Main PA	100M	QPSK	135	69	DFT-30	Left Cheek	0mm	Ant 4	DSI 0	518598	2592.99	14.46	15.20	1.186	-	-	0.12	0.200	0.237
FR1 n41_Main PA	100M	QPSK	135	69	DFT-30	Left Tilted	0mm	Ant 4	DSI 0	518598	2592.99	14.46	15.20	1.186	-	-	0.07	0.100	0.119
3500MHz																			
FR1 n77_Main PA Part27Q	100M	QPSK	1	137	DFT-30	Right Cheek	0mm	Ant 1	DSI 0	633332	3499.98	15.12	16.50	1.374	-	-	-0.18	0.211	0.290
FR1 n77_Main PA Part27Q	100M	QPSK	1	137	DFT-30	Right Tilted	0mm	Ant 1	DSI 0	633332	3499.98	15.12	16.50	1.374	-	-	-0.12	0.259	0.356
FR1 n77_Main PA Part27Q	100M	QPSK	1	137	DFT-30	Left Cheek	0mm	Ant 1	DSI 0	633332	3499.98	15.12	16.50	1.374	-	-	0.11	0.104	0.143



FCC SAR Test Report

Report No. : FA350505

Table with columns: Model, Power, Modulation, Channels, Frequency, Bandwidth, Location, Distance, Antenna, Frequency, Power, Power Density, SAR, SAR, SAR, SAR, SAR, SAR, SAR, SAR, SAR, SAR. Rows include various test configurations for FR1 n77_Main PA Part27Q and FR1 n77_Main PA Part27Q PC2.



FCC SAR Test Report

Report No. : FA350505

FR1 n77_Main PA Part27Q	100M	QPSK	135	69	DFT-30	Right Tilted	0mm	Ant 7	DSI 0	633332	3499.98	21.95	23.00	1.274	-	-	0.06	0.086	0.110
FR1 n77_Main PA Part27Q	100M	QPSK	135	69	DFT-30	Left Cheek	0mm	Ant 7	DSI 0	633332	3499.98	21.95	23.00	1.274	-	-	0.11	0.203	0.259
FR1 n77_Main PA Part27O	100M	QPSK	135	69	DFT-30	Left Tilted	0mm	Ant 7	DSI 0	633332	3499.98	21.95	23.00	1.274	-	-	0.15	0.051	0.065
FR1 n77_Main PA Part27O	100M	QPSK	1	137	DFT-30	Right Cheek	0mm	Ant 7	DSI 0	656000	3840	22.23	23.50	1.340	-	-	0.1	0.280	0.375
FR1 n77_Main PA Part27O	100M	QPSK	1	137	DFT-30	Right Tilted	0mm	Ant 7	DSI 0	656000	3840	22.23	23.50	1.340	-	-	0.06	0.198	0.265
FR1 n77_Main PA Part27O	100M	QPSK	1	137	DFT-30	Left Cheek	0mm	Ant 7	DSI 0	656000	3840	22.23	23.50	1.340	-	-	0.13	0.150	0.201
FR1 n77_Main PA Part27O	100M	QPSK	1	137	DFT-30	Left Tilted	0mm	Ant 7	DSI 0	656000	3840	22.23	23.50	1.340	-	-	-0.06	0.108	0.145
FR1 n77_Main PA Part27O	100M	QPSK	135	69	DFT-30	Right Cheek	0mm	Ant 7	DSI 0	656000	3840	22.20	23.50	1.349	-	-	-0.16	0.222	0.299
FR1 n77_Main PA Part27O	100M	QPSK	135	69	DFT-30	Right Tilted	0mm	Ant 7	DSI 0	656000	3840	22.20	23.50	1.349	-	-	0.1	0.155	0.209
FR1 n77_Main PA Part27O	100M	QPSK	135	69	DFT-30	Left Cheek	0mm	Ant 7	DSI 0	656000	3840	22.20	23.50	1.349	-	-	-0.16	0.122	0.165
FR1 n77_Main PA Part27O	100M	QPSK	135	69	DFT-30	Left Tilted	0mm	Ant 7	DSI 0	656000	3840	22.20	23.50	1.349	-	-	-0.04	0.091	0.123
FR1 n78_Main PA Part27Q	100M	QPSK	1	137	DFT-30	Right Cheek	0mm	Ant 7	DSI 0	633332	3499.98	20.59	22.00	1.384	-	-	-0.18	0.361	0.499
FR1 n78_Main PA Part27Q	100M	QPSK	1	137	DFT-30	Right Tilted	0mm	Ant 7	DSI 0	633332	3499.98	20.59	22.00	1.384	-	-	-0.18	0.090	0.125
FR1 n78_Main PA Part27Q	100M	QPSK	1	137	DFT-30	Left Cheek	0mm	Ant 7	DSI 0	633332	3499.98	20.59	22.00	1.384	-	-	0.19	0.237	0.328
FR1 n78_Main PA Part27Q	100M	QPSK	1	137	DFT-30	Left Tilted	0mm	Ant 7	DSI 0	633332	3499.98	20.59	22.00	1.384	-	-	-0.11	0.055	0.076
FR1 n78_Main PA Part27Q	100M	QPSK	135	69	DFT-30	Right Cheek	0mm	Ant 7	DSI 0	633332	3499.98	20.50	22.00	1.413	-	-	0.09	0.341	0.482
FR1 n78_Main PA Part27Q	100M	QPSK	135	69	DFT-30	Right Tilted	0mm	Ant 7	DSI 0	633332	3499.98	20.50	22.00	1.413	-	-	-0.04	0.078	0.110
FR1 n78_Main PA Part27Q	100M	QPSK	135	69	DFT-30	Left Cheek	0mm	Ant 7	DSI 0	633332	3499.98	20.50	22.00	1.413	-	-	0.01	0.213	0.301
FR1 n78_Main PA Part27Q	100M	QPSK	135	69	DFT-30	Left Tilted	0mm	Ant 7	DSI 0	633332	3499.98	20.50	22.00	1.413	-	-	0.08	0.049	0.069
FR1 n78_Main PA Part27O	100M	QPSK	1	137	DFT-30	Right Cheek	0mm	Ant 7	DSI 0	650000	3750	20.95	22.50	1.429	-	-	0.04	0.381	0.544
FR1 n78_Main PA Part27O	100M	QPSK	1	137	DFT-30	Right Tilted	0mm	Ant 7	DSI 0	650000	3750	20.95	22.50	1.429	-	-	0.15	0.057	0.081
FR1 n78_Main PA Part27O	100M	QPSK	1	137	DFT-30	Left Cheek	0mm	Ant 7	DSI 0	650000	3750	20.95	22.50	1.429	-	-	-0.07	0.141	0.201
FR1 n78_Main PA Part27O	100M	QPSK	1	137	DFT-30	Left Tilted	0mm	Ant 7	DSI 0	650000	3750	20.95	22.50	1.429	-	-	-0.16	0.027	0.039
FR1 n78_Main PA Part27O PC2	100M	QPSK	1	137	DFT-30	Right Cheek	0mm	Ant 7	DSI 0	650000	3750	23.91	25.50	1.442	50	1.000	0.13	0.398	0.574
FR1 n78_Main PA Part27O	100M	QPSK	135	69	DFT-30	Right Cheek	0mm	Ant 7	DSI 0	650000	3750	20.92	22.50	1.439	-	-	0.19	0.344	0.495
FR1 n78_Main PA Part27O	100M	QPSK	135	69	DFT-30	Right Tilted	0mm	Ant 7	DSI 0	650000	3750	20.92	22.50	1.439	-	-	0.07	0.031	0.045
FR1 n78_Main PA Part27O	100M	QPSK	135	69	DFT-30	Left Cheek	0mm	Ant 7	DSI 0	650000	3750	20.92	22.50	1.439	-	-	-0.03	0.086	0.124
FR1 n78_Main PA Part27O	100M	QPSK	135	69	DFT-30	Left Tilted	0mm	Ant 7	DSI 0	650000	3750	20.92	22.50	1.439	-	-	-0.11	0.025	0.036



15.2 Hotspot SAR

Plot No.	Band	BW (MHz)	Modulation	RB Size	RB offset	Mode	Test Position	Gap (mm)	Antenna	Power State	Ch.	Freq. (MHz)	Average Power (dBm)	Tune-Up Limit (dBm)	Tune-up Scaling Factor	Duty Cycle %	Duty Cycle Scaling Factor	Power Drift (dB)	Measured 1g SAR (W/kg)	Reported 1g SAR (W/kg)
750MHz																				
25	LTE Band 12	10M	QPSK	1	0	-	Front	10mm	Ant 0	DSI 4	23095	707.5	24.67	25.50	1.211	-	-	-0.17	0.285	0.345
	LTE Band 12	10M	QPSK	1	0	-	Back	10mm	Ant 0	DSI 4	23095	707.5	24.67	25.50	1.211	-	-	-0.11	0.274	0.332
	LTE Band 12	10M	QPSK	1	0	-	Right Side	10mm	Ant 0	DSI 4	23095	707.5	24.67	25.50	1.211	-	-	-0.04	0.168	0.203
	LTE Band 12	10M	QPSK	1	0	-	Bottom Side	10mm	Ant 0	DSI 4	23095	707.5	24.67	25.50	1.211	-	-	0.18	0.132	0.160
	LTE Band 12	10M	QPSK	25	0	-	Front	10mm	Ant 0	DSI 4	23095	707.5	23.61	24.50	1.227	-	-	0.09	0.268	0.329
	LTE Band 12	10M	QPSK	25	0	-	Back	10mm	Ant 0	DSI 4	23095	707.5	23.61	24.50	1.227	-	-	0.03	0.255	0.313
	LTE Band 12	10M	QPSK	25	0	-	Right Side	10mm	Ant 0	DSI 4	23095	707.5	23.61	24.50	1.227	-	-	0.07	0.161	0.198
	LTE Band 12	10M	QPSK	25	0	-	Bottom Side	10mm	Ant 0	DSI 4	23095	707.5	23.61	24.50	1.227	-	-	0.07	0.120	0.147
	LTE Band 12	10M	QPSK	1	0	-	Front	10mm	Ant 1	DSI 4	23095	707.5	23.88	25.50	1.452	-	-	-0.14	0.096	0.139
	LTE Band 12	10M	QPSK	1	0	-	Back	10mm	Ant 1	DSI 4	23095	707.5	23.88	25.50	1.452	-	-	0.01	0.145	0.211
	LTE Band 12	10M	QPSK	1	0	-	Left Side	10mm	Ant 1	DSI 4	23095	707.5	23.88	25.50	1.452	-	-	0.06	0.187	0.272
	LTE Band 12	10M	QPSK	1	0	-	Top Side	10mm	Ant 1	DSI 4	23095	707.5	23.88	25.50	1.452	-	-	0.15	0.109	0.158
	LTE Band 12	10M	QPSK	25	0	-	Front	10mm	Ant 1	DSI 4	23095	707.5	22.84	24.50	1.466	-	-	0.03	0.074	0.108
	LTE Band 12	10M	QPSK	25	0	-	Back	10mm	Ant 1	DSI 4	23095	707.5	22.84	24.50	1.466	-	-	-0.12	0.114	0.167
	LTE Band 12	10M	QPSK	25	0	-	Left Side	10mm	Ant 1	DSI 4	23095	707.5	22.84	24.50	1.466	-	-	-0.07	0.160	0.234
	LTE Band 12	10M	QPSK	25	0	-	Top Side	10mm	Ant 1	DSI 4	23095	707.5	22.84	24.50	1.466	-	-	-0.09	0.083	0.122
26	LTE Band 13	10M	QPSK	1	0	-	Front	10mm	Ant 0	DSI 4	23230	782	24.58	25.50	1.236	-	-	0.05	0.474	0.586
	LTE Band 13	10M	QPSK	1	0	-	Back	10mm	Ant 0	DSI 4	23230	782	24.58	25.50	1.236	-	-	0.15	0.437	0.540
	LTE Band 13	10M	QPSK	1	0	-	Right Side	10mm	Ant 0	DSI 4	23230	782	24.58	25.50	1.236	-	-	0.07	0.175	0.216
	LTE Band 13	10M	QPSK	1	0	-	Bottom Side	10mm	Ant 0	DSI 4	23230	782	24.58	25.50	1.236	-	-	-0.17	0.213	0.263
	LTE Band 13	10M	QPSK	25	0	-	Front	10mm	Ant 0	DSI 4	23230	782	23.62	24.50	1.225	-	-	-0.1	0.373	0.457
	LTE Band 13	10M	QPSK	25	0	-	Back	10mm	Ant 0	DSI 4	23230	782	23.62	24.50	1.225	-	-	-0.01	0.353	0.432
	LTE Band 13	10M	QPSK	25	0	-	Right Side	10mm	Ant 0	DSI 4	23230	782	23.62	24.50	1.225	-	-	-0.1	0.136	0.167
	LTE Band 13	10M	QPSK	25	0	-	Bottom Side	10mm	Ant 0	DSI 4	23230	782	23.62	24.50	1.225	-	-	0.03	0.168	0.206
	LTE Band 13	10M	QPSK	1	0	-	Front	10mm	Ant 1	DSI 4	23230	782	22.69	24.50	1.517	-	-	-0.16	0.196	0.297
	LTE Band 13	10M	QPSK	1	0	-	Back	10mm	Ant 1	DSI 4	23230	782	22.69	24.50	1.517	-	-	-0.08	0.255	0.387
	LTE Band 13	10M	QPSK	1	0	-	Left Side	10mm	Ant 1	DSI 4	23230	782	22.69	24.50	1.517	-	-	-0.16	0.275	0.417
	LTE Band 13	10M	QPSK	1	0	-	Top Side	10mm	Ant 1	DSI 4	23230	782	22.69	24.50	1.517	-	-	0.08	0.209	0.317
	LTE Band 13	10M	QPSK	25	0	-	Front	10mm	Ant 1	DSI 4	23230	782	22.65	24.50	1.531	-	-	0.04	0.192	0.294
	LTE Band 13	10M	QPSK	25	0	-	Back	10mm	Ant 1	DSI 4	23230	782	22.65	24.50	1.531	-	-	0.15	0.251	0.384
	LTE Band 13	10M	QPSK	25	0	-	Left Side	10mm	Ant 1	DSI 4	23230	782	22.65	24.50	1.531	-	-	-0.03	0.268	0.410
	LTE Band 13	10M	QPSK	25	0	-	Top Side	10mm	Ant 1	DSI 4	23230	782	22.65	24.50	1.531	-	-	-0.06	0.205	0.314
835MHz																				
27	GSM850	-	-	-	-	GPRS (4 Tx slots)	Front	10mm	Ant 0	DSI 4	189	836.4	27.15	28.00	1.216	-	-	-0.08	0.426	0.518
	GSM850	-	-	-	-	GPRS (4 Tx slots)	Back	10mm	Ant 0	DSI 4	189	836.4	27.15	28.00	1.216	-	-	0.04	0.382	0.465
	GSM850	-	-	-	-	GPRS (4 Tx slots)	Right Side	10mm	Ant 0	DSI 4	189	836.4	27.15	28.00	1.216	-	-	-0.06	0.161	0.196
	GSM850	-	-	-	-	GPRS (4 Tx slots)	Bottom Side	10mm	Ant 0	DSI 4	189	836.4	27.15	28.00	1.216	-	-	-0.01	0.241	0.293
	GSM850	-	-	-	-	GPRS (4 Tx slots)	Front	10mm	Ant 1	DSI 4	189	836.4	25.35	26.50	1.303	-	-	0.04	0.206	0.268
	GSM850	-	-	-	-	GPRS (4 Tx slots)	Back	10mm	Ant 1	DSI 4	189	836.4	25.35	26.50	1.303	-	-	-0.09	0.313	0.408
	GSM850	-	-	-	-	GPRS (4 Tx slots)	Left Side	10mm	Ant 1	DSI 4	189	836.4	25.35	26.50	1.303	-	-	0.12	0.163	0.212
	GSM850	-	-	-	-	GPRS (4 Tx slots)	Top Side	10mm	Ant 1	DSI 4	189	836.4	25.35	26.50	1.303	-	-	-0.04	0.219	0.285
28	WCDMA V	-	-	-	-	RMC 12.2Kbps	Front	10mm	Ant 0	DSI 4	4182	836.4	24.40	25.00	1.148	-	-	-0.01	0.466	0.535
	WCDMA V	-	-	-	-	RMC 12.2Kbps	Back	10mm	Ant 0	DSI 4	4182	836.4	24.40	25.00	1.148	-	-	-0.12	0.414	0.475
	WCDMA V	-	-	-	-	RMC 12.2Kbps	Right Side	10mm	Ant 0	DSI 4	4182	836.4	24.40	25.00	1.148	-	-	0.13	0.149	0.171
	WCDMA V	-	-	-	-	RMC 12.2Kbps	Bottom Side	10mm	Ant 0	DSI 4	4182	836.4	24.40	25.00	1.148	-	-	-0.14	0.182	0.209
	WCDMA V	-	-	-	-	RMC 12.2Kbps	Front	10mm	Ant 1	DSI 4	4182	836.4	21.35	23.00	1.462	-	-	-0.13	0.159	0.232
	WCDMA V	-	-	-	-	RMC 12.2Kbps	Back	10mm	Ant 1	DSI 4	4182	836.4	21.35	23.00	1.462	-	-	-0.04	0.234	0.342
	WCDMA V	-	-	-	-	RMC 12.2Kbps	Left Side	10mm	Ant 1	DSI 4	4182	836.4	21.35	23.00	1.462	-	-	-0.13	0.146	0.213
	WCDMA V	-	-	-	-	RMC 12.2Kbps	Top Side	10mm	Ant 1	DSI 4	4182	836.4	21.35	23.00	1.462	-	-	-0.07	0.164	0.240
29	LTE Band 26	15M	QPSK	1	0	-	Front	10mm	Ant 0	DSI 4	26865	831.5	24.69	25.50	1.205	-	-	0.05	0.563	0.678



FCC SAR Test Report

Report No. : FA350505

	LTE Band 26	15M	QPSK	1	0	-	Back	10mm	Ant 0	DSI 4	26865	831.5	24.69	25.50	1.205	-	-	0.03	0.515	0.621
	LTE Band 26	15M	QPSK	1	0	-	Right Side	10mm	Ant 0	DSI 4	26865	831.5	24.69	25.50	1.205	-	-	-0.16	0.220	0.265
	LTE Band 26	15M	QPSK	1	0	-	Bottom Side	10mm	Ant 0	DSI 4	26865	831.5	24.69	25.50	1.205	-	-	0.1	0.292	0.352
	LTE Band 26	15M	QPSK	36	0	-	Front	10mm	Ant 0	DSI 4	26865	831.5	23.66	24.50	1.213	-	-	0.15	0.439	0.533
	LTE Band 26	15M	QPSK	36	0	-	Back	10mm	Ant 0	DSI 4	26865	831.5	23.66	24.50	1.213	-	-	-0.02	0.407	0.494
	LTE Band 26	15M	QPSK	36	0	-	Right Side	10mm	Ant 0	DSI 4	26865	831.5	23.66	24.50	1.213	-	-	0.04	0.172	0.209
	LTE Band 26	15M	QPSK	36	0	-	Bottom Side	10mm	Ant 0	DSI 4	26865	831.5	23.66	24.50	1.213	-	-	0.18	0.227	0.275
	LTE Band 26	15M	QPSK	1	0	-	Front	10mm	Ant 1	DSI 4	26865	831.5	22.39	24.00	1.449	-	-	-0.02	0.152	0.220
	LTE Band 26	15M	QPSK	1	0	-	Back	10mm	Ant 1	DSI 4	26865	831.5	22.39	24.00	1.449	-	-	-0.04	0.223	0.323
	LTE Band 26	15M	QPSK	1	0	-	Left Side	10mm	Ant 1	DSI 4	26865	831.5	22.39	24.00	1.449	-	-	0.13	0.122	0.177
	LTE Band 26	15M	QPSK	1	0	-	Top Side	10mm	Ant 1	DSI 4	26865	831.5	22.39	24.00	1.449	-	-	-0.1	0.165	0.239
	LTE Band 26	15M	QPSK	36	0	-	Front	10mm	Ant 1	DSI 4	26865	831.5	22.37	24.00	1.455	-	-	-0.16	0.148	0.215
	LTE Band 26	15M	QPSK	36	0	-	Back	10mm	Ant 1	DSI 4	26865	831.5	22.37	24.00	1.455	-	-	0.13	0.219	0.319
	LTE Band 26	15M	QPSK	36	0	-	Left Side	10mm	Ant 1	DSI 4	26865	831.5	22.37	24.00	1.455	-	-	0.18	0.128	0.186
	LTE Band 26	15M	QPSK	36	0	-	Top Side	10mm	Ant 1	DSI 4	26865	831.5	22.37	24.00	1.455	-	-	0.11	0.162	0.236
	FR1 n5	20M	QPSK	1	1	DFT-15	Front	10mm	Ant 0	DSI 4	167300	836.5	24.39	25.50	1.291	-	-	-0.01	0.468	0.604
	FR1 n5	20M	QPSK	1	1	DFT-15	Back	10mm	Ant 0	DSI 4	167300	836.5	24.39	25.50	1.291	-	-	0.03	0.391	0.505
	FR1 n5	20M	QPSK	1	1	DFT-15	Right Side	10mm	Ant 0	DSI 4	167300	836.5	24.39	25.50	1.291	-	-	-0.14	0.147	0.190
	FR1 n5	20M	QPSK	1	1	DFT-15	Bottom Side	10mm	Ant 0	DSI 4	167300	836.5	24.39	25.50	1.291	-	-	0.03	0.211	0.272
30	FR1 n5	20M	QPSK	50	28	DFT-15	Front	10mm	Ant 0	DSI 4	167300	836.5	24.31	25.50	1.315	-	-	-0.06	0.492	0.647
	FR1 n5	20M	QPSK	50	28	DFT-15	Back	10mm	Ant 0	DSI 4	167300	836.5	24.31	25.50	1.315	-	-	-0.01	0.423	0.556
	FR1 n5	20M	QPSK	50	28	DFT-15	Right Side	10mm	Ant 0	DSI 4	167300	836.5	24.31	25.50	1.315	-	-	0.03	0.153	0.201
	FR1 n5	20M	QPSK	50	28	DFT-15	Bottom Side	10mm	Ant 0	DSI 4	167300	836.5	24.31	25.50	1.315	-	-	-0.19	0.221	0.291
	FR1 n5	20M	QPSK	1	1	DFT-15	Front	10mm	Ant 1	DSI 4	167300	836.5	20.71	22.50	1.510	-	-	0.08	0.087	0.131
	FR1 n5	20M	QPSK	1	1	DFT-15	Back	10mm	Ant 1	DSI 4	167300	836.5	20.71	22.50	1.510	-	-	-0.15	0.175	0.264
	FR1 n5	20M	QPSK	1	1	DFT-15	Left Side	10mm	Ant 1	DSI 4	167300	836.5	20.71	22.50	1.510	-	-	0.1	0.067	0.101
	FR1 n5	20M	QPSK	1	1	DFT-15	Top Side	10mm	Ant 1	DSI 4	167300	836.5	20.71	22.50	1.510	-	-	-0.11	0.099	0.149
	FR1 n5	20M	QPSK	50	28	DFT-15	Front	10mm	Ant 1	DSI 4	167300	836.5	20.69	22.50	1.517	-	-	-0.16	0.106	0.161
	FR1 n5	20M	QPSK	50	28	DFT-15	Back	10mm	Ant 1	DSI 4	167300	836.5	20.69	22.50	1.517	-	-	-0.01	0.185	0.281
	FR1 n5	20M	QPSK	50	28	DFT-15	Left Side	10mm	Ant 1	DSI 4	167300	836.5	20.69	22.50	1.517	-	-	0.05	0.089	0.135
	FR1 n5	20M	QPSK	50	28	DFT-15	Top Side	10mm	Ant 1	DSI 4	167300	836.5	20.69	22.50	1.517	-	-	-0.17	0.117	0.177
1750MHz																				
	WCDMA IV	-	-	-	-	RMC 12.2Kbps	Front	10mm	Ant 1	DSI 4	1413	1732.6	16.49	18.00	1.416	-	-	-0.18	0.139	0.197
	WCDMA IV	-	-	-	-	RMC 12.2Kbps	Back	10mm	Ant 1	DSI 4	1413	1732.6	16.49	18.00	1.416	-	-	-0.15	0.171	0.242
	WCDMA IV	-	-	-	-	RMC 12.2Kbps	Left Side	10mm	Ant 1	DSI 4	1413	1732.6	16.49	18.00	1.416	-	-	0.04	0.103	0.146
	WCDMA IV	-	-	-	-	RMC 12.2Kbps	Top Side	10mm	Ant 1	DSI 4	1413	1732.6	16.49	18.00	1.416	-	-	-0.14	0.215	0.304
	WCDMA IV	-	-	-	-	RMC 12.2Kbps	Front	10mm	Ant 2	DSI 4	1413	1732.6	21.61	22.00	1.094	-	-	0.16	0.473	0.517
	WCDMA IV	-	-	-	-	RMC 12.2Kbps	Back	10mm	Ant 2	DSI 4	1413	1732.6	21.61	22.00	1.094	-	-	-0.1	0.588	0.643
	WCDMA IV	-	-	-	-	RMC 12.2Kbps	Left Side	10mm	Ant 2	DSI 4	1413	1732.6	21.61	22.00	1.094	-	-	0.03	0.131	0.143
	WCDMA IV	-	-	-	-	RMC 12.2Kbps	Bottom Side	10mm	Ant 2	DSI 4	1413	1732.6	21.61	22.00	1.094	-	-	0.14	0.973	1.064
	WCDMA IV	-	-	-	-	RMC 12.2Kbps	Bottom Side	10mm	Ant 2	DSI 4	1312	1712.4	21.57	22.00	1.104	-	-	0.06	0.869	0.959
31	WCDMA IV	-	-	-	-	RMC 12.2Kbps	Bottom Side	10mm	Ant 2	DSI 4	1513	1752.6	21.42	22.00	1.143	-	-	-0.04	0.950	1.086
	LTE Band 4	20M	QPSK	1	0	-	Front	10mm	Ant 2	DSI 4	20175	1732.5	20.46	21.20	1.186	-	-	-0.14	0.322	0.382
	LTE Band 4	20M	QPSK	1	0	-	Back	10mm	Ant 2	DSI 4	20175	1732.5	20.46	21.20	1.186	-	-	-0.18	0.477	0.566
	LTE Band 4	20M	QPSK	1	0	-	Left Side	10mm	Ant 2	DSI 4	20175	1732.5	20.46	21.20	1.186	-	-	0.08	0.092	0.109
	LTE Band 4	20M	QPSK	1	0	-	Bottom Side	10mm	Ant 2	DSI 4	20175	1732.5	20.46	21.20	1.186	-	-	0.11	0.641	0.760
	LTE Band 4	20M	QPSK	50	0	-	Front	10mm	Ant 2	DSI 4	20175	1732.5	20.38	21.20	1.208	-	-	0.13	0.324	0.391
	LTE Band 4	20M	QPSK	50	0	-	Back	10mm	Ant 2	DSI 4	20175	1732.5	20.38	21.20	1.208	-	-	0.08	0.486	0.587
	LTE Band 4	20M	QPSK	50	0	-	Left Side	10mm	Ant 2	DSI 4	20175	1732.5	20.38	21.20	1.208	-	-	0.05	0.099	0.120
	LTE Band 4	20M	QPSK	50	0	-	Bottom Side	10mm	Ant 2	DSI 4	20175	1732.5	20.38	21.20	1.208	-	-	-0.06	0.652	0.787
	LTE Band 4	20M	QPSK	1	0	-	Front	10mm	Ant 3	DSI 4	20175	1732.5	21.65	23.00	1.365	-	-	-0.14	0.381	0.520
	LTE Band 4	20M	QPSK	1	0	-	Back	10mm	Ant 3	DSI 4	20175	1732.5	21.65	23.00	1.365	-	-	0.14	0.319	0.435
	LTE Band 4	20M	QPSK	1	0	-	Left Side	10mm	Ant 3	DSI 4	20175	1732.5	21.65	23.00	1.365	-	-	-0.04	0.438	0.598
	LTE Band 4	20M	QPSK	1	0	-	Top Side	10mm	Ant 3	DSI 4	20175	1732.5	21.65	23.00	1.365	-	-	-0.05	0.061	0.083
	LTE Band 4	20M	QPSK	50	0	-	Front	10mm	Ant 3	DSI 4	20175	1732.5	21.61	23.00	1.377	-	-	0.19	0.336	0.463
	LTE Band 4	20M	QPSK	50	0	-	Back	10mm	Ant 3	DSI 4	20175	1732.5	21.61	23.00	1.377	-	-	-0.03	0.286	0.394



FCC SAR Test Report

Report No. : FA350505

	LTE Band 4	20M	QPSK	50	0	-	Left Side	10mm	Ant 3	DSI 4	20175	1732.5	21.61	23.00	1.377	-	-	-0.12	0.417	0.574
	LTE Band 4	20M	QPSK	50	0	-	Top Side	10mm	Ant 3	DSI 4	20175	1732.5	21.61	23.00	1.377	-	-	0.04	0.058	0.080
	LTE Band 4	20M	QPSK	1	0	-	Front	10mm	Ant 4	DSI 4	20175	1732.5	24.69	25.50	1.205	-	-	0.04	0.035	0.042
	LTE Band 4	20M	QPSK	1	0	-	Back	10mm	Ant 4	DSI 4	20175	1732.5	24.69	25.50	1.205	-	-	0	0.041	0.049
	LTE Band 4	20M	QPSK	1	0	-	Right Side	10mm	Ant 4	DSI 4	20175	1732.5	24.69	25.50	1.205	-	-	-0.01	0.047	0.057
	LTE Band 4	20M	QPSK	1	0	-	Top Side	10mm	Ant 4	DSI 4	20175	1732.5	24.69	25.50	1.205	-	-	-0.18	0.020	0.024
	LTE Band 4	20M	QPSK	50	0	-	Front	10mm	Ant 4	DSI 4	20175	1732.5	23.73	24.50	1.194	-	-	-0.11	0.031	0.037
	LTE Band 4	20M	QPSK	50	0	-	Back	10mm	Ant 4	DSI 4	20175	1732.5	23.73	24.50	1.194	-	-	-0.05	0.038	0.045
	LTE Band 4	20M	QPSK	50	0	-	Right Side	10mm	Ant 4	DSI 4	20175	1732.5	23.73	24.50	1.194	-	-	-0.02	0.046	0.055
	LTE Band 4	20M	QPSK	50	0	-	Top Side	10mm	Ant 4	DSI 4	20175	1732.5	23.73	24.50	1.194	-	-	0.08	0.015	0.018
	LTE Band 66	20M	QPSK	1	0	-	Front	10mm	Ant 1	DSI 4	132322	1745	16.73	18.00	1.340	-	-	-0.16	0.131	0.175
	LTE Band 66	20M	QPSK	1	0	-	Back	10mm	Ant 1	DSI 4	132322	1745	16.73	18.00	1.340	-	-	0	0.171	0.229
	LTE Band 66	20M	QPSK	1	0	-	Left Side	10mm	Ant 1	DSI 4	132322	1745	16.73	18.00	1.340	-	-	0.19	0.112	0.150
	LTE Band 66	20M	QPSK	1	0	-	Top Side	10mm	Ant 1	DSI 4	132322	1745	16.73	18.00	1.340	-	-	-0.13	0.194	0.260
	LTE Band 66	20M	QPSK	50	0	-	Front	10mm	Ant 1	DSI 4	132322	1745	16.70	18.00	1.349	-	-	-0.19	0.128	0.173
	LTE Band 66	20M	QPSK	50	0	-	Back	10mm	Ant 1	DSI 4	132322	1745	16.70	18.00	1.349	-	-	0	0.165	0.223
	LTE Band 66	20M	QPSK	50	0	-	Left Side	10mm	Ant 1	DSI 4	132322	1745	16.70	18.00	1.349	-	-	0.07	0.108	0.146
	LTE Band 66	20M	QPSK	50	0	-	Top Side	10mm	Ant 1	DSI 4	132322	1745	16.70	18.00	1.349	-	-	-0.19	0.191	0.258
	LTE Band 66	20M	QPSK	1	0	-	Front	10mm	Ant 2	DSI 4	132322	1745	18.96	20.50	1.426	-	-	-0.15	0.253	0.361
	LTE Band 66	20M	QPSK	1	0	-	Back	10mm	Ant 2	DSI 4	132322	1745	18.96	20.50	1.426	-	-	-0.18	0.316	0.450
	LTE Band 66	20M	QPSK	1	0	-	Left Side	10mm	Ant 2	DSI 4	132322	1745	18.96	20.50	1.426	-	-	0.02	0.074	0.105
	LTE Band 66	20M	QPSK	1	0	-	Bottom Side	10mm	Ant 2	DSI 4	132322	1745	18.96	20.50	1.426	-	-	0.1	0.564	0.804
	LTE Band 66	20M	QPSK	1	0	-	Bottom Side	10mm	Ant 2	DSI 4	132072	1720	18.85	20.50	1.462	-	-	0.01	0.522	0.763
33	LTE Band 66	20M	QPSK	1	0	-	Bottom Side	10mm	Ant 2	DSI 4	132572	1770	18.78	20.50	1.486	-	-	0.1	0.588	0.874
	LTE Band 66	20M	QPSK	50	0	-	Front	10mm	Ant 2	DSI 4	132322	1745	18.91	20.50	1.442	-	-	0.04	0.248	0.358
	LTE Band 66	20M	QPSK	50	0	-	Back	10mm	Ant 2	DSI 4	132322	1745	18.91	20.50	1.442	-	-	0.07	0.301	0.434
	LTE Band 66	20M	QPSK	50	0	-	Left Side	10mm	Ant 2	DSI 4	132322	1745	18.91	20.50	1.442	-	-	0.07	0.069	0.100
	LTE Band 66	20M	QPSK	50	0	-	Bottom Side	10mm	Ant 2	DSI 4	132322	1745	18.91	20.50	1.442	-	-	-0.06	0.555	0.800
	LTE Band 66	20M	QPSK	50	0	-	Bottom Side	10mm	Ant 2	DSI 4	132072	1720	18.80	20.50	1.479	-	-	0.1	0.514	0.760
	LTE Band 66	20M	QPSK	50	0	-	Bottom Side	10mm	Ant 2	DSI 4	132572	1770	18.76	20.50	1.493	-	-	0.01	0.559	0.834
	LTE Band 66	20M	QPSK	100	0	-	Bottom Side	10mm	Ant 2	DSI 4	132322	1745	18.85	20.50	1.462	-	-	0.1	0.538	0.787
	LTE Band 66	20M	QPSK	1	0	-	Front	10mm	Ant 3	DSI 4	132322	1745	21.11	22.50	1.377	-	-	0.08	0.189	0.260
	LTE Band 66	20M	QPSK	1	0	-	Back	10mm	Ant 3	DSI 4	132322	1745	21.11	22.50	1.377	-	-	-0.14	0.166	0.229
	LTE Band 66	20M	QPSK	1	0	-	Left Side	10mm	Ant 3	DSI 4	132322	1745	21.11	22.50	1.377	-	-	-0.02	0.482	0.664
	LTE Band 66	20M	QPSK	1	0	-	Top Side	10mm	Ant 3	DSI 4	132322	1745	21.11	22.50	1.377	-	-	-0.06	0.060	0.083
	LTE Band 66	20M	QPSK	50	0	-	Front	10mm	Ant 3	DSI 4	132322	1745	21.04	22.50	1.400	-	-	-0.09	0.177	0.248
	LTE Band 66	20M	QPSK	50	0	-	Back	10mm	Ant 3	DSI 4	132322	1745	21.04	22.50	1.400	-	-	0.09	0.153	0.214
	LTE Band 66	20M	QPSK	50	0	-	Left Side	10mm	Ant 3	DSI 4	132322	1745	21.04	22.50	1.400	-	-	-0.06	0.447	0.626
	LTE Band 66	20M	QPSK	50	0	-	Top Side	10mm	Ant 3	DSI 4	132322	1745	21.04	22.50	1.400	-	-	0	0.054	0.076
	LTE Band 66	20M	QPSK	1	0	-	Front	10mm	Ant 4	DSI 4	132322	1745	23.80	24.50	1.175	-	-	-0.11	0.025	0.029
	LTE Band 66	20M	QPSK	1	0	-	Back	10mm	Ant 4	DSI 4	132322	1745	23.80	24.50	1.175	-	-	-0.04	0.031	0.036
	LTE Band 66	20M	QPSK	1	0	-	Right Side	10mm	Ant 4	DSI 4	132322	1745	23.80	24.50	1.175	-	-	0.03	0.037	0.044
	LTE Band 66	20M	QPSK	1	0	-	Top Side	10mm	Ant 4	DSI 4	132322	1745	23.80	24.50	1.175	-	-	0.06	0.018	0.021
	LTE Band 66	20M	QPSK	50	0	-	Front	10mm	Ant 4	DSI 4	132322	1745	22.88	23.50	1.153	-	-	-0.17	0.020	0.023
	LTE Band 66	20M	QPSK	50	0	-	Back	10mm	Ant 4	DSI 4	132322	1745	22.88	23.50	1.153	-	-	0.15	0.025	0.029
	LTE Band 66	20M	QPSK	50	0	-	Right Side	10mm	Ant 4	DSI 4	132322	1745	22.88	23.50	1.153	-	-	0.06	0.031	0.036
	LTE Band 66	20M	QPSK	50	0	-	Top Side	10mm	Ant 4	DSI 4	132322	1745	22.88	23.50	1.153	-	-	0.05	0.015	0.017
	FR1 n66_Other PA	40M	QPSK	1	1	DFT-15	Front	10mm	Ant 1	DSI 4	349000	1745	17.02	18.00	1.253	-	-	0.05	0.099	0.124
	FR1 n66_Other PA	40M	QPSK	1	1	DFT-15	Back	10mm	Ant 1	DSI 4	349000	1745	17.02	18.00	1.253	-	-	-0.04	0.119	0.149
	FR1 n66_Other PA	40M	QPSK	1	1	DFT-15	Left Side	10mm	Ant 1	DSI 4	349000	1745	17.02	18.00	1.253	-	-	-0.05	0.089	0.112
	FR1 n66_Other PA	40M	QPSK	1	1	DFT-15	Top Side	10mm	Ant 1	DSI 4	349000	1745	17.02	18.00	1.253	-	-	0.01	0.311	0.390
	FR1 n66_Other PA	40M	QPSK	108	54	DFT-15	Front	10mm	Ant 1	DSI 4	349000	1745	17.00	18.00	1.259	-	-	-0.16	0.111	0.140
	FR1 n66_Other PA	40M	QPSK	108	54	DFT-15	Back	10mm	Ant 1	DSI 4	349000	1745	17.00	18.00	1.259	-	-	0.16	0.134	0.169
	FR1 n66_Other PA	40M	QPSK	108	54	DFT-15	Left Side	10mm	Ant 1	DSI 4	349000	1745	17.00	18.00	1.259	-	-	0.01	0.098	0.123
	FR1 n66_Other PA	40M	QPSK	108	54	DFT-15	Top Side	10mm	Ant 1	DSI 4	349000	1745	17.00	18.00	1.259	-	-	0.02	0.324	0.408
	FR1 n66_Main PA	40M	QPSK	108	54	DFT-15	Top Side	10mm	Ant 1	DSI 4	349000	1745	14.83	16.50	1.469	-	-	0.09	0.230	0.338