


User Manual

Model : **FX797T**



Features

- 1, Super small and lightweight
- 2, Five bands 25 channels with raceband
- 3, Easy install, plug and play
- 4, Button control instead of switch to change channels

Operating Instructions

How to change frequencies (bands/channels)
Press Band/Channel button once to change channel.
Push and hold button for 2 seconds to change band,

Specifications:

Transmitter power: 25mW
Input power: 2,5-5V
Camera resolution: 600TVL
Min illumination: 1 lux
Field of view: 120° viewing angle
Antenna dimensions: 20mm X 25mm diameter
Antenna: 3 lobe right hand circular polarized
Video output: NTSC
Frequency: 5.8GHz 5 bands 25 channels, 5732MHz-5865MHz
Bands: see below channel table,
Push button operation, long press for band, short press for channel
2 row LED indicators, 5 LED for band, 8 LED for channel
PCB color: blue
Size: 20x17mm(LxW)
Weight: 3.8g

Band	CH							
	CH1	CH2	CH3	CH4	CH5	CH6	CH7	CH8
Band 1(F)	5740	5760	5780	5800	5820	5840	5860	---
Band 2(E)	---	---	---	---	---	---	---	---
Band 3(A)	5865	5845	5825	5805	5785	5765	5745	---
Band 4(R)	---	---	5732	5769	5806	5843	---	---
Band 5(B)	5732	5752	5771	5790	5809	5828	5847	---

FCC Compliance

This device complies with Part 15 of the FCC Rules.

Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference.
- (2) This device must accept any interference received, including interference that may cause undesired operation.

Warning: Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

Reorient or relocate the receiving antenna.

Increase the separation between the equipment and receiver.

Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

Consult the dealer or an experienced radio/TV technician for help.

size:45x70mm