

RF EXPOSURE EVALUATION

FCC ID: **2AGLC-SW-508A**

According to FCC 1.1310: The criteria listed in the following table shall be used to evaluate the environment impact of human exposure to radio frequency(RF) Radiation as specified in §1.1307(b):

The 1-g and 10-g SAR test exclusion thresholds for 100 MHz to 6 GHz at *test separation distances* ≤ 50 mm are determined by:

$[(\text{max. power of channel, including tune-up tolerance, mW})/(\text{min. test separation distance, mm})] \cdot [\sqrt{f_{\text{(GHz)}}}] \leq 3.0$ for 1-g SAR and ≤ 7.5 for 10-g extremity SAR,¹⁶ where

- $f_{\text{(GHz)}}$ is the RF channel transmit frequency in GHz
- Power and distance are rounded to the nearest mW and mm before calculation¹⁷
- The result is rounded to one decimal place for comparison

The test exclusions are applicable only when the minimum *test separation distance* is ≤ 50 mm and for transmission frequencies between 100 MHz and 6 GHz. When the minimum *test separation distance* is < 5 mm, a distance of 5 mm is applied to determine SAR test exclusion.

Routine SAR evaluation refers to that specifically required by §2.1093, using measurements or computer simulation. When routine SAR evaluation is not required, portable transmitters with output power greater than the applicable low threshold require SAR evaluation to qualify for TCB approval.

Mode: BDR

The maximum output power for low channel is: 0.962dBm= 1.248mW

Tune up tolerance is: 0.962 ± 1 dBm

The Max. Tune up Power =1.962dBm= 1.571mW

The calculation results= $1.571/5 \cdot \sqrt{2.402} = 0.487 < 3$

The maximum output power for middle channel is: 1.133dBm= 1.298mW

Tune up tolerance is: 1.133 ± 1 dBm

The Max. Tune up Power =2.133dBm= 1.634mW

The calculation results= $1.634/5 \cdot \sqrt{2.441} = 0.511 < 3$

The maximum output power for high channel is: 1.474dBm= 1.404mW

Tune up tolerance is: 1.474 ± 1 dBm

The Max. Tune up Power =2.474dBm= 1.768mW

The calculation results= $1.768/5 \cdot \sqrt{2.480} = 0.557 < 3$

Mode: EDR

The maximum output power for low channel is: 0.903dBm= 1.231mW

Tune up tolerance is: 0.903 ± 1 dBm

The Max. Tune up Power =1.903dBm= 1.550mW

The calculation results= $1.550/5 \cdot \sqrt{2.402} = 0.480 < 3$

The maximum output power for middle channel is: 1.097dBm= 1.287mW

Tune up tolerance is: 1.097 ± 1 dBm

The Max. Tune up Power =2.097dBm= 1.621mW

The calculation results= $1.621/5 \cdot \sqrt{2.441} = 0.507 < 3$

The maximum output power for high channel is: 1.427dBm= 1.389mW

Tune up tolerance is: 1.427 ± 1 dBm

The Max. Tune up Power =2.427dBm= 1.749mW

The calculation results= $1.749/5 \cdot \sqrt{2.480} = 0.551 < 3$

Test Results: **PASS**.