

## Tune Up Procedure of GO984

During manufacturing each device is individually calibrated. Measurement is performed in a fully calibrated setup using an CMU 200 base station simulator (system tester) and Spectrum analyzer 9k-30GHz FSP. Measurement procedure is outlined below:

### Measurement Procedure:

1. Set the device to operational voltage and on a predefined channel in a special test mode.
2. The actual output power is measured at several power levels.
3. The gain factors of each individual device are adjusted until the target value is met. The appropriate gain control settings for each output power level are stored in each device individually (for each power level). The user has no possibility to change these settings later on.
4. The maximum gains of each individual device are adjusted and measured until the target value is met. The production target power with tolerance compiles with the maximum power in test report.

### Maximum Target Power for Production Unit

Mode	GSM 850	GSM 1900
<b>GSM/PCS</b>	30.5±1 dBm	28.5±1 dBm
<b>GPRS 8 (1 Uplink) CS1</b>	30.5±1 dBm	28.5±1 dBm
<b>GPRS 10 (2 Uplink) CS1</b>	30.0±1 dBm	28.0±1 dBm
<b>GPRS 11 (3 Uplink) CS1</b>	28.0±1 dBm	26.5±1 dBm
<b>GPRS 12 (4 Uplink) CS1</b>	27.0±1 dBm	25.5±1 dBm

### Maximum Target Power for Production Unit

Mode	Bluetooth		
	Low	Middle	High
GFSK	-0.5±1 dBm	-1.0±1 dBm	-1.0±1 dBm
pi/4DQPSK	-1.0±1 dBm	-0.5±1 dBm	-1.0±1 dBm
8DPSK	-0.5±1 dBm	-0.5±1 dBm	0.0±1 dBm
BLE	-8.5±1 dBm	-8.5±1 dBm	-8.0±1 dBm

### Maximum Target Power for Production Unit

Mode	WIFI 2.4 GHz Tune-up Limit (dBm)		
	Low	Middle	High
802.11b	12.5±1 dBm	11.5±1 dBm	11.5±1 dBm
802.11g	9.5±1 dBm	11.0±1 dBm	9.0±1 dBm
802.11n(H20)	9.0±1 dBm	11.0±1 dBm	8.5±1 dBm
802.11n(H40)	7.5±1 dBm	10.0±1 dBm	8.0±1 dBm

## **Power unit: dBm**

Then these appropriate gain settings are stored in each device individually.

The user has no possibility to change these settings later on, and during manufacturing each device will be individual calibrated in this range. The measurement is done in a fully calibrated setup, which is based on the base station simulator. Furthermore, the highest power level is verified afterwards in a call measurement on three channels (low, middle and high).