

EXHIBIT 7 –FCC RF EXPOSURE (MPE) REPORT

**Prediction of MPE Limit
47 CFR § 2.1091**

$$S_{20} = \frac{P_A G_N}{4\pi R_{20}^2}$$

$$S_C = \frac{P_A G_N}{4\pi R_C^2}$$

$$R_C = \sqrt{\frac{P_A G_N}{4\pi S_L}}$$

$$S_L = \frac{f}{300} \text{ (mW/cm}^2\text{)}$$

S₂₀ = Power Density of the Device at 20cm

S_L = Power Density Limit

S_C = Power Density of the Device at the Compliance Distance R_C

R₂₀ = 20cm

R_C = Minimum Distance to the Radiating Element to Meet Compliance

P_T = Power Input to Antenna

P_A = Adjust Power

G_N = Numeric Gain of the Antenna

f = Transmit Frequency

Transmit Duty Cycle = 100%

Use Group = Occupational

Transmit Duty Cycle:	100.00	(%)
Tx Frequency (f):	924.00	(MHz)
RF Power at Antenna Input Port (P _T):	252.00	(mW)
Antenna Gain:	1.20	(dBi)
Numeric Antenna Gain (G _N):	1.32	(numeric)
Cable or Other Loss:	0.00	(dB)
Duty Cycle/Loss Adjusted Power (P _A):	252.00	(mW)

S _L =	3.049	(mW/cm ²)
S ₂₀ at 20cm =	0.066	(mW/cm ²)
R _C =	2.9	(cm)
S _C =	3.05	(mW/cm ²)

FCC ID:	2AK4V-DT-501	RESULT:	PASS
---------	--------------	---------	------