

# Proxess LLC

# RF Exposure Exhibit

## SCOPE OF WORK

EMC TESTING – Proxess MX-Series Mortise Lockset, Model Tested: MX Mortise

## REPORT NUMBER

104273165MPK-003

## ISSUE DATE

August 12, 2020

## REVISED DATE

N/A

## PAGES

10

## DOCUMENT CONTROL NUMBER

Non-Specific Radio Report Shell Rev. December 2017 MPK

© 2017 INTERTEK



## RF Exposure Exhibit (mobile devices)

**Report Number: 104273165MPK-003**  
**Project Number: G104273165**

**Report Issue Date: August 12, 2020**

**Product Designation: Proxess MX-Series Mortise Lockset**

**Model Tested: MX Mortise**

**HVIN: PXH01-MX02-DC**

**HVIN: PXH01-MX02-B**

**FCC ID: 2AKUZPXH01**

**IC: 22335-PXH01**

**to**

**47CFR 2.1091**

**RSS-102 Issue 5**

**for**

**Proxess LLC**


**Tested by:**

Intertek  
1365 Adams Court  
Menlo Park, CA 94025 USA

**Client:**

Proxess LLC  
8100 Southpark Way - Suite A4  
Littleton, CO 80120 USA

**Report prepared by:**



**Todd Moy / EMC Project Engineer**

**Report reviewed by:**



**Krishna Vemuri / EMC Manager**

*This report is for the exclusive use of Intertek's Client and is provided pursuant to the agreement between Intertek and its Client. Intertek's responsibility and liability are limited to the terms and conditions of the agreement. Intertek assumes no liability to any party, other than to the Client in accordance with the agreement, for any loss, expense or damage occasioned by the use of this report. Only the Client is authorized to permit copying or distribution of this report and then only in its entirety. Any use of the Intertek name or one of its marks for the sale or advertisement of the tested material, product or service must first be approved in writing by Intertek. The observations and test results in this report are relevant only to the sample tested. This report by itself does not imply that the material, product, or service is or has ever been under an Intertek certification program.*

<b>Report No. 104273165MPK-003</b>	
<b>Equipment Under Test:</b>	Proxess MX-Series Mortise Lockset
<b>Trade Name:</b>	Proxess LLC
<b>Model(s) Tested:</b>	MX Mortise
<b>Applicant:</b>	Proxess LLC
<b>Contact:</b>	Jeff Cahill
<b>Address:</b>	Proxess LLC 8100 Southpark Way - Suite A4 San Jose, CA 95131
<b>Country:</b>	USA
<b>Tel. Number:</b>	(303) 520-6763
<b>Email:</b>	jeff.cahill@proxess.com
<b>Applicable Regulation:</b>	47CFR 2.1091 RSS-102 Issue 5

## TABLE OF CONTENTS

<i>Proxess LLC</i> .....	1
<i>1.0 RF Exposure Summary</i> .....	5
<i>2.0 RF Exposure Limits</i> .....	5
<i>3.0 Test Results (Mobile Configuration)</i> .....	7
<i>Appendix A: Power Density Calculation</i> .....	9
<i>4.0 Document History</i> .....	10

## 1.0 RF Exposure Summary

Test	Reference FCC	Reference Industry Canada	Result
Radio frequency Radiation Exposure Evaluation	47 CFR§2.1091	RSS-102 Issue 5	Complies

## 2.0 RF Exposure Limits

In this document, we evaluate the RF Exposure to human body due the intentional transmission from the transmitter (EUT). The limits for Maximum Permissible Exposure (MPE) specified in FCC 1.1310 and RSS-102 are followed.

### 2.1 FCC Limits

According to FCC 1.1310 table 1: The criteria listed in the following table shall be used to evaluate the environmental impact of human exposure to radio-frequency (RF) radiation as specified in 1.1307(b)

#### LIMITS FOR MAXIMUM PERMISSIBLE EXPOSURE (MPE)

Frequency Range (MHz)	Electric Field Strength (V/m)	Magnetic Field Strength (A/m)	Power Density (mW/cm <sup>2</sup> )	Average Time (minutes)
<b>(A) Limits For Occupational / Control Exposures</b>				
0.3 – 3.0	614	1.63	*100	6
3.0 – 30	1842/f	4.89/f	*900/f <sup>2</sup>	6
30-300	61.4	0.163	1.0	6
300 - 1500	...	...	F/300	6
1500 - 100,000	...	...	5	6
<b>(B) Limits For General Population / Uncontrolled Exposure</b>				
0.3 – 1.34	614	1.63	*100	30
1.34 – 30	824/f	2.19/f	*180/f <sup>2</sup>	30
30 – 300	27.5	0.073	0.2	30
300 - 1500	...	...	F/1500	30
1500 - 100,000	...	...	1.0	30

F = Frequency in MHz

\* = plane wave equivalent density

## 2.2 Industry Canada Limits

According to RSS-102, Industry Canada has adopted the SAR and RF field strength limits established in Health Canada's RF exposure guideline, Safety Code 6.

Table 4: RF Field Strength Limits for Devices Used by the General Public (Uncontrolled Environment)				
Frequency Range (MHz)	Electric Field (V/m rms)	Magnetic Field (A/m rms)	Power Density (W/m <sup>2</sup> )	Reference Period (minutes)
0.003-10	83	90	-	Instantaneous*
0.1-10	-	0.73/f	-	6**
1.1-10	87/f <sup>0.5</sup>	-	-	6**
10-20	27.46	0.0728	-2	6
20-48	58.07/f <sup>0.25</sup>	0.1540/f <sup>0.25</sup>	8.944/f <sup>0.5</sup>	6
48-300	22.06	0.05852	1.291	6
300-6000	3.142 f <sup>0.3417</sup>	0.008335 f <sup>0.3417</sup>	0.02619 f <sup>0.6834</sup>	6
6000-15000	61.4	0.163	10	6
15000-150000	61.4	0.163	10	616000/f <sup>1.2</sup>
150000-300000	0.158 f <sup>0.5</sup>	4.21 x 10-4 f <sup>0.5</sup>	6.67 x 10 <sup>-5</sup> f	616000/f <sup>1.2</sup>

Note: f is frequency in MHz.  
 \* Based on nerve stimulation (NS).  
 \*\* Based on specific absorption rate (SAR).

### 3.0 Test Results (Mobile Configuration)

#### 3.1 Classification

Radio is installed inside a mobile host device. The antenna of the product, under normal use condition, is at least 20 cm away from the body of the user and accessible to the end user. Warning statement to the user for keeping at least 20 cm or more separation distance with the antenna should be included in user's manual.

#### 3.2 EIRP calculations

The Proxess MX-Series Mortise Lockset, Model: MX Mortise consists of two radios: 13.56 MHz RFID and Bluetooth. For RF exposure compliance refer reports # 104273165MPK-001B.

#### 3.3 Maximum RF Power

Frequency Range (MHz)	Peak FS @10m (dB $\mu$ V/m)	Note
13.56	37.3	FS measurement was taken from Report # 104273165MPK-001B.

Frequency Range (MHz)	RF Output (dBm)	Antenna Gain <sup>1</sup> (dBi)	Note
2402-2480	8.45	-0.65	Conducted power measurements were taken from FCC ID: SH6MDBT50Q.

<sup>1</sup>As declared by the manufacturer.

### 3.4 RF Exposure Calculation

#### 3.4.1 RF Exposure calculation for RFID, Proxess MX-Series Mortise Lockset, Model: MX Mortise:

Frequency Range (MHz)	Peak FS @10m (dB $\mu$ V/m)	Peak FS @20 cm* (dB $\mu$ V/m)	Peak FS @20 cm (V/m)	RSS Limit (V/m)	FCC Limit (V/m)	Results
13.56	37.3	105.26	0.18	27.46	60.77	Complies

\* Distance Correction Factor was used.

#### 3.4.2 RF Exposure calculation for Bluetooth, Proxess MX-Series Mortise Lockset, Model: MX Mortise:

Calculations for this report are based on highest power measured for each band.

Frequency Range (MHz)	EIRP (dBm)	EIRP (mW)	Power Density (mW/cm <sup>2</sup> ) @20 cm	FCC Limit (mW/cm <sup>2</sup> )	Results
2402-2480	8.45	7.00	0.0014	1	Complies

Note: Antenna gains below 0 are considered as 0dBi.

Frequency Range (MHz)	EIRP (dBm)	EIRP (mW)	Power Density (W/m <sup>2</sup> ) @20 cm	RSS Limit (W/m <sup>2</sup> )	Results
2402-2480	8.45	7.00	0.0139	5.47	Complies

Note: Antenna gains below 0 are considered as 0dBi.

#### **Appendix A: Power Density Calculation**

The Power Density can be calculated using the formula

$$S = \text{EIRP} / 4\pi D^2$$

Where: S is Power Density in mW/cm<sup>2</sup>

D is the distance from the antenna in cm.

**4.0 Document History**

Revision/ Job Number	Writer Initials	Reviewers Initials	Date	Change
1.0/ G104273165	TM	KV	August 12, 2020	Original document