



TEST REPORT

APPLICANT : Great Talent Technology Limited

PRODUCT NAME : Tablet

MODEL NAME : T8002

BRAND NAME : moxee

FCC ID : 2ALZM-T8002

STANDARD(S) : FCC 47CFR Part 2(2.1093)
IEEE 1528-2013

RECEIPT DATE : 2022-03-21

TEST DATE : 2022-04-08 to 2022-05-10

ISSUE DATE : 2022-05-20

Edited by: Xie Yiyun
Xie Yiyun (Rapporteur)

Approved by: Shen Junsheng
Shen Junsheng (Supervisor)

NOTE: This document is issued by Shenzhen Morlab Communications Technology Co., the test report shall not be reproduced except in full without prior written permission of the company. The test results apply only to the particular sample(s) tested and to the specific tests carried out which is available on request for validation and information confirmed at our website.





DIRECTORY

1	SAR Results Summary.....	5
2	Technical Information	6
2.1	Applicant and Manufacturer Information	6
2.2	Equipment under Test (EUT) Description	6
2.3	Environment of Test Site	8
3	Introduction	9
3.1	Introduction	9
3.2	SAR Definition	9
4	RF Exposure Limits	10
4.1	Uncontrolled Environment	10
4.2	Controlled Environment	10
5	Applied Reference Documents	11
6	SAR Measurement System	12
6.1	E-Field Probe	13
6.2	Data Acquisition Electronics (DAE)	14
6.3	Robot	14
6.4	Measurement Server	14
6.5	Light Beam Unit	15
6.6	Phantom	15
6.7	Device Holder	16
6.8	Data storage and Evaluation	17
6.9	Test Equipment List	19
7	Tissue Simulating Liquids	21
8	SAR System Verification	23
9	EUT Testing Position	27



9.1	Body-Supported Device Configurations	27
9.2	Wireless Router (Hotspot) Configurations.....	28
10	Measurement Procedures.....	29
10.1	Spatial Peak SAR Evaluation	30
10.2	Power Reference Measurement	30
10.3	Area Scan Procedures	30
10.4	Zoom Scan Procedures	31
10.5	SAR Averaged Methods	31
10.6	Power Drift Monitoring	31
11	SAR Test Configuration	32
12	Conducted Output Power	41
13	LTE Carrier Aggregation.....	41
13.1	LTE Uplink Carrier Aggregation.....	41
14	Exposure Positions Consideration	44
14.1	EUT Antenna Locations.....	44
14.2	Test Positions Consideration.....	44
15	SAR Test Results Summary.....	47
15.1	Test Guidance	47
15.2	Body SAR Data.....	48
15.3	Repeated SAR Assessment	52
16	Simultaneous Transmission Analysis	53
16.1	Simultaneous Transmission Consideration	53
16.2	Simultaneous Transmission Analysis.....	54
17	Uncertainty Assessment	58
18	Measurement Conclusion.....	59
	Annex A General Information.....	60
	Annex B Test Setup Photos	
	Annex C Plots of System Performance Check	



REPORT No.: SZ22020126S01

Annex D Plots of Maximum SAR Test Results

Annex E Conducted Power

Annex F DASY Calibration Certificate

Change History		
Version	Date	Reason for Change
1.0	2022-05-20	First edition

1 SAR Results Summary

The maximum results of Specific Absorption Rate (SAR) found during test as bellows:

Frequency Band		Highest SAR Summary
		Body
		1g SAR (W/kg)
GSM	GSM 850	1.006
	GSM 1900	0.729
WCDMA	Band II	0.542
	Band IV	0.641
	Band V	0.784
LTE	Band 2	0.540
	Band 4	0.488
	Band 5	0.700
	Band 12	1.016
	Band 25	0.485
	Band 26	0.856
	Band 41	1.149
	Band 66	0.593
	Band 71	0.732
WLAN	2.4GHz WLAN	0.314
	5GHz WLAN	0.308
2.4GHz Band	Bluetooth	0.218

Highest Simultaneous Transmission 1g SAR (W/kg)	1.330 W/kg	Limit(W/kg): 1.6 W/kg
--	------------	-----------------------

Note:

1. This device is compliance with Specific Absorption Rate (SAR) for general population or uncontrolled exposure limits (1.6 W/kg) specified in FCC 47 CFR part 1 (1.1310) and had been tested in accordance with the measurement methods and procedures specified in IEEE 1528-2013.
2. When the test result is a critical value, we will use the measurement uncertainty give the judgment result based on the 95% confidence intervals.



2 Technical Information

Note: Provide by applicant.

2.1 Applicant and Manufacturer Information

Applicant:	Great Talent Technology Limited
Applicant Address:	35F, HBC HuiLong Center Building-II Minzhi Street, Longhua, Shenzhen, P. R. China 518110
Manufacturer:	Great Talent Technology Limited
Manufacturer Address:	35F, HBC HuiLong Center Building-II Minzhi Street, Longhua, Shenzhen, P. R. China 518110

2.2 Equipment under Test (EUT) Description

Product Name:	Tablet
EUT IMEI:	357612470002073
Hardware Version:	T8002_V1.0
Software Version:	MT8BV1.0.0B001
Operation Frequency:	GSM 850: 824 MHz ~ 849 MHz GSM 1900: 1850 MHz ~ 1910 MHz WCDMA Band II: 1850 MHz ~ 1910 MHz WCDMA Band IV: 1710 MHz ~ 1755 MHz WCDMA Band V: 824 MHz ~ 849 MHz LTE Band 2: 1850 MHz ~ 1910 MHz LTE Band 4: 1710 MHz ~ 1755 MHz LTE Band 5: 824 MHz ~ 849 MHz LTE Band 12: 699 MHz ~ 716 MHz LTE Band 25: 1850 MHz ~ 1915 MHz LTE Band 26: 814 MHz ~ 849 MHz LTE Band 41: 2496 MHz ~ 2690 MHz LTE Band 66: 1710 MHz ~ 1780 MHz LTE Band 71: 663 MHz ~ 698 MHz WLAN 2.4GHz: 2412 MHz ~ 2462 MHz WLAN 5.2GHz: 5180 MHz ~ 5240 MHz WLAN 5.8GHz: 5745 MHz ~ 5825 MHz Bluetooth: 2402 MHz ~ 2480 MHz



Modulation technology:	GSM/GPRS: GMSK EDGE: 8PSK WCDMA: QPSK, 16QAM LTE: QPSK, 16QAM, 64QAM 802.11b: DSSS 802.11a/g/n-HT20/HT40/ac-VHT20/40/80: OFDM Bluetooth BR+EDR: GFSK, $\pi/4$ -DQPSK, 8-DPSK Bluetooth LE: GFSK
Multi-slot Class:	GPRS: Multi-slot Class 33 EDGE: Multi-slot Class 33
Operation Class:	Class B
Carrier Aggregation:	Uplink & Downlink
Antenna Type:	WWAN : Fixed Internal Antenna WLAN : PIFA Antenna Bluetooth : PIFA Antenna
SIM Cards Description:	GSM+WCDMA+LTE

2.3 Environment of Test Site

Temperature:	18°C ~25°C
Humidity:	35%~75% RH
Atmospheric Pressure:	1010 mbar

Test Frequency:	GSM 850MHz/1900MHz WCDMA Band II/IV/V FDD-LTE Band 2/4/5/12/25/26/66/71 TDD-LTE Band 41 WLAN 2.4GHz WLAN 5GHz Bluetooth
Power Level:	GSM 850 MHz (Maximum output power(level 5)) GSM 1900MHz (Maximum output power(level 0)) WCDMA Band II/IV/V (All Up Bits) FDD-LTE Band 2/4/5/12/25/26/66/71 (Maximum output power) TDD-LTE Band 41 (Maximum output power) WLAN 2.4GHz WLAN 5GHz Bluetooth
Operation Mode:	Call established

During SAR test, EUT is in Traffic Mode (Channel Allocated) at Normal Voltage Condition. A communication link is set up with a System Simulator (SS) by air link, and a call is established.

The EUT shall use its internal transmitter. The antenna(s), battery and accessories shall be those specified by the Factory. The EUT battery must be fully charged and checked periodically during the test to ascertain uniform power output. If a wireless link is used, the antenna connected to the output of the base station simulator shall be placed at least 50 cm away from the handset. The signal transmitted by the simulator to the antenna feeding point shall be lower than the output power level of the handset by at least 35 dB.

3 Introduction

3.1 Introduction

SAR is related to the rate at which energy is absorbed per unit mass in an object exposed to a radio field. The SAR distribution in a biological body is complicated and is usually carried out by experimental techniques or numerical modeling. The standard recommends limits for two tiers of groups, occupational or controlled and general population or uncontrolled, based on a person's awareness and ability to exercise control over his or her exposure. In general, occupational or controlled exposure limits are higher than the limits for general population or uncontrolled.

3.2 SAR Definition

The SAR definition is the time derivative (rate) of the incremental energy (dW) absorbed by (dissipated in) an incremental mass (dm) contained in a volume element (dv) of a given density (ρ). The equation description is as below:

$$SAR = \frac{d}{dt} \left(\frac{dU}{dm} \right) = \frac{d}{dt} \left(\frac{dU}{\rho dv} \right)$$

SAR is expressed in units of Watts per kilogram (W/kg)

SAR measurement can be either related to the temperature elevation in tissue by

$$SAR = C \left(\frac{\delta T}{\delta t} \right)$$

Where: C is the specific heat capacity, δT is the temperature rise and δt is the exposure duration, or related to the electrical field in the tissue by

$$SAR = \frac{\sigma \cdot E^2}{\rho}$$

Where: σ is the conductivity of the tissue, ρ is the mass density of the tissue and E is the RMS electrical field strength. However for evaluating SAR of low power transmitter, electrical field measurement is typically applied.



4 RF Exposure Limits

4.1 Uncontrolled Environment

Uncontrolled Environments are defined as locations where there is the exposure of individuals who have no knowledge or control of their exposure. The general population/uncontrolled exposure limits are applicable to situations in which the general public may be exposed or in which persons who are exposed as a consequence of their employment may not be made fully aware of the potential for exposure or cannot exercise control over their exposure. Members of the general public would come under this category when exposure is not employment-related; for example, in the case of a wireless transmitter that exposes persons in its vicinity.

4.2 Controlled Environment

Controlled Environments are defined as locations where there is exposure that may be incurred by persons who are aware of the potential for exposure, (i.e. as a result of employment or occupation). In general, occupational/controlled exposure limits are applicable to situations in which persons are exposed as a consequence of their employment, who have been made fully aware of the potential for exposure and can exercise control over their exposure. This exposure category is also applicable when the exposure is of a transient nature due to incidental passage through a location where the exposure levels may be higher than the general population/uncontrolled limits, but the exposed person is fully aware of the potential for exposure and can exercise control over his or her exposure by leaving the area or by some other appropriate means.

Limits for General Population/Uncontrolled Exposure (W/kg)

Type Exposure	Uncontrolled Environment Limit
Spatial Peak SAR (1g cube tissue for head and trunk)	1.6 W/kg
Spatial Peak SAR (10g cube tissue for limbs)	4.0 W/kg
Spatial Peak SAR (1g cube tissue for whole body)	0.08 W/kg

Note:

1. Occupational/Uncontrolled Environments are defined as locations where there is exposure that may be incurred by people who are aware of the potential for exposure (i.e. as a result of employment or occupation).
2. Whole-Body SAR is averaged over the entire body, partial-body SAR is averaged over any 1gram of tissue defined as a tissue volume in the shape of a cube. SAR for hands, wrists, feet and ankles is averaged over any 10 grams of tissue defined as a tissue volume in the shape of a cube.

5 Applied Reference Documents

Leading reference documents for testing:

Identity	Document Title	Method Determination /Remark
FCC 47CFR Part 2(2.1093)	Radio Frequency Radiation Exposure valuation: Portable Devices	No deviation
IEEE 1528-2013	IEEE Recommended Practice for Determining the Peak Spatial-Average Specific Absorption Rate (SAR) in the Human Head from Wireless Communications Devices: Measurement Techniques	No deviation
KDB 447498 D01v06	General RF Exposure Guidance	No deviation
KDB 248227 D01v02r02	SAR Measurement Procedures for 802.11 Transmitters	No deviation
KDB 616217 D04 v01r01	SAR Evaluation Considerations for Laptop, Notebook, Notebook and Tablet Computers	No deviation
KDB 865664 D01v01r04	SAR Measurement 100 MHz to 6 GHz	No deviation
KDB 865664 D02v01r02	RF Exposure Reporting	No deviation
KDB 941225 D06v02r01	SAR Evaluation Procedures For Portable Devices With Wireless Router Capabilities	No deviation
<p>Note 1: The test item is not applicable.</p> <p>Note 2: Additions to, deviation, or exclusions from the method shall be judged in the "method determination" column of add, deviate or exclude from the specific method shall be explained in the "Remark" of the above table.</p>		

6 SAR Measurement System




Fig.6.1 SPEAG DASY System Configurations

The DASY system for performance compliance tests is illustrated above graphically. This system consists of the following items:

- A standard high precision 6-axis robot with controller, a teach pendant and software.
- A data acquisition electronic (DAE) attached to the robot arm extension.
- A dosimetric probe equipped with an optical surface detector system.
- The electro-optical converter (EOC) performs the conversion between optical and electrical signals.
- A measurement server performs the time critical tasks such as signal filtering, control of the robot operation and fast movement interrupts.
- A probe alignment unit which improves the accuracy of the probe positioning.
- A computer operating Windows XP.
- DASY software.
- Remote control with teach pendant and additional circuitry for robot safety such as warning lamps, etc.
- The SAM twin phantom.
- A device holder.
- Tissue simulating liquid.

- Dipole for evaluating the proper functioning of the system.

Component details are described in the following sub-sections.

6.1 E-Field Probe

The SAR measurement is conducted with the dosimetric probe (manufactured by SPEAG). The probe is specially designed and calibrated for use in liquid with high permittivity. The dosimetric probe has special calibration in liquid at different frequency. This probe has a built in optical surface detection system to prevent from collision with phantom.

➤ E-Field Probe Specification

<EX3DV4 Probe>


Construction	Symmetrical design with triangular core Built-in shielding against static charges PEEK enclosure material (resistant to organic solvents, e.g., DGBE)	
Frequency	10 MHz to 6 GHz; Linearity: ± 0.2 dB	
Directivity	± 0.3 dB in HSL (rotation around probe axis) ± 0.5 dB in tissue material (rotation normal to probe axis)	
Dynamic Range	10 μ W/g to 100 mW/g; Linearity: ± 0.2 dB	
Dimensions	Overall length: 330 mm (Tip: 20 mm) Tip diameter: 2.5 mm (Body: 12 mm) Typical distance from probe tip to dipole centers: 1 mm	

Fig 6.2 Photo of EX3DV4

➤ E-Field Probe Calibration

Each probe needs to be calibrated according to a dosimetric assessment procedure with accuracy better than $\pm 10\%$. The spherical isotropy shall be evaluated and within ± 0.25 dB. The sensitivity parameters (Norm X, Norm Y and Norm Z), the diode compression parameter (DCP) and the conversion factor (ConvF) of the probe are tested. The calibration data can be referred to Annex E of this report.

6.2 Data Acquisition Electronics (DAE)

The Data acquisition electronics (DAE) consists of a highly sensitive electrometer-grade preamplifier with auto-zeroing, a channel and gain-switching multiplexer, a fast 16 bit AD-converter and a command decoder and control logic unit. Transmission to the measurement server is accomplished through an optical downlink for data and status information as well as an optical uplink for commands and the clock. The input impedance of the DAE is 200 MOhm; the inputs are symmetrical and floating. Common mode rejection is above 80 dB.




Fig 6.2 Photo of DAE

6.3 Robot

The SPEAG DASY system uses the high precision robots (DASY5: TX60XL) type from Stäubli SA (France). For the 6-axis controller system, the robot controller version (DASY5: CS8c) from Stäubli is used. The Stäubli robot series have many features that are important for our application:

- High precision (repeatability 0.02 mm)
- High reliability (industrial design)
- Low maintenance costs (virtually maintenance free due to direct drive gears; nobelt drives)
- Jerk-free straight movements
- Low ELF interference (motor control fields shielded via the closed metallic construction shields)



Fig. 6.3 Photo of Robot

6.4 Measurement Server

The measurement server is based on a PC/104 CPU board with CPU (DASY 5: 400MHz, Intel Celeron), chip-disk (DASY5: 128 MB), RAM (DASY5: 128 MB). The necessary circuits for communication with the DAE electronic box, as well as the 16 bit AD converter system for optical detection and digital I/O interface are contained on the DASY I/O board, which is directly connected to the PC/104 bus of the CPU board.

The measurement server performs all the real-time data evaluation for field measurements and surface detection, controls robot movements and handles safety operations.



Fig. 6.4 Photo of Server for DASYS5

6.5 Light Beam Unit

The light beam switch allows automatic "tooling" of the probe. During the process, the actual position of the probe tip with respect to the robot arm is measured, as well as the probe length and the horizontal probe offset. The software then corrects all movements, such that the robot coordinates are valid for the probe tip.

The repeatability of this process is better than 0.1 mm. If a position has been taught with an aligned probe, the same position will be reached with another aligned probe within 0.1 mm, even if the other probe has different dimensions. During probe rotations, the probe tip will keep its actual position.



Fig. 6.5 Photo of Light Beam

6.6 Phantom

<SAM Twin Phantom>

Shell Thickness	2 ± 0.2 mm (sagging: <1%) Center ear point: 6 ± 0.2 mm
Filling Volume Dimensions	Approx. 25 liters Length: 1000 mm; Width: 500 mm; Height: adjustable feet
Measurement Areas	Left Head, Right Head, Flat phantom




Fig. 6.6 Photo of SAM Phantom

The bottom plate contains three pair of bolts for locking the device holder. The device holder positions are adjusted to the standard measurement positions in the three sections. A white cover is provided to tap the phantom during off-periods to prevent water evaporation and changes in the

liquid parameters. On the phantom top, three reference markers are provided to identify the phantom position with respect to the robot.

6.7 Device Holder

<Device Holder for SAM Twin Phantom>

The SAR in the phantom is approximately inversely proportional to the square of the distance between the source and the liquid surface. For a source at 5 mm distance, a positioning uncertainty of ± 0.5 mm would produce a SAR uncertainty of ± 20 %. Accurate device positioning is therefore crucial for accurate and repeatable measurements. The positions in which the devices must be measured are defined by the standards.

The DASY device holder is designed to cope with different positions given in the standard. It has two scales for the device rotation (with respect to the body axis) and the device inclination (with respect to the line between the ear reference points). The rotation center for both scales is the ear reference point (ERP).

Thus the device needs no repositioning when changing the angles.

The DASY device holder is constructed of low-loss POM material having the following dielectric parameters: relative permittivity $\epsilon = 3$ and loss tangent $\delta = 0.02$. The amount of dielectric material has been reduced in the closest vicinity of the device, since measurements have suggested that the influence of the clamp on the test results could thus be lowered.

<Laptop Extension Kit>

The extension is lightweight and made of POM, acrylic glass and foam. It fits easily on the upper part of the mounting device in place of the phone positioned. The extension is fully compatible with the SAM Twin and ELI phantoms.



Fig 6.7 Device Holder




Fig 6.8 Laptop Extension Kit

6.8 Data storage and Evaluation

➤ Data Storage

The DASY software stores the assessed data from the data acquisition electronics as raw data (in microvolt readings from the probe sensors), together with all the necessary software parameters for the data evaluation (probe calibration data, liquid parameters and device frequency and modulation data) in measurement files. The post-processing software evaluates the desired unit and format for output each time the data is visualized or exported. This allows verifications of the complete software setup even after the measurement and allows correction of erroneous parameter settings. For example, if a measurement has been performed with an incorrect crest factor parameter in the device setup, the parameter can be corrected afterwards and the data can be reevaluated.

The measured data can be visualized or exported in different units or formats, depending on the selected probe type (e.g., [V/m], [mW/g]). Some of these units are not available in certain situations or give meaningless results, e.g., a SAR-output in a non-lose media, will always be zero. Raw data can also be exported to perform the evaluation with other software packages.

➤ Data Evaluation

The DASY post-processing software (SEMCAD) automatically executes the following procedures to calculate the field units from the microvolt readings at the probe connector. The parameters used in the evaluation are stored in the configuration modules of the software:

Probe Parameters:	- Sensitivity	Norm _i , a _{i0} , a _{i1} , a _{i2}
	- Conversion	ConvF _i
	- Diode compression point	dcp _i
Device Parameters:	- Frequency	f
	- Crest	cf
Media Parameters:	- Conductivity	σ
	- Density	ρ

These parameters must be set correctly in the software. They can be found in the component documents or they can be imported into the software from the configuration files issued for the DASY components. In the direct measuring mode of the multi-meter option, the parameters of the actual system setup are used. In the scan visualization and export modes, the parameters stored in the corresponding document files are used.

The first step of the evaluation is a linearization of the filtered input signal to account for the compression characteristics of the detector diode. The compensation depends on the input signal, the diode type and the DC-transmission factor from the diode to the evaluation electronics. If the

exciting field is pulsed, the crest factor of the signal must be known to correctly compensate for peak power.

The formula for each channel can be given as:

$$V_i = U_i + U_i^2 \cdot \frac{cf}{dcp_i}$$

With V_i = compensated signal of channel i, (i = x, y, z)

U_i = input signal of channel i, (i = x, y, z)

cf = crest factor of exciting field (DASY parameter)

dcpⁱ = diode compression point (DASY parameter)

From the compensated input signals, the primary field data for each channel can be evaluated:

$$\text{E- Field Probes: } E_i = \sqrt{\frac{V_i}{\text{Norm}_i \cdot \text{ConvF}}}$$

$$\text{H-Field Probes: } H_i = \sqrt{V_i} \cdot \frac{a_{i0} + a_{i1}f + a_{i2}f^2}{f}$$

With V_i = compensated signal of channel i, (i = x, y, z)

Norm_i = sensor sensitivity of channel i, (i = x, y, z), $\mu\text{V}/(\text{V/m})^2$

ConvF = sensitivity enhancement in solution

a_{ij} = sensor sensitivity factors for H-field probes

f = carrier frequency (GHz)

E_i = electric field strength of channel i in V/m

H_i = magnetic field strength of channel i in A/m

The RSS value of the field components gives the total field strength (Hermitian magnitude):

$$E_{\text{tot}} = \sqrt{E_x^2 + E_y^2 + E_z^2}$$

The primary field data are used to calculate the derived field units.

$$\text{SAR} = E_{\text{tot}}^2 \cdot \frac{\sigma}{\rho \cdot 1000}$$

With

SAR = local specific absorption rate in mW/g

E_{tot} = total field strength in V/m

σ = conductivity in (mho/m) or (Siemens/m)

ρ = equipment tissue density in g/cm³

Note that the density is set to 1, to account for actual head tissue density rather than the density of the tissue simulating liquid.



6.9 Test Equipment List

Manufacturer	Name of Equipment	Type/Model	Serial No./ SW Version	Calibration	
				Last Cal.	Due Date
SPEAG	750MHz System Validation Kit	D750V2	1173	2021.06.21	2024.06.20
SPEAG	900MHz System Validation Kit	D900V2	1d064	2021.12.17	2024.12.16
SPEAG	1800MHz System Validation Kit	D1800V2	2d158	2021.12.17	2024.12.16
SPEAG	2000MHz System Validation Kit	D2000V2	1050	2021.12.18	2024.12.17
SPEAG	2450MHz System Validation Kit	D2450V2	805	2021.12.17	2024.12.16
SPEAG	2600MHz System Validation Kit	D2600V2	1139	2021.06.25	2024.06.24
SPEAG	5000MHz System Validation Kit	D5GHzV2	1176	2021.12.19	2024.12.18
SPEAG	DOSIMETRIC ASSESSMENT SYSTEM	DASY52	52.10.4.1527	NCR	NCR
SPEAG	Dosimetric E-Field Probe	EX3DV4	3753	2021.07.26	2022.07.25
SPEAG	Dosimetric E-Field Probe	EX3DV4	7608	2022.01.12	2023.01.11
SPEAG	Data Acquisition Electronics	DAE4	480	2021.06.22	2022.06.21
SPEAG	SAM Twin Phantom 2	QD 000 P40 CB	TP-1464	NCR	NCR
SPEAG	Phone Positioner	N/A	N/A	NCR	NCR
Anritsu	Network Emulator	MT8820C	6200985414	2021.10.21	2022.10.20
Anritsu	Network Emulator	MT8821C	6261830572	2022.02.14	2023.02.13
Agilent	Network Analyzer	E5071B	MY42404762	2022.03.01	2023.02.28
Speag	Dielectric Assessment KIT	DAK-3.5	1279	2021.10.18	2022.10.17
mini-circuits	Amplifier	ZHL-42W+	608501717	NCR	NCR
Agilent	Signal Generator	N5182B	MY53050509	2022.01.07	2023.01.06
Agilent	Power Sensor	N8482A	MY41090849	2021.10.21	2022.10.20
Agilent	Power Meter	E4416A	MY45102093	2021.10.21	2022.10.20
Anritsu	Power Sensor	MA2411B	N/A	2021.10.21	2022.10.20
Anritsu	Power Meter	NRVD	101066	2021.10.21	2022.10.20
Agilent	Dual Directional Coupler	778D	50422	NA	NA
MCL	Attenuation	351-218-010	N/A	NA	NA
KTJ	Thermo meter	TA298	N/A	2021.12.21	2022.12.20
N/A	Tissue Simulating Liquids	HBBL600-10000V6		24H	

Note:

1. The calibration certificate of DASY can be referred to Annex F of this report.
2. Referring to KDB 865664 D01v01r04, the dipole calibration interval can be extended to 3 years with justification. The dipoles are also not physically damaged, or repaired during the interval.



3. The Insertion Loss calibration of Dual Directional Coupler and Attenuator were characterized via the network analyzer and compensated during system check.
4. The dielectric probe kit was calibrated via the network analyzer, with the specified procedure (calibrated in pure water) and calibration kit (standard) short circuit, before the dielectric measurement. The specific procedure and calibration kit are provided by Speag.
5. In system check we need to monitor the level on the power meter, and adjust the power amplifier level to have precise power level to the dipole; the measured SAR will be normalized to 1W input power according to the ratio of 1W to the input power to the dipole. For system check, the calibration of the power amplifier is deemed not critically required for correct measurement; the power meter is critical and we do have calibration for it
6. Attenuator insertion loss is calibrated by the network Analyzer, which the calibration is valid, before system check.
7. N.C.R means No Calibration Requirement.

7 Tissue Simulating Liquids

For the measurement of the field distribution inside the SAM phantom with DASY, the phantom must be filled with around 25 liters of homogeneous body tissue simulating liquid. For head SAR testing, the liquid height from the ear reference point (ERP) of the phantom to the liquid top surface is larger than 15 cm, which is shown in Fig. 7.1, for body SAR testing, the liquid height from the centre of the flat phantom to liquid top surface is larger than 15 cm, which is shown in Fig. 7.2.




Fig 7.1 Photo of Liquid Height for Head SAR



Fig 7.2 Photo of Liquid Height for Body SAR

The following table gives the recipes for tissue simulating liquids

Frequency (MHz)	Water (%)	Sugar (%)	Cellulose (%)	Salt (%)	Preventol (%)	DGBE (%)	Conductivity (σ)	Permittivity (ϵ_r)
Head								
750	41.1	57.0	0.2	1.4	0.2	0	0.89	41.9
835	40.3	57.9	0.2	1.4	0.2	0	0.90	41.5
1800,1900,2000	55.2	0	0	0.3	0	44.5	1.40	40.0
2450	55.0	0	0	0	0	45.0	1.80	39.2
2600	54.8	0	0	0.1	0	45.1	1.96	39.0

Simulating Liquid for 5GHz, Manufactured by SPEAG

Ingredients	(% by weight)
Water	64~78%
Mineral oil	11~18%
Emulsifiers	9~15%
Additives and Salt	2~3%



The relative permittivity and conductivity of the tissue material should be within $\pm 5\%$ of the values given in the table below recommended by the FCC OET 65 supplement C and RSS 102 Issue 5.

Target Frequency	Head		Body	
(MHz)	ϵ_r	σ (S/m)	ϵ_r	σ (S/m)
150	52.3	0.76	61.9	0.80
300	45.3	0.87	58.2	0.92
450	43.5	0.87	56.7	0.94
835	41.5	0.90	55.2	0.97
900	41.5	0.97	55.0	1.05
915	41.5	0.98	55.0	1.06
1450	40.5	1.20	54.0	1.30
1610	40.3	1.29	53.8	1.40
1800-2000	40.0	1.40	53.3	1.52
2450	39.2	1.80	52.7	1.95
3000	38.5	2.40	52.0	2.73
5800	35.3	5.27	48.2	6.00

(ϵ_r = relative permittivity, σ = conductivity and $\rho = 1000 \text{ kg/m}^3$)

The dielectric parameters of liquids were verified prior to the SAR evaluation using a Speag Dielectric Probe Kit and an Agilent Network Analyzer.

The following table shows the measuring results for simulating liquid.

Table 1: Dielectric Performance of Tissue Simulating Liquid

Frequency (MHz)	Tissue Type	Liquid Temp.(°C)	Conductivity (σ)	Conductivity Target (σ)	Delta (σ) (%)	Limit (%)	Date
750	HSL	22.1	0.912	0.89	2.47	± 5	2022.04.08
900	HSL	22.2	0.971	0.97	0.10	± 5	2022.04.18
1800	HSL	22.3	1.418	1.40	1.29	± 5	2022.05.07
2000	HSL	22.2	1.420	1.40	1.43	± 5	2022.04.20
2450	HSL	22.2	1.814	1.80	0.78	± 5	2022.04.22
2600	HSL	22.3	1.935	1.96	-1.28	± 5	2022.04.26
5250	HSL	22.1	4.865	4.71	3.29	± 5	2022.04.30
5750	HSL	22.1	5.170	5.22	-0.96	± 5	2022.05.10

Frequency (MHz)	Tissue Type	Liquid Temp.(°C)	Permittivity (ϵ_r)	Permittivity Target (ϵ_r)	Delta (ϵ_r) (%)	Limit (%)	Date
750	HSL	22.1	40.882	41.90	-2.43	± 5	2022.04.08
900	HSL	22.2	40.915	41.50	-1.41	± 5	2022.04.18
1800	HSL	22.3	40.030	40.00	0.08	± 5	2022.05.07
2000	HSL	22.2	40.770	40.00	1.93	± 5	2022.04.20



2450	HSL	22.2	39.573	39.20	0.95	±5	2022.04.22
2600	HSL	22.3	39.171	39.00	0.44	±5	2022.04.26
5250	HSL	22.1	37.178	35.95	3.42	±5	2022.04.30
5750	HSL	22.1	36.150	35.35	2.26	±5	2022.05.10

Note:

According to April 2019 TCB Workshop that FCC has permitted the use of single head-tissue simulating liquid specified in IEC 62209-1 for all SAR tests.

8 SAR System Verification

Each DASY system is equipped with one or more system validation kits. These units, together with the predefined measurement procedures within the DASY software, enable the user to conduct the system performance check and system validation. System validation kit includes a dipole, tripod holder to fix it underneath the flat phantom and a corresponding distance holder.

➤ System Validation

According to FCC KDB 865664 D02, SAR system verification is required to confirm measurement accuracy. The SAR systems (including SAR probes, system components and software versions) used for this device were validated against its performance specifications prior to the SAR measurements. Reference dipoles are used with the required tissue-equivalent media for system validation, according to the procedures outlined in FCC KDB 865664 D01 and IEEE 1528-2013. Since SAR probe calibrations are frequency dependent, each probe calibration point must be validated at a frequency within the valid frequency range of the probe calibration point, using the system that normally operates with the probe for routine SAR measurements and according to the required tissue-equivalent media. A tabulated summary of the system validation status, measurement frequencies, SAR probes, calibrated signal type(s) and tissue dielectric parameters has been included.

➤ Purpose of System Performance check

The system performance check verifies that the system operates within its specifications. System and operator errors can be detected and corrected. It is recommended that the system performance check be performed prior to any usage of the system in order to guarantee reproducible results. The system performance check uses normal SAR measurements in a simplified setup with a well characterized source. This setup was selected to give a high sensitivity to all parameters that might fail or vary over time. The system check does not intend to replace the calibration of the components, but indicates situations where the system uncertainty is exceeded due to drift or failure.

➤ System Setup

In the simplified setup for system evaluation, the EUT is replaced by a calibrated dipole and the power source is replaced by a continuous wave that comes from a signal generator. The calibrated dipole must be placed beneath the flat phantom section of the SAM twin phantom with the correct distance holder. The distance holder should touch the phantom surface with a light pressure at the reference marking and be oriented parallel to the long side of the phantom. The equipment setup is shown below:




Fig 8.1 Photo of Dipole Setup Evaluation




Fig 8.2 System Setup for System Evaluation

➤ System Verification Results

Comparing to the original SAR value provided by SPEAG, the verification data should be within its specification of 10%. Below table shows the target SAR and measured SAR after normalized to 1W input power. The table as below indicates the system performance check can meet the variation criterion and the plots can be referred to Annex C of this report.

Dipole S/N	Probe S/N	DAE S/N
D750V3-1173	7608	480
D900V2-1d064	7608	480
D1800V2-2d158	7608	480
D2000V2-1050	7608	480
D2450V2-805	7608	480
D2600V2-1139	7608	480
D5GHzV2-1176-5250	7608	480
D5GHzV2-1176-5750	3753	480



Frequency (MHz)	Tissue Type	Conductivity (σ)	Permittivity (ϵ_r)	CW Signal Validation		
				Sensitivity	Probe Linearity	Probe Isotropy
750	HSL	0.851	42.43	PASS	PASS	PASS
835	HSL	0.898	41.88	PASS	PASS	PASS
1750	HSL	1.386	39.91	PASS	PASS	PASS
1800	HSL	1.449	41.26	PASS	PASS	PASS
1900	HSL	1.435	39.65	PASS	PASS	PASS
2000	HSL	1.451	39.42	PASS	PASS	PASS
2300	HSL	1.764	38.99	PASS	PASS	PASS
2450	HSL	1.863	38.85	PASS	PASS	PASS
2600	HSL	1.973	38.58	PASS	PASS	PASS
5250	HSL	4.528	35.32	PASS	PASS	PASS
5600	HSL	4.905	34.89	PASS	PASS	PASS
5750	HSL	5.077	34.28	PASS	PASS	PASS

Frequency (MHz)	Tissue Type	Conductivity (σ)	Permittivity (ϵ_r)	Modulation Signal Validation		
				Mod. Type	Duty Factor	PAR
750	HSL	0.851	42.43	N/A	N/A	N/A
835	HSL	0.898	41.88	GMSK	PASS	N/A
1750	HSL	1.386	39.91	N/A	N/A	N/A
1800	HSL	1.449	41.26	N/A	N/A	N/A
1900	HSL	1.435	39.65	GMSK	PASS	N/A
2000	HSL	1.451	39.42	GMSK	PASS	N/A
2300	HSL	1.764	38.99	OFDM	PASS	PASS
2450	HSL	1.863	38.85	OFDM	PASS	PASS
2600	HSL	1.973	38.58	TDD	PASS	N/A
5250	HSL	4.528	35.32	OFDM	N/A	PASS
5600	HSL	4.905	34.89	OFDM	N/A	PASS
5750	HSL	5.077	34.28	OFDM	N/A	PASS



<Validation Results>

Date	Freq. (MHz)	Tissue Type	Input Power (mW)	Measured 1g SAR (W/kg)	Targeted 1g SAR (W/kg)	Normalized 1g SAR (W/kg)	Deviation (%)
2022.04.08	750	HSL	250	2.11	8.26	8.44	2.18
2022.04.18	900	HSL	250	2.76	11.20	11.04	-1.43
2022.05.07	1800	HSL	250	10.02	39.20	40.08	2.24
2022.04.20	2000	HSL	250	10.54	41.60	42.16	1.35
2022.04.22	2450	HSL	250	12.79	52.30	51.16	-2.18
2022.04.26	2600	HSL	250	13.44	54.00	53.76	-0.44
2022.04.30	5250	HSL	100	7.56	76.70	75.6	-1.43
2022.05.10	5750	HSL	100	7.72	78.70	77.2	-1.91

Date	Freq. (MHz)	Tissue Type	Input Power (mW)	Measured 1g SAR (W/kg)	Targeted 1g SAR (W/kg)	Normalized 1g SAR (W/kg)	Deviation (%)
2022.04.08	750	HSL	250	1.36	5.45	5.44	-0.18
2022.04.18	900	HSL	250	1.83	7.19	7.32	1.81
2022.05.07	1800	HSL	250	5.17	20.10	20.68	2.89
2022.04.20	2000	HSL	250	5.31	20.70	21.24	2.61
2022.04.22	2450	HSL	250	5.96	23.90	23.84	-0.25
2022.04.26	2600	HSL	250	6.09	24.50	24.36	-0.57
2022.04.30	5250	HSL	100	2.17	22.10	21.7	-1.81
2022.05.10	5750	HSL	100	2.27	22.50	22.7	0.89

Note: System checks the specific test data please see Annex C.

9 EUT Testing Position

This EUT was tested in six different positions. They are right cheek/right tilted/left cheek/left tilted for head, Front/Back of the EUT with phantom 15 mm gap, as illustrated below, please refer to Annex B for the test setup photos.

9.1 Body-Supported Device Configurations

According to KDB 616217 section 4.3, SAR should be separately assessed with each surface and separation distance positioned against the flat phantom that correspond to the intended use as specified by the manufacturer. The antennas in tablets are typically located near the back (bottom) surface and/or along the edges of the devices; therefore, SAR evaluation is required for these configurations. Exposures from antennas through the front (top) surface of the display section of a full-size tablet, away from the edges, are generally limited to the user's hands. Exposures to hands for typical consumer transmitters used in tablets are not expected to exceed the extremity SAR limit; therefore, SAR evaluation for the front surface of tablet display screens are generally not necessary, except for tablets that are designed to require continuous operations with the hand(s) next to the antenna(s).

- To position the device parallel to the phantom surface with either keypad up or down.
- To adjust the device parallel to the flat phantom.
- To adjust the distance between the device surface and the flat phantom to 0 mm.
- When each surface is measurement, the SAR Test Exclusion Threshold in KDB 447498 should be applied.




Fig.9.1 Illustration for Body Position

9.2 Wireless Router (Hotspot) Configurations

Some battery-operated handsets have the capability to transmit and receive internet connectivity through simultaneous transmission of WIFI in conjunction with a separate licensed transmitter. The FCC has provided guidance in KDB Publication 941225 D06 where SAR test considerations for handsets ($L \times W \geq$

9 cm x 5 cm) are based on a composite test separation distance of 10 mm from the front, back and edges of the device with antennas 2.5 cm or closer to the edge of the device, determined from general mixed use conditions for this type of devices. Since the hotspot SAR results may overlap with the body-worn accessory SAR requirements, the more conservative configurations can be considered, thus excluding some body-worn accessory SAR tests.

When the user enables the personal wireless router functions for the handset, actual operations include simultaneous transmission of both the WIFI transmitter and another licensed transmitter. Both transmitters often do not transmit at the same transmitting frequency and thus cannot be evaluated for SAR under actual use conditions. Therefore, SAR must be evaluated for each frequency transmission and mode separately and summed with the WIFI transmitter according to KDB 648474 publication procedures. The “Portable Hotspot” feature on the handset was NOT activated, to ensure the SAR measurements were evaluated for a single transmission frequency RF signal.




Fig.9.2 Illustration for Hotspot Position

10 Measurement Procedures

The measurement procedures are as follows:

<Conducted power measurement>

- For WWAN power measurement, use base station simulator to configure EUT WWAN transition in conducted connection with RF cable, at maximum power in each supported wireless interface and frequency band.
- Read the WWAN RF power level from the base station simulator.
- For WLAN/BT power measurement, use engineering software to configure EUT WLAN/BT continuously transmission, at maximum RF power in each supported wireless interface and frequency band.
- Connect EUT RF port through RF cable to the power meter or spectrum analyzer, and measure WLAN/BT output power.

<Conducted power measurement>

- Use base station simulator to configure EUT WWAN transmission in radiated connection, and engineering software to configure EUT WLAN/BT continuously transmission, at maximum RF power, in the highest power channel.
- Place the EUT in positions as Annex B demonstrates.
- Set scan area, grid size and other setting on the DASY software.
- Measure SAR results for the highest power channel on each testing position.
- Find out the largest SAR result on these testing positions of each band.
- Measure SAR results for other channels in worst SAR testing position if the Reported SAR or highest power channel is larger than 0.8 W/kg.

According to the test standard, the recommended procedure for assessing the peak spatial-average SAR value consists of the following steps:

- Power reference measurement.
- Area scan.
- Zoom scan.
- Power drift measurement.

10.1 Spatial Peak SAR Evaluation

The procedure for spatial peak SAR evaluation has been implemented according to the test standard. It can be conducted for 1g and 10g, as well as for user-specific masses. The DASY software includes all numerical procedures necessary to evaluate the spatial peak SAR value.

The base for the evaluation is a “cube” measurement. The measured volume must include the 1g and 10 g cubes with the highest averaged SAR values. For that purpose, the center of the measured volume is aligned to the interpolated peak SAR value of a previously performed area scan.

The entire evaluation of the spatial peak values is performed within the post-processing engine (SEMCAD). The system always gives the maximum values for 1g and 10g cubes. The algorithm to find the cube with highest averaged SAR is divided into the following stages:

- Extraction of the measured data (grid and values) from the Zoom Scan.
- Calculation of the SAR value at every measurement point based on all stored data (A/D values and measurement parameters).
- Generation of a high-resolution mesh within the measured volume.
- Interpolation of all measured values from the measurement grid to the high-resolution grid
- Extrapolation of the entire 3-D field distribution to the phantom surface over the distance from sensor to surface
- Calculation of the averaged SAR within masses of 1g and 10g.

10.2 Power Reference Measurement

The Power Reference Measurement and Power Drift Measurement are for monitoring the power drift of the device under test in the batch process. The minimum distance of probe sensors to surface determines the closest measurement point to phantom surface. This distance cannot be smaller than the distance of sensor calibration points to probe tip as defined in the probe properties.

10.3 Area Scan Procedures

Area scans are defined prior to the measurement process being executed with a user defined variable spacing between each measurement point (integral) allowing low uncertainty measurements to be conducted. Scans defined for FCC applications utilize a 10mm^2 step integral, with 1mm interpolation used to locate the peak SAR area used for zoom scan assessments.



When an Area Scan has measured all reachable points, it computes the field maxima found in the scanned area, within a range of the global maximum. The range (in dB) is specified in the standards for compliance testing.

10.4 Zoom Scan Procedures

Zoom Scans are used to assess the peak spatial SAR values within a cubic averaging volume containing 1 g and 10 g of simulated tissue. A density of 1000 kg/m^3 is used to represent the head and body tissue density and not the phantom liquid density, in order to be consistent with the definition of the liquid dielectric properties, i.e. the side length of the 1g cube is 10mm, with the side length of the 10 g cube 21,5mm. The zoom scan integer steps can be user defined so as to reduce uncertainty, but normal practice for typical test applications utilize a physical step of 5x5x7 (8mmx8mmx5mm) providing a volume of 32mm in the X & Y axis, and 30mm in the Z axis.

10.5 SAR Averaged Methods

In DASY, the interpolation and extrapolation are both based on the modified Quadratic Sheppard's method. The interpolation scheme combines a least-square fitted function method and a weighted average method which are the two basic types of computational interpolation and approximation.

Extrapolation routines are used to obtain SAR values between the lowest measurement points and the inner phantom surface. The extrapolation distance is determined by the surface detection distance and the probe sensor offset. The uncertainty increases with the extrapolation distance. To keep the uncertainty within 1% for the 1g and 10g cubes, the extrapolation distance should not be larger than 5 mm.

10.6 Power Drift Monitoring

All SAR testing is under the EUT install full charged battery and transmit maximum output power. In DASY measurement software, the power reference measurement and power drift measurement procedures are used for monitoring the power drift of EUT during SAR test. Both these procedures measure the field at a specified reference position before and after the SAR testing. The software will calculate the field difference in dB. If the power drifts more than 5%, the SAR will be retested.



11 SAR Test Configuration

<GSM Mode>

A summary of these settings are illustrated below:

For GSM850 frequency band, the power control is set to 5 for GSM/GPRS mode (GSMK-CS1) and set to 8 for EDGE mode (MCS5); For GSM1900 frequency band, the power control is set to 0 for GSM/GPRS mode (GSMK-CS1) and set to 2 for EDGE mode (MCS5).

1. Per KDB 447498 D01v06, the maximum output power channel is used for SAR testing and for further SAR test reduction.
2. Per KDB 941225 D01v03r01, SAR test reduction for GSM / GPRS / EDGE modes is determined by the source-based time-averaged output power including tune-up tolerance. The mode with highest specified time-averaged output power should be tested for SAR compliance in the applicable exposure conditions. For modes with the same specified maximum output power and tolerance, the higher number time-slot configuration should be tested. Therefore, the GPRS (4Tx slots) for GSM850/GSM1900 is considered as the primary mode.
3. Other configurations of GSM / GPRS / EDGE are considered as secondary modes.

Timeslot consignations:

Remark:

1. The frame-averaged power is linearly reported the maximum burst averaged power over 8 time slots. The calculated method are shown as below:

The duty cycle "x" of different time slots as below:

1 TX slot is 1/8, 2 TX slots is 2/8, 3 TX slots is 3/8 and 4 TX slots is 4/8

Based on the calculation formula:

Frame-averaged power = Burst averaged power + 10 log (x)

So,

Frame-averaged power (1 TX slot) = Burst averaged power (1 TX slot)– 9.03

Frame-averaged power (2 TX slots) = Burst averaged power (2 TX slots)– 6.02

Frame-averaged power (3 TX slots) = Burst averaged power (3 TX slots)– 4.26

Frame-averaged power (4 TX slots) = Burst averaged power (4 TX slots) – 3.01

2. CS1 coding scheme was used in GPRS conducted power measurements and SAR testing, MCS5 coding scheme was used in EGPRS conducted power measurements and SAR testing (if necessary).

No. of Slots	Slot 1	Slot 2	Slot 3	Slot 4
Slot Consignation	1Up 4Down	2Up 3Down	3Up 2Down	4Up 1Down
Duty Cycle	1:8.3	1:4.15	1:2.77	1:2.08
Correct Factor	-9.03dB	-6.02dB	-4.26dB	-3.01dB

<WCDMA Mode>

Summary of UMTS conducted power measurement:

1. The 3G SAR test reduction procedure is applied, when the maximum output power and tune-up tolerance specified for production units in a secondary mode is $\leq \frac{1}{4}$ dB higher than the primary mode, SAR measurement is not required for the secondary mode.
2. The following tests were conducted according to the test requirements outlines in 3GPP TS 34.121 specification.
3. The procedures in KDB 941225 D01v03r01 are applied for 3GPP Rel. 6 HSPA to configure the device in the required sub-test mode(s) to determine SAR test exclusion.
4. For HSPA+ devices supporting 16 QAM in the uplink, power measurements procedure is according to the configurations in Table C.11.1.4 of 3GPP TS 34.121-1.
5. Per KDB 941225 D01v03r01, RMC 12.2kbps setting is used to evaluate SAR. The maximum output power and tune-up tolerance specified for production units in HSDPA / HSUPA / DC-HSDPA / HSPA+ is $\leq \frac{1}{4}$ dB higher than RMC 12.2Kbps or when the highest reported SAR of the RMC12.2Kbps is scaled by the ratio of specified maximum output power and tune-up tolerance of HSDPA / HSUPA / DC-HSDPA / HSPA+ to RMC12.2Kbps and the adjusted SAR is ≤ 1.2 W/kg, SAR measurement is not required for HSDPA / HSUPA / DC-HSDPA / HSPA+, and according to the following RF output power, the output power results of the secondary modes (HSDPA / HSUPA / DC-HSDPA / HSPA+) are less than $\frac{1}{4}$ dB higher than the primary modes; therefore, SAR measurement is not required for HSDPA / HSUPA / DC-HSDPA / HSPA+.
6. A fixed level power reduction is applied for WCDMA Band II when handset open Hotspot mode, the power reduction triggered.

HSDPA Setup Configuration

Sub-test	β_c	β_d	β_d (SF)	β_c/β_d	$\beta_{hs}^{(2)}$	CM (dB) ⁽²⁾
1	2/15	15/15	64	2/15	4/15	0.0
2	12/15 ⁽³⁾	15/15 ⁽³⁾	64	12/15 ⁽³⁾	24/15	1.0
3	15/15	8/15	64	15/8	30/15	1.5
4	15/15	4/15	64	15/4	30/15	1.5

Note 1: Δ_{ACK} , Δ_{NACK} and $\Delta_{CQI} = 8 \Leftrightarrow A_{hs} = \beta_{hs}/\beta_c = 30/15 \Leftrightarrow \beta_{hs} = 30/15 * \beta_c$
Note 2: CM = 1 for $\beta_c/\beta_d = 12/15$, $\beta_{hs}/\beta_c = 24/15$.
Note 3: For subtest 2 the β_c/β_d ratio of 12/15 for the TFC during the measurement period (TF1, TF0) is achieved by setting the signaled gain factors for the reference TFC (TF1, TF1) to $\beta_c = 11/15$ and $\beta_d = 15/15$.

HSUPA Setup Configuration

Sub-test	β_c	β_d	β_d (SF)	β_c/β_d	$\beta_{hs}^{(1)}$	β_{ec}	β_{ed}	β_{ed} (SF)	β_{ed} (codes)	CM ⁽²⁾ (dB)	MPR (dB)	AG ⁽⁴⁾ Index	E-TFCI
1	11/15 ⁽³⁾	15/15 ⁽³⁾	64	11/15 ⁽³⁾	22/15	209/225	1039/225	4	1	1.0	0.0	20	75
2	6/15	15/15	64	6/15	12/15	12/15	94/75	4	1	3.0	2.0	12	67
3	15/15	9/15	64	15/9	30/15	30/15	$\beta_{ed1}: 47/15$ $\beta_{ed2}: 47/15$	4	2	2.0	1.0	15	92
4	2/15	15/15	64	2/15	4/15	2/15	56/75	4	1	3.0	2.0	17	71
5	15/15 ⁽⁴⁾	15/15 ⁽⁴⁾	64	15/15 ⁽⁴⁾	30/15	24/15	134/15	4	1	1.0	0.0	21	81

Note 1: Δ_{ACK} , Δ_{NACK} and $\Delta_{CQI} = 8 \Leftrightarrow A_{hs} = \beta_{hs}/\beta_c = 30/15 \Leftrightarrow \beta_{hs} = 30/15 * \beta_c$.

Note 2: CM = 1 for $\beta_c/\beta_d = 12/15$, $\beta_{hs}/\beta_c = 24/15$. For all other combinations of DPDCH, DPCCH, HS-DPCCH, E-DPDCH and E-DPCCH the MPR is based on the relative CM difference.

Note 3: For subtest 1 the β_c/β_d ratio of 11/15 for the TFC during the measurement period (TF1, TF0) is achieved by setting the signaled gain factors for the reference TFC (TF1, TF1) to $\beta_c = 10/15$ and $\beta_d = 15/15$.

Note 4: For subtest 5 the β_c/β_d ratio of 15/15 for the TFC during the measurement period (TF1, TF0) is achieved by setting the signaled gain factors for the reference TFC (TF1, TF1) to $\beta_c = 14/15$ and $\beta_d = 15/15$.

Note 5: Testing UE using E-DPDCH Physical Layer category 1 Sub-test 3 is not required according to TS 25.306 Table 5.1g.

Note 6: β_{ed} cannot be set directly; it is set by Absolute Grant Value.

HSPA+ 3GPP release 7 (uplink category 7) 16QAM, Setup Configuration:

Table C.11.1.4: β values for transmitter characteristics tests with HS-DPCCH and E-DCH with 16QAM

Sub-test	β_c (Note 3)	β_d	β_{hs} (Note 1)	β_{ec}	β_{ed} (2xSF2) (Note 4)	β_{ed} (2xSF4) (Note 4)	CM (dB) (Note 2)	MPR (dB) (Note 2)	AG Index (Note 4)	E-TFCI (Note 5)	E-TFCI (boost)
1	1	0	30/15	30/15	$\beta_{ed1}: 30/15$ $\beta_{ed2}: 30/15$	$\beta_{ed3}: 24/15$ $\beta_{ed4}: 24/15$	3.5	2.5	14	105	105

Note 1: Δ_{ACK} , Δ_{NACK} and $\Delta_{CQI} = 30/15$ with $\beta_{hs} = 30/15 * \beta_c$.

Note 2: CM = 3.5 and the MPR is based on the relative CM difference, MPR = MAX(CM-1,0).

Note 3: DPDCH is not configured, therefore the β_c is set to 1 and $\beta_d = 0$ by default.

Note 4: β_{ed} can not be set directly; it is set by Absolute Grant Value.

Note 5: All the sub-tests require the UE to transmit 2SF2+2SF4 16QAM EDCH and they apply for UE using E-DPDCH category 7. E-DCH TTI is set to 2ms TTI and E-DCH table index = 2. To support these E-DCH configurations DPDCH is not allocated. The UE is signaled to use the extrapolation algorithm.

DC-HSDPA Setup Configuration

The following tests were completed according to procedures in section 7.3.13 of 3GPP TS34.108 v9.5.0. A summary of these settings are illustrated below:

Downlink Physical Channels are set as per 3GPP TS34.121-1 v9.0.0 E.5.

Table E.5.0: Levels for HSDPA connection setup


Parameter During Connection setup	Unit	Value
P-CPICH_Ec/Ior	dB	-10
P-CCPCH and SCH_Ec/Ior	dB	-12
PICH_Ec/Ior	dB	-15
HS-PDSCH	dB	off
HS-SCCH_1	dB	off
DPCH_Ec/Ior	dB	-5
OCNS_Ec/Ior	dB	-3.1

Call is set up as per 3GPP TS34.108 v9.5.0 sub clause 7.3.13

The configurations of the fixed reference channels for HSDPA RF tests are described in 3GPP TS 34.121, annex C for FDD and 3GPP TS 34.122.

Table C.8.1.12: Fixed Reference Channel H-Set 12

Parameter	Unit	Value
Nominal Avg. Inf. Bit Rate	kbps	60
Inter-TTI Distance	TTI's	1
Number of HARQ Processes	Processes	6
Information Bit Payload (N_{INF})	Bits	120
Number Code Blocks	Blocks	1
Binary Channel Bits Per TTI	Bits	960
Total Available SML's in UE	SML's	19200
Number of SML's per HARQ Proc.	SML's	3200
Coding Rate		0.15
Number of Physical Channel Codes	Codes	1
Modulation		QPSK
<p>Note 1: The RMC is intended to be used for DC-HSDPA mode and both cells shall transmit with identical parameters as listed in the table.</p> <p>Note 2: Maximum number of transmission is limited to 1, i.e., retransmission is not allowed. The redundancy and constellation version 0 shall be used.</p>		


Figure C.8.19: Coding rate for Fixed reference Channel H-Set 12 (QPSK)



<LTE Mode>

LTE Target MPR level

The device implements maximum power reduction per 3GPP 36.101 requirements where the MPR target is as below table. The MPR settings are implemented configured into firmware and cannot be disabled by the end user or LTE carrier network.

Modulation	el bandwidth / Transmission bandwidth configuration [RB]						MPR	3GPP
	1.4	3.0	5	10	15	20	Target	
	MHz	MHz					(dB)	
QPSK	> 5	> 4	> 8	> 12	> 16	> 18	1	≤ 1
16 QAM	≤ 5	≤ 4	≤ 8	≤ 12	≤ 16	≤ 18	1	≤ 1
64 QAM	> 5	> 4	> 8	> 12	> 16	> 18	2	≤ 2

Note: The measurement result showed some difference from the target MPR level, due to expected 0.5dB measurement tolerance

LTE Bands

LTE Bands	el bandwidth / Transmission bandwidth configuration [RB]					
	1.4	3.0	5	10	15	20
	MHz	MHz	MHz	MHz	MHz	MHz
2	✓	✓	✓	✓	✓	✓
4	✓	✓	✓	✓	✓	✓
5	✓	✓	✓	✓	N/A	N/A
12	✓	✓	✓	✓	N/A	N/A
25	✓	✓	✓	✓	✓	✓
26	✓	✓	✓	✓	✓	N/A
41	N/A	N/A	✓	✓	✓	✓
66	✓	✓	✓	✓	✓	✓
71	N/A	N/A	✓	✓	✓	✓

Note:

1. Per KDB 941225 D05v02r05, when a properly configured base station simulator is used for the SAR and power measurements, spectrum plots for each RB allocation and offset configuration is not required.
2. Per KDB 941225 D05v02r05, start with the largest channel bandwidth and measure SAR for QPSK with 1 RB allocation, using the RB offset and required test channel combination with the highest maximum output power for RB offsets at the upper edge, middle and lower edge of each required test channel.
3. Per KDB 941225 D05v02r05, 50% RB allocation for QPSK SAR testing follows 1RB QPSK allocation procedure.
4. Per KDB 941225 D05v02r05, for QPSK with 100% RB allocation, SAR is not required when the

highest maximum output power for 100 % RB allocation is less than the highest maximum output power in 50% and 1 RB allocations and the highest reported SAR for 1 RB and 50% RB allocation are ≤ 0.8 W/kg. Otherwise, SAR is measured for the highest output power channel; and if the reported SAR is > 1.45 W/kg, the remaining required test channels must also be tested.

5. Per KDB 941225 D05v02r05, 16QAM/64QAM output power for each RB allocation configuration is $>$ not $\frac{1}{2}$ dB higher than the same configuration in QPSK and the reported SAR for the QPSK configuration is ≤ 1.45 W/kg; Per KDB941225 D05v02r05, 16QAM/64QAM SAR testing is not required.
6. Per KDB 941225 D05v02r05, smaller bandwidth output power for each RB allocation configuration is $>$ not $\frac{1}{2}$ Db higher than the same configuration in the largest supported bandwidth, and the reported SAR for the largest supported band width is ≤ 1.45 W/kg; Per KDB 941225 D05v02r05, smaller bandwidth SAR testing is not required.
7. For LTE B4 / B5 / B7 / B17 the maximum bandwidth does not support three non-overlapping channels, per KDB941225 D05v02r05, when a device supports overlapping channel assignment in a channel bandwidth configuration, the middle channel of the group of overlapping channels should be selected for testing.
8. LTE band 2 / 12 SAR test was covered by Band 25 / 17; according to April 2015 TCB workshop, SAR test for overlapping LTE bands can be reduced if
 - a. The maximum output power, including tolerance, for the smaller band is \leq the larger band to qualify for the SAR test exclusion.
 - b. The channel bandwidth and other operating parameters for the smaller band are fully supported by the larger band.
9. According to 2017 TCB workshop, for 64 QAM and 16 QAM should be verified by checking the signal constellation with a call box to avoid incorrect maximum power levels due to MPR and other requirements associated with signal modulation, and the following figure is taken from the "Fundamental Measurement >> Modulation Analysis >>constellation" mode of the device connect to the CMW500 base station, therefore, the device 64QAM and 16QAMsignal modulation are correct. Identify if Maximum Power Reduction (MPR) is optional or mandatory, i.e. built-in by design: only mandatory MPR may be considered during SAR testing, when the maximum output power is permanently limited by the MPR implemented within the UE; and only for the applicable RB (resource block) configurations specified in LTE standards: b) A-MPR (additional MPR) must be disabled.
10. Per KDB 447498 D01v06, the reported SAR is the measured SAR value adjusted for maximum tune-up tolerance.
 - a. Tune-up scaling Factor = tune-up limit power (mW) / EUT RF power (mW), where tune-up limit is the maximum rated power among all production units.
 - b. For SAR testing of WLAN signal with non-100% duty cycle, the measured SAR is scaled-up by the duty cycle scaling factor which is equal to " $1/(\text{duty cycle})$ "

- c. For WWAN: Reported SAR(W/kg)= Measured SAR(W/kg)*Tune-up Scaling Factor
 - d. For WLAN/Bluetooth: Reported SAR(W/kg)= Measured SAR(W/kg)* Duty Cycle scaling factor * Tune-up scaling factor
 - e. For TDD LTE SAR measurement, the duty cycle 1:1.59 (62.9 %) was used perform testing and considering the theoretical duty cycle of 63.3% for extended cyclic prefix in the uplink, and the theoretical duty cycle of 62.9% for normal cyclic prefix in uplink, a scaling factor of extended cyclic prefix $63.3\%/62.9\% = 1.006$ is applied to scale-up the measured SAR result. The Reported TDD LTE SAR = measured SAR (W/kg)* Tune-up Scaling Factor* scaling factor for extended cyclic prefix.
11. Per KDB 447498 D01v06, for each exposure position, testing of other required channels within the operating mode of a frequency band is not required when the reported 1-g or 10-g SAR for the mid-band or highest output power channel is: ≤ 0.8 W/kg or 2.0 W/kg, for 1-g or 10-g respectively, when the transmission band is ≤ 100 MHz ≤ 0.6 W/kg or 1.5 W/kg, for 1-g or 10-g respectively, when the transmission band is between 100 MHz and 200 MHz ≤ 0.4 W/kg or 1.0 W/kg, for 1-g or 10-g respectively, when the transmission band is ≥ 200 MHz
12. Per KDB 865664 D01v01r04, for each frequency band, repeated SAR measurement is required only when the measured SAR is ≥ 0.8 W/kg.
13. Per KDB 648474 D04v01r03, when the reported SAR for a body-worn accessory measured without a headset connected to the handset is ≤ 1.2 W/kg, SAR testing with a headset connected to the handset is not required.

<WLAN 2.4GHz>

1. SAR is measured for 2.4 GHz 802.11b DSSS using either the fixed test position or, when applicable, the initial test position procedure. SAR test reduction is determined according to the following:
 - a. When the reported SAR of the highest measured maximum output power channel for the exposure configuration is ≤ 0.8 W/kg, no further SAR testing is required for 802.11b DSSS in that exposure configuration.
 - b. When the reported SAR is > 0.8 W/kg, SAR is required for that position using the next highest measured output power channel. When any reported SAR is > 1.2 W/kg, SAR is required for the third channel; i.e., all channels require testing.
2. 2.4 GHz 802.11 g/n OFDM are additionally evaluated for SAR if the highest reported SAR for 802.11b, adjusted by the ratio of the OFDM to DSSS specified maximum output power, is > 1.2 W/kg. When SAR is required for OFDM modes in 2.4 GHz band, the Initial Test configuration Procedures should be followed.
3. For held-to-ear and hotspot operations, the initial test position procedures were applied. The test position with the highest extrapolated peak SAR will be used as the initial test position. When reported SAR for the initial test position is ≤ 0.4 W/kg, no additional testing for the remaining test positions was required. Otherwise, SAR is evaluated at the subsequent highest peak SAR positions until the reported SAR result is ≤ 0.8 W/kg or all test positions are



measured.

4. Justification for test configurations for WLAN per KDB Publication 248227 D02DR02-41929 for 2.4 GHz WI-FI single transmission chain operations, the highest measured maximum output power channel for DSSS was selected for SAR measurement. SAR for OFDM modes (2.4 GHz 802.11g/n) was not required due to the maximum allowed powers and the highest reported SAR.
5. A fixed level power reduction is applied for WiFi when handset operates "held to the body" condition or "held to the ear" condition, the power reduction triggered by audio receiver detection and call establish status.
6. Per KDB 248227 D01v02r02, In the 2.4 GHz band, separate SAR procedures are applied to DSSS and OFDM configurations to simplify DSSS test requirements. SAR is not required for the following 2.4 GHz OFDM conditions:
 - a. When KDB Publication 447498 SAR test exclusion applies to the OFDM configuration.
 - b. When the highest reported SAR for DSSS is adjusted by the ratio of OFDM to DSSS specified maximum output power and the adjusted SAR is ≤ 1.2 W/kg.

12 Conducted Output Power

Remark: The output power of GSM/WCDMA/LTE/WLAN/Bluetooth refers to the annex E of this report.

13 LTE Carrier Aggregation

13.1 LTE Uplink Carrier Aggregation

➤ Carrier Aggregation Configuration

<Intra-band>

2CC Uplink Carrier Aggregation for Intra-band				
No.	Combination	MIMO	Restriction	Completely Covered by Measurement Superset
1	CA_41C	41C	-	No

Note:

1. According to the 3GPP 36.101 table 6.2.2A-1 specifics that the aggregation maximum allowed output power is equivalent to the signal carrier scenario for intra-band contiguous carrier aggregation scenarios. When the non-contiguous RB allocation is applied the MPR shell complies with the table 6.2.3A defined in 3GPP 36.101.
2. According to the TCB Workshop publication, the output power of uplink CA would be measured with the wideband signal integration over the component carriers. And SAR measurement would be performed at the worst exposure condition of each band.
3. Additional SAR measurement for LTE UL CA with other DL CA combinations are not required when the maximum output power of this configuration is not $>1/4$ dB higher than the maximum output power for UL CA active.
4. According to October 2018 TCB Workshop publication, LTE uplink CA SAR assessment should follow:
5. If the signal uplink 1-g SAR values for each band are both less than 0.8 W/kg and the algebraic summation of the 1-g SAR values are less than 1.45 W/kg no additional measurements need to be performed.
6. If one or the signal uplink 1-g SAR values is greater than 0.8 W/kg, instead of algebraically summing the 1-g SAR values, sum up the SAR distributions, similar to the enlarged zoom scan (volume scan) procedures found in FCC KDB Publication 865664 D01. And PAG is required for this case.
7. If the algebraic sum of the 1-g SAR values is > 1.45 W/kg additional measurements may have to be made. Submit a KDB inquiry for additional guidance. And PAG is required for this case.

8. The output power of CA uplink refers to the annex E of this report.

➤ **Carrier Aggregation Configuration**

For the device supports bands and bandwidths and configurations are provided as follow table was according to 3GPP.

2CC Downlink Carrier Aggregation				
No.	Combination	MIMO	Restriction	Completely Covered by Measurement Superset
1	CA_2C	-	-	No
2	CA_25A-25A	-	-	No
3	CA_41A-41A	-	-	No
4	CA_2A-12A	-	-	No
5	CA_2A-71A	-	-	No
6	CA_4A-12A	-	-	No
7	CA_4A-71A	-	-	No
8	CA_12A-66A	-	-	No
9	CA_26A-41A	-	-	No
10	CA_66A-71A	-	-	No
11	CA_25A-25A	-	-	No
12	CA_2A-2A	-	-	No
13	CA_2A-4A	-	-	No
14	CA_2A-66A	-	-	No
15	CA_2A-5A	-	-	No
16	CA_4A-5A	-	-	No
17	CA_5A-66A	-	-	No
18	CA_4A-4A	-	-	No
19	CA_5B,	-	-	No
20	CA_5A-5A	-	-	No
21	CA_66A-66A	-	-	No
22	CA_66B	-	-	No
23	CA_66C	-	-	No

➤ **LTE Downlink Carrier Aggregation Conducted Power**

1. According to KDB941225 D05A v01r02, Uplink maximum output power measurement with downlink carrier aggregation active should be measured, using the highest output channel measured without downlink carrier aggregation, to confirm that uplink maximum output power with downlink carrier aggregation active remains within the specified tune-up tolerance limits and not more than ¼ dB higher than the maximum output measured without downlink carrier

aggregation active.


2. Uplink maximum output power with downlink carrier aggregation active does not show more than ¼ dB higher than the maximum output power without downlink carrier aggregation active, therefore SAR evaluation with downlink carrier aggregation active can be excluded.
3. For power measurement were control and acknowledge data is sent on uplink channels that operate identical to specifications when downlink carrier aggregation is inactive.
4. Selected highest measured power when downlink carrier aggregation is inactive for conducted power comparison with downlink carrier aggregation is active, to confirm that when downlink carrier aggregation is active uplink maximum output power remains within the specified tune-up tolerance limits and not more than ¼ dB higher than the maximum output power measured when downlink carrier aggregation inactive.
5. For non-contiguous intra-band CA, the SCC selected to provide maximum separation from the PCC and must remain fully within the downlink transmission band.
6. For Intra-band, contiguous CA, the downlink channels selected to perform the uplink power measurement must satisfy
7. 3GPP channel spacing (5.4.1A of 3GPP TS 36.521 or equivalent) and channel bandwidth (5.4.2A) requirements.

$$\text{Nominal channel spacing} = \left\lceil \frac{BW_{\text{Channel}(1)} + BW_{\text{Channel}(2)} - 0.1|BW_{\text{Channel}(1)} - BW_{\text{Channel}(2)}|}{0.6} \right\rceil 0.3 \text{ [MHz]}$$

8. The output power of CA downlink refers to the annex E of this report.

14 Exposure Positions Consideration

14.1 EUT Antenna Locations



14.2 Test Positions Consideration

Bands	Frequency (MHz)	Maximum Power		Exposure Position/Distance between the antennas and edge/surface of EUT (mm)				
		dBm	mW	Bottom Face	Edge 1	Edge 2	Edge 3	Edge 4
GSM 850	848	31	1259.0	0	5	51	200	5
GSM 1900	1909	24	251.0	0	5	51	200	5
WCDMA II	1907	17	50.0	0	5	51	200	5
WCDMA IV	1750	17	50.0	0	5	51	200	5
WCDMA V	846	23.7	234.0	0	5	51	200	5
LTE Band 2	1909	18	63.0	0	5	51	200	5
LTE Band 4	1754	17	50.0	0	5	51	200	5
LTE Band 5	20643	23.5	224.0	0	5	51	200	5



LTE Band 12	715	24	251.0	0	5	51	200	5
LTE Band 25	1914	17.5	56.0	0	5	51	200	5
LTE Band 26	848	23.5	224.0	0	5	51	200	5
LTE Band 41(HPUE)	2689	21	126.0	0	5	51	200	5
LTE Band 41	2689	21	126.0	0	5	51	200	5
LTE Band 66	1779	17.5	56.0	0	5	51	200	5
LTE Band 71	697	23	200.0	0	5	51	200	5
WLAN 2.4G	2462	12	16.0	0	5	5	200	100
WLAN 5.2G	5240	10	10.0	0	5	5	200	100
WLAN 5.8G	5825	11	13.0	0	5	5	200	100
Bluetooth	2480	10	10	0	5	5	200	100

Bands	Frequency (MHz)	Exposure Position/Calculated Threshold Value (SAR test exclusion power, mW)				
		Bottom Face	Edge 1	Edge 2	Edge 3	Edge 4
GSM 850	848	231.9	231.9	169.0	1011.0	231.9
GSM 1900	1909	69.4	69.4	119.0	1609.0	69.4
WCDMA II	1907	13.8	13.8	119.0	1609.0	13.8
WCDMA IV	1750	13.2	13.2	123.0	1613.0	13.2
WCDMA V	846	43.1	43.1	169.0	1009.0	43.1
LTE Band 2	1909	17.4	17.4	119.0	1609.0	17.4
LTE Band 4	1754	13.2	13.2	123.0	1613.0	13.2
LTE Band 5	20643	70.6	70.6	70.6	70.6	70.6
LTE Band 12	715	69.5	69.5	118.0	1608.0	69.5
LTE Band 25	1914	18.0	18.0	104.0	1594.0	18.0
LTE Band 26	848	73.5	73.5	101.0	1591.0	73.5
LTE Band 41(HPUE)	2689	73.5	73.5	101.0	73.5	73.5
LTE Band 41	2689	73.5	73.5	101.0	73.5	73.5
LTE Band 66	1779	73.5	73.5	101.0	73.5	73.5
LTE Band 71	697	73.5	73.5	101.0	73.5	73.5
WLAN 2.4G	2462	5.0	5.0	5.0	1596.0	596.0
WLAN 5.2G	5240	4.8	4.8	4.8	1562.0	562.0
WLAN 5.8G	5825	6.3	6.3	6.3	1562.0	562.0
Bluetooth	2480	3.1	3.1	3.1	1596.0	596.0

Note:

1. Per KDB 616217 D04v01r02, when the overall diagonal dimension of display is > 20 cm, the



test distance is 0mm; the SAR Test Exclusion Threshold in KDB 447498 section 4.3.1 can be applied to determine SAR test exclusion for adjacent edge configurations.

2. Per KDB 616217 D04v01r02, SAR evaluation for the front surface of tablet display screens is generally not necessary.
3. Per KDB 616217 D04v01r02, additional testing for hotspot SAR is not required.



15 SAR Test Results Summary

15.1 Test Guidance

1. The reported SAR is the measured SAR value adjusted for maximum tune-up tolerance.
 - a. Tune-up scaling Factor = tune-up limit power (mW) / EUT RF power (mW), where tune-up limit is the maximum rated power among all production units.
 - b. For SAR testing of WLAN signal with non-100% duty cycle, the measured SAR is scaled-up by the duty cycle scaling factor which is equal to "1/(duty cycle)".
 - c. For WLAN/Bluetooth: Reported SAR(W/kg)= Measured SAR(W/kg)* Duty Cycle scaling factor * Tune-up scaling factor.
2. Per KDB 447498 D01v06, for each exposure position, testing of other required channels within the operating mode of a frequency band is not required when the *reported* 1-g or 10-g SAR for the mid-band or highest output power channel is:
 - a. ≤ 0.8 W/kg or 2.0 W/kg, for 1-g or 10-g respectively, when the transmission band is ≤ 100 MHz
 - b. ≤ 0.6 W/kg or 1.5 W/kg, for 1-g or 10-g respectively, when the transmission band is between 100 MHz and 200 MHz
 - c. ≤ 0.4 W/kg or 1.0 W/kg, for 1-g or 10-g respectively, when the transmission band is ≥ 200 MHz
3. Per KDB248227 D01v02r02, a Wi-Fi device must be configured to transmit continuously at the required data rate, channel bandwidth and signal modulation, using the highest transmission duty factor supported by the test mode tools for SAR measurement. The test frequencies established using test mode must correspond to the actual channel frequencies required for operations in the U.S. When 802.11 frame gaps are accounted for in the transmission, a maximum transmission duty factor of 92 - 96% is typically achievable in most test mode configurations. A minimum transmission duty factor of 85% is required to avoid certain hardware and device implementation issues related to wide range SAR scaling. In addition, a periodic transmission duty factor is required for current generation SAR systems to measure SAR correctly. Unless it is permitted by specific KDB procedures or continuous transmission is specifically restricted by the device, the reported SAR must be scaled to 100% transmission duty factor to determine compliance at the maximum tune-up tolerance limit. When a device is not capable of sustaining continuous transmission or the output can become nonlinear, and it is limited by hardware design and unable to transmit at higher than 85% duty factor, a periodic duty factor within 15% of the maximum duty factor the device is capable of transmitting should be used. The reported SAR must be scaled to the maximum transmission duty factor to determine compliance. Descriptions of the procedures applied to establish the specific duty factor used for SAR testing are required in SAR reports to support the test results.
4. The receiver has data mode and WIFI mode, and the relationship between the two modes and



power is as follows:

- When WIFI mode off + data mode off, the full power will be applied to WWAN/WLAN body SAR testing.
- When WIFI mode on + data mode off, the reduced power will be applied to WWAN body SAR testing.
- When WIFI mode off + data mode on, the reduced power will be applied to WWAN body SAR testing.

15.2 Body SAR Data

Plot No.	Band/Mode	Test Position	CH.	Ave. Power (dBm)	Tune-up Limit (dBm)	Tune-up Scaling Factor	Meas. SAR _{1g} (W/kg)	Reported SAR _{1g} (W/kg)
Full Power								
	GPRS850/2TX slots	Bottom face	189	30.46	31.00	1.132	0.858	0.972
	GPRS850/2TX slots	Edge 1	189	30.46	31.00	1.132	0.420	0.476
	GPRS850/2TX slots	Edge 2	189	30.46	31.00	1.132	0.092	0.105
	GPRS850/2TX slots	Edge 3	189	30.46	31.00	1.132	0.041	0.046
	GPRS850/2TX slots	Edge 4	189	30.46	31.00	1.132	0.698	0.790
	GPRS850/2TX slots	Bottom face	128	30.40	31.00	1.148	0.848	0.974
1#	GPRS850/2TX slots	Bottom face	251	30.41	31.00	1.146	0.878	1.006
Reduced Power								
2#	GPRS1900/3TX slots	Bottom face	661	23.02	24.00	1.253	0.582	0.729
	GPRS1900/3TX slots	Edge 1	661	23.02	24.00	1.253	0.339	0.425
	GPRS1900/3TX slots	Edge 2	661	23.02	24.00	1.253	0.024	0.030
	GPRS1900/3TX slots	Edge 4	661	23.02	24.00	1.253	0.175	0.219
Reduced Power								
3#	Band II/RMC 12.2Kbps	Bottom face	9400	16.17	17.00	1.211	0.448	0.542
	Band II/RMC 12.2Kbps	Edge 1	9400	16.17	17.00	1.211	0.207	0.251
	Band II/RMC 12.2Kbps	Edge 4	9400	16.17	17.00	1.211	0.133	0.161
Reduced Power								
4#	Band IV/RMC 12.2Kbps	Bottom face	1413	16.19	17.00	1.205	0.532	0.641
	Band IV/RMC 12.2Kbps	Edge 1	1413	16.19	17.00	1.205	0.145	0.175
	Band IV/RMC 12.2Kbps	Edge 4	1413	16.19	17.00	1.205	0.254	0.306
Full Power								
5#	Band V/RMC 12.2Kbps	Bottom face	4182	22.46	23.70	1.330	0.589	0.784
	Band V/RMC 12.2Kbps	Edge 1	4182	22.46	23.70	1.330	0.245	0.326
	Band V/RMC 12.2Kbps	Edge 2	4182	22.46	23.70	1.330	0.049	0.065
	Band V/RMC 12.2Kbps	Edge 3	4182	22.46	23.70	1.330	0.012	0.016
	Band V/RMC 12.2Kbps	Edge 4	4182	22.46	23.70	1.330	0.436	0.580
Reduced Power								
6#	LTE Band 2/1RB#0 20M	Bottom face	18900	17.24	18.00	1.191	0.453	0.540
	LTE Band 2/1RB#0 20M	Edge 1	18900	17.24	18.00	1.191	0.178	0.212
	LTE Band 2/1RB#0 20M	Edge 4	18900	17.24	18.00	1.191	0.149	0.177
	LTE Band 2/50RB#0 20M	Bottom face	18900	16.58	17.00	1.102	0.334	0.368
	LTE Band 2/50RB#0 20M	Edge 1	18900	16.58	17.00	1.102	0.173	0.191
	LTE Band 2/50RB#0 20M	Edge 4	18900	16.58	17.00	1.102	0.137	0.151



Reduced Power								
7#	LTE Band 4/1RB#0 20M	Bottom face	20175	16.31	17.00	1.172	0.416	0.488
	LTE Band 4/1RB#0 20M	Edge 1	20175	16.31	17.00	1.172	0.115	0.135
	LTE Band 4/1RB#0 20M	Edge 4	20175	16.31	17.00	1.172	0.228	0.267
	LTE Band 4/50RB#0 20M	Bottom face	20175	15.42	16.00	1.143	0.374	0.427
	LTE Band 4/50RB#0 20M	Edge 1	20175	15.42	16.00	1.143	0.092	0.105
	LTE Band 4/50RB#0 20M	Edge 4	20175	15.42	16.00	1.143	0.176	0.201
Full Power								
8#	LTE Band 5/1RB#0 10M	Bottom face	20525	22.97	23.50	1.130	0.620	0.700
	LTE Band 5/1RB#0 10M	Edge 1	20525	22.97	23.50	1.130	0.265	0.299
	LTE Band 5/1RB#0 10M	Edge 2	20525	22.97	23.50	1.130	0.033	0.037
	LTE Band 5/1RB#0 10M	Edge 3	20525	22.97	23.50	1.130	0.011	0.012
	LTE Band 5/1RB#0 10M	Edge 4	20525	22.97	23.50	1.130	0.404	0.456
	LTE Band 5/25RB#0 10M	Bottom face	20525	21.98	22.50	1.127	0.426	0.480
	LTE Band 5/25RB#0 10M	Edge 1	20525	21.98	22.50	1.127	0.145	0.163
	LTE Band 5/25RB#0 10M	Edge 2	20525	21.98	22.50	1.127	0.020	0.023
	LTE Band 5/25RB#0 10M	Edge 3	20525	21.98	22.50	1.127	0.009	0.010
	LTE Band 5/25RB#0 10M	Edge 4	20525	21.98	22.50	1.127	0.209	0.236
Full Power								
	LTE Band 12/1RB#0 10M	Bottom face	23095	23.33	24.00	1.167	0.824	0.961
	LTE Band 12/1RB#0 10M	Edge 1	23095	23.33	24.00	1.167	0.554	0.646
	LTE Band 12/1RB#0 10M	Edge 2	23095	23.33	24.00	1.167	0.089	0.103
	LTE Band 12/1RB#0 10M	Edge 4	23095	23.33	24.00	1.167	0.293	0.342
9#	LTE Band 12/1RB#0 10M	Bottom face	23060	23.28	24.00	1.180	0.861	1.016
	LTE Band 12/1RB#0 10M	Bottom face	23130	23.24	24.00	1.191	0.813	0.968
	LTE Band 12/25RB#0 10M	Bottom face	23095	22.26	23.00	1.186	0.552	0.655
	LTE Band 12/25RB#0 10M	Edge 1	23095	22.26	23.00	1.186	0.420	0.498
	LTE Band 12/25RB#0 10M	Edge 2	23095	22.26	23.00	1.186	0.065	0.077
	LTE Band 12/25RB#0 10M	Edge 4	23095	22.26	23.00	1.186	0.289	0.343
	LTE Band 12/50RB#0 10M	Bottom face	23095	22.26	23.00	1.186	0.661	0.784
Reduced Power								
10#	LTE Band 25/1RB#0 20M	Bottom face	26365	16.75	17.50	1.189	0.408	0.485
	LTE Band 25/1RB#0 20M	Edge 1	26365	16.75	17.50	1.189	0.226	0.269
	LTE Band 25/1RB#0 20M	Edge 4	26365	16.75	17.50	1.189	0.160	0.190
	LTE Band 25/50RB#0 20M	Bottom face	26365	16.13	16.50	1.089	0.366	0.399
	LTE Band 25/50RB#0 20M	Edge 1	26365	16.13	16.50	1.089	0.190	0.207
	LTE Band 25/50RB#0 20M	Edge 4	26365	16.13	16.50	1.089	0.153	0.167
Full Power								
11#	LTE Band 26/1RB#0 15M	Bottom face	26865	22.48	23.50	1.265	0.677	0.856
	LTE Band 26/1RB#0 15M	Edge 1	26865	22.48	23.50	1.265	0.244	0.309
	LTE Band 26/1RB#0 15M	Edge 2	26865	22.48	23.50	1.265	0.031	0.039
	LTE Band 26/1RB#0 15M	Edge 4	26865	22.48	23.50	1.265	0.361	0.457
	LTE Band 26/1RB#0 15M	Bottom face	26765	22.41	23.50	1.285	0.652	0.838
	LTE Band 26/1RB#0 15M	Bottom face	26965	22.37	23.50	1.297	0.643	0.834
	LTE Band 26/36RB#0 15M	Bottom face	26865	21.45	22.50	1.274	0.512	0.652
	LTE Band 26/36RB#0 15M	Edge 1	26865	21.45	22.50	1.274	0.154	0.197
	LTE Band 26/36RB#0 15M	Edge 2	26865	21.45	22.50	1.274	0.027	0.035
	LTE Band 26/36RB#0 15M	Edge 4	26865	21.45	22.50	1.274	0.276	0.351
	LTE Band 26/72RB#0 15M	Bottom face	26865	22.48	23.50	1.265	0.507	0.641



Reduced Power (HPUE)								
	LTE Band 41/1RB#0 20M	Bottom face	40620	20.43	21.00	1.140	0.523	0.600
	LTE Band 41/1RB#0 20M	Edge 1	40620	20.43	21.00	1.140	0.422	0.485
	LTE Band 41/1RB#0 20M	Edge 2	40620	20.43	21.00	1.140	0.010	0.011
	LTE Band 41/1RB#0 20M	Edge 3	40620	20.43	21.00	1.140	0.007	0.008
	LTE Band 41/1RB#0 20M	Edge 4	40620	20.43	21.00	1.140	0.494	0.567
	LTE Band 41/50RB#0 20M	Bottom face	40620	19.41	20.00	1.146	0.360	0.415
	LTE Band 41/50RB#0 20M	Edge 1	40620	19.41	20.00	1.146	0.336	0.387
	LTE Band 41/50RB#0 20M	Edge 2	40620	19.41	20.00	1.146	0.007	0.008
	LTE Band 41/50RB#0 20M	Edge 3	40620	19.41	20.00	1.146	0.005	0.006
	LTE Band 41/50RB#0 20M	Edge 4	40620	19.41	20.00	1.146	0.352	0.406
Reduced Power								
	LTE Band 41/1RB#0 20M	Bottom face	40620	20.36	21.00	1.159	0.796	0.928
	LTE Band 41/1RB#0 20M	Edge 1	40620	20.36	21.00	1.159	0.730	0.851
	LTE Band 41/1RB#0 20M	Edge 2	40620	20.36	21.00	1.159	0.014	0.016
	LTE Band 41/1RB#0 20M	Edge 3	40620	20.36	21.00	1.159	0.008	0.009
	LTE Band 41/1RB#0 20M	Edge 4	40620	20.36	21.00	1.159	0.787	0.917
	LTE Band 41/1RB#0 20M	Bottom face	39750	20.12	21.00	1.225	0.737	0.908
	LTE Band 41/1RB#0 20M	Bottom face	40185	20.28	21.00	1.180	0.516	0.613
	LTE Band 41/1RB#0 20M	Bottom face	41055	19.96	21.00	1.271	0.706	0.902
	LTE Band 41/1RB#0 20M	Bottom face	41490	20.07	21.00	1.239	0.744	0.927
	LTE Band 41/1RB#0 20M	Edge 1	39750	20.12	21.00	1.225	0.278	0.342
	LTE Band 41/1RB#0 20M	Edge 1	40185	20.28	21.00	1.180	0.529	0.628
	LTE Band 41/1RB#0 20M	Edge 1	41055	19.96	21.00	1.271	0.806	1.030
	LTE Band 41/1RB#0 20M	Edge 1	41490	20.07	21.00	1.239	0.674	0.840
	LTE Band 41/1RB#0 20M	Edge 4	39750	20.12	21.00	1.225	0.424	0.522
	LTE Band 41/1RB#0 20M	Edge 4	40185	20.28	21.00	1.180	0.550	0.653
	LTE Band 41/1RB#0 20M	Edge 4	41055	19.96	21.00	1.271	0.836	1.069
12#	LTE Band 41/1RB#0 20M	Edge 4	41490	20.07	21.00	1.239	0.922	1.149
	LTE Band 41/50RB#0 20M	Bottom face	40620	19.45	20.00	1.135	0.642	0.733
	LTE Band 41/50RB#0 20M	Edge 1	40620	19.45	20.00	1.135	0.530	0.605
	LTE Band 41/50RB#0 20M	Edge 2	40620	19.45	20.00	1.135	0.010	0.012
	LTE Band 41/50RB#0 20M	Edge 3	40620	19.45	20.00	1.135	0.006	0.007
	LTE Band 41/50RB#0 20M	Edge 4	40620	19.45	20.00	1.135	0.639	0.730
	LTE Band 41/100RB#0 20M	Edge 4	40620	20.36	21.00	1.159	0.574	0.669
	LTE Band 41/1RB#0 20M CA_LTE Band 41C	Edge 4	41490	17.19	18.50	1.352	0.812	1.104
Reduced Power								
13#	LTE Band 66/1RB#0 20M	Bottom face	132322	16.63	17.50	1.222	0.485	0.593
	LTE Band 66/1RB#0 20M	Edge 1	132322	16.63	17.50	1.222	0.170	0.207
	LTE Band 66/1RB#0 20M	Edge 2	132322	16.63	17.50	1.222	0.011	0.014
	LTE Band 66/1RB#0 20M	Edge 4	132322	16.63	17.50	1.222	0.251	0.307
	LTE Band 66/1RB#0 20M	Bottom face	132322	15.51	16.50	1.256	0.405	0.509
	LTE Band 66/1RB#0 20M	Edge 1	132322	15.51	16.50	1.256	0.099	0.124
	LTE Band 66/1RB#0 20M	Edge 2	132322	15.51	16.50	1.256	0.007	0.009
	LTE Band 66/1RB#0 20M	Edge 4	132322	15.51	16.50	1.256	0.157	0.197
Full Power								
14#	LTE Band 71/1RB#0 20M	Bottom face	133322	22.43	23.00	1.140	0.642	0.732
	LTE Band 71/1RB#0 20M	Edge 1	133322	22.43	23.00	1.140	0.416	0.474



	LTE Band 71/1RB#0 20M	Edge 2	133322	22.43	23.00	1.140	0.102	0.116
	LTE Band 71/1RB#0 20M	Edge 3	133322	22.43	23.00	1.140	0.021	0.024
	LTE Band 71/1RB#0 20M	Edge 4	133322	22.43	23.00	1.140	0.125	0.143
	LTE Band 71/50RB#0 20M	Bottom face	133322	21.18	22.00	1.208	0.557	0.673
	LTE Band 71/50RB#0 20M	Edge 1	133322	21.18	22.00	1.208	0.356	0.430
	LTE Band 71/50RB#0 20M	Edge 2	133322	21.18	22.00	1.208	0.087	0.105
	LTE Band 71/50RB#0 20M	Edge 3	133322	21.18	22.00	1.208	0.014	0.017
	LTE Band 71/50RB#0 20M	Edge 4	133322	21.18	22.00	1.208	0.125	0.151
Full Power								
15#	WLAN 2.4GHz/802.11b	Bottom face	1	9.18	10.00	1.208	0.257	0.314
	WLAN 2.4GHz/802.11b	Edge 1	1	9.18	10.00	1.208	0.173	0.212
	WLAN 2.4GHz/802.11b	Edge 2	1	9.18	10.00	1.208	0.178	0.218
Full Power								
16#	WLAN 5.2GHz/802.11a	Bottom face	48	6.77	7.50	1.183	0.253	0.305
	WLAN 5.2GHz/802.11a	Edge 1	48	6.77	7.50	1.183	0.162	0.195
	WLAN 5.2GHz/802.11a	Edge 2	48	6.77	7.50	1.183	0.137	0.165
Full Power								
17#	WLAN 5.8GHz/802.11a	Bottom face	149	7.28	8.00	1.180	0.256	0.308
	WLAN 5.8GHz/802.11a	Edge 1	149	7.28	8.00	1.180	0.138	0.166
	WLAN 5.8GHz/802.11a	Edge 2	149	7.28	8.00	1.180	0.218	0.263
Full Power								
18#	Bluetooth/DH5	Bottom face	78	3.87	4.50	1.156	0.174	0.218
	Bluetooth/DH5	Edge 1	78	3.87	4.50	1.156	0.139	0.174
	Bluetooth/DH5	Edge 2	78	3.87	4.50	1.156	0.137	0.172

Note:

1. Per KDB 447498 D01v06, for each exposure position, if the highest output channel Reported SAR $\leq 0.8\text{W/kg}$, other channels SAR testing is not necessary.
2. Additional WLAN SAR testing was performed for simultaneous transmission analysis.
3. Per KDB 865664 D01v01r04, for each frequency band, repeated SAR measurement is required when the measured SAR is $\geq 0.8\text{W/kg}$.
4. Per KDB248227 D01v02r02, OFDM SAR is not required when the highest reported SAR for DSSS is adjusted by the ratio of OFDM to DSSS specified maximum output power and the adjusted SAR is $\leq 1.2\text{W/kg}$.
5. According to KDB 865664 D02v01r02, SAR plot is required for the highest measured SAR in each exposure configuration, wireless mode and frequency band combination.
6. For TDD-LTE, the reported SAR should be scaled with the duty cycle scaling factor 1.006.
7. The 2.4G WLAN reported 1g SAR (W/kg) should be scaled with the duty cycle scaling factor 1.013, 5G WLAN 802.11a with 1.020 and Bluetooth with 1.085.



15.3 Repeated SAR Assessment

In accordance with published RF Exposure KDB procedure 865664 D01 SAR measurement 100 MHz to 6 GHz. These additional measurements are repeated after the completion of all measurements requiring the same head or body tissue-equivalent medium in a frequency band. The test device should be returned to ambient conditions (normal room temperature) with the battery fully charged before it is re-mounted on the device holder for the repeated measurement(s) to minimize any unexpected variations in the repeated results.

4. Repeated measurement is not required when the original highest measured SAR is < 0.80 W/kg;
5. When the original highest measured SAR is ≥ 0.80 W/kg, repeat that measurement once.
6. Perform a second repeated measurement only if the ratio of largest to smallest SAR for the original and first repeated measurements is > 1.20 or when the original or repeated measurement is ≥ 1.45 W/kg ($\sim 10\%$ from the 1-g SAR limit).
7. Perform a third repeated measurement only if the original, first or second repeated measurement is ≥ 1.5 W/kg and the ratio of largest to smallest SAR for the original, first and second repeated measurements is > 1.20 .

➤ Repeated SAR

Plot No.	Band/Mode	Test Position	CH.	Ave. Power (dBm)	Tune-up Limit (dBm)	Tune-up Scaling Factor	Meas. SAR _{1g} (W/kg)	Reported SAR _{1g} (W/kg)
Full Power								
OR.	GPRS850/2TX slots	Bottom face	251	30.41	31.00	1.146	0.878	1.006
1st	GPRS850/2TX slots	Bottom face	251	30.41	31.00	1.146	0.832	0.953
Full Power								
OR.	LTE Band 12/1RB#0 10M	Bottom face	23060	23.28	24.00	1.180	0.861	1.016
1st	LTE Band 12/1RB#0 10M	Bottom face	23060	23.28	24.00	1.180	0.841	0.993
Reduced Power								
OR.	LTE Band 41/1RB#0 20M	Edge 4	41490	20.07	21.00	1.239	0.922	1.149
1st	LTE Band 41/1RB#0 20M	Edge 4	41490	20.07	21.00	1.239	0.903	1.125

16 Simultaneous Transmission Analysis

16.1 Simultaneous Transmission Consideration

No.	Simultaneous Transmission Consideration	Body
1	WWAN(2G/3G/4G)+WLAN 2.4GHz/5GHz	Yes
2	WWAN(2G/3G/4G)+Bluetooth	Yes

Note:

1. Simultaneous Transmission SAR evaluation is not required for BT and Wi-Fi, because the software mechanism have been incorporated to guarantee that the WLAN and Bluetooth transmitters would not simultaneously operate.
2. Per KDB 447498D01v06, simultaneous transmission SAR evaluation procedures is as followed:
Step 1: If sum of 1 g SAR <1.6 W/kg, Simultaneous SAR measurement is not required.
Step 2: If sum of 1 g SAR >1.6 W/kg, ratio of SAR to peak separation distance for pair of transmitters calculated.
Step 3: If the ratio of SAR to peak separation distance is ≤ 0.04 , Simultaneous SAR measurement is not required.
Step 4: If the ratio of SAR to peak separation distance is > 0.04 , Simultaneous SAR measurement is required and simultaneous transmission SAR value is calculated.
(The ratio is determined by: $(SAR_1 + SAR_2) \wedge 1.5/R_i \leq 0.04$,
 R_i is the separation distance between the peak SAR locations for the antenna pair in mm.

16.2 Simultaneous Transmission Analysis

➤ Body Simultaneous Transmission for WWAN(2/3/4G)+WLAN(2.4GHz)

WWAN Band	Exposure Position	1	2	3	1+2 Summed 1g SAR (W/kg)	1+3 Summed 1g SAR (W/kg)
		WWAN	2.4GHz WLAN	5GHz WLAN		
		1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)		
GSM850	Bottom face at 0mm	1.006	0.314	0.308	1.320	1.314
	Edge 1 at 0mm	0.476	0.212	0.195	0.688	0.671
	Edge 2 at 0mm	0.105	0.218	0.263	0.323	0.368
	Edge 3 at 0mm	0.046			0.046	0.046
	Edge 4 at 0mm	0.790			0.790	0.790
GSM1900	Bottom face at 0mm	0.729	0.314	0.308	1.043	1.037
	Edge 1 at 0mm	0.425	0.212	0.195	0.637	0.620
	Edge 2 at 0mm	0.030	0.218	0.263	0.248	0.293
	Edge 3 at 0mm				0.000	0.000
	Edge 4 at 0mm	0.219			0.219	0.219
WCDMA Band II	Bottom face at 0mm	0.542	0.314	0.308	0.856	0.850
	Edge 1 at 0mm	0.251	0.212	0.195	0.463	0.446
	Edge 2 at 0mm		0.218	0.263	0.218	0.263
	Edge 3 at 0mm				0.000	0.000
	Edge 4 at 0mm	0.161			0.161	0.161
WCDMA Band IV	Bottom face at 0mm	0.641	0.314	0.308	0.955	0.949
	Edge 1 at 0mm	0.175	0.212	0.195	0.387	0.370
	Edge 2 at 0mm		0.218	0.263	0.218	0.263
	Edge 3 at 0mm				0.000	0.000
	Edge 4 at 0mm	0.306			0.306	0.306
WCDMA Band V	Bottom face at 0mm	0.784	0.314	0.308	1.098	1.092
	Edge 1 at 0mm	0.326	0.212	0.195	0.538	0.521
	Edge 2 at 0mm	0.065	0.218	0.263	0.283	0.328
	Edge 3 at 0mm	0.016			0.016	0.016
	Edge 4 at 0mm	0.580			0.580	0.580
LTE Band 2	Bottom face at 0mm	0.540	0.314	0.308	0.854	0.848
	Edge 1 at 0mm	0.212	0.212	0.195	0.424	0.407
	Edge 2 at 0mm		0.218	0.263	0.218	0.263
	Edge 3 at 0mm				0.000	0.000
	Edge 4 at 0mm	0.177			0.177	0.177
LTE Band 4	Bottom face at 0mm	0.488	0.314	0.308	0.802	0.796
	Edge 1 at 0mm	0.135	0.212	0.195	0.347	0.330



	Edge 2 at 0mm		0.218	0.263	0.218	0.263
	Edge 3 at 0mm				0.000	0.000
	Edge 4 at 0mm	0.267			0.267	0.267
LTE Band 5	Bottom face at 0mm	0.700	0.314	0.308	1.014	1.008
	Edge 1 at 0mm	0.299	0.212	0.195	0.511	0.494
	Edge 2 at 0mm	0.037	0.218	0.263	0.255	0.300
	Edge 3 at 0mm	0.012			0.012	0.012
	Edge 4 at 0mm	0.456			0.456	0.456
LTE Band 12	Bottom face at 0mm	1.016	0.314	0.308	1.330	1.324
	Edge 1 at 0mm	0.646	0.212	0.195	0.858	0.841
	Edge 2 at 0mm	0.103	0.218	0.263	0.321	0.366
	Edge 3 at 0mm				0.000	0.000
	Edge 4 at 0mm	0.343			0.343	0.343
LTE Band 25	Bottom face at 0mm	0.485	0.314	0.308	0.799	0.793
	Edge 1 at 0mm	0.269	0.212	0.195	0.481	0.464
	Edge 2 at 0mm		0.218	0.263	0.218	0.263
	Edge 3 at 0mm				0.000	0.000
	Edge 4 at 0mm	0.190			0.190	0.190
LTE Band 26	Bottom face at 0mm	0.856	0.314	0.308	1.170	1.164
	Edge 1 at 0mm	0.309	0.212	0.195	0.521	0.504
	Edge 2 at 0mm	0.039	0.218	0.263	0.257	0.302
	Edge 3 at 0mm				0.000	0.000
	Edge 4 at 0mm	0.457			0.457	0.457
LTE Band 41	Bottom face at 0mm	0.928	0.314	0.308	1.242	1.236
	Edge 1 at 0mm	1.030	0.212	0.195	1.242	1.225
	Edge 2 at 0mm	0.016	0.218	0.263	0.234	0.279
	Edge 3 at 0mm	0.009			0.009	0.009
	Edge 4 at 0mm	1.149			1.149	1.149
LTE Band 66	Bottom face at 0mm	0.593	0.314	0.308	0.907	0.901
	Edge 1 at 0mm	0.207	0.212	0.195	0.419	0.402
	Edge 2 at 0mm	0.014	0.218	0.263	0.232	0.277
	Edge 3 at 0mm				0.000	0.000
	Edge 4 at 0mm	0.307			0.307	0.307
LTE Band 71	Bottom face at 0mm	0.732	0.314	0.308	1.046	1.040
	Edge 1 at 0mm	0.474	0.212	0.195	0.686	0.669
	Edge 2 at 0mm	0.116	0.218	0.263	0.334	0.379
	Edge 3 at 0mm	0.024			0.024	0.024
	Edge 4 at 0mm	0.151			0.151	0.151



➤ **Body Simultaneous Transmission for WWAN(2/3/4G)+Bluetooth**

WWAN Band	Exposure Position	1	2	1+2 Summed 1g SAR (W/kg)
		WWAN	Bluetooth	
		1g SAR (W/kg)	1g SAR (W/kg)	
GSM850	Bottom face at 0mm	1.006	0.218	1.224
	Edge 1 at 0mm	0.476	0.174	0.650
	Edge 2 at 0mm	0.105	0.172	0.277
	Edge 3 at 0mm	0.046		0.046
	Edge 4 at 0mm	0.790		0.790
GSM1900	Bottom face at 0mm	0.729	0.218	0.947
	Edge 1 at 0mm	0.425	0.174	0.599
	Edge 2 at 0mm	0.030	0.172	0.202
	Edge 3 at 0mm			0.000
	Edge 4 at 0mm	0.219		0.219
WCDMA Band II	Bottom face at 0mm	0.542	0.218	0.760
	Edge 1 at 0mm	0.251	0.174	0.425
	Edge 2 at 0mm		0.172	0.172
	Edge 3 at 0mm			0.000
	Edge 4 at 0mm	0.161		0.161
WCDMA Band IV	Bottom face at 0mm	0.641	0.218	0.859
	Edge 1 at 0mm	0.175	0.174	0.349
	Edge 2 at 0mm		0.172	0.172
	Edge 3 at 0mm			0.000
	Edge 4 at 0mm	0.306		0.306
WCDMA Band V	Bottom face at 0mm	0.784	0.218	1.002
	Edge 1 at 0mm	0.326	0.174	0.500
	Edge 2 at 0mm	0.065	0.172	0.237
	Edge 3 at 0mm	0.016		0.016
	Edge 4 at 0mm	0.580		0.580
LTE Band 2	Bottom face at 0mm	0.540	0.218	0.758
	Edge 1 at 0mm	0.212	0.174	0.386
	Edge 2 at 0mm		0.172	0.172
	Edge 3 at 0mm			0.000
	Edge 4 at 0mm	0.177		0.177
LTE Band 4	Bottom face at 0mm	0.488	0.218	0.706
	Edge 1 at 0mm	0.135	0.174	0.309
	Edge 2 at 0mm		0.172	0.172
	Edge 3 at 0mm			0.000



	Edge 4 at 0mm	0.267		0.267
LTE Band 5	Bottom face at 0mm	0.700	0.218	0.918
	Edge 1 at 0mm	0.299	0.174	0.473
	Edge 2 at 0mm	0.037	0.172	0.209
	Edge 3 at 0mm	0.012		0.012
	Edge 4 at 0mm	0.456		0.456
LTE Band 12	Bottom face at 0mm	1.016	0.218	1.234
	Edge 1 at 0mm	0.646	0.174	0.820
	Edge 2 at 0mm	0.103	0.172	0.275
	Edge 3 at 0mm			0.000
	Edge 4 at 0mm	0.343		0.343
LTE Band 25	Bottom face at 0mm	0.485	0.218	0.703
	Edge 1 at 0mm	0.269	0.174	0.443
	Edge 2 at 0mm		0.172	0.172
	Edge 3 at 0mm			0.000
	Edge 4 at 0mm	0.190		0.190
LTE Band 26	Bottom face at 0mm	0.856	0.218	1.074
	Edge 1 at 0mm	0.309	0.174	0.483
	Edge 2 at 0mm	0.039	0.172	0.211
	Edge 3 at 0mm			0.000
	Edge 4 at 0mm	0.457		0.457
LTE Band 41	Bottom face at 0mm	0.928	0.218	1.146
	Edge 1 at 0mm	1.030	0.174	1.204
	Edge 2 at 0mm	0.016	0.172	0.188
	Edge 3 at 0mm	0.009		0.009
	Edge 4 at 0mm	1.149		1.149
LTE Band 66	Bottom face at 0mm	0.593	0.218	0.811
	Edge 1 at 0mm	0.207	0.174	0.381
	Edge 2 at 0mm	0.014	0.172	0.186
	Edge 3 at 0mm			0.000
	Edge 4 at 0mm	0.307		0.307
LTE Band 71	Bottom face at 0mm	0.732	0.218	0.950
	Edge 1 at 0mm	0.474	0.174	0.648
	Edge 2 at 0mm	0.116	0.172	0.288
	Edge 3 at 0mm	0.024		0.024
	Edge 4 at 0mm	0.151		0.151



17 Uncertainty Assessment

According to KDB 865664 D01 SAR measurement 100 MHz to 6GHz, when the highest measured 1-g SAR is less than 1.5 W/kg and 10-g extremity SAR less than 3.75 W/kg, the expanded SAR measurement uncertainty must be less than 30% with a confidence interval of $k=2$. When these conditions are met, extensive SAR measurement uncertainty analysis described in IEEE 1528-2013 is not required in the SAR report and submitted for equipment approval. For this device, both the 1-g SAR is less than 1.5 W/kg. Therefore the measurement uncertainty table is not required in this report.



18 Measurement Conclusion

The SAR evaluation indicates that the EUT complies with the RF radiation exposure limits of FCC, with respect to all parameters subject to this test. These measurements were taken to simulate the RF effects of RF exposure under worst-case conditions. Precise laboratory measures were taken to assure repeatability of the tests. The results and statements relate only to the item(s) tested. Please note that the absorption and distribution of electromagnetic energy in the body are very complex phenomena that depend on the mass, shape, and size of the body, the orientation of the body with respect to the field vectors, and the electrical properties of both the body and the environment. Other variables that may play a substantial role in possible biological effects are those that characterize the environment (e.g. ambient temperature, air velocity, relative humidity, and body insulation) and those that characterize the individual (e.g. age, gender, activity level, debilitation, or disease). Because various factors may interact with one another to vary the specific biological outcome of an exposure to electromagnetic fields, any protection guide should consider maximal amplification of biological effects as a result of field-body interactions, environmental conditions, and physiological variables.



Annex A General Information

1. Identification of the Responsible Testing Laboratory

Laboratory Name:	Shenzhen Morlab Communications Technology Co., Ltd.
Laboratory Address:	FL.1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block 67, BaoAn District, ShenZhen, GuangDong Province, P. R. China
Telephone:	+86 755 36698555
Facsimile:	+86 755 36698525

2. Identification of the Responsible Testing Location

Name:	Shenzhen Morlab Communications Technology Co., Ltd.
Address:	FL.1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block 67, BaoAn District, ShenZhen, GuangDong Province, P. R. China

3. Facilities and Accreditations

The FCC designation number is CN1192, the test firm registration number is 226174.

Note:

The main report is end here and the other Annex (B,C,D,E,F) will be submitted separately.

***** END OF MAIN REPORT *****