

TEST REPORT

APPLICANT	:	Great Talent	Technology	Limited
-----------	---	--------------	------------	---------

- PRODUCT NAME : Tablet
- MODEL NAME : T8002
- BRAND NAME : moxee
- **FCC ID** : 2ALZM-T8002
- STANDARD(S) : 47 CFR Part 15 Subpart E
- **RECEIPT DATE** : 2022-02-14
- **TEST DATE** : 2022-02-22 to 2022-04-01
- **ISSUE DATE** : 2022-05-17

Edited by:

Pong /VIZ

Peng Mi (Rapporteur)

Approved by:

pm Shen Junsheng (Supervisor)

NOTE: This document is issued by Shenzhen Morlab Communications Technology Co., Ltd., the test report shall not be reproduced except in full without prior written permission of the company. The test results apply only to the particular sample(s) tested and to the specific tests carried out which is available on request for validation and information confirmed at our website.



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China

 Tel:
 86-755-36698555
 Fax:
 86-755-36698525

 Http://www.morlab.cn
 E-mail:
 service@morlab.cn





DIRECTORY

1. Technical Information	3			
1.1. Applicant and Manufacturer Information	Applicant and Manufacturer Information 3			
1.2. Equipment Under Test (EUT) Description	3			
1.3. Modulation Type and Data Rate of EUT	1			
1.4. The Channel Number and Frequency	5			
1.5. Test Standards and Results ······	5			
1.6. Environmental Conditions	7			
2. 47 CFR Part 15E Requirements ······ 8	3			
2.1. Antenna Requirement ······ 8	3			
2.2. Duty Cycle of the Test Signal)			
2.3. Maximum Conducted Output Power ······14	. Maximum Conducted Output Power ······14			
2.4. Emission Bandwidth ······18	3			
2.5. Peak Power Spectral Density)			
2.6. Frequency Stability	۶. Frequency Stability ••••••••••••••••••••••••••••••••••••			
.7. Conducted Emission ······62				
2.8. Restricted Frequency Bands ······66	5			
2.9. Radiated Emission ······78				
nex A Test Uncertainty ······94				
Annex B Testing Laboratory Information9	5			

Change History			
Version	Date	Reason for change	
1.0 2022-05-17		First edition	





1. Technical Information

Note: Provide by applicant.

1.1. Applicant and Manufacturer Information

Applicant:	Great Talent Technology Limited		
Applicant Address	35F, HBC HuiLong Center Building-II Minzhi Street, Longhua,		
Applicant Address:	Shenzhen, P. R. China 518110		
Manufacturer:	Great Talent Technology Limited		
Manufacturer Address	35F, HBC HuiLong Center Building-II Minzhi Street, Longhua,		
Manufacturer Address:	Shenzhen, P. R. China 518110		

1.2. Equipment Under Test (EUT) Description

Product Name:	Tablet		
Sample No.:	1#		
Hardware Version:	T8002_V1.0		
Software Version:	MT8BV1.0.0B001		
Modulation Type:	OFDM		
Modulation Mode:	802.11a, 802.11n (802.11ac (VHT20),	HT20), 802.11n (HT40) 802.11ac (VHT40), 802.11ac (VHT80)	
Operating Frequency Range:	5180MHz-5240MH	lz; 5745MHz-5825MHz	
Channel Number:	Refer to 1.3		
Antenna Type:	PIFA Antenna		
Antenna Gain:	3.35dBi		
	Battery		
	Brand Name:	Fenghua	
	Model No.:	BTE-4301	
	Serial No.:	N/A	
Accessory Information:	Capacity:	4300mAh	
	Rated Voltage:	3.85V	
	Charge Limit:	4.4V	
	Manufacturer:	Guangdong Fenghua New Energy Co., Ltd.	





Accessory Information:	AC Adapter		
	Brand Name:	Tianyin	
	Model No.:	TPA-46050200UU	
	Serial No.:	N/A	
	Rated Output:	5V2000mA	
	Rated Input:	100-240V~50/60Hz, 0.3A	
	Manufacturer:	Shenzhen Tianyin Electronics Co., Ltd.	

Note 1: WiFi hotspot only support U-NII-1 and U-NII-3 band.

Note 2: We use the dedicated software to control the EUT continuous transmission.

Note 3: For a more detailed description, please refer to Specification or User's Manual supplied by the applicant and/or manufacturer.

1.3. Modulation Type and Data Rate of EUT

Modulation technology	Modulation Type	Data Rate (Mbps) _{Note1}
OFDM (802.11a)	BPSK	6 /9
	QPSK	12/18
	16QAM	24/36
	64QAM	48/54
	BPSK	6.5
OFDM (802.11n)	QPSK	13/19.5
	16QAM	26/39
	64QAM	52/58.5/65
OFDM (802.11ac)	BPSK	6.5
	QPSK	13/19.5
	16QAM	26/39
	64QAM	52/58.5/65
	256QAM	78

Note1: The worst-case mode(black bold) in all data rates has been determined during the pre-scan, only the test data of the worst-case were recorded in this report.





1.4. The Channel Number and Frequency

(U-NII-1) 5180MHz-5240MHz						
Bandwidth	Channel	Frequency (MHz)	Channel	Frequency (MHz)		
201417	36	5180	40	5200		
20101112	44	5220	48	5240		
40MHz	38	5190	46	5230		
80MHz	42	5210				
(U-NII-3) 5745M⊦	(U-NII-3) 5745MHz-5825MHz					
Bandwidth	Channel	Frequency (MHz)	Channel	Frequency (MHz)		
	149	5745	153	5765		
20MHz	157	5785	161	5805		
	165	5825				
40MHz	151	5775	159	5795		
80MHz	155	5775				

Note 1: The black bold channels were selected for test.





1.5. Test Standards and Results

The objective of the report is to perform testing according to 47 CFR Part 15 Subpart E (U-NII band) for the EUT FCC ID Certification:

No.	Identity	Document Title
1	47 CFR Part 15(5-1-14 Edition)	Radio Frequency Devices

Test detailed items/section required by FCC rules and results are as below:

No.	Section	Description	Test Date	Test Engineer	Result	Method Determination /Remark
1	15.203	Antenna Requirement	N/A	N/A	PASS	No deviation
2	ANSI C63.10	Duty Cycle of the Test Signal	Feb. 22, 2022	Zou Yuantao	PASS	No deviation
3	15.407(a)	Maximum Conducted Output Power	Mar. 01, 2022	Zou Yuantao	PASS	No deviation
4	15.407(a) (e)	Emission Bandwidth	Feb. 25, 2022	Zou Yuantao	PASS	No deviation
5	15.407(a)	Peak Power Spectral Density	Feb. 25, 2022	Zou Yuantao	PASS	No deviation
6	15.407(g)	Frequency Stability	Mar. 01, 2022	Zou Yuantao	PASS	No deviation
7	15.207	Conducted Emission	Mar. 10, 2022	Wu Zhaoling	PASS	No deviation
8	15.407(b)	Restricted Frequency Bands	Mar. 31, 2022 Apr. 01, 2022	Su Zhan	PASS	No deviation
9	15.407(b)	Radiated Emission	Apr. 01, 2022	Su Zhan	PASS	No deviation

Note 1: The tests of Conducted Emission and Radiated Emission were performed according to the method of measurements prescribed in ANSI C63.102013.

Note 2: These RF tests were performed according to the method of measurements prescribed in KDB789033 D02 v02r01.

Note 3: The path loss during the RF test is calibrated to correct the results by the offset setting in the test equipments. The ref offset 11.0dB contains two parts that cable loss 1.0dB and





Attenuator 10dB.

Note 4: Additions to, deviation, or exclusions from the method shall be judged in the "method determination" column of add, deviate or exclude from the specific method shall be explained in the "Remark" of the above table.

Note 5: When the test result is a critical value, we will use the measurement uncertainty give the judgment result based on the 95% confidence intervals.

1.6. Environmental Conditions

During the measurement, the environmental conditions were within the listed ranges:

Temperature (°C):	15-35
Relative Humidity (%):	30-60
Atmospheric Pressure (kPa):	86-106







2. 47 CFR Part 15E Requirements

2.1. Antenna Requirement

2.1.1. Applicable Standard

According to FCC 15.203, an intentional radiator shall be designed to ensure that no antenna other than that furnished by the responsible party shall be used with the device. The use of a permanently attached antenna or of an antenna that uses a unique coupling to the intentional radiator shall be considered sufficient to comply with the provisions of this section.

2.1.2. Test Result: Compliant

Inside of the EUT has a PIFA antenna coupled with the metal shrapnel. Please refer to the EUT internal photos.





2.2. Duty Cycle of the Test Signal

2.2.1. Requirement

Preferably, all measurements of maximum conducted (average) output power will be performed with the EUT transmitting continuously (i.e., with a duty cycle of greater than or equal to 98%). When continuous operation cannot be realized, then the use of sweep triggering/signal gating techniques can be used to ensure that measurements are made only during transmissions at the maximum power control level. Such sweep triggering/signal gating techniques will require knowledge of the minimum transmission duration (T) over which the transmitter is on and is transmitting at its maximum power control level for the tested mode of operation. Sweep triggering/signal gating techniques can be set such that it does not exceed T at any time that data are being acquired (i.e., no transmitter OFF-time is to be considered).

When continuous transmission cannot be achieved and sweep triggering/signal gating cannot be implemented, alternative procedures are provided that can be used to measure the average power; however, they will require an additional measurement of the transmitter duty cycle (D). Within this sub clause, the duty cycle refers to the fraction of time over which the transmitter is ON and is transmitting at its maximum power control level. The duty cycle is considered to be constant if variations are less than $\pm 2\%$; otherwise, the duty cycle is considered to be nonconstant.

2.2.2. Test Description

Test Setup:



The EUT is coupled to the Spectrum Analyzer; the RF load attached to the EUT antenna terminal is 500hm; the path loss as the factor is calibrated to correct the reading.

2.2.3. Test Procedure

KDB 789033 Section B was used in order to prove compliance.

MORLAB

Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China



2.2.4. Test Result

A.Test Verdict:

Test Mode	Duty Cycle (%) (D)	Duty Factor (10*log[1/D])
802.11a	98.06	0.09
802.11n (HT20)	97.92	0.09
802.11n (HT40)	96.17	0.17
802.11ac(VHT20)	98.09	0.08
802.11ac(VHT40)	95.89	0.18
802.11ac(VHT80)	93.12	0.31

B.Test Plot:



(Channel 36, 5180MHz, 802.11a)



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555 Http://www.morlab.cn E-mail: service@morlab.cn





Marker		TRAC TY	: Log-Pwr	Avg Typ	Run	Trig: Free	: Fast	ms PN	92500	Δ1.	er 3 /	rk
Select Marke	.925 ms	/lkr3 1.	Δ١		dB	Atten: 24	in:Low	dB	Offset 11	Ref		
Norm	www.www.	3∆1 *********	presidential	here and the second	vitratorrioti	Al Margarith	and a state of the	1BM Hwyellianubr		Minur	- Inter	
Del												
Fixed											4	a a
c	Span 0 Hz (1001 pts)	S 100 ms (Sweep 5.0			0 MHz	VBW 8.	SHz	00000 Q z	1800 MH:	er 5.1 3W 8	nt s i
Properties	ION VALUE	FUNCTIO	ICTION WIDTH	CTION FL	Bm dB dB	11.51 dE -0.19 -0.11	ims ms (Δ) ims (Δ)	× 2.10 1.80 1.92	(Δ) (Δ)		0DE TRO N 1 11 1	
Mo 1 o												

(Channel 36, 5180MHz, 802.11n (HT20))



(Channel 38, 5190MHz, 802.11n (HT40))



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China





Marker	TRACE 1 2 2 4 8 TVPE WALLAND	: Log-Pwr	Avg Ty	e Run dB	Trig: Free Atten: 24	NO: Fast	ns P	93500	ker 3 Δ 1.
Selectividi Ke	kr3 1.935 ms 0.04 dB	ΔN					dB dBm	Offset 11 24.00	Ref Sidiy Ref
Norm	3∆1 mentonin terrestationen	ur-mananananananananananananananananananan	ale and the second second	1 Allentrist	Youtsellerrow	printratelium.anathat	white	nulaantu	aper productions
Del									
Fixed									
c	Span 0 Hz 00 ms (1001 pts)	Sweep 5.0	NCTION	F	3.0 MHz	VBW 8	SHz	00000 (z	ter 5.1800 BW 8 MH:
Properties				3m dB dB	11.13 dE -1,85 0.04	07 ms 98 ms (Δ) 35 ms (Δ)	2.5 1.8 1.9	(Δ) (Δ)	N 1 t Δ1 1 t Δ1 1 t
Mo 1 o									

(CH36_5180MHz _802.11ac (VHT20))



(CH38_5190MHz _802.11ac (VHT40))



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China



ker 3 Δ 494.000 μs	PNO: Fast +++ IFGain:Low	Trig: Free Run Atten: 24 dB	Avg Ty	ALIGNAUTO pe: Log-Pwr	02:53:37 PMFeb 21, 2022 TRACE 1 2 3 4 5 TYPE WWWWWWWW DET P NNNNN	Properties Select Marker
Ref Offset 11 dB B/div Ref 24.00 dBr	n			Δ	Mkr3 494.0 μs 0.59 dB	3
ann an than an a	red of the second	masodimen	-war where	www.12/2/30	1 walnowgrammente	Relative To
	05-					X Axis Scale Time Auto Mai
						Marker Trace [Trace1, Auto Init]
ter 5.210000000 GHz BW 8 MHz	VBW 8	.0 MHz		Sweep 1.0	Span 0 Hz 00 ms (1001 pts)	Line
MODE TRC SCL N 1 t Δ1 1 t (Δ) Δ1 1 t (Δ)	× 286.0 μs 460.0 μs (Δ) 494.0 μs (Δ)	Y -0.23 dBm -2.50 dB 0.59 dB	FUNCTION F	UNCTION WIDTH	FUNCTION VALUE	

(CH42_5210MHz _802.11ac (VHT80))





2.3. Maximum Conducted Output Power

2.3.1. Requirement

(1) For client devices in the 5.15-5.25 GHz band, the maximum conducted output power over the frequency band of operation shall not exceed 250mW provided the maximum antenna gain does not exceed 6dBi.

(2)For the 5.25-5.35 GHz and 5.47-5.725 GHz bands, the maximum conducted output power over the frequency bands of operation shall not exceed the lesser of 250mW or 11dBm + 10 log B, where B is the 26 dB emission bandwidth in megahertz.

(3) For the band 5.725-5.85 GHz, the maximum conducted output power over the frequency band of operation shall not exceed 1 W.

If transmitting antennas of directional gain greater than 6dBi are used, the maximum conducted output power shall be reduced by the amount in dB that the directional gain of the antenna exceeds 6dBi.

(4) According to KDB662911D01Measure-and-sum technique, the conducted emission level (e.g., transmit power or power in specified bandwidth) is measured at each antenna port. The measured results at the various antenna ports are then summed mathematically to determine the total emission level from the device. Summing is performed in units that are directly proportional to power.

(5) According to KDB 662911 D01, the directional gain = G_{ANT} +10log(N_{ANT})dBi, where G_{ANT} is the antenna gain in dBi, N_{ANT} is the number of outputs.

2.3.2. Test Description

Section E) 3) of KDB 789033 defines a methodology using a USB Wideband Power Sensor. **Test Setup:**



The EUT (Equipment under the test) which is coupled to the USB Wideband Power Sensor; the RF load attached to the EUT antenna terminal is 500hm; the path loss as the factor is calibrated to correct the reading, all test result in USB Wideband Power Sensor.





For ac (VHT80) mode power



The EUT (Equipment under the test) is coupled to the Spectrum analyzer; the RF load attached to the EUT antenna terminal is 500hm; the path loss as the factor is calibrated to correct the reading, all test result in Spectrum analyzer.



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555 Fax: 86-755-36698525 Http://www.morlab.cn E-mail: service@morlab.cn



2.3.3. Test Result

Maximum Average Conducted Output Power

802.11a Mode

			Average Po	wer (dBm)		Lie	mit	
Channel	Frequency (MHz)	Measured	Duty Factor	Duty Fa Calcula	actor ated	(dE	3m)	Verdict
		dBm	Facior	dBm	W	dBm	W	
36	5180	5.52		5.61	0.004			
44	5220	6.23		6.32	0.004	24	0.25	
48	5240	6.77	0.00	6.86	0.005			DAGG
149	5745	7.28	0.09	7.37	0.005			FA33
157	5785	6.21		6.30	0.004	30	1	
165	5825	6.14		6.23	0.004			

802.11n (HT20) Mode

			Average Po	wer (dBm)		1.5	mit	
Channel	Frequency (MHz)	Measured	Duty Factor	Duty Fa Calcula	actor ated	(dE	Bm)	Verdict
		dBm	Facior	dBm	W	dBm	W	
36	5180	5.31		5.40	0.003			
44	5220	6.12		6.21	0.004	24	0.25	
48	5240	6.61	0.00	6.70	0.005			DASS
149	5745	7.12	0.09	7.21	0.005			FA33
157	5785	6.55		6.64	0.005	30	1	
165	5825	6.03		6.12	0.004			

802.11n (HT40) Mode

			Average	Power		1.5	mit	
Channel	Frequency (MHz)	Measured	Duty	Duty Fa Calcul	actor ated	(dE	Bm)	Verdict
		dBm	Factor	dBm	W	dBm	W	
38	5190	5.36		5.53	0.004	24	0.25	
46	5230	6.22	0 17	6.39	0.004	24	0.25	DASS
151	5755	7.17	0.17	7.34	0.005	20	1	FA33
159	5795	6.62		6.79	0.005	30	Ι	





802.11ac (VHT20) Mode

	Fraguanay	, Average Power (dBm)					nit	
Channel		Measured	Duty	Duty Factor C	Calculated	(dE	8m)	Verdict
	(101112)	dBm	Factor	dBm	W	dBm	W	
36	5180	5.32		5.40	0.003			
44	5220	6.06		6.14	0.004	24	0.25	
48	5240	6.54	0.08	6.62	0.005			DASS
149	5745	7.06	0.00	7.14	0.005			FA33
157	5785	6.15		6.23	0.004	30	1	
165	5825	5.89		5.97	0.004			

802.11ac (VHT40) Mode

	Frequency		Average Power				nit	
Channel		Measured	Duty	Duty Factor C	Calculated	(dE	Bm)	Verdict
	(10172)	dBm	Factor	dBm	W	dBm	W	
38	5190	5.35		5.53	0.004	24	0.25	
46	5230	6.29	0.10	6.47	0.004	24	0.25	DASS
151	5755	7.20	0.10	7.38	0.005	20	1	PASS
159	5795	6.24		6.42	0.004	30	I	

802.11ac (VHT80) Mode

	Frequency		Average Power					
Channel		Measured	Duty	Duty Factor	Calculated	(dE	Bm)	Verdict
	(IVI⊓Z)	dBm	Factor	dBm	W	dBm	W	
42	5210	5.59	0.21	5.90	0.004	24	0.25	DAGG
155	5775	6.94	0.31	7.25	0.005	30	1	PASS







2.4. Emission Bandwidth

2.4.1. Requirement

For purposes of this subpart the emission bandwidth shall be determined by measuring the width of the signal between two points, one below the carrier center frequency and one above the carrier center frequency, that are 26 dB down relative to the maximum level of the modulated carrier. Determination of the emissions bandwidth is based on the use of measurement instrumentation employing a peak detector function with an instrument resolution bandwidth approximately equal to 1.0 percent of the emission bandwidth of the device under measurement. Within the 5.725-5.85 GHz band, the minimum 6 dB bandwidth of U-NII devices shall be at least 500 kHz.

2.4.2. Test Description

Test Setup:



The EUT is coupled to the Spectrum Analyzer; the RF load attached to the EUT antenna terminal is 500hm; the path loss as the factor is calibrated to correct the reading.

2.4.3. Test Procedure

1. KDB 789033 Section C) 1) Emission Bandwidth was used in order to prove compliance

a) Set RBW = approximately 1% of the emission bandwidth.

- b) Set VBW > RBW.
- c) Detector = Peak.
- d) Trace mode = max hold.

e) Measure the maximum width of the emission that is 26 dB down from the peak of the emission. Compare this with the RBW setting of the analyzer. Readjust RBW and repeat measurement as needed until the RBW/EBW ratio is approximately 1%.

2. KDB 789033 Section C) 2) minimum emission bandwidth for the band 5.725-5.85GHz was used in order to prove compliance.

Section 15.407(e) specifies the minimum 6 dB emission bandwidth of at least 500 KHz for theband5.715-5.85 GHz. The following procedure shall be used for measuring this bandwidth:





- a) Set RBW = 100 kHz.
- b) Set video bandwidth (VBW) \geq 3 × RBW.
- c) Detector = Peak.
- d) Trace mode = max hold.
- e) Sweep = auto couple.
- f) Allow the trace to stabilize.

g) Measure the maximum width of the emission that is constrained by the frequencies associated with the two outermost amplitude points (upper and lower frequencies) that are attenuated by 6 dB relative to the maximum level measured in the fundamental emission.

2.4.4. Test Result

802.11a Mode

A.Test Verdict:

Channel	Frequency (MHz)	26 dB Bandwidth (MHz)
36	5180	24.07
44	5220	24.14
48	5240	25.00
Channel	Frequency (MHz)	6 dB Bandwidth (MHz)
149	5745	15.74
157	5785	15.77
165	5825	15.16





B.Test Plot:







(Channel 44, 5220 MHz, 802.11a)



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555 Http://www.morlab.cn Fax: 86-755-36698525 E-mail: service@morlab.cn









(Channel 149,5745MHz, 802.11a)

MORLAB

Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555 Http://www.morlab.cn E-mail: service@morlab.cn











(Channel 165, 5825MHz, 802.11a)



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555 Fax: 86-755-36698525 Http://www.morlab.cn

E-mail: service@morlab.cn



802.11n (HT20) Mode

A.Test Verdict:

Channel	Frequency (MHz)	26 dB Bandwidth (MHz)
36	5180	25.26
44	5220	26.11
48	5240	24.91
Channel	Frequency (MHz)	6 dB Bandwidth (MHz)
149	5745	16.16
157	5785	17.18
165	5825	17.15

B.Test Plot:



(Channel 36, 5180MHz, 802.11n (HT20))



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555 Http://www.morlab.cn E-mail: service@morlab.cn











(Channel 48, 5240MHz, 802.11n (HT20))



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555 Http://www.morlab.cn E-mail: service@morlab.cn









(Channel 157, 5785MHz, 802.11 n (HT20))



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China







(Channel 165, 5825MHz, 802.11 n (HT20))



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555 Fax: 86-755-36698525 Http://www.morlab.cn E-mail: service@morlab.cn



802.11n (HT40) Mode

A.Test Verdict:

Channel	Frequency (MHz)	26 dB Bandwidth (MHz)
38	5190	40.69
46	5230	41.40
Channel	Frequency (MHz)	6 dB Bandwidth (MHz)
151	5755	36.37
159	5795	36.42

B.Test Plot:



(Channel 38, 5190MHz, 802.11n (HT40))



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555 Fax: 86-755-36698525

Http://www.morlab.cn

E-mail: service@morlab.cn









(Channel 151, 5755MHz, 802.11n (HT40))



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555 Http://www.morlab.cn E-mail: service@morlab.cn







(Channel 159, 5795MHz, 802.11n (HT40))



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555 Fax: 86-755-36698525 Http://www.morlab.cn E-mail: service@morlab.cn



802.11ac (VHT20) Mode

A.Test Verdict:

Channel	Frequency (MHz)	26 dB Bandwidth (MHz)				
36	5180	25.34				
44	5220	24.44				
48	5240	25.52				
Channel	Frequency (MHz)	6dB Bandwidth (MHz)				
149	5745	17.01				
157	5785	16.94				
165	5825	15.74				

B.Test Plot:



(Channel 36, 5180MHz, 802.11ac (VHT20))



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555 Fax: 86-755-36698525 Http://www.morlab.cn

E-mail: service@morlab.cn









(Channel 48, 5240MHz, 802.11ac (VHT20))

MORLAB

Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555 Http://www.morlab.cn E-mail: service@morlab.cn









(Channel 157, 5785MHz, 802.11ac (VHT20))



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555 Http://www.morlab.cn E-mail: service@morlab.cn







(Channel 165, 5825MHz, 802.11ac (VHT20))



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555 Fax: 86-755-36698525 Http://www.morlab.cn E-mail: service@morlab.cn



802.11ac (VHT40) Mode

A.Test Verdict:

Channel	Frequency (MHz)	26 dB Bandwidth (MHz)				
38	5190	40.80				
46	5230	40.89				
Channel	Frequency (MHz)	6dB Bandwidth (MHz)				
151	5755	36.37				
159	5795	36.37				

B.Test Plot:



(Channel 38, 5190MHz, 802.11ac (VHT40))











(Channel 151, 5755 MHz, 802.11ac (VHT40))

MORLAB

Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555 Http://www.morlab.cn E-mail: service@morlab.cn





enter Freq 5.795000000 GHz #/FGain:Low		SENSE:MT ALIGNAUTO enter Freq: 5.795000000 GHz rig: Free Run Avg Hold>10/10 Atten: 10 dB		11:21:19 AM Feb 25, 2022 Radio Std: None Radio Device: BTS		Frequency
dB/div Ref 20.00 dBm						
9 00 00	L. J.	الم المعاملة المعاملة المعام المحمد المحم	int			Center Fre 5.795000000 GH
10 graditetilevenderlikerenderlikerender			"Mundrikel	ladih indra Milaya	anywar-engly	
enter 5.795 GHz Res BW 100 kHz	VBW 300 kHz		Span Sweep	100 MHz 12.4 ms	CF Ste 10.000000 MH	
Occupied Bandwidt	h	Total Power	16.	8 dBm		<u>Auto</u> Mar
36	.182 MHz					Freq Offse
Transmit Freq Error x dB Bandwidth	-62.218 kHz 36.37 MHz	OBW Power x dB	-6	9.00 % 5.00 dB		0 H
			STAT	US		

(Channel 159, 5795MHz, 802.11ac (VHT40))



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China

Tel: 86-755-36698555 Fax: 86-755-36698525 Http://www.morlab.cn E-mail: service@morlab.cn


802.11ac (VHT80) Mode

A.Test Verdict:

Channel	Frequency (MHz)	26 dB Bandwidth (MHz)
42	5210	81.65
Channel	Frequency (MHz)	6dB Bandwidth (MHz)
155	5775	75.72

B.Test Plot:

dB -26.00 dB	#IFGain:Low	SENSE:INT r Freq: 5.210000000 GHz Free Run Avg Hold n: 10 dB	ALIGNAUTO-	Radio Der	M Feb 25, 2022 I: None vice: BTS	Mi Avg	eas Setup g/Hold Num 10
o dB/div Ref 20.00 dBm	í					<u>On</u>	Off
og 10.0	A	in proves and particulation	AMURANA			Exp	Avg Mode Repeat
00 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0				Jana los	downal messa		
0.0 00 00							DBW Power 99.00 %
enter 5.21 GHz Res BW 300 kHz	#	VBW 1 MHz		Spar Sweep	120 MHz 1.667 ms		
Occupied Bandwidt	^h 5.477 MHz	Total Power	17.1	dBm			x dE
Transmit Freq Error x dB Bandwidth	92.243 kHz 81.65 MHz	OBW Power x dB	99 -26.0	.00 % 00 dB			-26,00 dE
							Mor 1 of 3
6			STATUS				

(Channel 42, 5210MHz, 802.11ac (VHT80))







Agilent Spectrum Analyzer - Occupied B	SW.	SENSE:INT)	ALIGNAUTO	11:23:55 A	M Feb 25, 2022	
Center Freq 5.775000000	GHz Cente Trig: f #IFGain:Low #Atter	r Freq: 5.775000000 GHz Free Run Avg Ho 1: 10 dB	ld:>10/10	Radio Std: Radio Dev	None ice: BTS	Frequency
0 dB/div Ref 20.00 dBr	n					
00						Center Fre 5.775000000 GH
0.0 	dalidadad aqueed et anged al topological et al a	Very out the work of the shotel and	alarhasiydaral-holyl	*		
0.0 which which man we					Wateringto Page New York	
no 10						
enter 5.775 GHz Res BW 100 kHz	#	VBW 300 kHz		Span Sweep	120 MHz 14.87 ms	CF Ster 12.000000 MH
Occupied Bandwidt	th	Total Power	17.4	4 dBm		<u>Auto</u> Mar
7	5.450 MHz	0.514/15				Freq Offse
Transmit Freq Error x dB Bandwidth	-159.83 KHz 75.72 MHz	OBW Power x dB	-6.	9.00 % 00 dB		U.
			Lo STATU	6		

(Channel 155, 5775 MHz, 802.11ac (VHT80))



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China

Tel: 86-755-36698555 Fax: 86-755-36698525 Http://www.morlab.cn E-mail: service@morlab.cn



2.5. Peak Power Spectral Density

2.5.1. Requirement

(1)For client devices in the 5.15-5.25 GHz band, the maximum power spectral density shall not exceed 11dBm in any 1 megahertz band.

(2)For the 5.25-5.35 GHz and 5.47-5.725 GHz bands, the maximum power spectral density shall not exceed 11dBm in any 1 megahertz band.

(3) For the band 5.725-5.85 GHz, the maximum power spectral density shall not exceed 30dBm in any 500kHz band.

If transmitting antennas of directional gain greater than 6dBi are used, the maximum power spectral density shall be reduced by the amount in dB that the directional gain of the antenna exceeds 6dBi.

(4) According to KDB662911D01Measure-and-sum technique, the conducted emission level (e.g., transmit power or power in specified bandwidth) is measured at each antenna port. The measured results at the various antenna ports are then summed mathematically to determine the total emission level from the device. Summing is performed in units that are directly proportional to power.

(5) According to KDB 662911 D01, the directional gain = G_{ANT} +10log(N_{ANT}) dBi, where G_{ANT} is the antenna gain in dBi, N_{ANT} is the number of outputs.

2.5.2. Test Description

Test Setup:



The EUT is coupled to the Spectrum Analyzer; the RF load attached to the EUT antenna terminal is 500hm; the path loss as the factor is calibrated to correct the reading.





2.5.3. Test Procedure

KDB 789033 Section F) Maximum Power Spectral Density (PSD) Method SA-1 was used in order to prove compliance

- 1) Set span to encompass the entire 26-dB emission bandwidth
- 2) Set RBW = 1MHz. Set VBW ≥ 3MHz
- 3) Number of points in sweep \geq 2 Span / RBW. Sweep time = auto
- 4) Detector = Average
- 5) Trace mode=Max hold
- 6) Record the max value

2.5.4. Test Result

802.11a Mode

A.Test Verdict:

Channel	Frequency (MHz)	Measured PPSD (dBm/MHz)	Duty Factor	Corrected PPSD (dBm/MHz)	Limit (dBm/MHz)	Verdict
36	5180	2.36		2.45		
44	5220	2.59	0.09	2.68	11	PASS
48	5240	2.78		2.87		
Channel	Frequency (MHz)	Measured PPSD (dBm/500KHz)	Duty Factor	Corrected PPSD (dBm/500KHz)	Limit (dBm/500KHz)	Verdict
149	5745	1.36		1.45		
157	5785	-0.63	0.09	-0.54	30	PASS
165	5825	-2.09		-2.00		



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555 E-mail: service@morlab.cn Http://www.morlab.cn

Fax: 86-755-36698525



B.Test Plot:



(Channel 36, 5180MHz, 802.11)



(Channel 44, 5220MHz, 802.11a)



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555

Fax: 86-755-36698525 E-mail: service@morlab.cn







(Channel 48, 5240MHz, 802.11a)



(Channel 149, 5745MHz, 802.11a)

MORLAB

Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China







(Channel 157, 5785MHz, 802.11a)



(Channel 165, 5825MHz, 802.11a)

MORLAB

Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555 Fax: 86-755-36698525 Http://www.morlab.cn

E-mail: service@morlab.cn



802.11n (HT20) Mode

A.Test Verdict:

Channel	Frequency (MHz)	Measured PPSD (dBm/MHz)	Duty Factor	Corrected PPSD (dBm/MHz)	Limit (dBm/MHz)	Verdict
36	5180	1.40		1.49		
44	5220	1.93	0.09	2.02	11	PASS
48	5240	2.47		2.56		
Channel	Frequency (MHz)	Measured PPSD (dBm/500KHz)	Duty Factor	Corrected PPSD (dBm/500KHz)	Limit (dBm/500KHz)	Verdict
149	5745	0.88		0.97		
157	5785	-1.02	0.09	-0.93	30	PASS
165	5825	-2.63		-2.54		

B.Test Plot:



(Channel 36, 5180MHz, 802.11n (HT20))









(Channel 44, 5220MHz, 802.11n (HT20))



(Channel 48, 5240MHz, 802.11n (HT20))

MORLAB

Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555 Http://www.morlab.cn E-mail: service@morlab.cn

Fax: 86-755-36698525







(Channel 149, 5745MHz, 802.11n (HT20))



(Channel 157, 5785MHz, 802.11n (HT20))

MORLAB

Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555 Fax: Http://www.morlab.cn E-ma

Fax: 86-755-36698525 E-mail: service@morlab.cn







(Channel 165, 5825MHz, 802.11n (HT20))



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555 Fax: 86-755-36698525 Http://www.morlab.cn E-mail: service@morlab.cn

Page 47 of 98



802.11n (HT40) Mode

A.Test Verdict:

Channel	Frequency (MHz)	Measured PPSD (dBm/MHz)	Duty Factor	Corrected PPSD (dBm/MHz)	Limit (dBm/MHz)	Verdict
38	5190	-0.41	0.17	-0.24	11	DAGG
46	5230	0.06	0.17	0.23	11	FA33
Channel	Frequency (MHz)	Measured PPSD (dBm/500KHz)	Duty Factor	Corrected (dBm/500KHz)	Limit (dBm/500KHz)	Verdict
151	5755	-1.75	0.17	-1.58	20	DASS
159	5795	-3.55	0.17	-3.38		FA33

B.Test Plot:



(Channel 38, 5190MHz, 802.11n (HT40))









(Channel 46, 5230MHz, 802.11n (HT40))



(Channel 151, 5755MHz, 802.11n (HT40))



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China







(Channel 159, 5795MHz, 802.11n (HT40))



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555 Fax: 86-755-36698525 Http://www.morlab.cn E-mail: service@morlab.cn



802.11ac (VHT20) Mode

A.Test Verdict:

Channel	Frequency (MHz)	Measured PPSD (dBm/MHz)	Duty Factor	Corrected PPSD (dBm/MHz)	Limit (dBm/MHz)	Verdict
36	5180	0.10		0.18		
44	5220	0.48	0.08	0.56	11	PASS
48	5240	0.70		0.78		
Channel	Frequency (MHz)	Measured PPSD (dBm/500KHz)	Duty Factor	Corrected PPSD (dBm/500KHz)	Limit (dBm/500KHz)	Verdict
149	5745	-0.53		-0.45		
157	5785	-1.72	0.08	-1.64	30	PASS
165	5825	-3.56		-3.48		

B.Test Plot:



(Channel 36, 5180MHz, 802.11ac (VHT20))









(Channel 44, 5220 MHz, 802.11ac (VHT20))



(Channel 48, 5240MHz, 802.11ac (VHT20))

MORLAB

Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555 Http://www.morlab.cn E-mail: service@morlab.cn

Fax: 86-755-36698525







(Channel 149, 5745MHz, 802.11ac (VHT20))



(Channel 157, 5785MHz, 802.11ac (VHT20))



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China







(Channel 165, 5825MHz, 802.11ac (VHT20))



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555 Fax: 86-755-36698525 Http://www.morlab.cn E-mail: service@morlab.cn



802.11ac (VHT40) Mode

A.Test Verdict:

Channel	Frequency (MHz)	Measured PPSD (dBm/MHz)	Duty Factor	Corrected PPSD (dBm/MHz)	Limit (dBm/MHz)	Verdict
38	5190	-2.42	0.10	-2.24	11	DAGG
46	5230	-1.98	0.10	-1.80	11	FA33
Channel	Frequency (MHz)	Measured PPSD (dBm/500KHz)	Duty Factor	Corrected PPSD (dBm/500KHz)	Limit (dBm/500KHz)	Verdict
151	5755	-3.15	0.10	-2.97	20	DASS
159	5795	-4.32	0.18	-4.14	30	PASS

B.Test Plot:



(Channel 38, 5190MHz, 802.11ac (VHT40))









(Channel 46, 5230 MHz, 802.11ac (VHT40))



(Channel 151, 5755MHz, 802.11ac (VHT40))

MORLAB

Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555 Http://www.morlab.cn E-mail: service@morlab.cn

Fax: 86-755-36698525







(Channel 159, 5795MHz, 802.11ac (VHT40))



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555 Fax: 86-755-36698525 E-mail: service@morlab.cn Http://www.morlab.cn



802.11ac (VHT80) Mode

A.Test Verdict:

Channel	Frequency (MHz)	Measured PPSD (dBm/MHz)	Duty Factor	Corrected PPSD (dBm/MHz)	Limit (dBm/MHz)	Verdict
42	5210	-5.61	0.31	-5.30	11	PASS
Channel	Frequency (MHz)	Measured PPSD (dBm/500KHz)	Duty Factor	Corrected (dBm/500KHz)	Limit (dBm/500KHz)	Verdict
155	5775	-6.84	0.31	-6.53	30	PASS

B.Test Plot:



(Channel 42, 5210MHz, 802.11ac (VHT80))



Fax: 86-755-36698525





anter Fred F 775000000	CH-	Service and I	Aug Type: PMS	IRACE BERNARD	Frequency
enter Freq 5.77500000	PNO: Fast	Trig: Free Run Atten: 18 dB	Avg Hold:>10/10	TYPE MUMANUM	
Ref Offset 12 dB dB/div Ref 20.00 dBm			Mk	r1 5.768 76 GHz -6.836 dBm	Auto Tune
0.0					Center Free 5.775000000 GH
00					Start Fre 5.715000000 GH
no 00					Stop Fre 5.835000000 GH
				harres	CF Ste 12.000000 MH Auto Ma
a.a.					Freq Offse 0 H
u o					
enter 5.77500 GHz	#VRM	1.6 MH7*	#Sween	Span 120.0 MHz	

(Channel 155, 5775MHz, 802.11ac (VHT80))



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China

Tel: 86-755-36698555 Fax: 86-755-36698525 Http://www.morlab.cn E-mail: service@morlab.cn



2.6. Frequency Stability

2.6.1. Requirement

Manufacturers of U-NII devices are responsible for ensuring frequency stability such that an emission is maintained within the band of operation under all conditions of normal operation as specified in the user's manual.

2.6.2. Test Procedure

The EUT was placed inside of an environmental chamber as the temperature in the chamber was varied between 5°Cto 40°C. The temperature was incremented by 10° intervals and the unit was allowed to stabilize at each temperature before each measurement. The center frequency of the transmitting channel was evaluated at each temperature and the frequency deviation from the channel's center frequency was recorded. Data for the worst case channel is shown below.

U-NII-1 (Ch. 36)								
5180MHz								
VOLTAGE	POWER	TEMP	Fre. Dev.	Deviation				
(%)	(VDC)	(°C)	(kHz)	(ppm)				
100%		+20(Ref)	20	3.861				
100%		-30	21	4.054				
100%	-	-20	23	4.440				
100%	-	-10	25	4.826				
100%	5.00	0	19	3.668				
100%	5.00	+10	22	4.247				
100%		+20	20	3.861				
100%		+30	21	4.054				
100%		+40	22	4.247				
100%	-	+50	26	5.019				
115%	5.75	+20	27	5.212				
85%	4.25	+20	30	5.792				

2.6.3. Test Result



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China



U-NII-3 (Ch. 149)									
5745MHz									
VOLTAGE	POWER	TEMP	Fre. Dev.	Deviation					
(%)	(VDC)	(°C)	(kHz)	(ppm)					
100%		+20(Ref)	20	3.481					
100%		-30	22	3.829					
100%		-20	23	4.003					
100%		-10	21	3.655					
100%	5.00	0	22	3.829					
100%	5.00	+10	22	3.829					
100%		+20	25	4.352					
100%		+30	29	5.048					
100%		+40	30	5.222					
100%		+50	30	5.222					
115%	5.75	+20	32	5.570					
85%	4.25	+20	29	5.048					



Fax: 86-755-36698525



2.7. Conducted Emission

2.7.1. Requirement

According to FCC section 15.207, for an intentional radiator that is designed to be connected to the public utility (AC) power line, the radio frequency voltage that is conducted back onto the AC power line on any frequency within the band 150kHz to 30MHz shall not exceed the limits in the following table, as measured using a 50μ H/ 50Ω line impedance stabilization network (LISN).

	Conducted Limit (dBµV)					
	Quai-peak	Average				
0.15 - 0.50	66 to 56	56 to 46				
0.50 - 5	56	46				
5 - 30	60	50				

Note:

(a) The lower limit shall apply at the band edges.

(b) The limit decreases linearly with the logarithm of the frequency in the range 0.15 - 0.50MHz.

2.7.2. Test Description

Test Setup:



The Table-top EUT was placed upon a non-metallic table 0.8m above the horizontal metal reference ground plane. EUT was connected to LISN and LISN was connected to reference Ground Plane. EUT was 80cm from LISN. The set-up and test methods were according to ANSI C63.10: 2013.





2.7.3. Test Result

The maximum conducted interference is searched using Peak (PK), if the emission levels more than the AV and QP limits, and that have narrow margins from the AV and QP limits will be re-measured with AV and QP detectors. Tests for both L phase and N phase lines of the power mains connected to the EUT are performed. Set RBW=9kHz, VBW=30kHz. Refer to recorded points and plots below.

Note: Both of the test voltage AC 120V/60Hz and AC 230V/50Hzwere considered and tested respectively, only the results of the worst case AC 120V/60Hz were recorded in this report.

A.Test Setup:

Test Mode: EUT+ Adapter+Earphone WIFI TX Test Voltage: AC 120V/60Hz The measurement results are obtained as below: $E [dB\mu V] = U_R + L_{Cable loss} [dB] + A_{Factor}$ U_R: Receiver Reading AFactor: Voltage division factor of LISN





B.Test Plot:



(L Phase)

No.	Fre. Emission Le		.evel (dBµV)	Limit (dBµV)	Power-line	Verdict
	(MHz)	Quai-peak	Average	Quai-peak	Average		
1	0.5326	36.07	31.26	56.00	46.00		PASS
2	0.6585	33.68	26.34	56.00	46.00		PASS
3	1.0003	38.24	32.43	56.00	46.00	Lino	PASS
4	1.2036	33.19	22.40	56.00	46.00	Line	PASS
5	1.6529	31.56	22.62	56.00	46.00		PASS
6	14.9450	36.21	26.21	60.00	50.00		PASS







(N	Phase)
----	--------

No.	Fre. Emission Le		evel (dBµV)	Limit (dBµV)	Power-line	Verdict
	(MHz)	Quai-peak	Average	Quai-peak	Average		
1	0.3392	35.65	25.11	59.22	49.22		PASS
2	0.6542	34.33	22.60	56.00	46.00		PASS
3	0.8876	34.56	23.10	56.00	46.00	Neutrol	PASS
4	1.4640	32.79	20.96	56.00	46.00	neutrai	PASS
5	14.4085	43.11	28.22	60.00	50.00		PASS
6	18.6772	39.00	24.71	60.00	50.00		PASS





2.8. Restricted Frequency Bands

2.8.1. Requirement

The peak emissions outside of the frequency bands of operation shall be attenuated in accordance with the following limits:

(1) For transmitters operating in the 5.15–5.25 GHz band: all emissions outside of the 5.15–5.35 GHz band shall not exceed an EIRP of -27dBm/MHz.

(2) For transmitters operating in the 5.25–5.35 GHz band: all emissions outside of the 5.15–5.35 GHz band shall not exceed an EIRP of -27dBm/MHz.

(3) For transmitters operating in the 5.47–5.725 GHz band: all emissions outside of the 5.47–5.725 GHz band shall not exceed an EIRP of -27dBm/MHz.

(4) For transmitters operating in the 5.725-5.85 GHz band:

(i) All emissions shall be limited to a level of -27 dBm/MHz at 75 MHz or more above or below the band edge increasing linearly to 10 dBm/MHz at 25 MHz above or below the band edge, and from 25 MHz above or below the band edge increasing linearly to a level of 15.6 dBm/MHz at 5 MHz above or below the band edge, and from 5 MHz above or below the band edge increasing linearly to a level of 27 dBm/MHz at the band edge.

The following formula is used to convert the equipment isotropic radiated power(e.i.r.p.) to field strength (dBµV/m);

$$E = \frac{1000000 \times \sqrt{30P}}{3} \mu \text{V/m}$$

where P is the EIRP in Watts

Therefore: -27 dBm/MHz = 68.23 dBuV/m





Unwanted emissions below 1 GHz must comply with the general field strength limits set forth in § 15.209. According to FCC section 15.209 (a), except as provided elsewhere in this subpart, the emissions from an intentional radiator shall not exceed the field strength levels specified in the following table:

Frequency (MHz)	Field Strength (µV/m)	Measurement Distance (m)
0.009 - 0.490	2400/F(kHz)	300
0.490 - 1.705	24000/F(kHz)	30
1.705 - 30.0	30	30
30 - 88	100	3
88 - 216	150	3
216 - 960	200	3
Above 960	500	3

For Above 1000MHz, the emission limit in this paragraph is based on measurement instrumentation employing an average detector, measurement using instrumentation with a peak detector function, corresponding to 20dB above the maximum permitted average limit. In addition, radiated emissions which fall in the restricted bands, as defined in Section 15.205(a), also should comply with the radiated emission limits specified in Section 15.209(a)(above table).

2.8.2. Test Description

Test Setup



MORLAB

Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China



The EUT is located in a 3m Semi-Anechoic Chamber; the antenna factors, cable loss and so on of the site as factors are calculated to correct the reading.

KDB 789033 Section H) 3)5)6(d)) was used in order to prove compliance

For the Test Antenna:

Test Antenna is 3m away from the EUT. Test Antenna height is varied from 1m to 4m above the ground to determine the maximum value of the field strength.

2.8.3. Test Result

The lowest and highest channels are tested to verify Restricted Frequency Bands.

The measurement results are obtained as below:

 $E [dB\mu V/m] = U_R + A_T + A_{Factor} [dB]; A_T = L_{Cable loss} [dB] - G_{preamp} [dB]$

A_T: Total correction Factor except Antenna; U_R: Receiver Reading

Gpreamp: Preamplifier Gain; AFactor: Antenna Factor at 3m

Note 1: Restricted Frequency Bands were performed when antenna was at vertical and horizontal polarity, and only the worse test condition (vertical) was recorded in this test report.

Note 2 All test modes and bandwidth were considered and evaluated respectively by performing full test, only the worst data were recorded for each bandwidth.

802.11a Mode

		Detector	Receiver			Max.		
	Frequency	Delector	Reading	AT	A _{Factor}	Emission	Limit	Vordict
Channel	(MHz)		U _R	(dB)	(dB@3m)	Е	(dBµV/m)	veruici
			(dBµV)			(dBµV/m)		
36	5084.12	PK	45.81	-19.54	32.20	58.47	74	PASS
36	5150.00	AV	33.44	-19.54	32.20	46.10	54	PASS
48	5358.80	PK	43.16	-19.54	32.20	55.82	74	PASS
48	5358.58	AV	31.48	-19.54	32.20	44.14	54	PASS
149	5725.00	PK	53.95	-19.01	32.20	67.14	122.23	PASS
165	5850.00	PK	41.78	-19.01	32.20	54.97	122.23	PASS

A.Test Verdict:





B.Test Plot:

Reysight Spectrum Analyzer - Swept SA		CENCE JUIT		A ALICH OFF	05:44:00 00 00:00 70 70 7	
arker 2 5.084120000000	GHz PNO: Fast	Trig: Free Run	Avg Avg	Type: Voltage Hold:>100/100	TRACE 1 2 3 4	Marker
dB/div Ref 102.99 dBµV	IFGain:Low	#Atten: 6 dB		Mkr	2 5.084 12 G 45.805 dB	Select Marker 2
9						Norma
1 D 1 D 1 D 1 D 1 D 1 D 1 D 1 D	وودينا ورسيد المنازية		Naranan	alter and a second and	Pain fur mush	Delt
10 17						Fixed
art 4.5000 GHz Res BW (CISPR) 1 MHz	#VBV	V 3.0 MHz	FUNCTION	Sweep 1	Stop 5.1800 G 400 ms (1001 p	Hz (s)
N 1 F 5.15 N 1 F 5.08	50 00 GHz 34 12 GHz	44.160 dBµV 45.805 dBµV				Properties
						Mor 1 of
				STATUS	1-1	

(PEAK, Channel 36, 802.11a)



(AVERAGE, Channel 36, 802.11a)



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China



Marker Select Marker	06:50:50 PM Mar 30, 2022 TRACE 1 3 4 5 0 TYPE MWWWWW DET P P N N N N	ALIGN OFF Type: Voltage Hold:>100/100	л Ал Ал	SENSE: Trig: Free Run #Atten: 6 dB	GHz PNO: Fast IFGain:Low	50 Ω DC 00000000 (F PRESEL	er 2 5
2	2 5.358 80 GHz 43.161 dBµV	Mkr				2.99 dBµV	Ref 10	dív
Norm								444
Del	and a second	drub der das traces.	2	was 21	hajjar ² (reported).	musemure	U.	Le A
Fixed								
O	Stop 5.4600 GHz .000 ms (1001 pts)	Sweep 1.	FUNCTION	3.0 MHz	#VBW	1 MHz ×	0 GHz CISPR)	5.240 BW (
Properties				10.227 dBµV 13.161 dBµV	0 00 GHz 8 80 GHz	5.350 5.358	f	N 1 N 1
Mo 1 ol							2 Z 2 Z 2 Z 2 Z	

(PEAK, Channel 48, 802.11a)



(AVERAGE, Channel 48, 802.11a)







Marker Select Marker	MMar 30, 2022 CE 123450 PE MWWWWWW ET PPNNNN	06:55:46 P TRAC TYI D	ALIGN OFF : Voltage :>100/100	Avg Ty Avg Hol	SENSE:INT Free Run n: 6 dB	Trig: Fi #Atten:	GHz PNO: Fast C IFGain:Low	- Swept SA 50 Ω DC 00000000	F PRESEL	sight Spec
4	000 GHz 52 dBµV	5.725 0 53.95	Mkr4					.99 dBµV	Ref 102	3/dív
Norma	F									
Delta	J. J. J. J.	2	u	. \$	pro Anna de Jung La spar de	ment to and the	Anton de la constante	ورويا وراد ومعالم	horisettere	ynergitteekit
Fixed										
01	7450 GHz (1001 pts)	Stop 5.7 000 ms (Sweep 1.		Hz	W 3.0 MH	#VB	1 MHz	00 GHz CISPR)	t 5.46 s BW (
Properties	E E	FUNCTI	ICTION WIDTH	ICTION P	dBµV dBµV dBµV dBµV dBµV	41.676 c 43.940 c 44.261 c 53.952 c	000 GHz 000 GHz 000 GHz 000 GHz	5.650 5.700 5.720 5.725		N 1 N 1 N 1 N 1
Mor 1 of:										

(PEAK, Channel 149, 802.11a)



(PEAK, Channel 165, 802.11a)



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China



802.11n (HT40) Mode

A.Test Verdict:

		Detector	Receiver			Max.		
	Frequency	Delector	Reading	AT	A _{Factor}	Emission	Limit	Vordict
Channel	(MHz)		U _R	(dB)	(dB@3m)	Е	(dBµV/m)	verdict
		PN/AV	(dBµV)			(dBµV/m)		
38	5150.00	PK	47.37	-19.54	32.20	60.03	74	PASS
38	5150.00	AV	36.67	-19.54	32.20	49.33	54	PASS
48	5357.88	PK	42.02	-19.54	32.20	54.68	74	PASS
48	5353.97	AV	32.42	-19.54	32.20	45.08	54	PASS
151	5725.00	PK	55.71	-19.01	32.20	68.90	122.23	PASS
159	5925.00	PK	41.70	-19.01	32.20	54.89	68.23	PASS

B.Test Plot:

L REPRESEL 50 9 DC		SENSE:IN	T	ALIGN OFF	01:08:41 AM Apr 06, 2022	10000
ker 2 5.14860000000	GHz	Trig: Free Run	Avg	Type: Voltage	TRACE 1 2 3 4 5 6	Marker
	IFGain:Low	#Atten: 6 dB			DET PPNNN	Select Marker
B/div Ref 102.99 dBµV				Mkr	2 5.148 60 GHz 46.818 dBµV	2
						Norm
					2/	Del
	and a second	4_************************************	*******	אייראייעלאייעלאייעלאייעלאייעלאייעלאייעלא		Fixed
t 4.5000 GHz s BW (CISPR) 1 MHz	#VBI	W 3.0 MHz	FUNCTION	Sweep 1	Stop 5.1900 GHz 400 ms (1001 pts)	o
N 1 F 5.15 N 1 F 5.14	0 00 GHz 8 60 GHz	47.366 dBµV 46.818 dBµV				Properties
						Mo 1 o
					-	

(PEAK, Channel 38, 802.11n (HT40))



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China

Tel: 86-755-36698555 Http://www.morlab.cn E-mail: service@morlab.cn

Fax: 86-755-36698525


Marker	01:09:04 AM Apr 06, 2022	ALIGN OFF	τ	SENSE:IM		ter - swept SA	RF PRESEL	sight Spe
Select Marker		Hold: 14/100	A	Trig: Free Run #Atten: 6 dB	PNO: Fast IFGain:Low	000000000	5.1486	ker 2
2	2 5.148 60 GHz 36.132 dBµV	Mkr				2.99 dBµV	Ref 10	3/dív
Norm								
Del	(2)							
Fixed								
0	Stop 5.1900 GHz 19.3 ms (1001 pts)	Sweep 7	Finetica	1.1 kHz	#VBW	1 MHz	00 GHz (CISPR)	t 4.50 s BW
Properties	POWERDIN VALUE	POIL NOR YEAR	PONCHON	36,674 dBµV 36,132 dBµV	0 00 GHz 8 60 GHz	5.150 5.148	f	N 1
Mo 1 of								
		STATUS						

(AVERAGE, Channel 38, 802.11n (HT40))



(PEAK, Channel 48, 802.11n (HT40))





arker 2 5.353970000000	2022 4 5 Marker	07:14:16 PM Mar 30, 2022 TRACE 1 2 3 4 5 0 TYPE M
	Select Marker	
dB/div Ref 102.99 dBµV	μV 2	32.422 dBµV
9 10 10	Norma	
	Delt	
	Fixed	
art 5.2300 GHz Res BW (CISPR) 1 MHz	GHz	Stop 5.4600 GHz
R MODE TRC SCL X		FUNCTION VALUE
N 1 F 5.30	Properties	E
	Mor	
	1.01	

(AVERAGE, Channel 48, 802.11n (HT40))



(PEAK, Channel 151, 802.11n (HT40))



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China



Marker	07:29:54 PM Mar 30, 2022	ALIGN OFF	ti I	SENSE:IN	1	EL 50 Ω DC	RF PRES	
morner	TRACE 1 2 3 4 5 6 TYPE MWANNAN DET P P N N N N	Type: Voltage Hold:>100/100	Avg	Trig: Free Run	PNO: Fast C	5000000000	5.92	ker 4
Select Marker 4	4 5.925 00 GHz 41.704 dBµV	Mkr4		in a constant	IPGam:Low	102.99 dBµV	Ref	3/div
Norm							1 8-4	ساده می ا
Deli	aland to more attribution and one	while the other states and the se		23 million	\$ ¹ \$ ²	Hernstranglightered	Y	
Fixed								
0	Stop 6.0000 GHz .000 ms (1001 pts)	Sweep 1.	TimeTick	V 3.0 MHz	#VB	iz R) 1 MHz	950 G (CISF	t 5.79 s BW
Properties	POWLINGN VALUE	PONCTON WIDTH	PONCTION	41.704 dBµV 41.264 dBµV 41.278 dBµV 41.704 dBµV	850 00 GHz 855 00 GHz 880 00 GHz 925 00 GHz	5.8 5.8 5.8 5.8 5.9		N N N N
Mor 1 of								
	· · · · · · · · · · · · · · · · · · ·							

(PEAK, Channel 159, 802.11n (HT40))





802.11 ac (VHT80) Mode

A.Test Verdict:

		Detector	Receiver			Max.		
Channel	Frequency	Delector	Reading	AT	A _{Factor}	Emission	Limit	Vardiat
Channel	(MHz)		U _R	(dB)	(dB@3m)	Е	(dBµV/m)	vertici
		PN/AV	(dBuV)			(dBµV/m)		
42	5148.40	PK	55.79	-19.54	32.2	68.45	74	PASS
42	5143.00	AV	36.99	-19.54	32.2	49.65	54	PASS
42	5385.80	PK	43.79	-19.54	32.2	56.45	74	PASS
42	5355.80	AV	32.72	-19.54	32.2	45.38	54	PASS
155	5720.00	PK	53.51	-19.01	32.2	66.70	110.83	PASS
155	5850.00	PK	50.03	-19.01	32.2	63.22	122.23	PASS

B.Test Plot:



(Channel 42, PEAK, 802.11ac (VHT80))









(Channel 42, AVG, 802.11ac (VHT80))



(Channel 155, PEAK, 802.11ac (VHT80))

MORLAB

Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555 Fax Http://www.morlab.cn E-r



2.9. Radiated Emission

2.9.1. Requirement

The peak emissions outside of the frequency bands of operation shall be attenuated in accordance with the following limits:

(1) For transmitters operating in the 5.15–5.25 GHz band: all emissions outside of the 5.15–5.35 GHz band shall not exceed an EIRP of -27dBm/MHz.

(2) For transmitters operating in the 5.25–5.35 GHz band: all emissions outside of the 5.15–5.35 GHz band shall not exceed an EIRP of -27dBm/MHz.

(3) For transmitters operating in the 5.47–5.725 GHz band: all emissions outside of the 5.47–5.725 GHz band shall not exceed an EIRP of -27dBm/MHz.

(4) For transmitters operating in the 5.725-5.85 GHz band: All emissions within the frequency range from the band edge to 10 MHz above or below the band edge shall not exceed an e.i.r.p. of -17 dBm/MHz; for frequencies 10 MHz or greater above or below the band edge, emissions shall not exceed an e.i.r.p. of -27 dBm/MHz.

The following formula is used to convert the equipment isotropic radiated power(e.i.r.p.) to field strength (dBµV/m);

$$E = \frac{1000000 \times \sqrt{30P}}{3} \mu V/m}$$

where P is the EIRP in Watts
Therefore: -27 dBm/MHz = 68.23 dBuV/m

Unwanted emissions below 1 GHz must comply with the general field strength limits set forth in § 15.209. According to FCC section 15.209 (a), except as provided elsewhere in this subpart, the emissions from an intentional radiator shall not exceed the field strength levels specified in the following table:

Frequency (MHz)	Field Strength (µV/m)	Measurement Distance (m)
0.009 - 0.490	2400/F(kHz)	300
0.490 - 1.705	24000/F(kHz)	30
1.705 - 30.0	30	30
30 - 88	100	3
88 - 216	150	3
216 - 960	200	3
Above 960	500	3



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China



For Above 1000MHz, the emission limit in this paragraph is based on measurement instrumentation employing an average detector, measurement using instrumentation with a peak detector function, corresponding to 20dB above the maximum permitted average limit. In addition, radiated emissions which fall in the restricted bands, as defined in Section 15.205(a), also should comply with the radiated emission limits specified in Section 15.209(a)(above table).

2.9.2. Test Description

Test Setup:

1) For radiated emissions from 9kHz to 30MHz





Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555

Fax: 86-755-36698525

Http://www.morlab.cn



2) For radiated emissions from 30MHz to1GHz



3) For radiated emissions above 1GHz



The EUT is placed on a non-conducting table 80 cm above the ground plane for measurement below 1GHz; 1.5 m above the ground plane for measurement above 1GHz.The antenna to EUT distance is 3meters. The EUT is configured in accordance with ANSI C63.10. The EUT is set to transmit in a continuous mode.

MORLAB



For measurements below 30MHz, the emission limits shown in the above table are based on measurements employing a CISPR quasi-peak detector except for the frequency bands 9kHz-90 kHz, 110kHz-490 kHz. Radiated emission limits in these two bands are based on measurements employing an average detector.

For measurements below 1GHz the resolution bandwidth is set to 100kHz for peak detection measurements or 120kHz for quasi-peak detection measurements. Peak detection is used unless otherwise noted as quasi-peak.

For measurements above 1GHz the resolution bandwidth is set to 1MHz, the video band width is set to 3MHz for peak measurements and as applicable for average measurements.

The frequency range of interest is monitored at a fixed antenna height and EUT azimuth. The EUT is rotated through 360 degrees to maximize emissions received. The antenna is scanned from 1 to 4 meters above the ground plane to further maximize the emission. Measurements are made with the antenna polarized in both the vertical and the horizontal positions.

2.9.3. Test Result

According to ANSI C63.10, because of peak detection will yield amplitudes equal to or greater than amplitudes measured with the quasi-peak (or average) detector, the measurement data from a spectrum analyzer peak detector will represent the worst-case results, if the peak measured value complies with the quasi-peak (or average) limit, it is unnecessary to perform an quasi-peak measurement (or average).

The measurement results are obtained as below:

 $E [dB\mu V/m] = U_R + A_T + A_{Factor} [dB]; A_T = L_{Cable loss} [dB] - G_{preamp} [dB]$

A_T: Total correction Factor except Antenna

U_R: Receiver Reading

G_{preamp}: Preamplifier Gain

A_{Factor}: Antenna Factor at 3m

During the test, the total correction Factor A_T and A_{Factor} were built in test software.

Note 1: All radiated emission tests were performed in X, Y, Z axis direction. And only the worst axis test condition was recorded in this test report.

Note 2: For the frequency, which started from 9kHz to 30MHz, was pre-scanned and the result which was 20dB lower than the limit was not recorded.

Note 3: For the frequency, which started from 18GHz to 40GHz, was pre-scanned and the result which was 20dB lower than the limit was not recorded.

Note 4: All test modes and bandwidth were considered and evaluated respectively by performing full test, only the worst data were recorded for each bandwidth.





802.11a Mode





(Antenna Horizontal, 30MHz to 18GHz)



(Antenna Vertical, 30MHz to 18GHz)



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555 Http://www.morlab.cn



Plot for Channel 44



(Antenna Horizontal, 30MHz to 18GHz)



(Antenna Vertical, 30MHz to 18GHz)



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555

Fax: 86-755-36698525

Http://www.morlab.cn





(Antenna Horizontal, 30MHz to 18GHz)



(Antenna Vertical, 30MHz to 18GHz)



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555

Fax: 86-755-36698525

Http://www.morlab.cn E-mail: service@morlab.cn





(Antenna Horizontal, 30MHz to 18GHz)



(Antenna Vertical, 30MHz to 18GHz)



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555

Fax: 86-755-36698525

Http://www.morlab.cn





(Antenna Horizontal, 30MHz to 18GHz)



(Antenna Vertical, 30MHz to 18GHz)



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555 Http://www.morlab.cn Fax: 86-755-36698525





(Antenna Horizontal, 30MHz to 18GHz)



(Antenna Vertical, 30MHz to 18GHz)



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555

Fax: 86-755-36698525

Http://www.morlab.cn



802.11n (HT40) Mode

Plot for Channel 38



(Antenna Horizontal, 30MHz to 18GHz)



(Antenna Vertical, 30MHz to 18GHz)



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555 Http://www.morlab.cn







(Antenna Vertical, 30MHz to 18GHz)



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555 Http://www.morlab.cn





(Antenna Horizontal, 30MHz to 18GHz)



(Antenna Vertical, 30MHz to 18GHz)



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555

Fax: 86-755-36698525

Http://www.morlab.cn E-mail: service@morlab.cn





(Antenna Horizontal, 30MHz to 18GHz)



(Antenna Vertical, 30MHz to 18GHz)



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555

Fax: 86-755-36698525

Http://www.morlab.cn



802.11ac (VHT80) Mode

Plot for Channel 42



(Antenna Horizontal, 30MHz to 18GHz)



(Antenna Vertical, 30MHz to 18GHz)



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555 Http://www.morlab.cn





(Antenna Horizontal, 30MHz to 18GHz)



(Antenna Vertical, 30MHz to 18GHz)



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China Tel: 86-755-36698555

Fax: 86-755-36698525

Http://www.morlab.cn E-mail: service@morlab.cn



Annex A Test Uncertainty

Where relevant, the following measurement uncertainty levels have been estimated for test performed on the EUT as specified in CISPR 16-1-2:

Test Items	Uncertainty
Peak Output Power	±2.22dB
Power Spectral Density	±2.22dB
Bandwidth	±5%
Restricted Frequency Bands	±5%
Radiated Emission	±2.95dB
Conducted Emission	±2.44dB

This uncertainty represent an expanded uncertainty expressed at approximately the 95% confidence level using a coverage factor of k=2.





Annex B Testing Laboratory Information

1. Identification of the Responsible Testing Laboratory

Laboratory Name:	Shenzhen Morlab Communications Technology Co., Ltd.		
	FL.3, Building A, FeiYang Science Park, No.8 LongChang		
Laboratory Address:	Road, Block 67, BaoAn District, ShenZhen, GuangDong		
	Province, P. R. China		
Telephone:	+86 755 36698555		
Facsimile:	+86 755 36698525		

2. Identification of the Responsible Testing Location

Name:	Shenzhen Morlab Communications Technology Co., Ltd.
	FL.3, Building A, FeiYang Science Park, No.8 LongChang
Address:	Road, Block 67, BaoAn District, ShenZhen, GuangDong
	Province, P. R. China

3. Facilities and Accreditations

All measurement facilities used to collect the measurement data are located at FL.3, Building A, FeiYang Science Park, Block 67, BaoAn District, Shenzhen, 518101 P. R. China. The test site is constructed in conformance with the requirements of ANSI C63.10-2013and CISPR Publication 22; the FCC designation number is CN1192, the test firm registration number is 226174.





4. Test Equipments Utilized

4.1 Conducted Test Equipments

Equipment	Serial No.	Туре	Manufacturer	Cal. Date	Due Date
Attenuator 1	N/A	10dB	Resnet	N/A	N/A
EXA Signal		N00404	Agilant	2021.03.25	2022.03.24
Analzyer	IVI 1 5347 0830	N9010A	Aglient	2022.03.01	2023.02.28
USB Wideband	MV54190009		Agilant	2024 40 24	2022 10 20
Power Sensor	IVI 1 04 100000	02021XA	Aglient	2021.10.21	2022.10.20
RF Cable			Marlah		N1/A
(30MHz-26GHz)	CBUT	REUT	denom	IN/A	IN/A
Coaxial Cable	CB02	RF02	Morlab	N/A	N/A
SMA Connector			HUBER-	NI/A	NI/A
SIMA CONNECTOR	CINUT	KFU3	SUHNER	IN/A	IN/A
Temperature	12108015	DTL_003S101		2021 10 20	2022 10 10
Chamber	12100013	DTE-0033101		2021.10.20	2022.10.19

4.2 Conducted Emission Test Equipments

Equipment Name	Serial No.	Туре	Manufacturer	Cal. Date	Due Date
Dessiver	NU/50400000		KEVELOUT	2021.03.09	2022.03.08
Receiver	IVI Y 56400093	N9038A	KETSIGHT	2022.03.03	2023.03.02
	040744	NSLK	Coburer=book	2021.03.09	2022.03.08
LISIN	812744	8127	Schwarzbeck	2022.03.03	2023.03.02
Pulse Limiter	VTSD 9561	VTSD	Sobworzbook	2021 07 21	2022 07 20
(10dB)	F-B #206	9561-F	Schwarzbeck	2021.07.21	2022.07.20
Coaxial					
Cable(BNC)	CB01	EMC01	Morlab	N/A	N/A
(30MHz-26GHz)					

4.3 List of Software Used

Description	Manufacturer	Software Version
Test System	Tonscend	V2.5.77.0418
Morlab EMCR V1.2	Morlab	V1.0
TS+ -[JS32-CE]	Tonscend	V2.5.0.0





4.4Radiated Test Equipments

Equipment Name	Serial No.	Туре	Manufacturer	Cal. Date	Due Date
Receiver	MY54130016	N9038A	Agilent	2021.07.16	2022.07.15
Test Antenna - Bi-Log	9163-519	VULB 9163	Schwarzbeck	2019.05.24	2022.05.23
Test Antenna - Horn	BBHA9170 #774	BBHA 9170	Schwarzbeck	2019.07.26	2022.07.25
Test Antenna - Loop	1519-022	FMZB1519	Schwarzbeck	2022.02.11	2025.02.10
Test Antenna - Horn	01774	BBHA 9120D	Schwarzbeck	2019.07.26	2022.07.25
Coaxial Cable (N male) (9KHz-30MHz)	CB04	EMC04	Morlab	N/A	N/A
Coaxial Cable (N male) (30MHz-26GHz)	CB02	EMC02	Morlab	N/A	N/A
Coaxial Cable (N male) (30MHz-26GHz)	CB03	EMC03	Morlab	N/A	N/A
Coaxial Cable (N male) (30MHz-40GHz)	CB05	EMC05	Morlab	N/A	N/A
1-18GHz pre-Amplifier	61171/61172	S020180L32 03	Tonscend	2021.07.16	2022.07.15
26-40GHz pre-Amplifier	56774	S40M400L4 002	Tonscend	2021.07.16	2022.07.15
18-26.5GHz pre-Amplifier	46732	S10M100L38 02	Tonscend	2021.07.16	2022.07.15
Notch Filter	N/A	WRCG- 5150-5350	Wainwright	2021.07.16	2022.07.15
Notch Filter	N/A	WRCG- 5470-5725	Wainwright	2021.07.16	2022.07.15
Notch Filter	N/A	WRCG- 5725-5850	Wainwright	2021.07.16	2022.07.15



Fax: 86-755-36698525



Equipment Name	Serial No.	Туре	Manufacturer	Cal. Date	Due Date
Anechoic Chamber	N/A	9m*6m*6m	CRT	2020.01.06	2023.01.05

_____ END OF REPORT ____



Shenzhen Morlab Communications Technology Co., Ltd. FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block67, BaoAn District, ShenZhen , GuangDong Province, P. R. China

Tel: 86-755-36698555 Fa Http://www.morlab.cn E-

Fax: 86-755-36698525