


S15S Mini TWS Earbuds




FCC ID: 2AMBAS15S

User Manual

Specifications:

Bluetooth Version:	V5.0
Bluetooth Range:	Up to 33 feet
Support Profile:	HSP/HFP/A2DP/AVRCP
Earbud Battery:	3.7V/50mah
Box Charging Current:	500ma
Earbud Charging Current:	40ma
Music Play Time/Charge:	4-5 hours
Talk Time/Charge:	4-5 hours
USB Output:	DC5V 1A

Diagram:



Power On/Off:

Power on: Take the earbuds out of the box, they will power on automatically.

You can also touch and hold MFB 2 seconds to power on. **Power off:** Put the earbuds into the box, they will power off automatically.

You can also touch and hold MFB for 4 seconds, the indicator stay red for 1 second then go off means powered off. (If the 2 earbuds are connected, press one of the earbuds, the 2 will power off together)

LED Indicator:

Earbuds LED Indicator	
Earbuds Pairing:	Flash blue and red
Earbuds Connected:	One flash blue and red, other one flash blue 1 time every 5 seconds
Phone Connected:	Left and right both flash blue 1 time every 5 seconds
Battery Low:	Flash red
Charging:	Red light on
Charging finished:	Blue light on for 1 min then go off

Pairing Instruction:

1. Get the 2 earbuds out of the box, they will pair first, one flash blue, other one flash red and blue means paired.



2. Turn on the Bluetooth of your phone, search for "S15" and connect.




3. Open your phone music player and play, you can enjoy music wirelessly.



Button operation:

Touch and hold MFB for 2 seconds to switch previous music. Touch and hold MFB for 2 seconds to switch next music.



Touch 1 time: Play/Pause/Answer/Hang up
Touch 2 times: Redial
Touch 3 times: Activate phone voice control
Touch and hold for 2 seconds: Reject/Switch audio source from phone or earbuds


Auto-connect:

It will auto connect the last paired phone when turned on next time. (Turn on the Bluetooth of your phone first, and then turn on the earbuds.)

Charging:



Use micro USB cable to charge the box with DC 5V power supply only. (Do not use power supply higher than 5V)



DC 5V 1A USB output can charge your smart devices.

Clear pairing history

Long press the MFB for 10 seconds when earbuds are in power off state, you will hear an audio cue and the red-blue LED will flash 3 times, then it will flash blue and red. You need to put them back into the battery box and then take out, so they can pair again.

FCC Compliance Statement:

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) this device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.

RF Exposure Compliance Statement:

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

Correct Disposal Of This Product



(Waste Electrical & Electronic Equipment)

This marking shown on the product or its literature, indicates that it should not be disposed with other household wastes at the end of its working life.

To prevent possible harm to the environment or human health from uncontrolled waste disposal, please separate this from other types of wastes and recycle it responsibly to promote the sustainable reuse of material resources.

Household user should contact either the retailer where they purchased this product or their local government office for details of where and how they can take this item for environmentally safe recycling.

Business users should contact their supplier and check the terms and conditions of the purchase contract. This product should not be mixed with other commercial wastes for disposal.