

SMART DIMMER SWITCH USER MANUAL

Single Pole / 3 Way

03 Specification

Input Power	100-120V AC 60Hz
Dimming Control	Leading Edge
Communication	BLE MESH 2.4GHz**
Load	< 300W Incandescent/Halogen < 250W LED
Standby Power	< 1.8W
Button Life	500K times
Dimensions	100*45*45 mm

04 Contents Supplied

Dimmer, Panel, Wire Connectors, Screws

01 Product Outline

Panel, Touch Dimming, On/Off Switch, Dimming Levels, Status LED

02 Indicator Light Status

Light Color	Light Status	Switch Status	Remarks
Green	ON	Power OFF(Default)	Support Self-definition on APP
Green	OFF	Power ON	Connected to router and connected to cloud
ON	ON	Not Connected to the cloud	The white light is enabled only when the switch status is on.
White	Blink Quickly (5 to 10 interval)	Ready for default configuration mode	
	Blink Slowly (1 to 2 interval)	Ready for AP (Access Point) configuration mode	

05 Safety Information

WARNING: RISK OF ELECTRIC SHOCK

Electricity can cause personal injury and property damage if handled improperly. If you are not sure about any part of these instructions, please seek professional assistance from a qualified electrician. Ensure all work meets applicable local and national codes.

Tools you'll need

Phillips head Screwdriver, Flat head Screwdriver, Pliers, Voltage Tester

06 Installation

30min Approximately 30 minutes to install and setup the dimmer

STEP 1 Turn Off Power

Locate your circuit breaker panel and turn off the power to each switch you are replacing.

STEP 2 Remove the switch and pull it away from the wall.

STEP 3 Verify Power is Off

We recommend you to remove the hotplate from the old switch and use an electrical tester to test all wires connected to the switch to ensure there is no voltage in the circuit.

STEP 4 Pull Out Old dimmer

STEP 5 Identify The Old dimmer

A Single Pole Dimmer
Only one dimmer control one light or a bundle of lights.

B 3-Way Dimmer
Two Dimmer control the same light or the same bundle of lights.

STEP 6 Identify Line/Load Wire

Note: The color of your wire may be different from the color shown on the manual.

A Single Pole Dimmer

B 3-Way Dimmer

STEP 7 Find the NEUTRAL Wires

Neutral wire is required to install the smart dimmer. Most likely a bundle of one or more white wires in the wall.

Note: If there is no neutral, please try another location or call an electrician for help.

STEP 8 Test NEUTRAL and GROUND Wires

Make sure there is no power on the neutral wires from neighboring circuit. If necessary, shut off additional circuits until no voltage is found. GROUND wires are usually BARE COPPER or GREEN.

STEP 9 Take Pictures of the Wiring

Loosen the screw terminals and remove the old dimmer.

STEP 10 Wire the Smart Dimmer Switch

Replace ONE of your REGULAR 3-WAY SWITCHES with SMART SWITCH

Not Working Situation

07 Add Devices

STEP 1 Download Smart Life APP

STEP 2 Register And Login

08 Reset

Press and hold Switch button for 5s to reset the Dimmer and get into quick configure mode

09 Smart Life Skills (Alexa)

STEP 1 Log in your Alexa account on a smart phone or a computer, then tap Homes-Skills & Games

STEP 2 Search "Smart Life" and select the right one according to the blue logo (same with App)

STEP 3 Enable the skill

STEP 4 Login the account you registered on the App in Part 2, then click "Link Now"

STEP 5 The Account is linked successfully, and then tap Authorize to Complete.

STEP 6 Congratulations! Alexa Devices (Echo) can Control the Switch ON/OFF.

10 Smart Life Skills (Google)

STEP 1 Find "Home Control" in the hamburger menu on the Google Home app's home page > Home Control > "+"

STEP 2 Find "Smart Life" in the list

STEP 3 Input your Smart Life account and password you registered in Part 2, then tap "Link Now"

STEP 4 After you assign rooms for the Switch, your Switch will be listed in the Home Control page

STEP 5 Control your smart switch through Google Home

IC Caution

This device complies with industry Canada license-exempt RSSI standards. Operation is subject to the following two conditions: (1) This device may not cause interference, and (2) This device must accept any interference, including interference that may cause undesired operation of the device.

FCC Caution

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) This device must accept any interference received, including interference that may cause undesired operation.

1 正面

2 正面

3 正面

折叠方式