

RF EXPOSURE REPORT

Applicant	Earda Technologies Co.,Ltd
Address	A,LianFeng Creative Industry Park,2 JiSheng Road., HuangGe Town, NanSha District, Guangzhou,China



Manufacturer or Supplier	Earda Technologies Co.,Ltd
Address	A,LianFeng Creative Industry Park,2 JiSheng Road., HuangGe Town, NanSha District, Guangzhou,China
Product	Smart Dimmer Switch
Brand Name	Eardatek
Model	EDM-1WAA-US
Additional Model & Model Difference	EDM-1WAB-US
Date of tests	Oct. 30, 2020~ Nov. 12, 2020

☒ **FCC Part 2 (Section 2.1091)**

☒ **KDB 447498 D01**

☒ **IEEE C95.1**

CONCLUSION: The submitted sample was found to COMPLY with the test requirement

Tested by Aaron Liang Project Engineer / EMC Department	Approved by David Huang Supervisor/ EMC Department
	 Date: Nov. 13, 2020

This report is governed by, and incorporates by reference, CPS Conditions of Service as posted at the date of issuance of this report at <http://www.bureauveritas.com/home/about-us/our-business/cps/about-us/terms-conditions/> and is intended for your exclusive use. Any copying or replication of this report to or for any other person or entity, or use of our name or trademark, is permitted only with our prior written permission. This report sets forth our findings solely with respect to the test samples identified herein. The results set forth in this report are not indicative or representative of the quality or characteristics of the lot from which a test sample was taken or any similar or identical product unless specifically and expressly noted. Our report includes all of the tests requested by you and the results thereof based upon the information that you provided to us. Measurement uncertainty is only provided upon request for accredited tests. You have 60 days from date of issuance of this report to notify us of any material error or omission caused by our negligence or if you require measurement uncertainty; provided, however, that such notice shall be in writing and shall specifically address the issue you wish to raise. A failure to raise such issue within the prescribed time shall constitute your unqualified acceptance of the completeness of this report, the tests conducted and the correctness of the report contents.

TABLE OF CONTENTS

RELEASE CONTROL RECORD	3
1. CERTIFICATION.....	4
2. RF EXPOSURE LIMIT	5
3. MPE CALCULATION FORMULA.....	5
4. CLASSIFICATION	5
5. ANTENNA GAIN	6
6. CALCULATION RESULT OF MAXIMUM CONDUCTED POWER.....	6



Test Report No.: FM2010WSZ0078

RELEASE CONTROL RECORD

ISSUE NO.	REASON FOR CHANGE	DATE ISSUED
FM2010WSZ0078	Original release	Nov. 13, 2020

1. CERTIFICATION

FCC ID:	2AMM6-DM1WA
PRODUCT:	Smart Dimmer Switch
BRAND NAME:	Eardatek
MODEL NO.:	EDM-1WAA-US
ADDITIONAL NO.:	EDM-1WAB-US
TEST SAMPLE:	Engineering Sample
APPLICANT:	Earda Technologies Co.,Ltd
STANDARDS:	FCC Part 2 (Section 2.1091)
	KDB 447498 D01
	IEEE C95.1

2. RF EXPOSURE LIMIT

LIMITS FOR MAXIMUM PERMISSIBLE EXPOSURE (MPE)

FREQUENCY RANGE (MHz)	ELECTRIC FIELD STRENGTH (V/m)	MAGNETIC FIELD STRENGTH (A/m)	POWER DENSITY (mW/cm ²)	AVERAGE TIME (minutes)
LIMITS FOR GENERAL POPULATION / UNCONTROLLED EXPOSURE				
300-1500	...	...	F/1500	30
1500-100,000	...	...	1.0	30

F = Frequency in MHz

3. MPE CALCULATION FORMULA

$$P_d = (P_{out} * G) / (4 * \pi * r^2)$$

where

P_d = power density in mW/cm²

P_{out} = output power to antenna in mW

G = gain of antenna in linear scale

π = 3.1416

R = distance between observation point and center of the radiator in cm

4. CLASSIFICATION

The antenna of this product, under normal use condition, is at least 20cm away from the body of the user. So, this device is classified as **Mobile Device**.

5. ANTENNA GAIN

The antennas provided to the EUT, please refer to the following table:

Mode	Transmitter Circuit	Peak Gain (dBi)	Antenna Type
BT-LE	Chain 0	2.3	PCB Antenna
WIFI	Chain 0	2.3	PCB Antenna

6. CALCULATION RESULT OF MAXIMUM CONDUCTED POWER

The tuned conducted Average Power (declared by client)

Mode	Frequency (MHz)	Target Power (dBm)	Tolerance (dBm)	Lower Tolerance (dBm)	Upper Tolerance (dBm)
BT-LE (GFSK)	2402-2480MHz	4	+2	2	6
802.11b	2412-2462MHz	16	+2	14	18
802.11g	2412-2462MHz	15	+2	13	17
802.11n HT20	2412-2462MHz	14	+2	12	16
802.11n HT40	2422-2452MHz	15	+2	13	17

The measured conducted Average Power

Mode	Frequency (MHz)	Averaged Power (dBm)
BT-LE (GFSK)	2480	4.45
802.11b	2437	16.81
802.11g	2462	14.83
802.11n HT20	2462	14.14
802.11n HT40	2422	14.90



FREQUENCY BAND (MHz)	MAX AVERAGE POWER (dBm)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/cm ²)	LIMIT (mW/cm ²)
BT-LE 2402-2480	6	2.3	20	0.00135	1.0
WiFi 2412-2462	18	2.3	20	0.02132	1.0

CONCLUSION:

The BT and WLAN can transmit simultaneously, the formula of calculated the MPE is:

$$\text{CPD1} / \text{LPD1} + \text{CPD2} / \text{LPD2} + \dots \text{etc.} < 1$$

CPD = Calculation power density

LPD = Limit of power density

$$(0.00135/1) + (0.02132/1) = 0.02267 < 1, \text{ which is less than the "1" limit.}$$

--- END ---