

**** MPE Calculations ****

The MPE calculation for this exposure is shown below.

The peak radiated output power (EIRP) is calculated as follows:

<p>EIRP = P + G EIRP = 14.79 dBm + 3.3 dBi EIRP = 18.09 dBm</p>	<p>Where, P = Power input to the antenna (mW) G = Power gain of the antenna (dBi)</p>
-----------------------------------------------------------------------------------------------------------	---------------------------------------------------------------------------------------------------------------------------------

Power density at the specific separation:

<p>$S = PG / (4R^2 \pi)$ $S = (30.13 * 2.14) / (4 * 20^2 * \pi)$ $S = 0.0128 \text{ mW/cm}^2$</p>	<p>Where, S = Maximum power density (mW/cm²) P = Power input to the antenna (mW) G = Numeric power gain of the antenna R = Distance to the center of the radiation of the antenna (20 cm = limit for MPE)</p>
----------------------------------------------------------------------------------------------------------------------------------------------	-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------

The Maximum permissible exposure (MPE) for the general population is 1 mW/cm².

The power density does not exceed the 1 mW/cm² limit.

Therefore, the exposure condition is compliant with FCC rules.

Estimated safe separation:

<p>$R = \sqrt{PG / 4 \pi}$ $R = \sqrt{30.13 * 2.14 / 4 \pi}$ $R = 2.26 \text{ cm}$</p>	<p>Where, P = Power input to the antenna (mW) G = Numeric power gain of the antenna R = Distance to the center of the radiation of the antenna (20 cm = limit for MPE)</p>
-----------------------------------------------------------------------------------------------------------------------------------	----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------

The numeric gain(G) of the antenna with a gain specified in dB is determined by:

$G = \text{Log}^{-1} (\text{dB antenna gain} / 10)$

$G = \text{Log}^{-1} (3.3 / 10)$

$G = 2.14$