Enalish

Ultra - Wireless Neckband Stereo Headset M/N:24400-RK:Factory Code:HBS-730



All rights reserved

Electronics inc ,2012

Note For the best performance and to prevent any damage to ormisuse of the HBS-730.please read all of the information careful y prior to using the HBS 730

Any modifications or changes to this manual due to typographical errors or inaccuracies of stated information shall on y be made by HH Electronics Inc

Description of barts



Ltem	Description
Bluetooth specification	4.0(Headest/Hands-Free/A2DP Profiles)
Hattery	Battery 3.7 V/I 80mAh
Standby time/Talk time	UP to 300Hrs/UP to 10Hrs
Music play time	UP to 8 Hrs
Charging time	<2.0 Hrs
Operation temperature	-10°C°60°C
Dimension (Wainlet	135 6mm(W) X 167 3mm(1) X 16 3mm(7) /32n

How to Use

Pairing

- Defore using the headset for the first time. your must pair it with a Bluetoothenabled handset
- -To pair your headset with an additional handset, the headset must be placed in pairing Mode.
- -There are 2 Pairing Mode Methods with the HBS-730

Easy Pairing(First Time Pairing)

- 1. Move the power switch to the 'ON' side to turn on the HBS-730. When the headset enters Pairing Mode, the LED indicator will show a solid blue light 2. Using your handset, find the Bluetooth Menu and "search for" or "add" new
- Select " HBS730" form the list of devices and pair it with your handset 3. If asked for the Pass/PIN code please enter "0000" (4 Zeros).
- *Note:if your handset supports Secure Simple Pairing(SSP), you will not need to enter Pass/PIN code
- Once pairing has completed successfully, you will hear "Your headset pairde" 4. Some handsets might ask for permission to access the phone's contact list
- if you receive a message from your handset, please select "OK" or "Allow access"

- -The HBS-730 will automatically turn off if not paired within 3 minutes Manual Pairing (Pairing with another phone or re-pairing)
- -With the Power off, press the CALL button and move the power switch to the "ON" side at the same time for 1 second.
- When the headset enters Pairing Mode, the LED indicator will show a solid blue light.After the procedure repeat Easy Paliring steps 2 through 4

Advanced Multipoint

The HBS-730 is capable of having two devices connected to the headset at the same time. This will give you the freedom of using call waiting between calls on both of your connected phones

Connection

- Pair the headset with one of your Bluetooth enabled handsets. (perthe pairing instructions on page 2).
- Turn off the headset.
- With the Power off, press the CALL button and move the power switch to eht "ON" side at the same time for 1 second to enter Manual Pairing mode.
- Now,pair and connect the headset with your other Bluetooth- enabled handset (this will be your primary handset

How to Use

 Once this handset is paired and connected go back and connect the originally paired hand set to the headset this will now be your secondary handset

- If the HBS-730 is turned off(either accidentally or intehtionally) while connected to a handset, the headset and handset will disconnect. The headset and handset will automatically reconnect when the HBS-730 is turned back on while in range Out of range
- If the paired devices are separated by a range of 10meters (33 feet) or more, the headset and handset will disconnect and HBS-730 will vibrate to alert
- If the headset and handset do not automatically reconnect when they are back within the required range, briefly press the CALL button on the HBS 730 to reconnect manually
- * It is possible to use these functions only when your handset supports them. For further information about using these features please consult your handset's
- While in multi-connection and streaming, non-streaming paired device which is out of range will be disconnected and HBS-730 whill alert once and not try to reconnect

Controls

Power on/Power off - Move the power switch to the 'ON' or 'OFF'side How to Use

Volume Control

- Briefly press the VOLUME button

- While charging, the LED indicator will show a solid red light

Low battery

- -An announcement will be made once every 2 minutes
- if the battery is not charged, the headset will turn off.

Answering a call/Ending a call

- When there is an incoming call the headset will ring and vibrate
- Briefly press the VOLUME DOWN button to stop vibration
- Briefly press the CALL button

Last number redial

- If you make a call from the handset, the call will(subject to phone) settings) automatically transfer to the headset. If the call is not automatically transferred, you can manually transfer the call by press and hold VOLUME UP button for 3 seconds Woice dialing
- Briefly press the CALL button to activate "Voice Command" Note: If the handset does not support Voice Dialing, it is possible that performing this action will activate last Number Redial

How to Use

Transferring a call

- While on a call on your handset, press and hold VOLUME UP button for 3 seconds to transfer the audio either from headset to handset or from handset to headset

Call waiting

- Answer a second call without hanging up the first call by pressing the CALL button for 1 second (you will hear a beep). Press the Call button for 1 second to turn to the original call.
- Briefly press the CALL button to terminate the active call or both calls at once

Audio streaming

- PLAY: Briefly press the PLAY/PAUSE button
- PAUSE: Briefly press the PLAY/PAUSE button
- STOP: Press and hold the PLAY/PAUSE button
- NEXT SONG: Briefly press the FF button.
- PREVIOUS SONG: Briefly press the REW button

FCC Statement

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment. NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful in terference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference

to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

Reorient or relocate the receiving antenna.

Increase the separation between the equipment and receiver.

- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected. Consult the dealer or an experienced radio/TV technician for help.
- The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.