R6III说明书

铜版纸120g 过哑油，风琴折

正面

HIBY R6 III
HIGH RESOLUTION MUSIC PLAYER
QUICK GUIDE
快速上手指南

HIBY MAKE MUSIC MORE MUSICAL

中文

前言

感谢您购买了HiBy推出的便携高清无损音乐播放器。为使您更好地使用本产品，请在使用前仔细阅读本说明书。

按键与接口



开机/关机、睡眠/锁屏/亮屏

1、开机：长按电源键两秒后开机；
2、关机、睡眠：开机状态下长按电源键，即可弹出关机/重启菜单；
3、锁屏：开机状态下，点击电源键即可锁屏；
4、亮屏：点击电源键或双击屏幕。

操作系统

HiBy R6III内置安卓13系统，与日常安卓系统手机操作态统一致，可随意安装第三方APP或；
1、音乐播放APP
内置海贝音乐APP专业版，专为HiFi设计的音乐播放器，功能强大简单易用；
2、应用市场
内置搜安应用市场，可以搜索下载任何APP。

3.5mm&4.4mm LO线路输出

LO线路输出：使用时，相关接口检测到设备接入自动切换LO模式。

COAX同轴输出

R6III同轴输出使用TYPE-C口，可以连接使用TYPE-C转RCA线，相关线材可以通过HiBy官方直补店铺购买。店铺信息可以直接在销售后官方店铺链接。

RGB LED

1、R6III 电源键上的LED灯被作为当前播放音频的标识，分别显示对应的颜色：
2、各播放状态指示灯：
MQA——绿色
MQA studio——白色
MQA core（MQB）——紫色
不编码——浅蓝色
PCM 32kHz~48kHz——黄色
PCM 64kHz~192kHz——青色
PCM >352.8kHz——橙色
DSD64、DSD512——白色

USB DAC OUT数字转盘

确认USB口，使用R6III作播解码放大器，相关线材可以通过HiBy官方商店店铺购买，店铺信息可以查询本新售后官方店铺链接。

文件传输

连接线连接到最后手机后，连接成功后，电脑在机器上的状态栏下，选择USB接入功能信息块，在弹出窗口中点击传输文件，即可在电脑中找作将文件拉入本机内存储中实现文件中。

USB DAC 内置解码数字音频指号

1、国作为电脑USB DAC，使用USB数据线与电脑连接后，下拉状态栏，即从R6III的USB音频输入；
2、部分系统需要设置USB模式，请前往www.hiby.com进入产品服务——产品支持——USB DAC 内部说，下载并详细设置内部的USB DAC使用方法.pdf

无线连接功能

1、蓝牙5.0
R6III支持蓝牙的蓝牙设备（包括手耳机、蓝牙音箱等）时，需要先和该蓝牙设备进行配对，步骤如下：
a.下拉状态栏点击设置-蓝牙首面；
b.打开蓝牙开关；
c.点击“与新设备配对”，将会自动搜索可用设备；
d.点击连接到相应设备，连接成功的设备将显示在“已配对的设备”处。

2、WIFI
R6III支持2.4G/5G 双频WIFI，日常使用时，不可以通过海贝音乐APP，进行WIFI传输，使用APP下的HiBylink，使用私有云DLNA/局域网将。

DTA安卓全局无损输出架构

1、DTA（Direct Transport Audio）安卓全局无损输出系统，通过软件层面通过安卓系统中全局将SRC，选择输出图片原始的声音；
2、R6III内置海贝音乐APP可以直接输出外置DSD512，PCM768kHz/32bit无损音频格式；将2.第三方APP，也能做于自身，导致无法直接输出相应采样率的歌曲。

固件更新

OTA在线升级

1.通过连接WiFi进行升级；
2.R6III会自动检测版本，如果检测到需要版本的固件，将在状态栏显示更新；
3.可通过【设置】→【系统】→【系统更新】，下载并确固件；
4.下载完成后，安装并保存可。

特殊辅助功能

双传
1、关机；
2、先按住上一曲键，再按电源键开机。等待出现机器人界面；
3、在机器人界面，按住电源键不放的同时按一下上一曲；
4、上一曲/下一曲为选择项目，电源键为确认按键。
这个时候您可以进入选择界面中的 wipe 开头的选项进行恢复（全部数据清除，慎重操作！）。

强制关机

强制关机：开机状态下，机器出现卡死状态或其他异常情况无法正常关机键盘，可以长按电源键+下一曲按钮15秒，进行强制关机。

更多详细操作，请扫描以下二维码关注海贝音乐公众号，将获取下载详细指导。

WeChat 微信公众号

注意事项

1. 不可将设备长时间暴露在高温环境中。
2. 请勿将R6III放置在潮湿或有水的地方使用。
3. 设备在充电过程中，请使用原装充电器，并确保充电环境通风良好。
4. 请勿将设备放置在不稳定的表面上，以免设备掉落损坏。
5. 请勿使用非原装充电线，以免造成设备损坏或充电不稳定。

电池使用注意事项

1. 请勿将R6III长时间处于低电量状态，以免影响电池寿命。
2. 请勿将R6III放置在高温环境中，以免电池过热。
3. 请勿将R6III放置在潮湿环境中，以免电池受潮。
4. 请勿将R6III放置在强磁场环境中，以免电池受到干扰。

HiBy官方直营店
HiBy Official Online Store

官方天猫店Tmall
https://hiyam.tmall.com

官方直营京东店JD.com
https://mall.jd.com/index-852084.html

国外官网Website
www.hiby.com

想知道我们更多产品信息？

WeChat 微信公众号
Weibo-SINA 微博名称

全国售后
咨询电话：400-8820-032 或直接前往附近经销商进行咨询

东莞市歌劲电子科技有限公司

服务热线：400-8820-032 / 0086-769-23582316
官方网址：www.hiby.com
电子邮箱：service@hiby.com
地址：东莞市松山湖科技产业园区总部一路2号

反面

ENGLISH

Foreword

Thank you for purchasing HiBy's new generation portable digital audio player, the R6III. To help you get the best out of the R6III, this user guide has been compiled to introduce you to the R6III's features and how to use them. Please read thoroughly in the first days of ownership.

Buttons and ports



Power on/off, restart, screen locking/unlocking

1.Power on: press and hold power button for two seconds
2.Power off / restart: hold power button while R6III is powered on to bring up power off / restart option screen; Ipress briefly to unlock the screen first if it is locked)
3.Lock screen: Press power button briefly while R6III is powered on to lock / unlock screen;
4.Turn on screen: when R6III is powered on with screen off, press power button briefly or double-tap the screen to turn it on.

Operating System

The R6III sports a lightly customized Android 12 operating system with UI may be operated in the same way as most smartphones, including the installation of 3rd party audio and general apps and use of the Play Store.

Music player app

Pre-loaded with HiByMusic Professional edition, specially customized for HiFi digital audio players for powerful features, perfect sound and ease of use.

Micro SD card installation

Micro SD Card sizes of up to 2TB are accepted.

Charging

PC2.0 is supported.

3.5mm and 4.4mm line out

Auto line-out mode switch: the device automatically detects when it is connected to an amplifier rather than headphones and switches automatically to Line Out mode.

RGB LED

1.The LED on the R6III power button doubles as an indicator light for the audio format being sent to the DAC:
2.
MQA—green
MQA Studio—blue
MQA core/MQB—purple
Not decoding—pale blue
PCM:
48kHz and under—yellow
64-192kHz—cyan blue
>352.8kHz—orange
AI DSD: white

Coaxial digital audio output

The R6III supports coaxial digital output via its type-c port. This may be adapted to regular RCA connectors via our Type-C-3.RCA interconnect, available at store.hiby.com or one of the various retail partners listed at the end of this document.

USB Digital audio output

Connect USB DAC / amps to the R6III USB type-C port.

File transfer: connect the R6III to the computer via the provided USB type-C cable. After this, pull down the notification shade on the R6III, scroll down to the bottom and tap twice on "USB for charging", then select "File transfer" in the menu. Now the R6III will function as an MTP storage device for file transfer. On a Mac it is necessary to also install Android File Transfer to enable MTP file transfer.

Acting as USB DAC

a.connect the R6III to the computer via the provided USB type-C cable. After this, pull down the notification shade on the R6III, scroll down to the bottom and tap twice on "USB for charging", then then select "USB DAC in" in the menu.
b.On windows 7 it would be necessary to install the USB audio driver for this; go to store.hiby.com -> Scroll to bottom -> Click "download" under Support -> "USB DAC Driver & Guidance" -> "HiBy R6III USB DAC Driver Download and installation Guide"

Wireless connectivity

1.Bluetooth5.0
Connect the R6III with new Bluetooth audio devices as follows:
a.Pull down the notification shade then pull down again to expand the list of quick status indicator buttons; press and hold on the Bluetooth icon to enter the Bluetooth setup screen;
b.Turn on the Bluetooth master switch;
c.Tap "Pair new device" to search for nearby Bluetooth devices (set the Bluetooth device to be paired to broadcast or pairing mode according to its instructions)
d.Tap on the name of your Bluetooth device on the R6III to pair with it: once successfully paired, it will appear under the list of "paired devices".

2.WiFi
The R6III supports both 2.4GHz and GHz WiFi. Apart from using it to connect it to the internet for music streaming, internet etc., it can also be used for music transfer, remote control via HiByLink and/or playing music from network resources via DLNA / LAN etc.

Fireware update

Over-the-air online update
1.Updating is automatically via WiFi is recommended.
2.The R6III will automatically detect updates and prompt about the update in the notification shade if an update is found.
3. You may also go to Settings->System->System Updates to manually check for and download updates.

Direct Transport Audio architecture for lossless digital audio on Android

1. DTA (Direct Transport Audio) is the name of HiBy's full-time bitperfect android audio framework: it bypasses Android's sample rate conversion by modifying its audio stack to output bitperfect audio. The HiBy Music app bundled with the R6 III may bitperfectly output up to and including DSD512 / PCM 768kHz/32bit, however many third party apps assume bad Android resampling and will conduct "high-quality" resampling internally, in which event is impossible to obtain bitperfect audio from such apps despite DTA.

For further in-depth operation instructions, please visit [URL] or scan the following QR code:

To learn more

Facebook

International official website
http://store.hiby.com

Global after-sales service
Please contact us at service@hiby.com or directly contact the store you purchased from.

FCC WARNING

This device complies with Part 15 of the FCC Rules.Operation is subject to the following two conditions:
(1)This device may not cause harmful interference, and
(2)this device must accept any interference received, including interference that may cause undesired operation.
changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.
NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates,uses and can radiate radiofrequency energy and, if not installed and used in accordance with the instructions,may cause harmful interference to radio communications. However,there is no guarantee that interference will not occur in a particular installation.
If this equipment does cause harmful interference to radio or television reception , which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
-- Reorient or relocate the receiving antenna.-- Increase the separation between the equipment and receiver.
-- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
-- Consult the dealer or an experienced radio/TV technician for help.

Cautions

1. Do no, repair, disassemble, or place the product in a place with water.
2. When the product is not used for a long time, it is necessary to periodically charge the product to ensure battery life.
3. While you use the headphones, you will not be able to hear the external environment. For your safety, please avoid using the headphones in a dangerous environment.
4. Charging with a charger with too high voltage may damage the device. Please choose a recommended charger or charge.
5. Hold the power button for 30 seconds to force restart the device if the system crashes.

DONGGUAN SMARTACTION TECHNOLOGY CO.,LTD.

TEL: 0086-769-23582316 Website: www.hiby.com
Email: service@hiby.com
Address: Room 1201, Liuying Commercial Building, No.39, Hengpen 1st Road, Nancheng District, Dongguan, Guangdong, China

配件清单

120g 铜版纸

配件清单

HiBy R6III机器本体*1
HiBy R6III保水盒*1
Type-c to Type-c数据线*1
说明书*1
合格证*1
保修卡*1
配件清单*1
贴纸 *1

HIBY MAKE MUSIC MORE MUSICAL