

Welcome Guide

5 in 1 Magnetic Wireless Power Bank Charging Dock

Thanks for your support of this magnetic wireless charging station, please read this guide carefully before enjoying this product.

What's included

Wireless Charging Dock-Specifications

Type C Input	5V/3A, 9V/2A, 9V/2.22A, 9V/3A
Wireless Output (Phone)	5W, 7.5W, 10W, 15W(Max)
AirPods Output	5W (MAX)
IMatch Output	2W
USB-A Output	5V/1A (MAX)
Popgun Output	9V/2A (MAX)
Product size	6.06*4.06*1.24 inch
Weight	30.34g(1.06oz)

Wireless Charging Dock-Product Structure

- Wireless Charging Area for Power Bank
- Popgun
- TWS Earphone Indicator / Power Indicator
- Wireless Charging Area for TWS earphone or other Qi-enabled devices
- Non-slip Mat
- Wireless Charger for Apple Watch
- Type-C Input
- USB A Output

Wireless Charging Dock-LED Usage

Standby mode	Red light on
Charging mode	Green light on
Charging full	Green light on
FOD	Red-green light flash

Connected Indicator:
When connected the source, the LED light near the earphone wireless charging area is red on. When you charge earphone, this LED light is changed to earphone wireless charging indicator.

Wireless Charging Dock-Stand

Please adjust the comfortable view angle (30°-80°) according to your need.

Apple Watch Charger-Product Structure

- Wireless Charging Area for Apple Watch
- Type-C Input
- Watch Charging Indicator

Apple Watch Charger-Specifications

Type C Input	5V/1A
Output	7W

Apple Watch Charger-LED Usage

Standby mode	Green light on
Charging mode	Green light breathing

Power Bank

Specifications

Battery Capacity	10000mAh
Rated Capacity	6000mAh
Type C Input	5V/2A, 9V/2A, 12V/1.5A (Max 18W)
Type C Output	5V/2.4A, 9V/2.22A, 12V/1.67A (Max 20W)
USB-A Output	5V/4.5A(SPC), 5V/3A, 9V/2A, 12V/1.5A (Max 22.5W)
Wireless Output	5W, 7.5W, 10W, 15W(Max)
Simultaneous Output	5V/1A
Transmission Distance	6mm
Product size	4.43*2.68*0.63 inch
Weight	8.29g(0.29oz)

Product Structure

- Wireless Charging Area
- Indicator
- Pass-through charging via Type C Input/Output
- Switch
- Heat Dissipation Hole
- Copper Sheet for the Charging Dock (BMS, 4 in 1 Charging Station, will release soon.)
- USB A Output
- Foldable & Adjustable Aluminum Stand (0°-180°)

Digital Display Screen

Digital Display	100
Fully Charged	Real-time Power
Charging	Number Flashes
Low Power	Number Flashes

Fast Charging Indicator

Fast Charging Mode	## ON
No Fast Charging Mode	## OFF
2 or More Devices Charged Simultaneously	## OFF

Wireless Charging Status Indicator

Standby Mode	(=) (H) OFF
Wireless Charging Mode	(=) (H) ON
Fully Charged Mode	(=) (H) ON
FOD Mode	(=) (H) Flashing

Tip:
1. If wireless charging mark off, please kindly check whether there is magnet or metal element to affect the charging.
2. If wireless charging mark on, there is not wireless charging mark on the screen.
3. When start to charge, it would not show fast charging mark immediately. It need several seconds to change to fast charging mode.
4. When the power bank only charge 1 device, it's fast charging. If charge 2 or more devices simultaneously, the max output power 5V/3A, not fast charging.

Switch & Stand

The stable stand of this power bank is not only for the angle-adjusting, but also can be folded to flat for travelling. You can adjust the angle(0°-180°) according to your needs.

When your phone don't need to charge, it can be a simple MagSafe stand to support the phone (in horizontal or vertical). Just double quick press the switch to power off.

Single Press: Turn On
Double Press: Turn Off

0°-180°

Wireless Charging Dock-How To Use

Please use the included QC 18W adapter and cable to connect this wireless charging dock to the power source.

Note: Please use our QC 18W adapter (plug in the correct region port/Type-C port on the dock), USB-A and the Type-C port on the top of the dock.

Wireless Charging Dock - Extra USB Output

Using the USB-A to Type-C Cable(Not Included), connect the USB-A cable into the dock and the other side to the devices you want to charge, such as iPad, phone, earphone, tablet and so on.

Wireless Charging Dock - Wireless Charging for power bank

After connecting the power source, please put the power bank in the charging dock and make sure that the copper sheet on the power bank bottom is touched with that of charging dock. It will charge automatically. The specific figures on the LED screen of power bank will show the charging status.

Wireless Charging for phone

Please fit the product with the back of your iPhone (12, 13, 14 and subsequent series or AirPods 3) or other wireless charging phone (which with MagSafe-compatible ring attached). It will charge your phone via the built-in magnetic wireless charging. Max to be 15W. iPhone series is 7.5W due to iPhone's restrict.

Note: If power bank and phone are charged simultaneously, it's fast wireless charging for phone while power bank is in slow charging. When the phone full charged, the power bank is in fast charging mode.

Wireless Charging Dock - Wireless charging for Apple Watch

Please insert the watch charger into the corresponding position of the charging dock.

Note: This product is only available for Apple Watch. If Samsung watch, it's not compatible.

Wireless Charging Dock - Wireless charging for Apple Watch

Please make sure your Apple Watch is corresponded to the area of the wireless charger for Apple Watch. It will automatically detect the Apple Watch and charge it.

Wireless Charging Dock - Wireless charging for TWS earphone

Please lay down your earphone on the charging area and then it will automatically detect and charge(5W Max).

Wireless Charging Operation

Please press the button on the top left firstly when charge devices. And then fit the product with the back of your iPhone (12, 13, 14 and subsequent series or AirPods 3) or other wireless charging phone (which with MagSafe-compatible ring attached). (Please note some of magnetic rings from the 1st might not work). And it can also used with AirPods 3.

Note: 1. The magnetic wireless power bank is mainly used for iPhone 12, iPhone 13, iPhone 14 and subsequent series, or phones with MagSafe-compatible ring attached. (Please note some of magnetic rings from the 1st might not work). And it can also used with AirPods 3.
2. If your phone without MagSafe case, please charge it via the Type-C output port or USB-A output port.

Charging The Power Bank

Please charge the product when the power or battery is low.

- Using the included cable, connect the USB-A connector into QC/POD adapter and the Type-C connector to the input connector of the power bank.
- During charging or complete, the battery power LED indicator will show charging status with the specific figures.

Pass Through Charging
You can put your iPhone 12/13/14 and subsequent series, AirPods 3 on the wireless charging area and connect the power bank to the power source (POD or QC Adapter). It will charge the power bank itself and your iPhone 12/13/14/AirPods 3 at the same time.

Note: While pass through charging, the phone will be in fast charging and power bank will slow charge. When phone is fully charged, the power bank is in fast charging mode.

USB-A Output Operation

1. Insert the charging cable into USB-A output port.
2. Plug the other end of the cable into a terminal such as phone, iPad, earphone, Switch and so on.

Note: When the power bank only charge one device, whether C port or wireless charging area, the output support fast charging. If two device, the maximum output power is 5V/3A, not fast charging.

Type C Output Operation

- Insert the charging cable Type-C end into Output.
- Plug the other end of the cable into a terminal such as phone.
- Using the USB-A to Type-C Cable (Not Included), connect the C cable into the power bank and the other side to the devices you want to charge, such as iPad, phone, earphone, Switch and so on.

Note: When the power bank only charge one device, whether C port or wireless charging area, the output support fast charging. If two device, the maximum output power is 5V/3A, not fast charging.

Warning

- Do not drop, misuse or apply excessive force to your power bank. Power banks contain batteries and circuit board with fragile components that can be damaged if misused.
- If your power bank smells or heats, stop use immediately and dispose of the power bank in an appropriate manner.
- Store power bank in a cool and dry place. Do not store in hot or humid environments.
- All power banks have safety power cut-off features to stop overcharging & overheating.
- When charging a device the power bank may feel warm, this is a normal operating condition & should not be cause for concern.
- It is normal that this charger and your phone will be hot under operating conditions and it may be more hotter when charging and using at the same time (such as playing music).
- In normal conditions, battery performance will decline over several years.

Remarks

When your wireless power bank works improperly

- Check your device is not any obstacles on the wireless power bank, such as magnet, metal, credit card and other foreign object.
- When the wireless power bank is over-heating take your mobile device away from your wireless power bank and the power bank will stop charging automatically when over-heating. Please try charging again when the wireless power bank cooling down.

FC CE RoHS
Made in China

品名:	DMS04-套装-说明书	规格:	100g 双胶纸 四色 双面印刷 对折+风琴折
版本:	20230421		尺寸:80x120 mm
制作:	李志敏		
料号:			

FCC warning statements:

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Caution: Any changes or modifications to this device not explicitly approved by manufacturer could void your authority to operate this equipment.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

The device has been evaluated to meet general RF exposure requirement This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment.

This equipment should be installed and operated with minimum distance 20cm between the radiator & your body.