

## CTC Laboratories, Inc. (FCC Designation Number: CN1208)

Room 101 Building B, No. 7, Langing 1st Road, Luhu Community, Guanhu Subdistrict, Longhua District, Shenzhen, Guangdong, China

Tel: +86-755-27521059 Fax: +86-755-27521011 http://www.sz-ctc.org.cn

# **Maximum Permissible Exposure Evaluation**

**FCC ID: 2APN5SGC** 

According to FCC 1.1310: The criteria listed in the following table shall be used to evaluate the environment impact of human exposure to radio frequency (RF) Radiation as specified in §1.1307(b).

### **EUT Specification**

Applicant	Shenzhen Sonoff Technologies Co.,Ltd.			
Address	3F & 6F, Bldg A, No. 663, Bulong Rd, Shenzhen, Guangdong, China			
Product Name:	Smart Garage Door Controller			
Trade Mark:	Sonoff			
Model/Type Reference:	SGC300			
Listed Model(s):	SGC200, SGC100			
Model Differences:	All these models are identical in the same PCB, layout, electrical circuit. The difference is controlling the number of channels. The SGC300 controls three channels. The SGC200 controls two channels. SGC100 controls one channel.			
Frequency Band (Operating)	BT: 2402~2480MHz WiFi: 2412-2462MHz			
Device Category	☐ Portable (<5mm separation) ☐ Mobile (>20cm separation) ☐ Fixed (>20cm separation) ☐ Others			
Exposure Classification	☐Occupational/Controlled exposure (S=5mW/cm²) ☐General Population/Uncontrolled exposure (S=1mW/cm²)			
Antenna Diversity	Single antenna  ☐Multiple antennas  ☐TX diversity  ☐RX diversity  ☐TX/RX diversity			
Antenna Gain (Max)	2.82dBi			
Evaluation Applied				



Report No.: CTC2024082012



**Limits for Maximum Permissible Exposure (MPE)** 

Frequency Range (MHz)	Electric Field Strength (V/m)	Magnetic Field Strength (A/m)	Power Density (mW/cm²)	Averaging Time (minutes)		
(A) Limits for Occupational/Controlled Exposure						
300-1500			F/300	<6		
1500-100000			5	<6		
(B) Limits for General Population/Uncontrolled Exposure						
300-1500			F/1500	<30		
1500-100000			1	<30		

#### **Calculation Method**

Friis transmission formula: Pd=(Pout\*G)/(4\*Pi\*R<sup>2</sup>)

Where:

Pd= Power density in mW/cm<sup>2</sup>

Pout= output power to antenna in mW

G= gain of antenna in linear scale

Pi= 3.1416

R= distance between observation point and center of the radiator in cm

Pd limit of MPE is 1mW/cm<sup>2</sup>. If we know the maximum gain of the antenna and total power input to the antenna, through the calculation, we will know the distance where the MPE limit is reached.

#### **Measurement Result**

Mode	Frequency (MHz)	Antenna Gain (dBi)	Dowor	Tune Up Tolerance (dB)	Power	Power Density at 20cm (mW/cm²)	(mW/cm <sup>2</sup> )	Result
ВТ	2480	2.82	1.81	±1	3.00	0.0008	1	Pass
802.11n(HT20)	2462	2.82	21.17	±1	22.00	0.0604	1	Pass

The BT and WiFi can transmit simultaneously.

Mode	Frequency (MHz)	Antenna Gain (dBi)	Power Density at 20cm (mW/cm²)	Total Power density at 20cm (mW/cm2)	Limit (mW/cm²)	Result
ВТ	2480	2.82	0.0008	0.0612	1	Pass
802.11n(HT20)	2462	2.82	0.0604	0.0012		

#### Note:

- Calculate in the worst-case mode.
- 2. Max. Tune Up Power is declared by manufacturer, and used to calculate.
- 3. For a more detailed features description, please refer to the RF Test Report.

Tel.: (86)755-27521059

For anti-fake verification, please visit the official website of Certification and Accreditation Administration of the People's Republic of China: yz.cnca.cn