



CTC Laboratories, Inc.


1-2/F., Building 2, Jiaquan Building, Guanlan High-Tech Park, Shenzhen, Guangdong, China
Tel: +86-755-27521059 Fax: +86-755-27521011 <http://www.sz-ctc.org.cn>

Maximum Permissible Exposure Evaluation

FCC ID: 2APN5ZBMICRO

According to FCC 1.1310: The criteria listed in the following table shall be used to evaluate the environment impact of human exposure to radio frequency (RF) Radiation as specified in §1.1307(b)

EUT Specification

Product Name:	Zigbee USB Smart Adaptor
Trade Mark:	 , Sonoff
Model/Type reference:	ZBMicro
Listed Model(s):	/
Frequency band (Operating)	Zigbee: 2.405GHz ~ 2.480GHz
Device category	<input type="checkbox"/> Portable (<5mm separation) <input type="checkbox"/> Mobile (>20cm separation) <input checked="" type="checkbox"/> Fixed (>20cm separation) <input type="checkbox"/> Others ____
Exposure classification	<input type="checkbox"/> Occupational/Controlled exposure (S=5mW/cm ²) <input checked="" type="checkbox"/> General Population/Uncontrolled exposure (S=1mW/cm ²)
Antenna diversity	<input checked="" type="checkbox"/> Single antenna <input type="checkbox"/> Multiple antenna <input type="checkbox"/> TX diversity <input type="checkbox"/> RX diversity <input type="checkbox"/> TX/RX diversity
Antenna gain (Max)	1.42dBi
Evaluation applied	<input checked="" type="checkbox"/> MPE Evaluation <input type="checkbox"/> SAR Evaluation

CTC Laboratories, Inc.

1-2/F., Building 2, Jiaquan Building, Guanlan High-Tech Park, Shenzhen, Guangdong, China
Tel.: (86)755-27521059 Fax: (86)755-27521011 [Http://www.sz-ctc.org.cn](http://www.sz-ctc.org.cn)



For anti-fake verification, please visit the official website of Certification and Accreditation Administration of the People's Republic of China : yz.cnca.cn



Limits for Maximum Permissible Exposure (MPE)

Frequency Range(MHz)	Electric Field Strength(V/m)	Magnetic Field Strength(A/m)	Power Density(mW/cm ²)	Average Time
(A) Limits for Occupational/Control Exposures				
300-1500	--	--	F/300	6
1500-100000	--	--	5	6
(B) Limits for General Population/Uncontrol Exposures				
300-1500	--	--	F/1500	6
1500-100000	--	--	1	30

Friis transmission formula: $P_d = (P_{out} * G) / (4 * \pi * R^2)$

Where

P_d = Power density in mW/cm²

P_{out} = output power to antenna in mW

G = gain of antenna in linear scale

π = 3.1416

R = distance between observation point and center of the radiator in cm

P_d the limit of MPE 1mW/cm². If we know the maximum gain of the antenna and total power input to the antenna, through the calculation, we will know the distance where the MPE limit is reached.

Measurement Result

Zigbee - Worst case						
Type	Frequency (MHz)	Max. Measured Power (dBm)	Max. Tune up Power (dBm)	Antenna Gain (dBi)	Power density at 20cm (mW/cm ²)	Power density Limit (mW/cm ²)
OQPSK	2440	8.422	9.50	1.42	0.0025	1

Note:

1. Calculate by Worst-case mode.
2. Max. Tune Up Power by Manufacturer's Declaration, and Max. Tune Up Power is used to calculate.
3. For a more detailed features description, please refer to the RF Test Report.

*****THE END*****