


成品尺寸:525X128MM 105克铜版纸黑白正反面印刷

折叠成品尺寸: 105X128MM

Smart Pan and Tilt Camera Users Manual

Model: IPC208



1 What's included

- Rotative Camera
- Type-c Charging Cable
- AC Charger
- Screw + Anchors

3 Initial Setup

Turn On the Camera

Connect the power supply with the IP camera and you will hear the sound 'camera' start.

If the camera is failed to connect, it needs to be reset. To reset the IP camera, press and hold the "Reset" button until the camera automatically moving and hear the prompt sound, It will take around 15 seconds.

Installing the Memory Card

Class 4 or higher Micro SD memory card required (up to 128GB) for normal use.

Camera Operation

Preparations before use
Mobile device system requirements:
Android OS 4.4 or higher
iOS 9.0 or higher

Smart phone or tablet, IP Camera, Router

Install the App

Use your mobile phone or tablet to search for "TuyaSmart" in Google Play (for Android OS) or in the Apple app store (for iOS) to find the app, and install it according to the instructions.

Register an account
If this is the first time using the app, an account need to be registered as below:

4 Connecting Your IP Camera with the App

Note: Your IPC Camera is supported only on a 2.4GHz Wi-Fi network. For setup, make sure your mobile device is connected to a 2.4GHz Wi-Fi network

- After installing the app 'Tuya Smart', open the app and follow the prompts to setup the app. Then tap '+' or 'Add Device' from the home page. Tap 'Security & Sensor', then choose 'Smart Camera'.
- Power the device on and hear the sound of 'camera' start.

Make sure your smart device is connected to a 2.4G Wi-Fi network, then tap 'Confirm'.

- The app will guide you to scan mobile device with the camera.

When you tap 'Continue' the mobile phone displays a QR code. Hold the camera 15 to 20 cm in front of the mobile device for the camera to scan the QR code.

- In connecting, make sure your router, mobile and device are as close as possible.

Once the camera get the information from mobile device, the camera will have a sound 'camera configured' which means the camera is connected successfully. Your camera's Live Camera view with streaming video will be opened.

5 Using the Tuya Smart App

- Back to the home page
- Device name
- Settings
- Image quality (SD/HD) switch
- Speaker turn on/off
- Switch to full screen
- Screenshot of the live (photo saved to your mobile device)
- Speak to the camera
- Record the view of the camera (video saved to your mobile device)
- Hide the control panel
- Playback the local recorded video (Feature only available after inserted a memory card.)
- Photo Album (To view the recorded images which saved in your mobile phone through the app)
- Changing the color theme in the frame.
- Click to have the camera physically face down (private mode on/off)
- Night vision switch
- Click to turn the motion tracking on/off
- Click to turn the motion detection on/off
- Siren alarm on/off
- Camera direction control panel

Playback the Saved Files

a) Choose the device, get into the live view, press the 'playback' (Only available when the micro SD card is inserted.)

b) Users could review the videos that have filmed by the camera.

c) Users could choose the date to review videos.

Camera Settings:

Device Name: Users could modify the device name.
Share Device: Users could share the device to your friends.
Device Information: Users could see the device owner, IP address, device ID, etc.
Use Echo: Instruction for how to work with Amazon Alexa.
Basic Function Settings: Indicator light on/off, Flip screen, time watermark, speech method for one-to-way talk.
Motion detection: User could switch on/off the motion detection alarm and set the sensitivity of motion detector.
Memory card settings: Users could check the memory of the card and wipe off the SD card memory.
Value-added Service Purchase: Cloud storage service for users. (Subscription fee would be charged for this function.)
Feedback: Users could submit problems or advices to the service provider to optimize the service.
Firmware Information: To view the information of current and previous firmware version.
Remove Device:
a) When users want to change the internet connection, please press 'Remove Device' and reset the camera to pairing with new Wi-Fi.
b) No longer to use the camera.

Specification

| | |
|--------------------------|----------------------------------|
| Installation | Wall hanging, desktop |
| Sensor | 1/2.3" CMOS |
| Resolution | 2MP, 1920(H)*1080(V) |
| Frame | 1080P@15fps |
| Focal Length | 2.8mm |
| Lens Angle | 100° |
| Rotative Angle | 360°(H), 50°(V) |
| Video Compression Format | H.264 |
| Compression Bit Rate | 128 Kbps~2Mbps |
| Local Storage | Yes, micro SD card (up to 128GB) |
| Cloud Storage | Optional |
| Audio | Two-way audio |
| Power Supply | DC5V/1A |
| WiFi Antenna | 2.4GHz |
| Operation Environment | -10°C ~ 50°C, 30% ~ 80%RH |

FCC WARNING

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

To maintain compliance with FCC's RF Exposure guidelines, This equipment should be installed and operated with minimum 20cm distance between the radiator and your body. Use only the supplied antenna.