



# 1 MAXIMUM PERMISSIBLE EXPOSURE (MPE)

## 1.1 General Description of E.U.T

**Product Name** ..... : Kettle  
**Model No.** ..... : CS108-NK  
**FCC ID** ..... : 2ARBY-CS108-NK  
**Rated Voltage** ..... : AC 120V, 60Hz, 1200W

## 1.2 Standard Applicable

According to §1.1307(b)(1) and KDB 447498 D01 General RF Exposure Guidance v06, system operating under the provisions of this section shall be operating in a manner that the public is not exposed to radio frequency energy level in excess limit for maximum permissible exposure.

### (a) Limits for Occupational / Controlled Exposure

Frequency range (MHz)	Electric Field Strength (E) (V/m)	Magnetic Field Strength (H) (A/m)	Power Density (S) (mW/cm <sup>2</sup> )	Averaging Times   E <sup>2</sup> ,   H   <sup>2</sup> or S (minutes)
0.3-3.0	614	1.63	(100)*	6
3.0-30	1842/f	4.89/f	(900/f)*	6
30-300	61.4	0.163	1.0	6
300-1500	/	/	F/300	6
1500-100000	/	/	5	6

### (b) Limits for General Population / Uncontrolled Exposure

Frequency range (MHz)	Electric Field Strength (E) (V/m)	Magnetic Field Strength (H) (A/m)	Power Density (S) (mW/cm <sup>2</sup> )	Averaging Times   E <sup>2</sup> ,   H   <sup>2</sup> or S (minutes)
0.3-1.34	614	1.63	(100)*	30
1.34-30	824/f	2.19/f	(180/f)*	30
30-300	27.5	0.073	0.2	30
300-1500	/	/	F/1500	30
1500-100000	/	/	1	30

Note: f = frequency in MHz; \* = Plane-wave equivalents power density



### 1.3 MPE Calculation Method

$$S = (30 \cdot P \cdot G) / (377 \cdot R^2)$$

S = power density (in appropriate units, e.g., mW/cm<sup>2</sup>)

P = power input to the antenna (in appropriate units, e.g., mW)

G = power gain of the antenna in the direction of interest relative to an isotropic radiator, the power gain factor is normally numeric gain.

R = distance to the center of radiation of the antenna (in appropriate units, e.g., cm)

### 1.4 MPE Calculation Result

Prediction distance (mm)	Prediction frequency (MHz)	Antenna Gain (dBi)	Numeric gain	Maximum Tune-up output power (dBm)	Maximum peak output power (mW)	PD (mW/cm <sup>2</sup> )	Limit (mW/cm <sup>2</sup> )
>200	2480	0	1	0.386	1.093	0.00021744	1.0

Result: Pass

====End of Report====



# WALTEK