

Smart platooninsert
Manual

Works with Alexa
Simplified steps to install App on your smart device and pair with Amazon Alexa and Google Assistant using Smart Life App on Apple Store / Google Play Store

Ver: E3197_alena

Works with Amazon Alexa. Compatible with any smart phone or tablet including Android devices and Apple.

Download or scan the QR code and install the Smart Life App for either iOS or Android. Once downloaded or scan the QR code, the app will ask you to register your device. Enter your phone number or email which ever one makes you feel comfortable and select the country you live in. If phone number selected you will receive a text with a registration code. If you choose email you will then receive a password.

Input the Registration Code you received via text if phone method used or create password if email method chosen.

Adding a New Device in Quick Connection

- Make sure the Wi-Fi smart device is standby (the blue light button flash in 2 times per second if the smart device is plug or switch) after plug in the socket.
- Otherwise, you should press the power button Keep to 6 seconds to reset the device (for plug or switch, bulb should be turned on/off the power in 3 times continuously).
- The smart Wi-Fi devices only supports 2.4GHz Wi-Fi router.
- Open app and click "+" to add device.
- Select Wi-Fi network, input Wi-Fi password, Connect and click.
- Once connected the app will prompt the connection- click OK.

Press Connect now

- Go to WLAN setting in your smart phone and select the "Smart Life" for your Wi-Fi, no need to input password once you select the "Smart Life" (you can directly to connect it if your OS is Android).
- Go back to app and press "Connect" Device name is "Smart Life".
- Confirm Device

Once App is installed on your device and you have added your smart device to your app you will be able to control it.

Next step is to sync with Alexa or echo:

- Go to Home menu on Alexa App
- Select "Skills" to home menu of Amazon Alexa
- Type (Smart Life) on search window and find
- Click on the App (Smart Life) and press Enable to link with echo/Alexa.
- Input the registered user name and password to log in Smart Life app.

Whether connected devices have reached the maximum number of router's connections. If no, please try by turning off the Wi-Fi connection of some device. Router's wireless MAC filtering function is enabled. Remove the device from the filter list and make sure that router is not prohibiting device from connection.

How to reset device?

- Reset plug, switch, etc. Keep press reset button for 6 seconds until indicator light flashes, or for bulb to turn on/off the power in 3 times continuously, representing successful reset.
- Indicator light slowly flashes (one time per 3 seconds), representing AP mode.
- Under AP mode, long press reset button for 3 seconds until indicator light slowly flashes, representing switching to AP mode and vice versa.
- Reset smart light: Turn off light first. Switch light with the steps: Switch on-off-on-off-on (time interval cannot exceed 10 seconds). Flashing light represents successful reset; if no light flashes, please repeat the steps above.
- Quick light flashes (4 times per second), represent AP mode. Slow light flashes (2 times per 3 seconds)

Your Smart Life App has been linked with Alexa, and you now can control any device added to your Smart Life App. Remember that if you rename the device you added, it must be to a simple name Alexa can recognize Ex: Turn off light.

"Echo turn off living room light" or "Alexa turn off" (What ever you have plugged in smart socket or what ever name you choose for that device plugged or added to your App)

Using Google Home to control smart devices Link Smart Life account in Home Control

Tap "Home Control" in the hamburger menu on the Google Home app's home page, then tap "

Find "Smart Life" in the list. In the new window, select your Smart Life account's region, type your Smart Life account and password, then tap "Link Now". After you assign rooms for devices, your devices will be listed in the Home Control page.

Control your smart devices through Google Home Now you can control your smart devices through Google Home.

Q & A

Why failed to add device?

- Please check whether device is powered on;
- Whether phone is connected with Wi-Fi;
- Whether device is ready for configuration. To get the device ready before configuration, normally you can manually press on the device to get it ready. Please refer to "Product Instructions" or Device Reset Instruction for details. Notice Each time to add device, reset Wi-Fi to get device ready for configuration and make sure router is working properly.

4. Check router or related-If router is dual-band router, select 2.4G network and add device. You also need to enable router's broadcasting function. Set up wireless router: Set encryption method as WPA2-PSK, and authorization type as AES, or set both as auto. Wireless mode cannot be ITa only. Don't use Chinese to name router Wi-Fi. To stay strong Wi-Fi signal, please keep device and router within certain distance.

Whether connected devices have reached the maximum number of router's connections. If no, please try by turning off the Wi-Fi connection of some device. Router's wireless MAC filtering function is enabled. Remove the device from the filter list and make sure that router is not prohibiting device from connection.

How to reset device?

- Reset plug, switch, etc. Keep press reset button for 6 seconds until indicator light flashes, or for bulb to turn on/off the power in 3 times continuously, representing successful reset.
- Indicator light slowly flashes (one time per 3 seconds), representing AP mode.
- Under AP mode, long press reset button for 3 seconds until indicator light slowly flashes, representing switching to AP mode and vice versa.
- Reset smart light: Turn off light first. Switch light with the steps: Switch on-off-on-off-on (time interval cannot exceed 10 seconds). Flashing light represents successful reset; if no light flashes, please repeat the steps above.
- Quick light flashes (4 times per second), represent AP mode. Slow light flashes (2 times per 3 seconds)

Under AP mode, turn off lights and then switch light with the steps: Switch on-off-on-off-on (time interval cannot exceed 10 seconds). Light begins to slowly flash, representing that it has switched to AP mode and vice versa.

How to add device under AP mode?

- Make sure that indicator light quickly flashes or light slowly flashes;
- Tap "Add device" in App and then "AP mode" in the top right corner. Connect to device hotspot first and then Wi-Fi;
- Tap "Next" to add device.

Can I control device with 3G/4G/4G network? When adding device for the first time, it requires that device and phone need to be under the same Wi-Fi environment. After successfully adding device, you can remote control device with 3G/4G network.

How can I share my device with family?

Open App, go to "Profile" - "Device Sharing" - "Share Smart Life" - "Add Sharing", then you can share the device with the added family members.

How can I manage the devices shared by others?

Open App, go to "Profile" - "Device Sharing" - "Share Received", then you can find the devices shared by other users. It also allows to add remarks to users or delete certain shares by long pressing or swiping left.

Product Data sheet

Item	Property	Parameter	Remark
1	Input Voltage	AC100V	
2	Input Frequency	50Hz/60Hz	
3	WiFi standard	IEEE 802.11 b/g/n	
4	WiFi frequency	2.4GHz	
5	Remote Monitoring	Mobile	
6	App support	iOS/Android	
7	Indicator light	Blue and Red led	

Notice
Model Y2H-A24

- Please check if there is damage caused by transportation, if yes, please contact supplier for replacement.
- Please follow the specification instruction and notice to keep products in a good and safe use condition.
- Put the socket in proper condition and out of reach of the children.
- Plug in fully to the socket while using.
- The total power of being electric connected appliances could not be bigger than the maximum power of the socket.
- Do not disassemble or install the socket, otherwise there may cause security risks.

English version:
- Disconnection means: Type 1B
- Pollution degree: 2
- Rated impulse voltage: 1500V
- Nominal action: 6000cycles
- Rating: AC 120-240V 50/60Hz 15A 3600W Resistive
Caution: Risk of electric shock; Dry location use only; Used indoor only.

1 2
3 4
5 6
7 8
9 10
11 12

FCC Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Responsible for compliance could void the user's authority to operate this equipment. (Example- use only shielded interface cables when connecting to computer or peripheral devices).

This equipment complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) This device must accept any interference received, including interference that may cause undesired operation.

FCC Radiation Exposure Statement:

Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

The equipment complies with FCC Radiation exposure limits set forth for uncontrolled environment. This equipment should be installed and operated with minimum distance 20cm between the radiator and your body.