DATE											
APPROVED	atomi ŝmart°	折线不	(2)	3	4	5	6	7		I can't find the atomi.smart.XXXX network in my WiFi list.  Make sure your atomi smart device is plugged in and the light is blinking quickly. If not, unplug your atomi smart	I just replaced my router.  To reset the WiFi without losing your atomi smart devices settings, hold down the power button and wait for the LED to change from amber to blinking white, then release.
DESCRIPTION	Let's get started!  Smart WiFi Ceiling Light  Quick Start Guide	Get the app  Download the atomi smart app from the App Store or Google Play.	Register  Follow the on-screen instructions and register an account.	Add your smart device  Press "Add Device" or the "+" sign and choose the smart device to install from the device list.	Select the right network  Enter your WiFi password and "Confirm".  Make sure you're connected to a 2.4GHz WiFi network (atomi Smart can't connect to 5GHz networks).	Plug in your smart device  And press "Continue" on the atomi smart app.	Connect to the network  Press "Go to Connect" and follow the instructions on the screen.	© WiFi Settings    atomi-smart-XXXX   ?=     network-2   ?=     network-3   ?=     Netwo	Troubleshooting  Smart WiFi Ceiling Light	My WiFi network doesn't appear in the atomi smart app.  Use your smartphone to confirm that you have at least two WiFi bars in the vicinity of your atomi smart device. If not, move your atomi smart device closer to your router. (The list will refresh every 10 seconds).  Cannot connect to my WiFi network.  Make sure that you have entered the correct WiFi password during setup. Check if there are problems with your internet connection. If the WiFi signal is too weak, reset your WiFi router and try again.  My atomi smart device appears as "Unavailable" in the app.  Refresh the device list.  My atomi smart app is frozen.  Force quit and re-launch the atomi smart app.	When the LED begins to alternate white and amber, follow steps 3-5 to associate your atomi smart device with your new network.  I'm still having trouble!  WiFi networks come in a lot of shapes and sizes with many quirks of their own. It doesn't mean your atomi smart device is malfunctioning. If problems persist, please try these steps, in this order.  1. Force quit and re-launch the atomi smart app. Check to see if this fixes the issue.  2. Unplug your atomi smart device and plug it back in. Check to see if this fixes the issue.  3. Unplug your router and plug it back in. Check to see if this fixes the issue.  4. Delete and reinstall the atomi smart app. Check to see if this fixes the issue.  For more troubleshooting tips go to www.atomismart.com/helpCeilingLight
版本 REV	Still can't connect? Need assistance? Our friendly customer service team will work hard to put a smile back on your face. Here's how we can connect.  1-800-757-1440 Mon-Fri 9:00-5:00 EST (US)  or support@atomiusa.com	Wiring  Smart WiFi Ceiling Light	Turn off circuit breaker  Find your light's control in your circuit breaker and turn it off.  Then make sure the power is off by flipping your switch a few times.		Follow the steps below:  1. Mount screws into the junction box, leaving the screws half an inch long.  2. Pass the power wire through the hole of the base, and turn it clockwise to lock the base in junction box.  3. Hang the wire rope at the hanging position of the mounting base to assist the installation.  4. Screw the LN wire L-L N-N with a screw cap.  5. Put wiring cap and wires back to the junction box.  6. Rotate the lamp body clockwise to fix the lamp on the base.	3  Turn on circuit breaker  Turn on your switch's power from the circuit breaker.	Welcome to the atomi smart family!  We know you will love our products so much that we are giving you an exclusive 15% off your next purchase on atomismart.com.  Log onto https://atomismart.com/shop-now/  Add to Cart  Enter promo code ATOMI15OFF  Proceed to checkout  Free shipping on orders over \$50 *within the contiguous US only*	The following terms and conditions apply to the promo code:  1. Coupon is only valid on the atomi smart website www.atomismart.com.  2. A valid code must be entered at the checkout page in order to redeem the promotion.  3. Customers can only redeem one time at checkout.  4. Customers can only use the promo code once.  5. atomi smart reserves the right to cancel or modify any order, or revoke the use of the promo code for any reason.  6. Unless otherwise stated, promo codes are not valid in conjunction with other promotions or discounts.  7. Additional terms and conditions may be specified in relation to specific promo code (for example, duration, leigibility, discount amount and products covered), and will govern the use and redemption of those vouchers.  8. Promo code is not exchangeable for cash.  9. atomi smart will not be liable and/or be required to offer replacement codes, discounts, credits, cash or otherwise compensate oustomers for:  a. discontinued or cancelled promo code:  b. improper use of, or inability to redeem, a promo code: or  c. the inability to redeem promo coded cute to technical issues.		FCC Notice:  This device complies with Part 15 of the FCC Rules. Operation is subject to the two following conditions:  1. This device may not cause harmful interference.  2. This device must accept any interference received, including interference that may cause undesired operation.  Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.  Note:This equipment has been tested and found to comply with the limits for a class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation.  This equipment generates uses and can radiate radio frequence energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:  - Reorient or relocate the receiving antenna.  - Increase the separation between the equipment and receiver.  - Connect the equipment into an autlet on a circuit different from that to which the receiver is connected.  - Consult the dealer or an experienced radio/TV technician for help.  The device has been evaluated to meet general RF exposure requirement, This equipmen should be installed and operated with a minumum distance of 20 cm between the radiator and your body.	

上图展示,印刷请用"428-Al24XF-01 A0 AT1515-Smart-Ceiling-Light-userguide说明书\_客户原图档\_AT1515-Smart-Ceiling-Light-userguide.ai"

折叠示意图:

折叠后尺寸92x120mm



文件编号	428-AI24XF-01	客户代码	LAC0117(AI)		励品和	能照明有限公司
台馬卢文	AT1515	版本	Y0	LAC Lighting	Guang Long Lacled http://www.lacled	t Lighting Co.Ltd 1.com
7 7 7	ı	1-1		7 四十米		日の石田田石田田石田田田田田田田田田田田田田田田田田田田田田田田田田田田田田田
		1		大工2.11大	内 加	1787年1188日1188日1188日1188日1188日1188日1188日
系统城品科号		核对		BOM线目	表面处理	风琴折页折10次过为
<b>引置</b>		上六 V任				1013v170mm
		汉作			アノ	IUIIUZIVCINI