

## FCC 47 CFR MPE REPORT

Soundlab Technology Company Limited

Soundbar

Model Number: Bar 40 Sound Bar

FCC ID: 2ATKO-BAR40

Prepared for:	Soundlab Technology Company Limited
	No.101,202,Building 1, Microlab Industrial Park, No.2 Baozi South Road, Kengzi,
	Pingshan District, ShenZhen, China
Prepared By:	EST Technology Co., Ltd.
	Chilingxiang, Qishantou, Santun, Houjie, Dongguan, Guangdong, China
Tel: 86-769-83081888-808	

Report Number:	ESTE-R1909050
Date of Test:	Aug. 06~Sep. 09, 2019
Date of Report:	Sep. 11, 2019

## Maximum Permissible Exposure

### 1、Applicable Standard

Systems operating under the provisions of this section shall be operated in a manner that ensures that the public is not exposed to radio frequency energy level in excess limit for maximum permissible exposure. In accordance with 47 CFR FCC Part 2 Subpart J, section 2.1091 this device has been defined as a mobile device whereby a distance of 0.2m normally can be maintained between the user and the device.

#### (a)、Limits for Occupational / Controlled Exposure

Frequency Range (MHz)	Electric Field Strength E (V/m)	Magnetic Field Strength (H) (A/m)	Power Density (S) (mW/cm <sup>2</sup> )	Averaging Times   E   2 ,   H   2 or S (minutes)
0.3-3.0	614	1.63	(100)*	6
3.0-30	1842/f	4.89/f	(900/f)*	6
30-300	61.4	0.163	1.0	6
300-1500			F/300	6
1500-10000			5	6

#### (b)、Limits for General Population / Uncontrolled Exposure

Frequency Range (MHz)	Electric Field Strength E (V/m)	Magnetic Field Strength (H) (A/m)	Power Density (S) (mW/cm <sup>2</sup> )	Averaging Times   E   2 ,   H   2 or S (minutes)
0.3-1.34	614	1.63	(100)*	30
1.34-30	824/f	2.19/f	(180/f)*	30
30-300	27.5	0.073	0.2	30
300-1500			F/1500	30
1500-10000			1.0	30

Note: f=frequency in MHz; \*Plane-wave equivalent power density

### 2、MPE Calculation Method

$$E \text{ (V/m)} = (30 \cdot P \cdot G)^{0.5} / d \qquad \text{Power Density: } Pd \text{ (W/m}^2\text{)} = E^2 / 377$$

E = Electric Field (V/m)

P = Peak RF output Power (W)

G = EUT Antenna numeric gain (numeric)

d = Separation distance between radiator and human body (m)

The formula can be changed to

$$Pd = (30 \cdot P \cdot G) / (377 \cdot d^2)$$

From the peak EUT RF output power, the minimum mobile separation distance, d=0.2m, as well as the gain of the used antenna, the RF power density can be obtained

**3、 Conducted Power Result**

Mode	Frequency (MHz)	Peak output power (dBm)	Peak output power (mW)	Target power (dBm)	Antenna gain	
					(dBi)	(Linear)
GFSK	2402	-3.63	0.434	$-4 \pm 1$	1.7	1.479
	2441	-1.85	0.653	$-2 \pm 1$	1.7	1.479
	2480	0.14	1.033	$0 \pm 1$	1.7	1.479
8-DPSK	2402	-2.19	0.604	$-3 \pm 1$	1.7	1.479
	2441	-0.38	0.916	$-1 \pm 1$	1.7	1.479
	2480	1.56	1.432	$1 \pm 1$	1.7	1.479

**4、 Calculated Result and Limit**

Mode	Target power (dBm)	Antenna gain		Power Density (S) (mW/cm <sup>2</sup> )	Limited of Power Density (S) (mW/cm <sup>2</sup> )	Test Result
		(dBi)	(Linear)			
GFSK	1	1.7	1.479	<b>0.00037</b>	1	Compiles
8-DPSK	2	1.7	1.479	<b>0.00047</b>	1	Compiles

For 2.4G SRD

Ant gain=2.38dBi

Ant numeric gain=1.73

Field strength = 83.42 dBuV/m@3m

$P = \{ [10^{(83.42/20)} / 10^6 * 3]^2 / (30 * 1.73) \} * 1000 \text{mW} = 0.038 \text{mW}$

$Pd = (30 * 0.038 * 1.73) / (377 * 20^2) = 0.00001 < 1$