

SAR TEST REPORT

For

Mobile Phone

Model Number: V2236

FCC ID: 2AUCY-V2236

Report Number: WT228002560

Test Laboratory : Shenzhen Academy of Metrology and Quality Inspection
Site Location : NETC Building, No.4 Tongfa Road, Xili Town, Nanshan District, Shenzhen, Guangdong, China
Tel : 0086-755-86928965
Fax : 0086-755-86009898-31396
Web : www.smq.com.cn
Email : emcrf@smq.com.cn

Test report declaration

Applicant : vivo Mobile Communication Co., Ltd.
Address : No.1, vivo Road, Chang'an, Dongguan,Guangdong,China
Manufacturer : vivo Mobile Communication Co., Ltd.
Address : No.1, vivo Road, Chang'an, Dongguan,Guangdong,China
EUT Description : Mobile Phone
Model No. : V2236
Brand : vivo
FCC ID : 2AUCY-V2236

Test Standards:

FCC 47CFR Part 2(2.1093) IEEE Std 1528-2013 KDB 447498 D01v06 KDB 248227 D01v02r02 KDB 865664 D01v01r04 KDB 865664 D02v01r02 KDB 648474 D04v01r03 KDB 941225 D01v03r01 KDB 941225 D05v02r05 KDB 941225 D06v02r01

The EUT described above is tested by Shenzhen Academy of Metrology and Quality Inspection EMC Laboratory to determine the compliance of the applicable standards stated above. Shenzhen Academy of Metrology and Quality Inspection EMC Laboratory is assumed full responsibility for the accuracy of the test results.

The results documented in this report only apply to the tested sample, under the conditions and modes of operation as described herein.

The test report shall not be reproduced in part without written approval of the laboratory.


Project Engineer:



Date: Nov. 29, 2022

(Zhang Qiang)


Checked by:



Date: Nov. 29, 2022

(Shi Chang Da)

Approved by:



Date: Nov. 29, 2022

(Lin YiXiang)

TABLE OF CONTENTS

1. REPORTED SAR SUMMARY.....	5
1.1. Statement of Compliance.....	5
1.2. RF exposure limits (ICNIRP Guidelines).....	6
1.3. Ratings and System Details.....	7
1.4. Test specification(s).....	8
1.5. List of Test and Measurement Instruments.....	9
2. GENERAL INFORMATION.....	11
2.1. Report information.....	11
2.2. Laboratory Accreditation and Relationship to Customer.....	11
3. SAR MEASUREMENT SYSTEM CONFIGURATION.....	12
3.1. SAR Measurement Set-up.....	12
3.2. Probe description.....	13
3.3. Phantom description.....	14
3.4. Device holder description.....	15
4. SAR MEASUREMENT PROCEDURE.....	16
4.1. Scanning procedure.....	16
7. SYSTEM VERIFICATION PROCEDURE.....	22
7.1. Tissue Verification.....	22
8. SAR MEASUREMENT VARIABILITY AND UNCERTAINTY.....	27
8.1. SAR measurement variability.....	27
8.2. SAR measurement uncertainty.....	27
9. Test Configuration.....	28
10. TEST RESULTS.....	40
10.1. EUT Antenna Locations.....	40
11. MEASUREMENT RESULTS.....	41
11.1. Conducted Power.....	41
11.2. SAR measurement Results.....	42
11.3. GSM850 SAR results.....	45
11.4. PCS1900 SAR results.....	46

11.5. WCDMA Band II SAR results.....	47
11.6. WCDMA Band IV SAR results.....	48
11.7. WCDMA Band V SAR results.....	49
11.8. LTE Band 2 SAR results.....	50
11.9. LTE Band 4 SAR results.....	51
11.10. LTE Band 5 SAR results.....	52
11.11. LTE Band 7 SAR results.....	53
11.12. LTE Band 13 SAR results.....	54
11.13. LTE Band 26 SAR results.....	55
11.14. LTE Band 38 SAR results.....	56
11.15. LTE Band 41 SAR results.....	57
11.16. LTE Band 66 SAR results.....	58
11.17. 2.4GWi-Fi SAR results.....	59
11.18. 5.2GWi-Fi SAR results.....	60
11.19. 5.3GWi-Fi SAR results.....	61
11.20. 5.6GWi-Fi SAR results.....	62
11.21. 5.8GWi-Fi SAR results.....	63
11.22. BT SAR results.....	64
11.23. Repeated SAR results.....	65
12. EXPOSURE POSITIONS CONSIDERATION.....	67
12.1. Multiple Transmitter Evaluation.....	67
12.2. Simultaneous Transmission Possibilities.....	68
12.3. SAR Summation Scenario.....	69
12.4. Simultaneous Transmission Conclusion.....	72

1. REPORTED SAR SUMMARY

1.1. Statement of Compliance

The maximum results of Specific Absorption Rate (SAR) found during testing are as follows.

Band		Highest SAR Summary			
		Head (Gap 0mm)	Hotspot (Gap10mm)	Body-worn (Gap15mm)	Extremity (Gap 0mm)
		1g SAR (W/kg)			10g SAR (W/kg)
GSM	GSM850	0.73	0.45	0.3	N/A
	PCS1900	0.74	0.53	0.27	N/A
WCDMA	WCDMA Band II	0.93	0.64	0.37	N/A
	WCDMA Band IV	0.56	0.52	0.35	N/A
	WCDMA Band V	0.63	0.43	0.26	N/A
LTE	LTE Band 2	0.76	0.63	0.36	N/A
	LTE Band 4	0.97	0.5	0.32	N/A
	LTE Band 5	0.76	0.39	0.27	N/A
	LTE Band 7	0.92	0.54	0.54	N/A
	LTE Band13	0.87	0.34	0.23	N/A
	LTE Band26	0.97	0.39	0.27	N/A
	LTE Band 38	0.71	0.65	0.42	N/A
	LTE Band 41	0.62	0.63	0.46	N/A
	LTE Band 66	0.75	0.54	0.34	N/A
WLAN	2.4GHzWLAN	0.65	0.49	0.2	N/A

	5GHzWLAN	0.36	0.71	0.46	0.86
2.4GHz Band	Bluetooth	0.08	0.05	0.01	N/A

Maximum Report SAR 1g(W/kg)	Head	0.97	Limit(W/kg): 1.6 W/kg
	Hotspot(10mm)	0.71	
	Body-worn(15mm)	0.54	
Maximum Report SAR 10g(W/kg)	Extremity (Gap 0mm)	0.86	Limit(W/kg): 4.0 W/kg

Highest Simultaneous SAR 1g(W/kg)	LTE Band 38+WIFI 5G+BT	1.39	Limit(W/kg): 1.6 W/kg
--------------------------------------	---------------------------	------	-----------------------

Note:

1. This device is in compliance with Specific Absorption Rate (SAR) for general population or uncontrolled exposure limits (1.6W/kg as averaged over any 1 gram of tissue; specified in FCC 47 CFR part 2 (2.1093) and ANSI/IEEE C95.1-1992), and had been tested in accordance with the measurement methods and procedures specified in IEEE 1528-2013 and FCC KDB publications.
2. When the test result is a critical value, we will use the measurement uncertainty give the judgment result based on the 95% risk level.

1.2. RF exposure limits (ICNIRP Guidelines)

Human Exposure	Uncontrolled Environment General Population	Controlled Environment Occupational
Spatial Peak SAR*(Brain/Body)	1.60mW/g	8.00mW/g
Spatial Average SAR** (Whole Body)	0.08mW/g	0.40mW/g
Spatial Peak SAR***(Limbs)	4.00mW/g	20.00mW/g

Table 2: RF exposure limits

The limit applied in this test report is shown in bold letters

Notes:

- * The Spatial Peak value of the SAR averaged over any 1 grams of tissue (defined as a tissue volume

in the shape of a cube) and over the appropriate averaging time

** The Spatial Average value of the SAR averaged over the whole body.

*** The Spatial Peak value of the SAR averaged over any 1 grams of tissue (defined as a tissue volume in the shape of a cube) and over the appropriate averaging time. Uncontrolled Environments are defined as locations where there is the exposure of individuals who have no knowledge or control of their exposure. Controlled Environments are defined as locations where there is exposure that may be incurred by persons who are aware of the potential for exposure, (i.e. as a result of employment or occupation.)

1.3. Ratings and System Details

EUT Description	Mobile Phone
Model No.	V2236
Brand	vivo
EUT Supports Radios application:	GSM850:TX 824MHz~849MHz PCS1900: TX 1850MHz~1910MHz WCDMA Band V: TX 824MHz~849MHz WCDMA Band IV: TX 1710MHz~1755MHz WCDMA Band II: TX 1850MHz~1910MHz LTE Band 2: TX 1850MHz~1910MHz LTE Band 4: TX 1710MHz~1755MHz LTE Band 5: TX 824MHz~849MHz LTE Band 7: TX 2500MHz~2570MHz LTE Band 13: TX 777MHz~787MHz LTE Band 26: TX 814MHz~849MHz LTE Band 38: TX 2570MHz~2620MHz LTE Band 41: TX 2535MHz~2655MHz LTE Band 66: TX 1710MHz~1780MHz 2.4GWiFi:2412MHz~2462MHz 5GWiFi: U-NII 1(5180~5240 MHz) U-NII 2A (5260~5320 MHz) U-NII 2C (5500~5700 MHz) U-NII 3(5745~5825 MHz) BT:2402MHz~2480MHz
Modulation Mode	GSM/GPRS/EGPRS AMR I RMC 12.2Kbps HSDPA HSUPA LTE: QPSK, 16QAM, 64QAM WLAN 2.4GHz : 802.11b/g/n HT20/HT40/VHT20/VHT40 WLAN 5GHz : 802.11a/n/ac

	HT20/HT40/VHT20/VHT40/VHT80 Bluetooth BR/EDR/L E
Battery information	B-Y1 Minimal Capacity: 4910mAh Typical capacity: 5000mAh Typical Voltage:3.89V Charge Cutoff Voltage:4.45V
Hardware version:	MP_0.1
Software version:	PD2236GF_EX_A_12.0.0.8.W30.V000L1
IMEI	860275060001069

1.4.Test specification(s)

FCC 47CFR Part 2(2.1093)	Radiofrequency Radiation Exposure Evaluation: Portable Devices
IEEE Std 1528-2013	Recommended Practice for Determining the Peak Spatial-Average Specific Absorption Rate(SAR) in the Human Head from Wireless Communications Devices: Measurement Techniques
KDB 447498 D01v06	General RF Exposure Guidance No deviation
KDB 248227 D01v02r02	SAR Measurement Procedures for 802.11Transmitters
KDB 865664 D01v01r04	SAR Measurement 100 MHz to 6 GHz
KDB 865664 D02v01r02	RF Exposure Reporting
KDB 648474 D04v01r03	Handset SAR
KDB 941225 D01v03r01	3G SAR MEAUREMENT PROCEDURES
KDB 941225 D05v02r05	SAR Evaluation Consideration for LTEDevices
KDB 941225 D06v02r01	SAR Evaluation Procedures For PortableDevices With Wireless Router Capabilities
<p>Note 1: The test item is not applicable.</p> <p>Note 2: Additions to, deviation, or exclusions from the method shall be judged in the "method determination" column of add, deviate or exclude from the specific method shall be explained in the "Remark" of the above table.</p>	

1.5.List of Test and Measurement Instruments

	Equipment	Model No.	Serial No.	Manufacturer	Last Calibration Date	Period
☒	SAR test system	TX60L	F08/5AY8A1/A/01+F08/	SPEAG	NCR	NCR
☒	Electronic Data Transmitter	DAE4	1636	SPEAG	2021.12.30	1year
☒	SAR Probe	EX3DV4	7623	SPEAG	2022.01.24	1year
☒	Software	85070	--	Agilent	--	--
☒	Software	DASY5	--	SPEAG	--	--
☒	System Validation Dipole,750MHz	D750V3	1103	SPEAG	2020.01.06	3year
☒	System Validation Dipole,835MHz	D835V2	4d141	SPEAG	2021.08.31	3year
☒	System Validation Dipole,1750MHz	D1750V2	1108	SPEAG	2020.01.03	3year
☒	System Validation Dipole,1900MHz	D1900V2	5d162	SPEAG	2021.09.01	3year
☒	System Validation Dipole,2450MHz	D2450V2	818	SPEAG	2021.08.26	3year
☒	System Validation Dipole,2600MHz	D2600V2	1074	SPEAG	2020.01.02	3year
☒	System Validation Dipole,5GHz	D5GzV2	1185	SPEAG	2019.12.31	3year
☒	Dielectric Probe Kit	85070E	MY44300455	Agilent	NCR	NCR
☒	Dual-directional coupler,0.10-2.0GHz	778D	MY48220198	Agilent	NCR	NCR
☒	Dual-directional coupler,2.00-18GHz	772D	MY46151160	Agilent	NCR	NCR
☒	Power Amplifier	ZVE-8G	SC280800926	MINI-CIRCUITS	NCR	NCR
☒	Power Amplifier	ZHL42W	81709	MINI-CIRCUITS	NCR	NCR
☒	Signal Generator	SMR20	100047	R&S	2022.02.19	1year
☒	Power Sensor	NRP-Z21	102626	R&S	2022.05.13	1year
☒	Power Sensor	NRP-Z21	102627	R&S	2022.05.13	1year
☒	Call Tester	CMU 200	100110	R&S	2022.05.18	1year

<input checked="" type="checkbox"/>	Network Analyzer	E5071C	MY46109550	Agilent	2022.02.19	1Year
<input checked="" type="checkbox"/>	Flat Phantom	ELI4.0	TP-1904	SPEAG	NCR	NCR
<input checked="" type="checkbox"/>	Twin Phantom	SAM	TP-1504	SPEAG	NCR	NCR
<input checked="" type="checkbox"/>	Wideband Radio Communication Tester	CMW500	125469	R&S	2022.05.18	1Year
<input checked="" type="checkbox"/>	Precision Thermometer	--	--	--	2022.06.20	1Year

Table 3: List of Test and Measurement Equipment

Note: All the test equipments are calibrated once a year, except the dipoles, which are calibrated every three years. Moreover, we have self-calibration every year to the dipoles.

2. GENERAL INFORMATION

2.1. Report information

This report is not a certificate of quality; it only applies to the sample of the specific product/equipment given at the time of its testing. The results are not used to indicate or imply that they are application to the similar items. In addition, such results must not be used to indicate or imply that SMQ approves recommends or endorses the manufacture, supplier or use of such product/equipment, or that SMQ in any way guarantees the later performance of the product/equipment.

The sample/s mentioned in this report is/are supplied by Applicant, SMQ therefore assumes no responsibility for the accuracy of information on the brand name, model number, origin of manufacture or any information supplied.

Additional copies of the report are available to the Applicant at an additional fee. No third part can obtain a copy of this report through SMQ, unless the applicant has authorized SMQ in writing to do so.

The lab will not be liable for any loss or damage resulting from false, inaccurate, inappropriate or incomplete product information provided by the applicant/manufacturer.

2.2. Laboratory Accreditation and Relationship to Customer


The testing report were performed by the Shenzhen Academy of Metrology and quality Inspection EMC Laboratory (Guangdong EMC compliance testing center), in their facilities located at NETC Building, No.4 Tongfa Rd., Xili, Nanshan, Shenzhen, China. At the time of testing, Laboratory is accredited by the following organizations: China National Accreditation Service for Conformity Assessment (CNAS) accredits the Laboratory for conformance to FCC standards, EMC international standards and EN standards. The Registration Number is CNAS L0579. The Laboratory is Accredited Testing Laboratory of FCC with Designation number CN1165 and Site registration number 582918. The Laboratory is registered to perform emission tests with Innovation, Science and

Economic Development (ISED), and the registration number is 11177A. The Laboratory is registered to perform emission tests with VCCI, and the registration numbers are C-20048, G20076, R-20077, R-20078, and T-20047.

The Laboratory is Accredited Testing Laboratory of American Association for Laboratory Accreditation (A2LA) and certificate number is 3292.01.

3. SAR MEASUREMENT SYSTEM CONFIGURATION

3.1. SAR Measurement Set-up



The DASY5 system for performing compliance tests consists of the following items:

- A standard high precision 6-axis robot (Stäubli RX family) with controller and software. An arm extension for accommodating the data acquisition electronics (DAE).
- A dosimetric probe, i.e. an isotropic E-field probe optimized and calibrated for usage in tissue simulating liquid. The probe is equipped with an optical surface detector system.
- A data acquisition electronic (DAE) which performs the signal amplification, signal multiplexing, AD-conversion, offset measurements, mechanical surface detection, collision detection, etc. The unit is battery powered with standard or rechargeable batteries. The signal is optically transmitted to the EOC.
- A unit to operate the optical surface detector which is connected to the EOC.

- The Electro-Optical Coupler (EOC) performs the conversion from the optical into a digital electric signal of the DAE. The EOC is connected to the DASY5 measurement server.
- The DASY5 measurement server, which performs all real-time data evaluation for field measurements and surface detection, controls robot movements and handles safety operation. • A computer operating Windows XP.
- DASY5 software and SEMCAD data evaluation software.


Remote control with teach panel and additional circuitry for robot safety such as warning lamps, etc.


- The generic twin phantom enabling the testing of left-hand and right-hand usage.
- The device holder for handheld mobile phones.
- Tissue simulating liquid mixed according to the given recipes.
- System checks dipoles allowing validating the proper functioning of the system.
- Test environment
- The DASY5 measurement system is placed at the head end of a room with dimensions: 4.5 x 4 x 3 m³, the SAM phantom is placed in a distance of 1.3 m from the side walls and 1.1m from the rear wall.

Picture 1 of the photo documentation shows a complete view of the test environment.

3.2. Probe description

Isotropic E-Field Probe EX3DV4 for Dosimetric Measurements


Construction	Symmetrical design with triangular core Interleaved sensors Built-in shielding against static charges PEEK enclosure material (resistant to organic solvents, e.g., DGBE)	
Calibration	ISO/IEC 17025 calibration service available.	
Frequency	10 MHz to >6 GHz (dosimetry); Linearity: ± 0.2 dB (30 MHz to 6 GHz)	
Directivity	± 0.3 dB in HSL (rotation around probe axis) ± 0.5 dB in tissue material (rotation normal to probe axis)	
Dynamic range	10 µW/g to > 100 mW/g; Linearity: ± 0.2 dB (noise:	

	typically $1 \mu\text{W/g}$)	
Dimensions	Overall length: 337 mm (Tip: 20mm) Tip length: 2.5 mm (Body: 12mm) Typical distance from probe tip to dipole centers: 1mm	
Application	High precision dosimetric measurements in any exposure scenario (e.g., very strong gradient fields). Only probe which enables compliance testing for frequencies up to 6 GHz with precision of better 30%.	

3.3. Phantom description

The used SAM Phantom meets the requirements specified in Edition 01-01 of Supplement C to OET Bulletin 65 for Specific Absorption Rate (SAR) measurements.

The phantom consists of a fibreglass shell integrated in a wooden table. It allows left-hand and right-hand head as well as body-worn measurements with a maximum liquid depth of 18 cm in head position and 22 cm in planar position (body measurements). The thickness of the Phantom shell is 2 mm +/- 0.1 mm.





ELI4 Phantom

Shell Thickness	2mm+/- 0.2mm
Filling Volume	Approximately 30 liters
Measurement Areas	Flat phantom
The ELI4 phantom is intended for compliance testing of handheld and body-mounted wireless devices in the frequency range of 30MHz to 6GHz. ELI4 is fully compatible with the latest draft of the standard IEC 62209-2 and all known tissue simulating liquids.	

The phantom shell material is resistant to all ingredients used in the tissue-equivalent liquid recipes. The shell of the phantom including ear spacers is constructed from low permittivity and low loss material, with a relative permittivity ≤ 5 and a loss tangent ≤ 0.05 .

3.4. Device holder description

The DASY5 device holder has two scales for device rotation (with respect to the body axis) and the device inclination (with respect to the line between the ear openings). The plane between the ear openings and the mouth tip has a rotation angle of 65° . The bottom plate contains three pair of bolts for locking the device holder. The device holder positions are adjusted to the standard measurement positions in the three sections. This device holder is used for standard



mobile phones or PDA's only. If necessary an additional support of polystyrene material is used.

Larger DUT's (e.g. notebooks) cannot be tested using this device holder. Instead a support of bigger polystyrene cubes and thin polystyrene plates is used to position the DUT in all relevant positions to find and measure spots with maximum SAR values.

Therefore those devices are normally only tested at the flat part of the SAM.

4. SAR MEASUREMENT PROCEDURE

4.1. Scanning procedure

- The DASY5 installation includes predefined files with recommended procedures for measurements and system check. They are read-only document files and destined as fully defined but unmeasured masks. All test positions (head or body-worn) are tested with the same configuration of test steps differing only in the grid definition for the different test positions.
- The reference and drift measurements are located at the beginning and end of the batch process. They measure the field drift at one single point in the liquid over the complete procedure. The indicated drift is mainly the variation of the DUT's output power and should vary max. +/- 5 %.
- The surface check measurement tests the optical surface detection system of the DASY5 system by repeatedly detecting the surface with the optical and mechanical surface detector and comparing the results. The output gives the detecting heights of both systems, the difference between the two systems and the standard deviation of the detection repeatability. Air bubbles or refraction in the liquid due to separation of the sugar-water mixture gives poor repeatability (above $\pm 0.1\text{mm}$). To prevent wrong results tests are only executed when the liquid is free of air bubbles. The difference between the optical surface detection and the actual surface depends on the probe and is specified with each probe. (It does not depend on the surface reflectivity or the probe angle to the surface within $\pm 30^\circ$.)
- The area scan measures the SAR above the DUT or verification dipole on a parallel plane to the surface. It is used to locate the approximate location of the peak SAR with 2D spline interpolation. The robot performs a stepped movement along one grid axis while the local electrical field strength is measured by the probe. The probe is touching the surface of the SAM during acquisition of measurement values. The standard scan uses large grid spacing for faster measurement. Standard grid spacing for head measurements is 15 mm in x- and y- dimension ($\leq 2\text{GHz}$), 12 mm in x- and y- dimension (2-4 GHz) and 10mm in x- and y- dimension (4-6GHz). If a finer resolution is needed, the grid spacing can be reduced. Grid spacing and orientation have no

influence on the SAR result. For special applications where the standard scan method does not find the peak SAR within the grid, e.g. mobile phones with flip cover, the grid can be adapted in orientation.

Results of this coarse scan are shown in Appendix B.

- A “zoom scan” measures the field in a volume around the 2D peak SAR value acquired in the previous “coarse” scan. This is a fine grid with maximum scan spatial resolution: Δx_{zoom} , $\Delta y_{zoom} \leq 2\text{GHz} \leq 8\text{ mm}$, $2\text{-}4\text{GHz} - \leq 5\text{ mm}$ and $4\text{-}6\text{ GHz} - \leq 4\text{ mm}$; $\Delta z_{zoom} \leq 3\text{GHz} - \leq 5\text{ mm}$, $3\text{-}4\text{ GHz} - \leq 4\text{ mm}$ and $4\text{-}6\text{GHz} - \leq 2\text{mm}$ where the robot additionally moves the probe along the z-axis away from the bottom of the Phantom. DASY5 is also able to perform repeated zoom scans if more than 1 peak is found during area scan. Test results relevant for the specified standard (see chapter 1.5.) are shown in table form in chapter 3.2.
- A Z-axis scan measures the total SAR value at the x-and y-position of the maximum SAR value found during the cube scan. The probe is moved away in z-direction from the bottom of the SAM phantom in 2mm steps. This measurement shows the continuity of the liquid and can – depending in the field strength- also show the liquid depth. A z-axis scan of the measurement with maximum SAR value is shown in Appendix B.

The following table summarizes the area scan and zoom scan resolutions per FCC KDB 865664D01:

Frequency	Maximum Area Scan resolution ($\Delta x_{area}, \Delta y_{area}$)	Maximum Zoom Scan spatial resolution ($\Delta x_{zoom}, \Delta y_{zoom}$)	Maximum Zoom Scan spatial resolution			Minimum zoom scan volume (x,y,z)
			Uniform Grid	Graded Grad		
				$\Delta z_{zoom}(n)$	$\Delta z_{zoom}(1)$	
$\leq 2\text{GHz}$	$\leq 15\text{mm}$	$\leq 8\text{mm}$	$\leq 5\text{mm}$	$\leq 4\text{mm}$	$\leq 1.5 * \Delta z_{zoom}(n-1)$	$\geq 30\text{mm}$
2-3GHz	$\leq 12\text{mm}$	$\leq 5\text{mm}$	$\leq 5\text{mm}$	$\leq 4\text{mm}$	$\leq 1.5 * \Delta z_{zoom}(n-1)$	$\geq 30\text{mm}$
3-4GHz	$\leq 10\text{mm}$	$\leq 5\text{mm}$	$\leq 4\text{mm}$	$\leq 3\text{mm}$	$\leq 1.5 * \Delta z_{zoom}(n-1)$	$\geq 28\text{mm}$
4-5GHz	$\leq 10\text{mm}$	$\leq 4\text{mm}$	$\leq 3\text{mm}$	$\leq 2.5\text{mm}$	$\leq 1.5 * \Delta z_{zoom}(n-1)$	$\geq 25\text{mm}$

5-6GHz	≤10mm	≤4mm	≤2mm	≤2mm	≤ 1.5*Δzzoom(n-1)	≥22mm
--------	-------	------	------	------	----------------------	-------

Spatial Peak SAR Evaluation

- The spatial peak SAR - value for 1 and 10 g is evaluated after the Cube measurements have been done. The bases of the evaluation are the SAR values measured at the points of the fine cube grid consisting of 5 x 5 x 7 points (with 8mm horizontal resolution) or 7 x 7 x 7 points (with 5mm horizontal resolution).
- The algorithm that finds the maximal averaged volume is separated into three different stages.
- The data between the dipole center of the probe and the surface of the phantom are extrapolated. This data cannot be measured since the center of the dipole is 2.7 mm away from the tip of the probe and the distance between the surface and the lowest measuring point is about 1 mm (see probe calibration sheet). The extrapolated data from a cube measurement can be visualized by selecting 'Graph Evaluated'.
- The maximum interpolated value is searched with a straight-forward algorithm. Around this maximum the SAR - values averaged over the spatial volumes (1g or 10 g) are computed using the 3d-spline interpolation algorithm. If the volume cannot be evaluated (i.e., if a part of the grid was cut off by the boundary of the measurement area) the evaluation will be started on the corners of the bottom plane of the cube.
- All neighboring volumes are evaluated until no neighboring volume with a higher average value is found.
- Extrapolation
- The extrapolation is based on a least square algorithm [W. Gander, Computermathematik, p.168-180]. Through the points in the first 3 cm along the z-axis, polynomials of order four are calculated. These polynomials are then used to evaluate the points between the surface and the probe tip. The points, calculated from the surface, have a distance of 1 mm from each other.

Interpolation

- The interpolation of the points is done with a 3d-Spline. The 3d-Spline is composed of three one-dimensional splines with the "Not a knot"-condition [W. Gander, Computermathematik, p.141-150] (x, y and z -direction) [Numerical Recipes in C, Second Edition, p.123ff].
- Volume Averaging
- At First the size of the cube is calculated. Then the volume is integrated with the trapezoidal

algorithm. 8000 points (20x20x20) are interpolated to calculate the average.

- Advanced Extrapolation
- DASY5 uses the advanced extrapolation option which is able to compensate boundary effects on E-field probes.

6.1.1. Data Storage and Evaluation

Data Storage

The DASY5 software stores the acquired data from the data acquisition electronics as raw data (in microvolt readings from the probe sensors), together with all necessary software parameters for the data evaluation (probe calibration data, liquid parameters and device frequency and modulation data) in measurement files with the extension DAE4. The software evaluates the desired unit and format for output each time the data is visualized or exported. This allows verification of the complete software setup even after the measurement and allows correction of incorrect parameter settings. For example, if a measurement has been performed with a wrong crest factor parameter in the device setup, the parameter can be corrected afterwards and the data can be re-evaluated.

The measured data can be visualized or exported in different units or formats, depending on the selected probe type ([V/m], [A/m], [°C], [mW/g], [mW/cm²], [dBrel], etc.). Some of these units are not available in certain situations or show meaningless results, e.g., a SAR output in a lossless media will always be zero. Raw data can also be exported to perform the evaluation with other software packages.

Data Evaluation by SEMCAD

The SEMCAD software automatically executes the following procedures to calculate the field units from the microvolt readings at the probe connector. The parameters used in the evaluation are stored in the configuration modules of the software:

Probe parameters:	- Sensitivity	Normi, ai0, ai1, ai2
- Conversion factor	ConvFi	
- Diode compression point	Dcpi	
Device parameters:	- Frequency	f
- Crest factor	cf	
Media parameters:	- Conductivity	σ
- Density	ρ	

These parameters must be set correctly in the software. They can be found in the component documents or they can be imported into the software from the configuration files issued for the DASY5 components. In the direct measuring mode of the multimeter option, the parameters of the actual system setup are used. In the scan visualization and export modes, the parameters stored in the corresponding document files are used.

The first step of the evaluation is a linearization of the filtered input signal to account for the compression characteristics of the detector diode. The compensation depends on the input signal, the diode type and the DC-transmission factor from the diode to the evaluation electronics.

If the exciting field is pulsed, the crest factor of the signal must be known to correctly compensate for peak power. The formula for each channel can be given as:

$$V_i = U_i + U_i^2 \cdot cf/dcpi$$

with V_i = compensated signal of channel i ($i = x, y, z$)

U_i = input signal of channel i ($i = x, y, z$)

cf = crest factor of exciting field (DASY parameter)

$dcpi$ = diode compression point (DASY parameter)

From the compensated input signals the primary field data for each channel can be evaluated:

E-field probes: $E_i = (V_i / Norm_i \cdot ConvF)^{1/2}$

H-field probes: $H_i = (V_i)^{1/2} \cdot (ai_0 + ai_1f + ai_2f^2)/f$

with V_i = compensated signal of channel i ($i = x, y, z$)

$Norm_i$ = sensor sensitivity of channel i ($i = x, y, z$)

[mV/(V/m)²] for E-field Probes

$ConvF$ = sensitivity enhancement in solution

ai_j = sensor sensitivity factors for H-field probes

- f = carrier frequency [GHz]
- E_i = electric field strength of channel i in V/m
- H_i = magnetic field strength of channel i in A/m

The RSS value of the field components gives the total field strength (Hermitian magnitude):

$$E_{tot} = (E_x^2 + E_y^2 + E_z^2)^{1/2}$$

The primary field data are used to calculate the derived field units.

$$SAR = (E_{tot}^2 \cdot \sigma) / (\rho \cdot 1000)$$

with SAR = local specific absorption rate in mW/g

E_{tot} = total field strength in V/m

σ = conductivity in [mho/m] or [Siemens/m]

ρ = equivalent tissue density in g/cm³

Note that the density is normally set to 1 (or 1.06), to account for actual brain density rather than the density of the simulation liquid. The power flow density is calculated assuming the excitation field to be a free space field.

$$P_{pwe} = E_{tot}^2 / 3770 \quad \text{or} \quad P_{pwe} = H_{tot}^2 \cdot 37.7$$

with P_{pwe} = equivalent power density of a plane wave in mW/cm²

E_{tot} = total electric field strength in V/m

H_{tot} = total magnetic field strength in A/m

7. SYSTEM VERIFICATION PROCEDURE

7.1. Tissue Verification

The simulating liquids should be checked at the beginning of a series of SAR measurements to determine if the dielectric parameters are within the tolerances of the specified target values. The measured conductivity and relative permittivity should be within $\pm 5\%$ of the target values.

The following materials are used for producing the tissue-equivalent materials

Ingredient (% by weight)	Head Tissue				
	750	835	1750	1900	2450
Water	34.4	41.45	52.64	55.24	62.7
Salt(NaCl)	0.79	1.45	0.36	0.306	0.5
Sugar	64.81	56.0	0.0	0.0	0.0
HEC	0.0	1.0	0.0	0.0	0.0
Bactericide	0.0	0.1	0.0	0.0	0.0
Triton X-100	0.0	0.0	0.0	0.0	0.0
DGBE	0.0	0.0	47.0	44.54	36.8

Table 4 : Tissue Dielectric Properties

Salt: 99+% Pure Sodium Chloride; Sugar: 98+% Pure Sucrose; Water: De-ionized, 16M Ω + resistivity

HEC: Hydroxyethyl Cellulose; DGBE: 99+% Di(ethylene glycol) butyl ether, [2-(2-butoxyethoxy)ethanol]

Triton X-100(ultra pure): Polyethylene glycol mono[4-(1,1,3,3-tetramethylbutyl)phenyl]ether

Tissue-equivalent liquid measurements:

f/MHz	Date Tested	Dielectric Parameters	Target	Tolerance (%)	Temp (°C)
750	2022.11.11	$\epsilon_r=42.44$	41.9 (39.81~44.00)	±5	20
		$\sigma=0.88$	0.89 (0.85~0.93)		
835	2022.11.13	$\epsilon_r =41.73$	41.5 (39.43~43.58)	±5	20
		$\sigma=0.93$	0.90 (0.86~0.95)		
1750	2022.11.15	$\epsilon_r =39.77$	40.1 (38.10~42.11)	±5	20
		$\sigma=1.40$	1.37 (1.30~1.44)		
1900	2022.11.18	$\epsilon_r =40.74$	40.0 (38.00~42.00)	±5	20
		$\sigma=1.44$	1.40 (1.33~1.47)		
2450	2022.11.24	$\epsilon_r =39.31$	39.2 (37.24~41.16)	±5	20
		$\sigma=1.86$	1.80 (1.71~1.89)		
2600	2022.11.21	$\epsilon_r =39.93$	39.0 (37.05~40.95)	±5	20
		$\sigma=2.03$	1.96 (1.86~2.06)		
5.2G	2022.11.28	$\epsilon_r =36.43$	36.0 (34.20~37.80)	±5	20
		$\sigma=4.73$	4.66 (4.43~4.89)		
5.6G	2022.11.28	$\epsilon_r =36.11$	35.5 (33.82~37.38)	±5	20
		$\sigma=5.10$	5.07 (4.71~5.21)		
5.75G	2022.11.28	$\epsilon_r =35.38$	35.3	±5	20


			(33.54~37.07)		
		$\sigma=5.32$	5.27 (5.01~5.53)		

System check, Tissue-equivalent liquid:

f/MHz	Date Tested	Power (mW)	SAR(W/kg), 1g	SAR(W/kg), 10g	Target 1g	Target 10g	Tolerance (%)	Temp (°C)
750	2022.11.11	250	8.76	5.88	8.66 (7.80 ~9.52)	5.83 (5.25 ~6.41)	±10	20
835	2022.11.13	250	9.04	6.04	9.58 (8.63 ~10.53)	6.19 (5.58 ~6.80)	±10	20
1750	2022.11.15	250	35.84	18.84	35.70 (32.13 ~39.27)	18.80 (16.92 ~20.68)	±10	20
1900	2022.11.18	250	38.96	20.00	39.70 (35.73 ~43.67)	20.20 (18.18 ~22.22)	±10	20
2450	2022.11.24	250	51.20	23.48	52.20 (46.98 ~57.42)	23.80 (21.42 ~26.18)	±10	20
2600	2022.11.21	250	55.20	24.48	56.90 (51.21 ~62.59)	25.20 (22.68 ~27.72)	±10	20
5.25 G	2022.11.28	100	75.90	22.20	76.50 (68.85 ~84.15)	21.80 (19.62 ~23.98)	±10	20
5.6G	2022.11.28	100	79.00	22.5	80.20 (72.18 ~88.22)	22.80 (20.52 ~25.08)	±10	20
5.75 G	2022.11.28	100	76.40	21.80	78.20 (70.38 ~86.02)	22.20 (19.98 ~24.42)	±10	20

System Checking

The manufacturer calibrates the probes annually. A system check measurement was made following the determination of the dielectric parameters of the tissue-equivalent liquid, using the dipole validation kit. A power level was supplied to the dipole antenna, which was placed under the flat section of the twin SAM phantom.



The system checking results (dielectric parameters and SAR values) are given in the table below.

The system check is performed for verifying the accuracy of the complete measurement system and performance of the software. The system check is performed with tissue equivalent material according to IEEE P1528 (described above). The following table shows system check results for all frequency bands and tissue liquids used during the tests (Graphic Plot(s) see Appendix A).

8. SAR MEASUREMENT VARIABILITY AND UNCERTAINTY

8.1. SAR measurement variability

Per KDB865664 D01 SAR measurement 100MHz to 6GHz v01r04, SAR measurement variability must be assessed for each frequency band, which is determined by the SAR probe calibration point and tissue-equivalent medium used for the device measurements. The additional measurements are repeated after the completion of all measurement requiring the same head or body tissue-equivalent medium in a frequency band. The test device should be returned to ambient conditions (normal room temperature) with the battery fully charged before it is re-mounted on the device holder for the repeated measurement(s) to minimize any unexpected variations in the repeated results.

- 1) Repeated measurement is not required when the original highest measured SAR is <0.80 W/kg; step2) through 4) do not apply.
- 2) When the original highest measured SAR is ≥ 0.8 W/kg , repeat that measurement once.
- 3) Perform a second repeated measurement only if the ratio of largest to smallest SAR for the original and first repeated measurements is >1.20 or when the original or repeated measurement is ≥ 1.45 W/kg (~10% from the 1-g SAR limit).
- 4) Perform a third repeated measurement only if the original, first or second repeated measurement is ≥ 1.5 W/kg and the ratio of largest to smallest SAR for the original, first and second repeated measurements is >1.20 .

The same procedures should be adapted for measurements according to extremity and occupational exposure limits by applying a factor of 2.5 for extremity exposure and a factor of 5 for occupational exposure to the corresponding SAR thresholds.

8.2. SAR measurement uncertainty

Per KDB865664 D01 SAR Measurement 100MHz to 6GHz v01r03, when the highest measured 1-g SAR within a frequency band is <1.5 W/kg, the extensive SAR measurement uncertainty analysis described in IEEE Std 1528-2003 is not required in SAR reports submitted for equipment approval. The equivalent ratio(1.5/1.6) is applied to

extremity and occupational exposure conditions.

9. Test Configuration

The DUT is tested using a CMU 200 or E5515C communications tester as controller unit to set test channels and maximum output power to the DUT, as well as for measuring the conducted peak power.

Test positions as described in the tables above are in accordance with the specified test standard.

GSM Test Configuration

SAR tests for GSM 850 and PCS 1900, a communication link is set up with a System Simulator (SS) by air link. Using CMU 200 or E5515C the power level is set to “5” for GSM 850, set to “0” for PCS 1900. Since the GPRS class is 12 for this EUT, it has at most 4 timeslots in uplink and at most 4 timeslots in downlink, the maximum total timeslots is 5.

According to specification 3GPP TS 51.010, the maximum power of the GSM can do the power reduction for the multi-slot. The allowed power reduction in the multi-slot configuration is as following:

Output power of reductions:

Number of timeslots in uplink assignment	Permissible nominal reduction of maximum output power,(dB)
1	0
2	0 to 3,0
3	1,8 to 4,8
4	3,0 to 6,0

WCDMA Test Configuration

The following tests were completed according to the test requirements outlined in section 5.2 of the 3GPP TS34.121-1 specification. The EUT supports power Class 3, which has a nominal maximum output power of 24 dBm (+1.7/-3.7).

	Mode	Rel99
	Subtest	---

WCDMA General Settings	Loopback Mode	Test Mode 1
	Rel99 RMC	12.2kbps RMC
	Power Control Algorithm	Algorithm2
	β_c / β_d	8/15

Handsets with Release 5 HSDPA

The 3G SAR test reduction procedure is applied to HSDPA body-worn accessory configurations with 12.2 kbps RMC as the primary mode. Otherwise, SAR is measured for HSDPA using the HSDPA body SAR procedures in the “Release 5 HSDPA Data Devices” section of this document, for the highest reported SAR body-worn accessory exposure configuration in 12.2 kbps RMC. Handsets with both HSDPA and HSUPA are tested according to Release 6 HSPA test procedures.

HSDPA should be configured according to the UE category of a test device. The number of HSDSCH/HS-PDSCHs, HARQ processes, minimum inter-TTI interval, transport block sizes and RV coding sequence are defined by the H-set. To maintain a consistent test configuration and stable transmission conditions, QPSK is used in the H-set for SAR testing. HS-DPCCH should be configured with a CQI feedback cycle of 4 ms with a CQI repetition factor of 2 to maintain a constant rate of active CQI slots. DPCCH and DPDCH gain factors (β_c , β_d), and HS-DPCCH power offset parameters (Δ_{ACK} , Δ_{NACK} , Δ_{CQI}) should be set according to values indicated in the Table below. The CQI value is determined by the UE category, transport block size, number of HS-PDSCHs and modulation used in the H-set.

Sub-set	β_c	β_d	β_d (SF)	β_c/β_d	β_{hs} (note 1, note 2)	CM(dB) (note 3)	MPR(dB)
1	2/15	15/15	64	2/15	4/15	0.0	0.0
2	12/15 (note 4)	15/15 (note 4)	64	12/15 (note 4)	24/15	1.0	0.0
3	15/15	8/15	64	15/8	30/15	1.5	0.5
4	15/15	4/15	64	15/4	30/15	1.5	0.5

Note1: Δ_{ACK} , Δ_{NACK} and $\Delta_{CQI} = 8$ $\beta_{hs} = \beta_{hs}/\beta_c = 30/15$ $\beta_{hs} = 30/15 * \beta_c$
Note2: CM=1 for $\beta_c/\beta_d = 12/15$, $\beta_{hs}/\beta_c = 24/15$.
Note3: For subtest 2 the β_c/β_d ratio of 12/15 for the TFC during the measurement period (TF1, TF0) is achieved by setting the signaled gain factors for the reference TFC (TFC1, TF1) to $\beta_c = 11/15$ and $\beta_d = 15/15$.

HSUPA Test Configuration

The 3G SAR test reduction procedure is applied to HSPA (HSUPA/HSDPA with RMC)

body-worn accessory configurations with 12.2 kbps RMC as the primary mode. Otherwise, SAR is measured for HSPA using the HSPA body SAR procedures in the “Release 6 HSPA Data Devices” section of this document, for the highest reported body-worn accessory exposure SAR configuration in 12.2 kbps RMC. When VOIP is applicable for next to the ear head exposure in HSPA, the 3G SAR test reduction procedure is applied to HSPA with 12.2 kbps RMC as the primary mode; otherwise, the same HSPA configuration used for body-worn accessory measurements is tested for next to the ear head exposure.

Due to inner loop power control requirements in HSPA, a communication test set is required for output power and SAR tests. The 12.2 kbps RMC, FRC H-set 1 and E-DCH configurations for HSPA are configured according to the β values indicated in Table 2 and other applicable procedures described in the ‘WCDMA Handset’ and ‘Release 5 HSDPA Data Devices’ sections of this document

Sub-set	β_c	β_d	β_d (SF)	β_c/β_d	$\beta_{hs}^{(1)}$	β_{ec}	β_{ed}	β_{ed} (SF)	β_{ed} (codes)	CM ⁽²⁾ (dB)	MPR (dB)	AG ⁽⁴⁾ Index	E-TFCI
1	11/15 ⁽³⁾	15/15 ⁽³⁾	64	11/15 ⁽³⁾	22/15	209/225	1039/225	4	1	1.0	0.0	20	75
2	6/15	15/15	64	6/15	12/15	12/15	94/75	4	1	3.0	2.0	12	67
3	15/15	9/15	64	15/9	30/15	30/15	β_{ed1} : 47/15 β_{ed2} : 47/15	4	2	2.0	1.0	15	92
4	2/15	15/15	64	2/15	4/15	2/15	56/75	4	1	3.0	2.0	17	71
5	15/15 ⁽⁴⁾	15/15 ⁽⁴⁾	64	15/15 ⁽⁴⁾	30/15	24/15	134/15	4	1	1.0	0.0	21	81
<p>Note 1: $\Delta_{ACK}, \Delta_{NACK}$ and $\Delta_{CQI} = 8 \Leftrightarrow A_{hs} = \beta_{hs}/\beta_c = 30/15 \Leftrightarrow \beta_{hs} = 30/15 * \beta_c$.</p> <p>Note 2: CM = 1 for $\beta_c/\beta_d = 12/15$, $\beta_{hs}/\beta_c = 24/15$. For all other combinations of DPDCH, DPCCH, HS- DPCCH, E-DPDCH and E-DPCCH the MPR is based on the relative CM difference.</p> <p>Note 3: For subtest 1 the β_c/β_d ratio of 11/15 for the TFC during the measurement period (TF1, TF1) is achieved by setting the signaled gain factors for the reference TFC (TF1, TF1) to $\beta_c = 10/15$ and $\beta_d = 15/15$.</p> <p>Note 4: For subtest 5 the β_c/β_d ratio of 15/15 for the TFC during the measurement period (TF1, TF0) is achieved by setting the signaled gain factors for the reference TFC (TF1, TF1) to $\beta_c = 14/15$ and $\beta_d = 15/15$.</p> <p>Note 5: Testing UE using E-DPDCH Physical Layer category 1 Sub-test 3 is not required according to TS 25.306 Figure 5.1g.</p> <p>Note 6: β_{ed} can not be set directly; it is set by Absolute Grant Value.</p>													

UE E-DCH Category	Maximum E-DCH Codes Transmitted	Number of HARQ Processes	E-DCH TTI (ms)	Minimum Spreading Factor	Maximum E-DCH Transport Block Bits	Max Rate (Mbps)
1	1	4	10	4	7110	0.7296
2	2	8	2	4	2798	1.4592
	2	4	10	4	14484	
3	2	4	10	4	14484	1.4592
4	2	8	2	2	5772	2.9185
	2	4	10	2	20000	2.00
5	2	4	10	2	20000	2.00
6 (No DPDCH)	4	8	2	2 SF2 & 2 SF4	11484	5.76
	4	4	10		20000	2.00
7 (No DPDCH)	4	8	2	2 SF2 & 2 SF4	22996	?
	4	4	10		20000	?
NOTE: When 4 codes are transmitted in parallel, two codes shall be transmitted with SF2 and two with SF4. UE Categories 1 to 6 supports QPSK only. UE Category 7 supports QPSK and 16QAM. (TS25.306-7.3.0)						

HSPA, HSPA+ and DC-HSDPA Test Configuration

measurement is required for HSPA, HSPA+ or DC-HSDPA, a KDB inquiry is required to confirm that the wireless mode configurations in the test setup have remained stable throughout the SAR measurements.³⁵ Without prior KDB confirmation to determine the SAR results are acceptable, a PBA is required for TCB approval. SAR test exclusion for HSPA, HSPA+ and DC-HSDPA is determined according to the following:

- 1) The HSPA procedures are applied to configure 3GPP Rel. 6 HSPA devices in the required Sub-test mode(s) to determine SAR test exclusion.
- 2) SAR is required for Rel. 7 HSPA+ when SAR is required for Rel. 6 HSPA; otherwise, the 3G SAR test reduction procedure is applied to (Up antenna) HSPA+ with 12.2 kbps RMC as the primary mode.³⁶ Power is measured for HSPA+ that supports Up antenna 16 QAM according to configurations in Table C.11.1.4 of 3GPP TS 34.121-1 to determine SAR test reduction.
- 3) SAR is required for Rel. 8 DC-HSDPA when SAR is required for Rel. 5 HSDPA; otherwise, the 3G SAR test reduction procedure is applied to DC-HSDPA with 12.2 kbps RMC as the primary mode. Power is measured for DC-HSDPA according to the H-Set 12, FRC configuration in Table C.8.1.12 of 3GPP TS 34.121-1 to determine SAR test reduction. A primary and a secondary serving HS-DSCH Cell are required to perform the power measurement and for the results to be

acceptable.

4) Regardless of whether a PBA is required, the following information must be verified and included in the SAR report for devices supporting HSPA, HSPA+ or DC-HSDPA: a) The output power measurement results and applicable release version(s) of 3GPP TS 34.121.

i) Power measurement difficulties due to test equipment setup or availability must be resolved between the grantee and its test lab.

b) The power measurement results are in agreement with the individual device implementation and specifications. When Enhanced MPR (E-MPR) applies, the normal MPR targets may be modified according to the Cubic Metric (CM) measured by the device, which must be taken into consideration.

c) The UE category, operating parameters, such as the β and Δ values used to configure the device for testing, power setback procedures described in 3GPP TS 34.121 for the power measurements, and HSPA/HSPA+ channel conditions (active and stable) for the entire duration of the measurement according to the required E-TFCl and AG index values.

5) When SAR measurement is required, the test configurations, procedures and power measurement results must be clearly described to confirm that the required test parameters are used, including E-TFCl and AG index stability and output power conditions.

HS-DSCH category	Maximum number of HS-DSCH codes received	Minimum inter-TTI interval	Maximum number of bits of an HS-DSCH transport block received within an HS-DSCH TTI NOTE 1	Total number of soft channel bits	Supported modulations without MIMO operation or dual cell operation	Supported modulations with MIMO operation and without dual cell operation	Supported modulations with dual cell operation	
Category 1	5	3	7298	19200	QPSK, 16QAM	Not applicable (MIMO not supported)	Not applicable (dual cell operation not supported)	
Category 2	5	3	7298	28800				
Category 3	5	2	7298	28800				
Category 4	5	2	7298	38400				
Category 5	5	1	7298	57600				
Category 6	5	1	7298	67200				
Category 7	10	1	14411	115200				
Category 8	10	1	14411	134400				
Category 9	15	1	20251	172800				
Category 10	15	1	27952	172800				
Category 11	5	2	3630	14400				QPSK
Category 12	5	1	3630	28800				QPSK, 16QAM, 64QAM
Category 13	15	1	35280	259200				QPSK, 16QAM
Category 14	15	1	42192	259200				QPSK, 16QAM
Category 15	15	1	23370	345600	QPSK, 16QAM	Not applicable (dual cell operation not supported)		
Category 16	15	1	27952	345600	QPSK, 16QAM			
Category 17 NOTE 2	15	1	35280	259200	QPSK, 16QAM, 64QAM		-	
			23370	345600	-		QPSK, 16QAM	
Category 18 NOTE 3	15	1	42192	259200	QPSK, 16QAM, 64QAM		-	
			27952	345600	-		QPSK, 16QAM	
Category 19	15	1	35280	518400	QPSK, 16QAM, 64QAM			
Category 20	15	1	42192	518400				
Category 21	15	1	23370	345600	-		-	QPSK, 16QAM
Category 22	15	1	27952	345600				
Category 23	15	1	35280	518400				
Category 24	15	1	42192	518400				

LTE Test Configuration

SAR for LTE band exposure configurations is measured according to the procedures of KDB 941225 D05 SAR for LTE Devices v02r05. The CMW500 WideBand Radio Communication Tester was used for LTE output power measurements and SAR testing. Closed loop power control was used so the UE transmits with maximum output power during SAR testing. SAR test were performed with the same number of RB and RB offsets transmitting on all TTI frames (Maximum TTI)

1) Spectrum Plots for RB configurations

A properly configured base station simulator was used for LTE output power measurements and SAR testing. Therefore, spectrum plots for RB configurations were not required to be included in this report.

2) MPR

When MPR is implemented permanently within the UE, regardless of network

requirements, only those RB configurations allowed by 3GPP for the channel bandwidth and modulation combinations may be tested with MPR active. Configurations with RB allocations less than the RB thresholds required by 3GPP must be tested without MPR. The allowed Maximum Power Reduction (MPR) for the maximum output power due to higher order modulation and transmit bandwidth configuration (resource blocks) is specified in Table 6.2.3-1 of the 3GPP TS36.101:

Maximun Power Reduction(MRP) for Power Class 3

Modulation	Channel bandwidth / Transmission bandwidth(N_{RB})						MPR(dB)
	1.4 MHz	3.0 MHz	5 MHz	10 MHz	15 MHz	20 MHz	
QPSK	>5	>4	>8	>12	>16	>18	≤ 1
16 QAM	≤ 5	≤ 4	≤ 8	≤ 12	≤ 16	≤ 18	≤ 1
16 QAM	>5	>4	>8	>12	>16	>18	≤ 2

Configuration of special subframe (lengths of DwPTS/GP/UpPTS)

Special subframe configuration	Normal cyclic prefix in downlink			Extended cyclic prefix in downlink		
	DwPTS	UpPTS		DwPTS	UpPTS	
		Normal cyclic prefix in uplink	Extended cyclic prefix in uplink		Normal cyclic prefix in uplink	Extended cyclic prefix in uplink
0	$6592 T_S$	$2192 T_S$	$2560 T_S$	$7680 T_S$	$2192 T_S$	$2560 T_S$
1	$19760 T_S$			$20480 T_S$		
2	$21952 T_S$			$23040 T_S$		
3	$24144 T_S$			$25600 T_S$		
4	$26336 T_S$			$7680 T_S$		
5	$6592 T_S$	$4384 T_S$	$5120 T_S$	$20480 T_S$	$4384 T_S$	$5120 T_S$
6	$19760 T_S$			$23040 T_S$		
7	$21952 T_S$			$12800 T_S$		

8	$24144 T_S$			-	-	-
9	$13168 T_S$			-	-	-

Uplink-downlink configurations

Uplink-downlink configuration	Downlink-to-Uplink Switch-point periodicity	Subframe number										
		0	1	2	3	4	5	6	7	8	9	
0	5 ms	D	S	U	U	U	D	S	U	U	U	
1	5 ms	D	S	U	U	D	D	S	U	U	D	
2	5 ms	D	S	U	D	D	D	S	U	D	D	
3	10 ms	D	S	U	U	U	D	D	D	D	D	
4	10 ms	D	S	U	U	D	D	D	D	D	D	
5	10 ms	D	S	U	D	D	D	D	D	D	D	
6	5 ms	D	S	U	U	U	D	S	U	U	D	

Calculated Duty Cycle = Extended cyclic prefix in uplink x (Ts) x # of S + # of U

Example for Calculated Duty Cycle for Uplink-Downlink Configuration 0:

Calculated Duty Cycle = $5120 \times [1/(15000 \times 2048)] \times 2 + 6 \text{ ms} = 63.33\%$

Where $T_s = 1/(15000 \times 2048)$ seconds

LTE Test Configuration

SAR for LTE band exposure configurations is measured according to the procedures of KDB 941225 D05 SAR for LTE Devices v02r05. The CMW500 WideBand Radio Communication Tester was used for LTE output power measurements and SAR testing. Closed loop power control was used so the UE transmits with maximum output power during SAR testing. SAR test were performed with the same number of RB and RB offsets transmitting on all TTI frames (Maximum TTI)

1) Spectrum Plots for RB configurations

A properly configured base station simulator was used for LTE output power measurements and SAR testing. Therefore, spectrum plots for RB configurations were not required to be included in this report.

2) MPR

When MPR is implemented permanently within the UE, regardless of network requirements, only those RB configurations allowed by 3GPP for the channel bandwidth

and modulation combinations may be tested with MPR active. Configurations with RB allocations less than the RB thresholds required by 3GPP must be tested without MPR. The allowed Maximum Power Reduction (MPR) for the maximum output power due to higher order modulation and transmit bandwidth configuration (resource blocks) is specified in Table 6.2.3-1 of the 3GPP TS36.101:

Maximun Power Reduction(MRP) for Power Class 3

Modulation	Channel bandwidth / Transmission bandwidth(N_{RB})						MPR(dB)
	1.4 MHz	3.0 MHz	5 MHz	10 MHz	15 MHz	20 MHz	
QPSK	>5	>4	>8	>12	>16	>18	≤1
16 QAM	≤5	≤4	≤8	≤12	≤16	≤18	≤1
64 QAM	>5	>4	>8	>12	>16	>18	≤2

Configuration of special subframe (lengths of DwPTS/GP/UpPTS)

Special subframe configuration	Normal cyclic prefix in downlink			Extended cyclic prefix in downlink		
	DwPTS	UpPTS		DwPTS	UpPTS	
		Normal cyclic prefix in uplink	Extended cyclic prefix in uplink		Normal cyclic prefix in uplink	Extended cyclic prefix in uplink
0	6592 T_S	2192 T_S	2560 T_S	7680 T_S	2192 T_S	2560 T_S
1	19760 T_S			20480 T_S		
2	21952 T_S			23040 T_S		
3	24144 T_S			25600 T_S		
4	26336 T_S	4384 T_S	5120 T_S	7680 T_S	4384 T_S	5120 T_S
5	6592 T_S			20480 T_S		
6	19760 T_S			23040 T_S		
7	21952 T_S			12800		

			T_s		
8	$24144 T_s$		-	-	-
9	$13168 T_s$		-	-	-

Uplink-downlink configurations

Uplink-downlink configuration	Downlink-to-Uplink Switch-point periodicity	Subframe number									
		0	1	2	3	4	5	6	7	8	9
0	5 ms	D	S	U	U	U	D	S	U	U	U
1	5 ms	D	S	U	U	D	D	S	U	U	D
2	5 ms	D	S	U	D	D	D	S	U	D	D
3	10 ms	D	S	U	U	U	D	D	D	D	D
4	10 ms	D	S	U	U	D	D	D	D	D	D
5	10 ms	D	S	U	D	D	D	D	D	D	D
6	5 ms	D	S	U	U	U	D	S	U	U	D

Calculated Duty Cycle = Extended cyclic prefix in uplink x (Ts) x # of S + # of U

Example for Calculated Duty Cycle for Uplink-Downlink Configuration 0:

Calculated Duty Cycle = $5120 \times [1/(15000 \times 2048)] \times 2 + 6 \text{ ms} = 63.33\%$

Where Ts = $1/(15000 \times 2048)$ seconds

3) A-MPR

A-MPR(Additional MPR) has been disabled for all SAR tests by using Network Signalling Value of "NS_01" on the base station simulator.

4) LTE procedures for SAR testing

A) Largest channel bandwidth standalone SAR test requirements

i) QPSK with 1 RB allocation

Start with the largest channel bandwidth and measure SAR for QPSK with 1 RB allocation, using the RB offset and required test channel combination with the highest maximum output power for RB offsets at the upper edge, middle and lower edge of each required test channel. When the reported SAR is $\leq 0.8\text{W/kg}$, testing of the remaining RB offset configurations and required test channels is not required for 1RB allocation; otherwise, SAR is required for the remaining required test channels and only for the RB offset configuration with the highest output power for that channel. When the reported SAR of a required test channel is $> 1.45 \text{ W/kg}$, SAR is required for all three RB offset configurations for that required test channel.

ii) QPSK with 50% RB allocation

The procedures required for 1 RB allocation in i) are applied to measure the SAR for QPSK with 50% RB allocation.

iii) QPSK with 100% RB allocation

For QPSK with 100% RB allocation, SAR is not required when the highest maximum output power for 100 % RB allocation is less than the highest maximum output power in 50% and 1 RB allocations and the highest reported SAR for 1 RB and 50% RB allocation in i) and ii) are ≤ 0.8 W/kg. Otherwise, SAR is measured for the highest output power channel and if the reported SAR is > 1.45 W/kg, the remaining required test channels must also be tested.

iv) Higher order modulations


For each modulation besides QPSK; e.g., 16-QAM, 64-QAM, apply the QPSK procedures in above sections to determine the QAM configurations that may need SAR measurement. For each configuration identified as required for testing, SAR is required only when the highest maximum output power for the configuration in the higher order modulation is $> \frac{1}{2}$ dB higher than the same configuration in QPSK or when the reported SAR for the QPSK configuration is > 1.45 W/kg.

B) Other channel bandwidth standalone SAR test requirements

For the other channel bandwidths used by the device in a frequency band, apply all the procedures required for the largest channel bandwidth in section A) to determine the channels and RB configurations that need SAR testing and only measure SAR when the highest maximum output power of a configuration requiring testing in the smaller channel bandwidth is $> \frac{1}{2}$ dB higher than the equivalent channel configurations in the largest channel bandwidth configuration or the reported SAR of a configuration for the largest channel bandwidth is > 1.45 W/kg.

10. TEST RESULTS

10.1. EUT Antenna Locations



The WWLAN part of this product has two antennas. It only supports single transmission, but does not support MIMO.

ANT0	GSM850/1900;WCDMA Band 2/4/5;LTE Band 2/4/5/7/13/26/28/38/41/66
ANT1	GSM850/1900;WCDMA Band 2/4/5;LTE Band 2/4/5/7/13/26/28/38/41/66
ANT2	TX/RX WIFI 2.4G/5G Bluetooth

11. MEASUREMENT RESULTS

Result: Passed

Date of testing : 2022.11.11~2022.11.28;
Ambient temperature : 20°C~22°C
Relative humidity : 50~68%

11.1. Conducted Power

For the measurements a Rohde & Schwarz Radio Communication Tester CMU 200 was used. SAR drift measured at the same position in liquid before and after each SAR test.

Note: CMU200 measures GSM peak and average output power for active timeslots. For SAR the time based average power is relevant. The difference in between depends on the duty cycle of the TDMA signal:

No. of Timeslots	1	2	3	4
Duty Cycle	1:8.3	1:4.1	1:2.77	1:2.08
Time based avg. power compared to slotted avg. power	-9.00dB	-6.00 dB	-4.26dB	-3.00dB

The signalling modes differ as follows:

Mode	Coding scheme	Modulation
GPRS	CS1 to CS4	GMSK
EDGE	MCS1 to MCS4	GMSK
EDGE	MCS5 to MCS9	8PSK

Apart from modulation change (GMSK/8PSK) coding schemes differ in code rate without influence on the RF signal. Therefore one coding scheme per mode was selected for conducted power measurements.

11.2. SAR measurement Results

General Notes:

- 1) Per KDB447498 D01v06, all measurement SAR results are scaled to the maximum tune-up tolerance limit to demonstrate compliant.
- 2) Per KDB447498 D01v06, testing of other required channels within the operating mode of a frequency band is not required when the reported 1-g or 10-g SAR for the mid-band or highest output power channel is ≤ 0.8 W/kg or 2.0W/kg, for 1-g or 10-g respectively, when the transmission band is ≤ 100 MHz. When the maximum output power variation across the required test channels is $>1/2$ dB, instead of the middle channel, the highest output power channel must be used.
- 3) Per KDB865664 D01v01r04, for each frequency band, repeated SAR measurement is required only when the measure SAR is ≥ 0.8 W/kg; if the deviation among the repeated measurement is $\leq 20\%$, and the measured SAR < 1.45 W/kg, only one repeated measurement is required.
- 4) Per KDB 941225 D06 Hotspot Mode SAR v02:r01, the DUT dimension is bigger than 9cm*5cm, so 10mm is chosen as the test separation distance for Hotspot mode. When the antenna-to-edge distance is greater than 2.5cm, such position does not need to be tested.
- 5) Per KDB648474 D04v01r03, SAR is evaluated without a headset connected to the device. When the standalone reported body-worn SAR is ≤ 1.2 W/kg, no additional SAR evaluations using a headset are required.
- 6) Per KDB865664 D02v01r02, SAR plot is only required for the highest measured SAR in each exposure configuration, wireless mode and frequency band combination; plots are also required when the measured SAR is > 1.5 W/kg, or > 7.0 W/kg for occupational exposure. The published RF exposure KDB procedures may require additional plots; for example, to support SAR to peak location separation ratio test exclusion and/or volume scan plots-processing (refer to appendix B for details).

GSM Notes:

Per KDB941225 D01v03r01, SAR test reduction for GPRS and EDGE modes is determined

by the source-based time-averaged output power specified for production units, including tune-up tolerance. The data mode with highest specified time-averaged output power should be tested for SAR compliance in the applicable exposure conditions. For modes with the same specified maximum output power and tolerance, the higher number time-slot configuration should be tested.

UMTS Notes:

Per KDB 941225 D01v03r01, when maximum output power and tune-up tolerance specified for production units in a secondary mode is $\leq 1/4$ dB higher than the primary mode or when the highest reported SAR of the primary mode is scaled by the ratio of specified maximum output power and tune-up tolerance of secondary to primary mode and the adjusted SAR is ≤ 1.2 W/kg, SAR measurement is not required for the secondary mode..

Per KDB941225 D01v03, SAR is required for Rel. 8 DC-HSDPA when SAR is required for Rel. 5 HSDPA; otherwise, the 3G SAR test reduction procedure is applied to DC-HSDPA with 12.2 kbps RMC as the primary mode. Power is measured for DC-HSDPA according to the H-Set 12, FRC configuration in Table C.8.1.12 of 3GPP TS 34.121-1 to determine SAR test reduction. A primary and a secondary serving HS-DSCH Cell are required to perform the power measurement and for the results to be acceptable.

LTE Notes:

- 7) 1. Per KDB 941225 D05v02r05, start with the largest channel bandwidth and measure SAR for QPSK with 1 RB allocation, using the RB offset and required test channel combination with the highest maximum output power for RB offsets at the upper edge, middle and lower edge of each required test channel.
- 8) 2. Per KDB 941225 D05v02r05, 50% RB allocation for QPSK SAR testing follows 1RB QPSK allocation procedure.
- 9) 3. Per KDB 941225 D05v02r05, For QPSK with 100% RB allocation, SAR is not required when the highest maximum output power for 100 % RB allocation is less than the highest maximum output power in 50% and 1 RB allocations and the highest reported SAR for 1 RB and 50% RB allocation are ≤ 0.8 W/kg. Otherwise, SAR is measured for the highest output power channel; and if the reported SAR is > 1.45 W/kg, the remaining required test channels must also be tested.
- 11) 4. Per KDB 941225 D05v02r05, 16QAM output power for each RB allocation configuration is $>$ not Vs dB higher than the same configuration in QPSK and the reported SAR for the

QPSK configuration is ≤ 1.45 W/kg; Per KDB 941225 D05v02r05, 16QAM SAR testing is not required.

- 12)5. Per KDB 941225 D05v02r05, Smaller bandwidth output power for each RB allocation configuration is $>$ not % dB higher than the same configuration in the largest supported bandwidth, and the reported SAR for the largest supported bandwidth is ≤ 1.45 W/kg; Per KDB 941225 D05v02r05, smaller bandwidth SAR testing is not required.
- 13)6. For LTE B41/B5/B12/B17 1 B26 1 B381 B71 the maximum bandwidth does not support three non-overlapping channels, per KDB 941225 D05v02r05, when a device supports overlapping channel assignment in a channel bandwidth configuration, the middle channel of the group of overlapping channels should be selected for testing.
- 14)7. LTE band 2/4/17/38 SAR test was covered by Band 25/66/12/41; according to TCB workshop, SAR test for overlapping LTE bands can be reduced if
- 15)a. The maximum output power, including tolerance, for the smaller band is \leq the larger band to qualify for the SAR test exclusion. The channel bandwidth and other operating parameters for the smaller band are fully supported by the larger band.

WLAN Notes

Per KDB 248227 D01v02r02, for all positions/configurations tested using the initial test position and subsequent test positions, when the reported SAR is > 0.8 W/kg, SAR is measured for these test positions/configurations on the subsequent next highest measured output power channel(s) until the reported SAR is ≤ 1.2 W/kg or all required channels are tested.

Per KDB 248227 D01v02r02, for 802.11g/n SAR testing is required. When the highest reported SAR for DSSS is adjusted by the ratio of OFDM to DSSS specified maximum output power and the adjusted SAR is > 1.2 W/kg.

Per KDB 248227 D01v02r02, for OFDM transmission configurations in the 2.4 GHz bands, When the same maximum power is specified for multiple transmission modes in a frequency band, the largest channel bandwidth, lowest order modulation, lowest data rate and lowest order 802.11g/n mode is used for SAR measurement, on the highest measured output power channel for each frequency band.

11.3. GSM850 SAR results

Configuration	Power Level	Mode	Position	Dist.(mm)	Ch.	Freq.(MHz)	Meas. Power (dBm)	Max. tune-up power (dBm)	Scaling Factor	1g Meas SAR (W/kg)	1g Scaled SAR (W/kg)
Ant1	DSI1	GSM (CS)	Left Cheek	0	190	836.6	28.71	29.5	1.199	0.429	0.51
	DSI1	GSM (CS)	Left Tilt	0	190	836.6	28.71	29.5	1.199	0.401	0.48
	DSI1	GSM (CS)	Right Cheek	0	190	836.6	28.71	29.5	1.199	0.612	0.73
	DSI1	GSM (CS)	Right Tilt	0	190	836.6	28.71	29.5	1.199	0.479	0.57
Ant0	DSI1	GSM (CS)	Left Cheek	0	190	836.6	31.54	32.5	1.247	0.124	0.15
	DSI1	GSM (CS)	Left Tilt	0	190	836.6	31.54	32.5	1.247	0.091	0.11
	DSI1	GSM (CS)	Right Cheek	0	190	836.6	31.54	32.5	1.247	0.118	0.15
	DSI1	GSM (CS)	Right Tilt	0	190	836.6	31.54	32.5	1.247	0.063	0.08
Ant1	original Power	GPRS/EDGE (GMSK, 2 Tx slots)	Front	10	190	836.6	30.55	31.5	1.245	0.275	0.34
	original Power	GPRS/EDGE (GMSK, 2 Tx slots)	Back	10	190	836.6	30.55	31.5	1.245	0.365	0.45
	original Power	GPRS/EDGE (GMSK, 2 Tx slots)	Left	10	190	836.6	30.55	31.5	1.245	0.116	0.14
	original Power	GPRS/EDGE (GMSK, 2 Tx slots)	Right	10	190	836.6	30.55	31.5	1.245	0.159	0.20
	original Power	GPRS/EDGE (GMSK, 2 Tx slots)	Top	10	190	836.6	30.55	31.5	1.245	0.343	0.43
	original Power	GPRS/EDGE (GMSK, 2 Tx slots)	Bottom	10	190	836.6	30.55	31.5	1.245	0.012	0.01
Ant0	original Power	GPRS/EDGE (GMSK, 2 Tx slots)	Front	10	190	836.6	30.59	31.5	1.233	0.170	0.21
	original Power	GPRS/EDGE (GMSK, 2 Tx slots)	Back	10	190	836.6	30.59	31.5	1.233	0.335	0.41
	original Power	GPRS/EDGE (GMSK, 2 Tx slots)	Left	10	190	836.6	30.59	31.5	1.233	0.184	0.23
	original Power	GPRS/EDGE (GMSK, 2 Tx slots)	Right	10	190	836.6	30.59	31.5	1.233	0.115	0.14
	original Power	GPRS/EDGE (GMSK, 2 Tx slots)	Top	10	190	836.6	30.59	31.5	1.233	0.010	0.01
	original Power	GPRS/EDGE (GMSK, 2 Tx slots)	Bottom	10	190	836.6	30.59	31.5	1.233	0.252	0.31
Ant1	original Power	GPRS/EDGE (GMSK, 2 Tx slots)	Front	15	190	836.6	30.55	31.5	1.245	0.152	0.19
	original Power	GPRS/EDGE (GMSK, 2 Tx slots)	Back	15	190	836.6	30.55	31.5	1.245	0.244	0.30
Ant0	original Power	GPRS/EDGE (GMSK, 2 Tx slots)	Front	15	190	836.6	30.59	31.5	1.233	0.148	0.18
	original Power	GPRS/EDGE (GMSK, 2 Tx slots)	Back	15	190	836.6	30.59	31.5	1.233	0.151	0.19

11.4. PCS1900 SAR results

Configuration	Power Level	Mode	Position	Dist.(mm)	Ch.	Freq.(MHz)	Meas. Power (dBm)	Max. tune-up power (dBm)	Scaling Factor	1g Meas SAR (W/kg)	1g Scaled SAR (W/kg)
Ant1	DSI1	GSM (CS)	Left Cheek	0	661	1880	25.81	26.5	1.172	0.351	0.41
	DSI1	GSM (CS)	Left Tilt	0	661	1880	25.81	26.5	1.172	0.395	0.46
	DSI1	GSM (CS)	Right Cheek	0	661	1880	25.81	26.5	1.172	0.533	0.62
	DSI1	GSM (CS)	Right Tilt	0	661	1880	25.81	26.5	1.172	0.629	0.74
Ant0	original Power	GSM (CS)	Left Cheek	0	661	1880	29.08	30.5	1.387	0.070	0.10
	original Power	GSM (CS)	Left Tilt	0	661	1880	29.08	30.5	1.387	0.051	0.07
	original Power	GSM (CS)	Right Cheek	0	661	1880	29.08	30.5	1.387	0.076	0.11
	original Power	GSM (CS)	Right Tilt	0	661	1880	29.08	30.5	1.387	0.060	0.08
Ant1	DSI5	GPRS/EDGE (GMSK, 2 Tx slots)	Front	10	661	1880	25.05	25.5	1.109	0.213	0.24
	DSI5	GPRS/EDGE (GMSK, 2 Tx slots)	Back	10	661	1880	25.05	25.5	1.109	0.258	0.29
	DSI5	GPRS/EDGE (GMSK, 2 Tx slots)	Left	10	661	1880	25.05	25.5	1.109	0.055	0.06
	DSI5	GPRS/EDGE (GMSK, 2 Tx slots)	Right	10	661	1880	25.05	25.5	1.109	0.053	0.06
	DSI5	GPRS/EDGE (GMSK, 2 Tx slots)	Top	10	661	1880	25.05	25.5	1.109	0.390	0.43
	DSI5	GPRS/EDGE (GMSK, 2 Tx slots)	Bottom	10	661	1880	25.05	25.5	1.109	0.007	0.01
Ant0	DSI5	GPRS/EDGE (GMSK, 2 Tx slots)	Front	10	661	1880	24.96	25.5	1.132	0.162	0.18
	DSI5	GPRS/EDGE (GMSK, 2 Tx slots)	Back	10	661	1880	24.96	25.5	1.132	0.367	0.42
	DSI5	GPRS/EDGE (GMSK, 2 Tx slots)	Left	10	661	1880	24.96	25.5	1.132	0.047	0.05
	DSI5	GPRS/EDGE (GMSK, 2 Tx slots)	Right	10	661	1880	24.96	25.5	1.132	0.115	0.13
	DSI5	GPRS/EDGE (GMSK, 2 Tx slots)	Top	10	661	1880	24.96	25.5	1.132	0.006	0.01
	DSI5	GPRS/EDGE (GMSK, 2 Tx slots)	Bottom	10	661	1880	24.96	25.5	1.132	0.467	0.53
Ant1	DSI4	GPRS/EDGE (GMSK, 2 Tx slots)	Front	15	661	1880	26.01	26.5	1.119	0.143	0.16
	DSI4	GPRS/EDGE (GMSK, 2 Tx slots)	Back	15	661	1880	26.01	26.5	1.119	0.166	0.19
Ant0	DSI4	GPRS/EDGE (GMSK, 2 Tx slots)	Front	15	661	1880	24.93	25.5	1.140	0.091	0.10
	DSI4	GPRS/EDGE (GMSK, 2 Tx slots)	Back	15	661	1880	24.93	25.5	1.140	0.239	0.27

11.5. WCDMA Band II SAR results

Configuration	Power Level	Mode	Position	Dist.(mm)	Ch.	Freq.(MHz)	Meas. Power (dBm)	Max. tune-up power (dBm)	Scaling Factor	1g Meas SAR (W/kg)	1g Scaled SAR (W/kg)
Head											
Ant1	DSI1	RMC	Left Cheek	0	9400	1880	16.58	18.0	1.387	0.325	0.45
	DSI1	RMC	Left Tilt	0	9400	1880	16.58	18.0	1.387	0.380	0.53
	DSI1	RMC	Right Cheek	0	9400	1880	16.58	18.0	1.387	0.461	0.64
	DSI1	RMC	Right Tilt	0	9400	1880	16.58	18.0	1.387	0.674	0.93
	DSI1	RMC	Right Tilt	0	9262	1852.4	16.53	18.0	1.403	0.587	0.82
	DSI1	RMC	Right Tilt	0	9538	1907.6	16.68	18.0	1.355	0.522	0.71
Ant0	original Power	RMC	Left Cheek	0	9400	1880	23.00	24.0	1.259	0.131	0.16
	original Power	RMC	Left Tilt	0	9400	1880	23.00	24.0	1.259	0.097	0.12
	original Power	RMC	Right Cheek	0	9400	1880	23.00	24.0	1.259	0.148	0.19
	original Power	RMC	Right Tilt	0	9400	1880	23.00	24.0	1.259	0.104	0.13
Ant1	DSI5	RMC	Front	10	9400	1880	18.74	20.0	1.337	0.196	0.26
	DSI5	RMC	Back	10	9400	1880	18.74	20.0	1.337	0.240	0.32
	DSI5	RMC	Left	10	9400	1880	18.74	20.0	1.337	0.063	0.08
	DSI5	RMC	Right	10	9400	1880	18.74	20.0	1.337	0.046	0.06
	DSI5	RMC	Top	10	9400	1880	18.74	20.0	1.337	0.374	0.50
	DSI5	RMC	Bottom	10	9400	1880	18.74	20.0	1.337	0.008	0.01
Ant0	DSI5	RMC	Front	10	9400	1880	18.77	20.0	1.327	0.149	0.20
	DSI5	RMC	Back	10	9400	1880	18.77	20.0	1.327	0.389	0.52
	DSI5	RMC	Left	10	9400	1880	18.77	20.0	1.327	0.043	0.06
	DSI5	RMC	Right	10	9400	1880	18.77	20.0	1.327	0.114	0.15
	DSI5	RMC	Top	10	9400	1880	18.77	20.0	1.327	0.009	0.01
	DSI5	RMC	Bottom	10	9400	1880	18.77	20.0	1.327	0.485	0.64
Ant1	DSI4	RMC	Front	15	9400	1880	20.14	21.5	1.368	0.160	0.22
	DSI4	RMC	Back	15	9400	1880	20.14	21.5	1.368	0.192	0.26
Ant0	DSI4	RMC	Front	15	9400	1880	19.60	21.0	1.380	0.106	0.15
	DSI4	RMC	Back	15	9400	1880	19.60	21.0	1.380	0.265	0.37

11.6. WCDMA Band IV SAR results

Configuration	Power Level	Mode	Position	Dist.(mm)	Ch.	Freq.(MHz)	Meas. Power (dBm)	Max. tune-up power (dBm)	Scaling Factor	1g Meas SAR (W/kg)	1g Scaled SAR (W/kg)
Head											
Ant1	DSI1	RMC	Left Cheek	0	1412	1732.4	17.67	18.0	1.079	0.307	0.33
	DSI1	RMC	Left Tilt	0	1412	1732.4	17.67	18.0	1.079	0.377	0.41
	DSI1	RMC	Right Cheek	0	1412	1732.4	17.67	18.0	1.079	0.451	0.49
	DSI1	RMC	Right Tilt	0	1412	1732.4	17.67	18.0	1.079	0.519	0.56
Ant0	original Power	RMC	Left Cheek	0	1412	1732.4	22.94	24.0	1.276	0.114	0.15
	original Power	RMC	Left Tilt	0	1412	1732.4	22.94	24.0	1.276	0.111	0.14
	original Power	RMC	Right Cheek	0	1412	1732.4	22.94	24.0	1.276	0.102	0.13
	original Power	RMC	Right Tilt	0	1412	1732.4	22.94	24.0	1.276	0.095	0.12
Ant1	DSI5	RMC	Front	10	1412	1732.4	18.77	20.0	1.327	0.192	0.25
	DSI5	RMC	Back	10	1412	1732.4	18.77	20.0	1.327	0.225	0.30
	DSI5	RMC	Left	10	1412	1732.4	18.77	20.0	1.327	0.055	0.07
	DSI5	RMC	Right	10	1412	1732.4	18.77	20.0	1.327	0.011	0.01
	DSI5	RMC	Top	10	1412	1732.4	18.77	20.0	1.327	0.314	0.42
	DSI5	RMC	Bottom	10	1412	1732.4	18.77	20.0	1.327	0.007	0.01
Ant0	DSI5	RMC	Front	10	1412	1732.4	17.88	19.0	1.294	0.117	0.15
	DSI5	RMC	Back	10	1412	1732.4	17.88	19.0	1.294	0.393	0.51
	DSI5	RMC	Left	10	1412	1732.4	17.88	19.0	1.294	0.011	0.01
	DSI5	RMC	Right	10	1412	1732.4	17.88	19.0	1.294	0.067	0.09
	DSI5	RMC	Top	10	1412	1732.4	17.88	19.0	1.294	0.008	0.01
	DSI5	RMC	Bottom	10	1412	1732.4	17.88	19.0	1.294	0.398	0.52
Ant1	DSI4	RMC	Front	15	1412	1732.4	20.21	21.5	1.346	0.144	0.19
	DSI4	RMC	Back	15	1412	1732.4	20.21	21.5	1.346	0.183	0.25
Ant0	DSI4	RMC	Front	15	1412	1732.4	18.78	20.0	1.324	0.097	0.13
	DSI4	RMC	Back	15	1412	1732.4	18.78	20.0	1.324	0.261	0.35

11.7. WCDMA Band V SAR results

Configuration	Power Level	Mode	Position	Dist.(mm)	Ch.	Freq.(MHz)	Meas. Power (dBm)	Max. tune-up power (dBm)	Scaling Factor	1g Meas SAR (W/kg)	1g Scaled SAR (W/kg)
Head											
Ant1	DSI1	RMC	Left Cheek	0	4175	835	20.66	21.0	1.081	0.405	0.44
	DSI1	RMC	Left Tilt	0	4175	835	20.66	21.0	1.081	0.392	0.42
	DSI1	RMC	Right Cheek	0	4175	835	20.66	21.0	1.081	0.578	0.63
	DSI1	RMC	Right Tilt	0	4175	835	20.66	21.0	1.081	0.470	0.51
Ant0	original Power	RMC	Left Cheek	0	4175	835	23.27	24.0	1.183	0.143	0.17
	original Power	RMC	Left Tilt	0	4175	835	23.27	24.0	1.183	0.100	0.12
	original Power	RMC	Right Cheek	0	4175	835	23.27	24.0	1.183	0.127	0.15
	original Power	RMC	Right Tilt	0	4175	835	23.27	24.0	1.183	0.071	0.08
Ant1	original Power	RMC	Front	10	4175	835	23.33	24.0	1.167	0.244	0.28
	original Power	RMC	Back	10	4175	835	23.33	24.0	1.167	0.365	0.43
	original Power	RMC	Left	10	4175	835	23.33	24.0	1.167	0.104	0.12
	original Power	RMC	Right	10	4175	835	23.33	24.0	1.167	0.136	0.16
	original Power	RMC	Top	10	4175	835	23.33	24.0	1.167	0.302	0.35
	original Power	RMC	Bottom	10	4175	835	23.33	24.0	1.167	0.007	0.01
Ant0	original Power	RMC	Front	10	4175	835	23.27	24.0	1.183	0.136	0.16
	original Power	RMC	Back	10	4175	835	23.27	24.0	1.183	0.267	0.32
	original Power	RMC	Left	10	4175	835	23.27	24.0	1.183	0.169	0.20
	original Power	RMC	Right	10	4175	835	23.27	24.0	1.183	0.100	0.12
	original Power	RMC	Top	10	4175	835	23.27	24.0	1.183	0.009	0.01
	original Power	RMC	Bottom	10	4175	835	23.27	24.0	1.183	0.229	0.27
Ant1	original Power	RMC	Front	15	4175	835	23.33	24.0	1.167	0.144	0.17
	original Power	RMC	Back	15	4175	835	23.33	24.0	1.167	0.221	0.26
Ant0	original Power	RMC	Front	15	4175	835	23.27	24.0	1.183	0.086	0.10
	original Power	RMC	Back	15	4175	835	23.27	24.0	1.183	0.119	0.14

11.8. LTE Band 2 SAR results

Configuration	Power Level	BW	Modulation	RB Num	RB Start	Position	Dist. mm	Ch.	Freq. (MHz)	Meas. Power (dBm)	Max. tune-up power (dBm)	Scaling Factor	1g Meas SAR (W/kg)	1g Scaled SAR (W/kg)
Head														
Ant1	DSI1	20MHz	QPSK	1	50	Left Cheek	0	18900	1880	17.17	18.0	1.211	0.369	0.45
	DSI1	20MHz	QPSK	1	50	Left Tilt	0	18900	1880	17.17	18.0	1.211	0.423	0.51
	DSI1	20MHz	QPSK	1	50	Right Cheek	0	18900	1880	17.17	18.0	1.211	0.520	0.63
	DSI1	20MHz	QPSK	1	50	Right Tilt	0	18900	1880	17.17	18.0	1.211	0.627	0.76
Ant0	original Power	20MHz	QPSK	1	50	Left Cheek	0	18900	1880	23.43	24.0	1.140	0.148	0.17
	original Power	20MHz	QPSK	1	50	Left Tilt	0	18900	1880	23.43	24.0	1.140	0.109	0.12
	original Power	20MHz	QPSK	1	50	Right Cheek	0	18900	1880	23.43	24.0	1.140	0.174	0.20
	original Power	20MHz	QPSK	1	50	Right Tilt	0	18900	1880	23.43	24.0	1.140	0.114	0.13
Ant1	DSI5	20MHz	QPSK	1	50	Front	10	18900	1880	19.17	20.0	1.211	0.223	0.27
	DSI5	20MHz	QPSK	1	50	Back	10	18900	1880	19.17	20.0	1.211	0.261	0.32
	DSI5	20MHz	QPSK	1	50	Left	10	18900	1880	19.17	20.0	1.211	0.077	0.09
	DSI5	20MHz	QPSK	1	50	Right	10	18900	1880	19.17	20.0	1.211	0.054	0.07
Ant0	DSI5	20MHz	QPSK	1	50	Top	10	18900	1880	19.17	20.0	1.211	0.400	0.48
	DSI5	20MHz	QPSK	1	50	Front	10	18900	1880	19.28	20.0	1.180	0.162	0.19
	DSI5	20MHz	QPSK	1	50	Back	10	18900	1880	19.28	20.0	1.180	0.423	0.50
	DSI5	20MHz	QPSK	1	50	Left	10	18900	1880	19.28	20.0	1.180	0.048	0.06
	DSI5	20MHz	QPSK	1	50	Right	10	18900	1880	19.28	20.0	1.180	0.129	0.15
	DSI5	20MHz	QPSK	1	50	Top	10	18900	1880	19.28	20.0	1.180	0.007	0.01
Ant1	DSI4	20MHz	QPSK	1	50	Bottom	10	18900	1880	19.28	20.0	1.180	0.532	0.63
	DSI4	20MHz	QPSK	1	50	Front	15	18900	1880	20.58	21.5	1.236	0.177	0.22
Ant0	DSI4	20MHz	QPSK	1	50	Back	15	18900	1880	20.58	21.5	1.236	0.189	0.23
	DSI4	20MHz	QPSK	1	50	Front	15	18900	1880	20.23	21.0	1.194	0.114	0.14
Ant0	DSI4	20MHz	QPSK	1	50	Back	15	18900	1880	20.23	21.0	1.194	0.300	0.36

11.9. LTE Band 4 SAR results

Configuration	Power Level	BW	Modulation	RB Num	RB Start	Position	Dist. mm	Ch.	Freq. (MHz)	Meas. Power (dBm)	Max. tune-up power (dBm)	Scaling Factor	1g Meas SAR (W/kg)	1g Scaled SAR (W/kg)
Head														
Ant1	DSI1	20MHz	QPSK	1	50	Left Cheek	0	20175	1732.5	18.09	19.0	1.233	0.399	0.49
	DSI1	20MHz	QPSK	1	50	Left Tilt	0	20175	1732.5	18.09	19.0	1.233	0.485	0.60
	DSI1	20MHz	QPSK	1	50	Right Cheek	0	20175	1732.5	18.09	19.0	1.233	0.574	0.71
	DSI1	20MHz	QPSK	1	50	Right Tilt	0	20175	1732.5	18.09	19.0	1.233	0.675	0.83
	DSI1	20MHz	QPSK	1	50	Right Tilt	0	20050	1754.9	18.09	19.0	1.233	0.652	0.80
	DSI1	20MHz	QPSK	1	50	Right Tilt	0	20300	1745	18.09	19.0	1.233	0.790	0.97
Ant0	original Power	20MHz	QPSK	1	50	Left Cheek	0	20175	1732.5	23.25	24.0	1.189	0.132	0.16
	original Power	20MHz	QPSK	1	50	Left Tilt	0	20175	1732.5	23.25	24.0	1.189	0.113	0.13
	original Power	20MHz	QPSK	1	50	Right Cheek	0	20175	1732.5	23.25	24.0	1.189	0.127	0.15
	original Power	20MHz	QPSK	1	50	Right Tilt	0	20175	1732.5	23.25	24.0	1.189	0.125	0.15
	DSI5	20MHz	QPSK	1	50	Front	10	20175	1732.5	19.18	20.0	1.208	0.206	0.25
Ant1	DSI5	20MHz	QPSK	1	50	Back	10	20175	1732.5	19.18	20.0	1.208	0.239	0.29
	DSI5	20MHz	QPSK	1	50	Left	10	20175	1732.5	19.18	20.0	1.208	0.061	0.07
	DSI5	20MHz	QPSK	1	50	Right	10	20175	1732.5	19.18	20.0	1.208	0.009	0.01
	DSI5	20MHz	QPSK	1	50	Top	10	20175	1732.5	19.18	20.0	1.208	0.326	0.39
	DSI5	20MHz	QPSK	1	50	Bottom	10	20175	1732.5	18.21	19.0	1.199	0.415	0.50
Ant0	DSI5	20MHz	QPSK	1	50	Front	10	20175	1732.5	18.21	19.0	1.199	0.130	0.16
	DSI5	20MHz	QPSK	1	50	Back	10	20175	1732.5	18.21	19.0	1.199	0.410	0.49
	DSI5	20MHz	QPSK	1	50	Left	10	20175	1732.5	18.21	19.0	1.199	0.009	0.01
	DSI5	20MHz	QPSK	1	50	Right	10	20175	1732.5	18.21	19.0	1.199	0.069	0.08
	DSI5	20MHz	QPSK	1	50	Top	10	20175	1732.5	18.21	19.0	1.199	0.007	0.01
Ant1	DSI4	20MHz	QPSK	1	50	Front	15	20175	1732.5	20.62	21.5	1.225	0.146	0.18
	DSI4	20MHz	QPSK	1	50	Back	15	20175	1732.5	20.62	21.5	1.225	0.196	0.24
Ant0	DSI4	20MHz	QPSK	1	50	Front	15	20175	1732.5	19.35	20.0	1.161	0.099	0.11
	DSI4	20MHz	QPSK	1	50	Back	15	20175	1732.5	19.35	20.0	1.161	0.279	0.32

11.10. LTE Band 5 SAR results

Configuration	Power Level	BW	Modulation	RB Num	RB Start	Position	Dist. mm	Ch.	Freq. (MHz)	Meas. Power (dBm)	Max. tune-up power (dBm)	Scaling Factor	1g Meas SAR (W/kg)	1g Scaled SAR (W/kg)
Head														
Ant1	DSI1	10MHz	QPSK	1	13	Left Cheek	0	20525	836.5	20.13	21.0	1.222	0.414	0.51
	DSI1	10MHz	QPSK	1	13	Left Tilt	0	20525	836.5	20.13	21.0	1.222	0.411	0.50
	DSI1	10MHz	QPSK	1	13	Right Cheek	0	20525	836.5	20.13	21.0	1.222	0.626	0.76
	DSI1	10MHz	QPSK	1	13	Right Tilt	0	20525	836.5	20.13	21.0	1.222	0.493	0.60
Ant0	original Power	10MHz	QPSK	1	13	Left Cheek	0	20525	836.5	23.18	24.0	1.208	0.186	0.22
	original Power	10MHz	QPSK	1	13	Left Tilt	0	20525	836.5	23.18	24.0	1.208	0.102	0.12
	original Power	10MHz	QPSK	1	13	Right Cheek	0	20525	836.5	23.18	24.0	1.208	0.140	0.17
	original Power	10MHz	QPSK	1	13	Right Tilt	0	20525	836.5	23.18	24.0	1.208	0.074	0.09
	original Power	10MHz	QPSK	1	13	Front	10	20525	836.5	23.14	24.0	1.219	0.254	0.31
	original Power	10MHz	QPSK	1	13	Back	10	20525	836.5	23.14	24.0	1.219	0.320	0.39
	original Power	10MHz	QPSK	1	13	Left	10	20525	836.5	23.14	24.0	1.219	0.111	0.14
	original Power	10MHz	QPSK	1	13	Right	10	20525	836.5	23.14	24.0	1.219	0.137	0.17
	original Power	10MHz	QPSK	1	13	Top	10	20525	836.5	23.14	24.0	1.219	0.306	0.37
	original Power	10MHz	QPSK	1	13	Bottom	10	20525	836.5	23.14	24.0	1.219	0.010	0.01
Ant0	original Power	10MHz	QPSK	1	13	Front	10	20525	836.5	23.18	24.0	1.208	0.139	0.17
	original Power	10MHz	QPSK	1	13	Back	10	20525	836.5	23.18	24.0	1.208	0.311	0.38
	original Power	10MHz	QPSK	1	13	Left	10	20525	836.5	23.18	24.0	1.208	0.162	0.20
	original Power	10MHz	QPSK	1	13	Right	10	20525	836.5	23.18	24.0	1.208	0.101	0.12
	original Power	10MHz	QPSK	1	13	Top	10	20525	836.5	23.18	24.0	1.208	0.008	0.01
	original Power	10MHz	QPSK	1	13	Bottom	10	20525	836.5	23.18	24.0	1.208	0.231	0.28
Ant1	original Power	10MHz	QPSK	1	13	Front	15	20525	836.5	23.14	24.0	1.219	0.149	0.18
	original Power	10MHz	QPSK	1	13	Back	15	20525	836.5	23.14	24.0	1.219	0.223	0.27
Ant0	original Power	10MHz	QPSK	1	13	Front	15	20525	836.5	23.18	24.0	1.208	0.128	0.15
	original Power	10MHz	QPSK	1	13	Back	15	20525	836.5	23.18	24.0	1.208	0.138	0.17

11.11. LTE Band 7 SAR results

Configuration	Power Level	BW	Modulation	RB Num	RB Start	Position	Dist. mm	Ch.	Freq. (MHz)	Meas. Power (dBm)	Max. tune-up power (dBm)	Scaling Factor	1g Meas SAR (W/kg)	1g Scaled SAR (W/kg)	
Head															
Ant1	DSI1	20MHz	QPSK	1	50	Left Cheek	0	21100	2535	16.28	17.0	1.180	0.207	0.24	
	DSI1	20MHz	QPSK	1	50	Left Tilt	0	21100	2535	16.28	17.0	1.180	0.274	0.32	
	DSI1	20MHz	QPSK	1	50	Right Cheek	0	21100	2535	16.28	17.0	1.180	0.542	0.64	
	DSI1	20MHz	QPSK	1	50	Right Tilt	0	21100	2535	16.28	17.0	1.180	0.731	0.86	
	DSI1	20MHz	QPSK	1	50	Right Tilt	0	20850	2510	16.21	17.0	1.199	0.771	0.92	
	DSI1	20MHz	QPSK	1	50	Right Tilt	0	21350	2560	16.22	17.0	1.197	0.599	0.72	
Ant0	original Power	20MHz	QPSK	1	50	Left Cheek	0	21100	2535	23.47	24.0	1.130	0.170	0.19	
	original Power	20MHz	QPSK	1	50	Left Tilt	0	21100	2535	23.47	24.0	1.130	0.121	0.14	
	original Power	20MHz	QPSK	1	50	Right Cheek	0	21100	2535	23.47	24.0	1.130	0.174	0.20	
	original Power	20MHz	QPSK	1	50	Right Tilt	0	21100	2535	23.47	24.0	1.130	0.165	0.19	
	DSI5	20MHz	QPSK	1	50	Front	10	21100	2535	15.07	16.0	1.239	0.107	0.13	
	DSI5	20MHz	QPSK	1	50	Back	10	21100	2535	15.07	16.0	1.239	0.438	0.54	
	Ant1	DSI5	20MHz	QPSK	1	50	Left	10	21100	2535	15.07	16.0	1.239	0.093	0.12
		DSI5	20MHz	QPSK	1	50	Right	10	21100	2535	15.07	16.0	1.239	0.009	0.01
		DSI5	20MHz	QPSK	1	50	Top	10	21100	2535	15.07	16.0	1.239	0.374	0.46
		DSI5	20MHz	QPSK	1	50	Bottom	10	21100	2535	15.07	16.0	1.239	0.006	0.01
Ant0	DSI5	20MHz	QPSK	1	50	Front	10	21100	2535	19.31	20.0	1.172	0.118	0.14	
	DSI5	20MHz	QPSK	1	50	Back	10	21100	2535	19.31	20.0	1.172	0.236	0.28	
	DSI5	20MHz	QPSK	1	50	Left	10	21100	2535	19.31	20.0	1.172	0.082	0.10	
	DSI5	20MHz	QPSK	1	50	Right	10	21100	2535	19.31	20.0	1.172	0.088	0.10	
	DSI5	20MHz	QPSK	1	50	Top	10	21100	2535	19.31	20.0	1.172	0.010	0.01	
	DSI5	20MHz	QPSK	1	50	Bottom	10	21100	2535	19.31	20.0	1.172	0.205	0.24	
Ant1	DSI4	20MHz	QPSK	1	50	Front	15	21100	2535	18.23	19.0	1.194	0.109	0.13	
	DSI4	20MHz	QPSK	1	50	Back	15	21100	2535	18.23	19.0	1.194	0.456	0.54	
Ant0	DSI4	20MHz	QPSK	1	50	Front	15	21100	2535	21.34	22.0	1.164	0.102	0.12	
	DSI4	20MHz	QPSK	1	50	Back	15	21100	2535	21.34	22.0	1.164	0.234	0.27	

11.12. LTE Band 13 SAR results

Configuration	Power Level	BW	Modulation	RB Num	RB Start	Position	Dist. mm	Ch.	Freq. (MHz)	Meas. Power (dBm)	Max. tune-up power (dBm)	Scaling Factor	1g Meas SAR (W/kg)	1g Scaled SAR (W/kg)
Head														
Ant1	DSI1	10MHz	QPSK	1	13	Left Cheek	0	23230	782	22.31	23.0	1.172	0.487	0.57
	DSI1	10MHz	QPSK	1	13	Left Tilt	0	23230	782	22.31	23.0	1.172	0.472	0.55
	DSI1	10MHz	QPSK	1	13	Right Cheek	0	23230	782	22.31	23.0	1.172	0.746	0.87
	DSI1	10MHz	QPSK	1	13	Right Tilt	0	23230	782	22.31	23.0	1.172	0.582	0.68
Ant0	original Power	10MHz	QPSK	1	13	Left Cheek	0	23230	782	23.30	24.0	1.175	0.111	0.13
	original Power	10MHz	QPSK	1	13	Left Tilt	0	23230	782	23.30	24.0	1.175	0.108	0.13
	original Power	10MHz	QPSK	1	13	Right Cheek	0	23230	782	23.30	24.0	1.175	0.102	0.12
	original Power	10MHz	QPSK	1	13	Right Tilt	0	23230	782	23.30	24.0	1.175	0.095	0.11
	original Power	10MHz	QPSK	1	13	Front	10	23230	782	23.13	24.0	1.222	0.183	0.22
Ant1	original Power	10MHz	QPSK	1	13	Back	10	23230	782	23.13	24.0	1.222	0.276	0.34
	original Power	10MHz	QPSK	1	13	Left	10	23230	782	23.13	24.0	1.222	0.145	0.18
	original Power	10MHz	QPSK	1	13	Right	10	23230	782	23.13	24.0	1.222	0.135	0.16
	original Power	10MHz	QPSK	1	13	Top	10	23230	782	23.13	24.0	1.222	0.199	0.24
Ant0	original Power	10MHz	QPSK	1	13	Bottom	10	23230	782	23.13	24.0	1.222	0.007	0.01
	original Power	10MHz	QPSK	1	13	Front	10	23230	782	23.30	24.0	1.175	0.138	0.16
	original Power	10MHz	QPSK	1	13	Back	10	23230	782	23.30	24.0	1.175	0.232	0.27
	original Power	10MHz	QPSK	1	13	Left	10	23230	782	23.30	24.0	1.175	0.226	0.27
	original Power	10MHz	QPSK	1	13	Right	10	23230	782	23.30	24.0	1.175	0.142	0.17
	original Power	10MHz	QPSK	1	13	Top	10	23230	782	23.30	24.0	1.175	0.011	0.01
Ant1	original Power	10MHz	QPSK	1	13	Bottom	10	23230	782	23.30	24.0	1.175	0.206	0.24
	original Power	10MHz	QPSK	1	13	Front	15	23230	782	23.13	24.0	1.222	0.144	0.18
Ant0	original Power	10MHz	QPSK	1	13	Back	15	23230	782	23.13	24.0	1.222	0.190	0.23
	original Power	10MHz	QPSK	1	13	Front	15	23230	782	23.30	24.0	1.175	0.088	0.10
Ant0	original Power	10MHz	QPSK	1	13	Back	15	23230	782	23.30	24.0	1.175	0.101	0.12

11.13. LTE Band 26 SAR results

Configuration	Power Level	BW	Modulation	RB Num	RB Start	Position	Dist. mm	Ch.	Freq. (MHz)	Meas. Power (dBm)	Max. tune-up power (dBm)	Scaling Factor	1g Meas SAR (W/kg)	1g Scaled SAR (W/kg)	
Head															
Ant1	DSI1	15MHz	QPSK	1	13	Left Cheek	0	26865	831.5	21.64	22.5	1.219	0.541	0.66	
	DSI1	15MHz	QPSK	1	13	Left Tilt	0	26865	831.5	21.64	22.5	1.219	0.537	0.65	
	DSI1	15MHz	QPSK	1	13	Right Cheek	0	26865	831.5	21.64	22.5	1.219	0.684	0.83	
	DSI1	15MHz	QPSK	1	13	Right Tilt	0	26865	831.5	21.64	22.5	1.219	0.643	0.78	
	DSI1	15MHz	QPSK	1	13	Right Cheek	0	26765	821.5	21.58	22.5	1.236	0.782	0.97	
Ant0	original Power	15MHz	QPSK	1	13	Left Cheek	0	26865	831.5	23.22	24.0	1.197	0.139	0.17	
	original Power	15MHz	QPSK	1	13	Left Tilt	0	26865	831.5	23.22	24.0	1.197	0.115	0.14	
	original Power	15MHz	QPSK	1	13	Right Cheek	0	26865	831.5	23.22	24.0	1.197	0.137	0.16	
	original Power	15MHz	QPSK	1	13	Right Tilt	0	26865	831.5	23.22	24.0	1.197	0.076	0.09	
	original Power	15MHz	QPSK	1	13	Front	10	26865	831.5	23.07	24.0	1.239	0.233	0.29	
	original Power	15MHz	QPSK	1	13	Back	10	26865	831.5	23.07	24.0	1.239	0.315	0.39	
	Ant1	original Power	15MHz	QPSK	1	13	Left	10	26865	831.5	23.07	24.0	1.239	0.102	0.13
		original Power	15MHz	QPSK	1	13	Right	10	26865	831.5	23.07	24.0	1.239	0.139	0.17
		original Power	15MHz	QPSK	1	13	Top	10	26865	831.5	23.07	24.0	1.239	0.284	0.35
		original Power	15MHz	QPSK	1	13	Bottom	10	26865	831.5	23.07	24.0	1.239	0.008	0.01
Ant0	original Power	15MHz	QPSK	1	13	Front	10	26865	831.5	23.22	24.0	1.197	0.146	0.17	
	original Power	15MHz	QPSK	1	13	Back	10	26865	831.5	23.22	24.0	1.197	0.286	0.34	
	original Power	15MHz	QPSK	1	13	Left	10	26865	831.5	23.22	24.0	1.197	0.174	0.21	
	original Power	15MHz	QPSK	1	13	Right	10	26865	831.5	23.22	24.0	1.197	0.107	0.13	
	original Power	15MHz	QPSK	1	13	Top	10	26865	831.5	23.22	24.0	1.197	0.010	0.01	
	original Power	15MHz	QPSK	1	13	Bottom	10	26865	831.5	23.22	24.0	1.197	0.252	0.30	
Ant1	original Power	15MHz	QPSK	1	13	Front	15	26865	831.5	23.07	24.0	1.239	0.149	0.18	
	original Power	15MHz	QPSK	1	13	Back	15	26865	831.5	23.07	24.0	1.239	0.220	0.27	
Ant0	original Power	15MHz	QPSK	1	13	Front	15	26865	831.5	23.22	24.0	1.197	0.135	0.16	
	original Power	15MHz	QPSK	1	13	Back	15	26865	831.5	23.22	24.0	1.197	0.143	0.17	

11.14. LTE Band 38 SAR results

Configuration	Power Level	BW	Modulation	RB Num	RB Start	Position	Dist. mm	Ch.	Freq. (MHz)	Meas. Power (dBm)	Max. tune-up power (dBm)	Scaling Factor	1g Meas SAR (W/kg)	1g Scaled SAR (W/kg)
Head														
Ant1	DSI1	20MHz	QPSK	1	50	Left Cheek	0	38000	2595	19.77	20.5	1.183	0.149	0.18
	DSI1	20MHz	QPSK	1	50	Left Tilt	0	38000	2595	19.77	20.5	1.183	0.191	0.23
	DSI1	20MHz	QPSK	1	50	Right Cheek	0	38000	2595	19.77	20.5	1.183	0.454	0.54
	DSI1	20MHz	QPSK	1	50	Right Tilt	0	38000	2595	19.77	20.5	1.183	0.597	0.71
Ant0	original Power	20MHz	QPSK	1	50	Left Cheek	0	38000	2595	23.63	24.0	1.089	0.163	0.18
	original Power	20MHz	QPSK	1	50	Left Tilt	0	38000	2595	23.63	24.0	1.089	0.088	0.10
	original Power	20MHz	QPSK	1	50	Right Cheek	0	38000	2595	23.63	24.0	1.089	0.172	0.19
	original Power	20MHz	QPSK	1	50	Right Tilt	0	38000	2595	23.63	24.0	1.089	0.147	0.16
Ant1	DSI5	20MHz	QPSK	1	50	Front	10	38000	2595	19.19	20.0	1.205	0.116	0.14
	DSI5	20MHz	QPSK	1	50	Back	10	38000	2595	19.19	20.0	1.205	0.541	0.65
	DSI5	20MHz	QPSK	1	50	Left	10	38000	2595	19.19	20.0	1.205	0.138	0.17
	DSI5	20MHz	QPSK	1	50	Right	10	38000	2595	19.19	20.0	1.205	0.012	0.01
	DSI5	20MHz	QPSK	1	50	Top	10	38000	2595	19.19	20.0	1.205	0.380	0.46
	DSI5	20MHz	QPSK	1	50	Bottom	10	38000	2595	19.19	20.0	1.205	0.010	0.01
Ant0	DSI5	20MHz	QPSK	1	50	Front	10	38000	2595	21.23	22.0	1.194	0.179	0.21
	DSI5	20MHz	QPSK	1	50	Back	10	38000	2595	21.23	22.0	1.194	0.261	0.31
	DSI5	20MHz	QPSK	1	50	Left	10	38000	2595	21.23	22.0	1.194	0.059	0.07
	DSI5	20MHz	QPSK	1	50	Right	10	38000	2595	21.23	22.0	1.194	0.157	0.19
	DSI5	20MHz	QPSK	1	50	Top	10	38000	2595	21.23	22.0	1.194	0.011	0.01
	DSI5	20MHz	QPSK	1	50	Bottom	10	38000	2595	21.23	22.0	1.194	0.290	0.35
Ant1	DSI4	20MHz	QPSK	1	50	Front	15	38000	2595	20.75	21.5	1.189	0.075	0.09
	DSI4	20MHz	QPSK	1	50	Back	15	38000	2595	20.75	21.5	1.189	0.352	0.42
Ant0	DSI4	20MHz	QPSK	1	50	Front	15	38000	2595	22.26	23.0	1.186	0.128	0.15
	DSI4	20MHz	QPSK	1	50	Back	15	38000	2595	22.26	23.0	1.186	0.207	0.25

11.15. LTE Band 41 SAR results

Configuration	Power Level	BW	Modulation	RB Num	RB Start	Position	Dist. mm	Ch.	Freq. (MHz)	Meas. Power (dBm)	Max. tune-up power (dBm)	Scaling Factor	1g Meas SAR (W/kg)	1g Scaled SAR (W/kg)
Head														
Ant1	DSI1	20MHz	QPSK	1	50	Left Cheek	0	40640	2595	19.86	20.5	1.159	0.148	0.17
	DSI1	20MHz	QPSK	1	50	Left Tilt	0	40640	2595	19.86	20.5	1.159	0.196	0.23
	DSI1	20MHz	QPSK	1	50	Right Cheek	0	40640	2595	19.86	20.5	1.159	0.463	0.54
	DSI1	20MHz	QPSK	1	50	Right Tilt	0	40640	2595	19.86	20.5	1.159	0.537	0.62
Ant0	original Power	20MHz	QPSK	1	50	Left Cheek	0	40640	2595	23.67	24.0	1.079	0.165	0.18
	original Power	20MHz	QPSK	1	50	Left Tilt	0	40640	2595	23.67	24.0	1.079	0.089	0.10
	original Power	20MHz	QPSK	1	50	Right Cheek	0	40640	2595	23.67	24.0	1.079	0.173	0.19
	original Power	20MHz	QPSK	1	50	Right Tilt	0	40640	2595	23.67	24.0	1.079	0.146	0.16
	DSI5	20MHz	QPSK	1	50	Front	10	40640	2595	19.37	20.0	1.156	0.114	0.13
Ant1	DSI5	20MHz	QPSK	1	50	Back	10	40640	2595	19.37	20.0	1.156	0.547	0.63
	DSI5	20MHz	QPSK	1	50	Left	10	40640	2595	19.37	20.0	1.156	0.139	0.16
	DSI5	20MHz	QPSK	1	50	Right	10	40640	2595	19.37	20.0	1.156	0.010	0.01
	DSI5	20MHz	QPSK	1	50	Top	10	40640	2595	19.37	20.0	1.156	0.378	0.44
	DSI5	20MHz	QPSK	1	50	Bottom	10	40640	2595	19.37	20.0	1.156	0.007	0.01
Ant0	DSI5	20MHz	QPSK	1	50	Front	10	40640	2595	21.16	22.0	1.213	0.179	0.22
	DSI5	20MHz	QPSK	1	50	Back	10	40640	2595	21.16	22.0	1.213	0.259	0.31
	DSI5	20MHz	QPSK	1	50	Left	10	40640	2595	21.16	22.0	1.213	0.056	0.07
	DSI5	20MHz	QPSK	1	50	Right	10	40640	2595	21.16	22.0	1.213	0.157	0.19
	DSI5	20MHz	QPSK	1	50	Top	10	40640	2595	21.16	22.0	1.213	0.007	0.01
	DSI5	20MHz	QPSK	1	50	Bottom	10	40640	2595	21.16	22.0	1.213	0.286	0.35
Ant1	DSI4	20MHz	QPSK	1	50	Front	15	40640	2595	20.82	21.5	1.169	0.081	0.09
	DSI4	20MHz	QPSK	1	50	Back	15	40640	2595	20.82	21.5	1.169	0.394	0.46
Ant0	DSI4	20MHz	QPSK	1	50	Front	15	40640	2595	22.38	23.0	1.153	0.127	0.15
	DSI4	20MHz	QPSK	1	50	Back	15	40640	2595	22.38	23.0	1.153	0.194	0.22

11.16. LTE Band 66 SAR results

Configuration	Power Level	BW	Modulation	RB Num	RB Start	Position	Dist. mm	Ch.	Freq. (MHz)	Meas. Power (dBm)	Max. tune-up power (dBm)	Scaling Factor	1g Meas SAR (W/kg)	1g Scaled SAR (W/kg)
Head														
Ant1	DS11	20MHz	QPSK	1	50	Left Cheek	0	132322	1745	17.68	18.5	1.208	0.372	0.45
	DS11	20MHz	QPSK	1	50	Left Tilt	0	132322	1745	17.68	18.5	1.208	0.451	0.54
	DS11	20MHz	QPSK	1	50	Right Cheek	0	132322	1745	17.68	18.5	1.208	0.542	0.65
	DS11	20MHz	QPSK	1	50	Right Tilt	0	132322	1745	17.68	18.5	1.208	0.624	0.75
Ant0	original Power	20MHz	QPSK	1	50	Left Cheek	0	132322	1745	23.30	24.0	1.175	0.140	0.16
	original Power	20MHz	QPSK	1	50	Left Tilt	0	132322	1745	23.30	24.0	1.175	0.105	0.12
	original Power	20MHz	QPSK	1	50	Right Cheek	0	132322	1745	23.30	24.0	1.175	0.131	0.15
	original Power	20MHz	QPSK	1	50	Right Tilt	0	132322	1745	23.30	24.0	1.175	0.116	0.14
	DSI5	20MHz	QPSK	1	50	Front	10	132322	1745	20.08	21.0	1.236	0.264	0.33
Ant1	DSI5	20MHz	QPSK	1	50	Back	10	132322	1745	20.08	21.0	1.236	0.308	0.38
	DSI5	20MHz	QPSK	1	50	Left	10	132322	1745	20.08	21.0	1.236	0.079	0.10
	DSI5	20MHz	QPSK	1	50	Right	10	132322	1745	20.08	21.0	1.236	0.011	0.01
	DSI5	20MHz	QPSK	1	50	Top	10	132322	1745	20.08	21.0	1.236	0.434	0.54
	DSI5	20MHz	QPSK	1	50	Bottom	10	132322	1745	20.08	21.0	1.236	0.009	0.01
Ant0	DSI5	20MHz	QPSK	1	50	Front	10	132322	1745	18.17	19.0	1.211	0.119	0.14
	DSI5	20MHz	QPSK	1	50	Back	10	132322	1745	18.17	19.0	1.211	0.408	0.49
	DSI5	20MHz	QPSK	1	50	Left	10	132322	1745	18.17	19.0	1.211	0.013	0.02
	DSI5	20MHz	QPSK	1	50	Right	10	132322	1745	18.17	19.0	1.211	0.070	0.08
	DSI5	20MHz	QPSK	1	50	Top	10	132322	1745	18.17	19.0	1.211	0.006	0.01
	DSI5	20MHz	QPSK	1	50	Bottom	10	132322	1745	18.17	19.0	1.211	0.436	0.53
Ant1	DSI4	20MHz	QPSK	1	50	Front	15	132322	1745	21.17	22.0	1.211	0.179	0.22
	DSI4	20MHz	QPSK	1	50	Back	15	132322	1745	21.17	22.0	1.211	0.237	0.29
Ant0	DSI4	20MHz	QPSK	1	50	Front	15	132322	1745	19.16	20.0	1.213	0.095	0.12
	DSI4	20MHz	QPSK	1	50	Back	15	132322	1745	19.16	20.0	1.213	0.283	0.34

11.17. 2.4GWi-Fi SAR results

Config	Mode	Power Level	Position	Dist. (mm)	Ch.	Freq. (MHz)	Meas. Power (dBm)	Max. tune-up power (dBm)	Scaling Factor	1g Meas SAR (W/kg)	1g Scaled SAR (W/kg)
Head											
Ant2	802.11b	Power Reduce	Left Cheek	0	6	2437	16.45	18.0	1.429	0.456	0.65
	802.11b	Power Reduce	Left Tilt	0	6	2437	16.45	18.0	1.429	0.359	0.51
	802.11b	Power Reduce	Right Cheek	0	6	2437	16.45	18.0	1.429	0.212	0.30
	802.11b	Power Reduce	Right Tilt	0	6	2437	16.45	18.0	1.429	0.275	0.39
	802.11b	original Power	Front	10	6	2437	18.50	20.0	1.413	0.180	0.25
	802.11b	original Power	Back	10	6	2437	18.50	20.0	1.413	0.347	0.49
	802.11b	original Power	Left	10	6	2437	18.50	20.0	1.413	0.049	0.07
	802.11b	original Power	Right	10	6	2437	18.50	20.0	1.413	0.202	0.29
	802.11b	original Power	Top	10	6	2437	18.50	20.0	1.413	0.218	0.31
	802.11b	original Power	Bottom	10	6	2437	18.50	20.0	1.413	0.049	0.07
	802.11b	original Power	Front	15	6	2437	18.50	20.0	1.413	0.107	0.15
	802.11b	original Power	Back	15	6	2437	18.50	20.0	1.413	0.141	0.20

11.18. 5.2GWi-Fi SAR results

Config	Mode	Power Level	Position	Dist. (mm)	Ch.	Freq. (MHz)	Meas. Power (dBm)	Max. tune-up power (dBm)	Scaling Factor	1g Meas SAR (W/kg)	1g Scaled SAR (W/kg)
Head											
Ant2	802.11a	Power Reduce	Left Cheek	0	40	5200	15.41	17.0	1.442	0.197	0.28
	802.11a	Power Reduce	Left Tilt	0	40	5200	15.41	17.0	1.442	0.209	0.30
	802.11a	Power Reduce	Right Cheek	0	40	5200	15.41	17.0	1.442	0.072	0.10
	802.11a	Power Reduce	Right Tilt	0	40	5200	15.41	17.0	1.442	0.098	0.14
	802.11a	Power Reduce	Front	10	40	5200	14.43	16.0	1.435	0.056	0.08
	802.11a	Power Reduce	Back	10	40	5200	14.43	16.0	1.435	0.474	0.68
	802.11a	Power Reduce	Left	10	40	5200	14.43	16.0	1.435	0.056	0.08
	802.11a	Power Reduce	Right	10	40	5200	14.43	16.0	1.435	0.257	0.37
	802.11a	Power Reduce	Top	10	40	5200	14.43	16.0	1.435	0.330	0.47
	802.11a	Power Reduce	Bottom	10	40	5200	14.43	16.0	1.435	0.066	0.09
	802.11a	Power Reduce	Front	15	40	5200	14.43	16.0	1.435	0.066	0.09
	802.11a	Power Reduce	Back	15	40	5200	14.43	16.0	1.435	0.308	0.44

11.19. 5.3GWi-Fi SAR results

Config	Mode	Power Level	Position	Dist. (mm)	Ch.	Freq. (MHz)	Meas. Power (dBm)	Max. tune-up power (dBm)	Scaling Factor	1g Meas SAR (W/kg)	1g Scaled SAR (W/kg)
Head											
Ant2	802.11a	Power Reduce	Left Cheek	0	56	5280	15.47	17.0	1.422	0.175	0.25
	802.11a	Power Reduce	Left Tilt	0	56	5280	15.47	17.0	1.422	0.162	0.23
	802.11a	Power Reduce	Right Cheek	0	56	5280	15.47	17.0	1.422	0.082	0.12
	802.11a	Power Reduce	Right Tilt	0	56	5280	15.47	17.0	1.422	0.102	0.15
	802.11a	Power Reduce	Front	10	56	5280	13.58	15.0	1.387	0.102	0.14
	802.11a	Power Reduce	Back	10	56	5280	13.58	15.0	1.387	0.496	0.69
	802.11a	Power Reduce	Left	10	56	5280	13.58	15.0	1.387	0.040	0.06
	802.11a	Power Reduce	Right	10	56	5280	13.58	15.0	1.387	0.289	0.40
	802.11a	Power Reduce	Top	10	56	5280	13.58	15.0	1.387	0.294	0.41
	802.11a	Power Reduce	Bottom	10	56	5280	13.58	15.0	1.387	0.077	0.11
	802.11a	Power Reduce	Front	15	56	5280	13.58	15.0	1.387	0.038	0.05
	802.11a	Power Reduce	Back	15	56	5280	13.58	15.0	1.387	0.311	0.43

Config	Mode	Power Level	Position	Dist. (mm)	Ch.	Freq. (MHz)	Meas. Power (dBm)	Max. tune-up power (dBm)	Scaling Factor	10g Meas SAR (W/kg)	10g Scaled SAR (W/kg)
Ant2	802.11a	Power Reduce	Front	0	56	5280	13.58	15.0	1.387	0.097	0.13
	802.11a	Power Reduce	Back	0	56	5280	13.58	15.0	1.387	0.641	0.81
	802.11a	Power Reduce	Left	0	56	5280	13.58	15.0	1.387	0.011	0.02
	802.11a	Power Reduce	Right	0	56	5280	13.58	15.0	1.387	0.289	0.36
	802.11a	Power Reduce	Top	0	56	5280	13.58	15.0	1.387	0.672	0.85
	802.11a	Power Reduce	Bottom	0	56	5280	13.58	15.0	1.387	0.016	0.02
	802.11a	Power Reduce	Top	0	52	5260	13.58	15.0	1.387	0.598	0.75
	802.11a	Power Reduce	Top	0	64	5320	13.58	15.0	1.387	0.547	0.69

11.20. 5.6GWi-Fi SAR results

Config	Mode	Power Level	Position	Dist. (mm)	Ch.	Freq. (MHz)	Meas. Power (dBm)	Max. tune-up power (dBm)	Scaling Factor	1g Meas SAR (W/kg)	1g Scaled SAR (W/kg)
Head											
Ant2	802.11a	Power Reduce	Left Cheek	0	120	5600	15.57	17.0	1.390	0.258	0.36
	802.11a	Power Reduce	Left Tilt	0	120	5600	15.57	17.0	1.390	0.221	0.31
	802.11a	Power Reduce	Right Cheek	0	120	5600	15.57	17.0	1.390	0.086	0.12
	802.11a	Power Reduce	Right Tilt	0	120	5600	15.57	17.0	1.390	0.130	0.18
	802.11a	Power Reduce	Front	10	120	5600	14.45	16.0	1.429	0.142	0.20
	802.11a	Power Reduce	Back	10	120	5600	14.45	16.0	1.429	0.432	0.62
	802.11a	Power Reduce	Left	10	120	5600	14.45	16.0	1.429	0.150	0.21
	802.11a	Power Reduce	Right	10	120	5600	14.45	16.0	1.429	0.341	0.49
	802.11a	Power Reduce	Top	10	120	5600	14.45	16.0	1.429	0.311	0.44
	802.11a	Power Reduce	Bottom	10	120	5600	14.45	16.0	1.429	0.162	0.23
	802.11a	Power Reduce	Front	15	120	5600	14.45	16.0	1.429	0.097	0.14
	802.11a	Power Reduce	Back	15	120	5600	14.45	16.0	1.429	0.275	0.39

Config	Mode	Power Level	Position	Dist. (mm)	Ch.	Freq. (MHz)	Meas. Power (dBm)	Max. tune-up power (dBm)	Scaling Factor	10g Meas SAR (W/kg)	10g Scaled SAR (W/kg)
Ant2	802.11a	Power Reduce	Front	0	120	5600	14.45	16.0	1.429	0.160	0.16
	802.11a	Power Reduce	Back	0	120	5600	14.45	16.0	1.429	0.765	0.77
	802.11a	Power Reduce	Left	0	120	5600	14.45	16.0	1.429	0.026	0.03
	802.11a	Power Reduce	Right	0	120	5600	14.45	16.0	1.429	0.542	0.54
	802.11a	Power Reduce	Top	0	120	5600	14.45	16.0	1.429	0.863	0.86
	802.11a	Power Reduce	Bottom	0	120	5600	14.45	16.0	1.429	0.053	0.05
	802.11a	Power Reduce	Top	0	100	5500	14.45	16.0	1.429	0.742	0.74
	802.11a	Power Reduce	Top	0	140	5700	14.45	16.0	1.429	0.841	0.84

11.21. 5.8GWi-Fi SAR results

Config	Mode	Power Level	Position	Dist. (mm)	Ch.	Freq. (MHz)	Meas. Power (dBm)	Max. tune-up power (dBm)	Scaling Factor	1g Meas SAR (W/kg)	1g Scaled SAR (W/kg)
Head											
Ant2	802.11a	original Power	Left Cheek	0	157	5785	15.49	17.0	1.416	0.119	0.17
	802.11a	original Power	Left Tilt	0	157	5785	15.49	17.0	1.416	0.186	0.26
	802.11a	original Power	Right Cheek	0	157	5785	15.49	17.0	1.416	0.074	0.10
	802.11a	original Power	Right Tilt	0	157	5785	15.49	17.0	1.416	0.112	0.16
	802.11a	original Power	Front	10	157	5785	15.49	17.0	1.416	0.060	0.08
	802.11a	original Power	Back	10	157	5785	15.49	17.0	1.416	0.505	0.71
	802.11a	original Power	Left	10	157	5785	15.49	17.0	1.416	0.165	0.23
	802.11a	original Power	Right	10	157	5785	15.49	17.0	1.416	0.240	0.34
	802.11a	original Power	Top	10	157	5785	15.49	17.0	1.416	0.297	0.42
	802.11a	original Power	Bottom	10	157	5785	15.49	17.0	1.416	0.178	0.25
	802.11a	original Power	Front	15	157	5785	15.49	17.0	1.416	0.158	0.22
	802.11a	original Power	Back	15	157	5785	15.49	17.0	1.416	0.324	0.46

11.22. BT SAR results

Config	Mode	Power Level	Position	Dist. (mm)	Ch.	Freq. (MHz)	Meas. Power (dBm)	Max. tune-up power (dBm)	Scaling Factor	1g Meas SAR (W/kg)	1g Scaled SAR (W/kg)
Head											
Ant2	BT	original Power	Left Cheek	0	39	2441	10.33	11.0	1.167	0.066	0.08
	BT	original Power	Left Tilt	0	39	2441	10.33	11.0	1.167	0.052	0.06
	BT	original Power	Right Cheek	0	39	2441	10.33	11.0	1.167	0.021	0.02
	BT	original Power	Right Tilt	0	39	2441	10.33	11.0	1.167	0.042	0.05
	BT	original Power	Front	10	39	2441	10.33	11.0	1.167	0.012	0.01
	BT	original Power	Back	10	39	2441	10.33	11.0	1.167	0.022	0.03
	BT	original Power	Left	10	39	2441	10.33	11.0	1.167	0.043	0.05
	BT	original Power	Right	10	39	2441	10.33	11.0	1.167	0.018	0.02
	BT	original Power	Top	10	39	2441	10.33	11.0	1.167	0.022	0.03
	BT	original Power	Bottom	10	39	2441	10.33	11.0	1.167	0.023	0.03
	BT	original Power	Front	15	39	2441	10.33	11.0	1.167	0.007	0.01
	BT	original Power	Back	15	39	2441	10.33	11.0	1.167	0.011	0.01

11.23. Repeated SAR results

Remark:

1. Per KDB 865664 D01v01r04, for each frequency band, repeated SAR measurement is required only when the measured SAR is $\geq 0.8\text{W/kg}$.
2. Per KDB 865664 D01v01r04, if the ratio among the repeated measurement is ≤ 1.2 and the measured SAR $< 1.45\text{W/kg}$, only one repeated measurement is required.
3. The ratio is the difference in percentage between original and repeated measured SAR.
4. All measurement SAR result is scaled-up to account for tune-up tolerance and is compliant.


Band	Mode	Test Position	Ch.	Freq. (MHz)	Average Power (dBm)	Tune-Up Limit (dBm)	Scaling Factor	Measured SAR (W/kg)	Reported SAR (W/kg)
WCDMA Band II	RMC	Right Tilt	9400	1880	16.58	18.0	1.387	0.674	0.93
WCDMA Band II	RMC	Right Tilt	0	9262	1852.4	16.53	18.0	1.403	0.587

LTE Band 2	20M Hz	QPS K	1	50	Right Tilt	0	20175	1732.5	18.09	19.0	1.233	0.675	0.83
	20M Hz	QPS K	1	50	Right Tilt	0	20050	1754.9	18.09	19.0	1.233	0.652	0.80
	20M Hz	QPS K	1	50	Right Tilt	0	20300	1745	18.09	19.0	1.233	0.790	0.97
LTE Band 7	20M Hz	QPS K	1	50	Right Tilt	0	21100	2535	16.28	17.0	1.180	0.731	0.86
	20M Hz	QPS K	1	50	Right Tilt	0	20850	2510	16.21	17.0	1.199	0.771	0.92
LTE Band 13	10M Hz	QPS K	1	13	Right Cheek	0	23230	782	22.31	23.0	1.172	0.746	0.87
LTE Band 26	15M Hz	QPS K	1	13	Right Cheek	0	26865	831.5	21.64	22.5	1.219	0.684	0.83
	15M Hz	QPS K	1	13	Right Cheek	0	26765	821.5	21.58	22.5	1.236	0.782	0.97

	15M Hz	QPS K	1	13	Right Chee k	0	2696 5	841.5	21.61	22.5	1.227	0.670	0.82
--	-----------	----------	---	----	--------------------	---	-----------	-------	-------	------	-------	-------	------

12. EXPOSURE POSITIONS CONSIDERATION

12.1. Multiple Transmitter Evaluation



The reference plane is the Back side

Antennas	Distance of the Antenna to the EUT surface edge					
	Front	Back	Left	Right	Top	Bottom
ANT0	≤25mm	≤25mm	≤25mm	≤25mm	>25mm	≤25mm
ANT1	≤25mm	≤25mm	≤25mm	>25mm	≤25mm	>25mm
ANT2	≤25mm	≤25mm	>25mm	≤25mm	≤25mm	>25mm

Antennas	Positions for SAR tests; Hotspot mode					
	Front	Back	Left	Right	Top	Bottom
ANT0	Yes	Yes	Yes	Yes	No	Yes
ANT1	Yes	Yes	Yes	No	Yes	No
ANT2	Yes	Yes	No	Yes	Yes	No

12.2. Simultaneous Transmission Possibilities

The Simultaneous Transmission Possibilities of this device are as below:

	Simultaneous Transmission Configurations	Portable Handset	
		Head	Body-worn
	GSM Voice + 2.4GHz WLAN	Yes	Yes
	GPRS/EDGE + 2.4GHz WLAN	Yes	Yes
	WCDMA + 2.4GHz WLAN	Yes	Yes
	LTE + 2.4GHz WLAN	Yes	Yes
	GSM Voice + 5GHz WLAN	Yes	Yes
	GPRS/EDGE + 5GHz WLAN	Yes	Yes
	WCDMA + 5GHz WLAN	Yes	Yes
	LTE + 5GHz WLAN	Yes	Yes
	GSM Voice + Bluetooth	Yes	Yes
	GPRS/EDGE + Bluetooth	Yes	Yes
	WCDMA + Bluetooth	Yes	Yes
	LTE + Bluetooth	Yes	Yes
	GSM Voice + 5GHz WLAN + Bluetooth	Yes	Yes
	GPRS/EDGE +5GHz WLAN + Bluetooth	Yes	Yes
	WCDMA + 5GHz WLAN + Bluetooth	Yes	Yes
	LTE + 5GHz WLAN + Bluetooth	Yes	Yes
	5GHz WLAN + Bluetooth	Yes	Yes

Table 7: Simultaneous Transmission Possibilities

Note:

- 1) Bluetooth share the same Tx antenna and can't transmit simultaneously.
- 2) 2G&3G&4G can't transmit simultaneously.
- 3) Held to ear configurations are not applicable to Bluetooth and therefore were not considered for simultaneous transmission.

12.3. SAR Summation Scenario

Test Position		Left head touched	Left head tilted 15°	Righthhead touched	Right head tilted 15°
	GSM850	0.51	0.48	0.73	0.57
	PCS1900	0.41	0.46	0.62	0.74
	WCDMA Band II	0.45	0.53	0.64	0.93
	WCDMA Band IV	0.33	0.41	0.49	0.56
	WCDMA Band V	0.44	0.42	0.63	0.51
	LTE Band 2	0.45	0.51	0.63	0.76
	LTE Band 4	0.49	0.60	0.71	0.97
	LTE Band 5	0.51	0.50	0.76	0.60
	LTE Band 7	0.24	0.32	0.64	0.92
	LTE Band13	0.57	0.55	0.87	0.68
	LTE Band26	0.66	0.65	0.97	0.78
	LTE Band 38	0.18	0.23	0.54	0.71
	LTE Band 41	0.18	0.23	0.54	0.62
	LTE Band 66	0.45	0.54	0.65	0.75
	WIFI2.4G	0.65	0.51	0.30	0.39
	WIFI 5G	0.36	0.31	0.12	0.18
BT	0.08	0.06	0.02	0.05	
Σ 1g SAR(W/kg)		1.31	1.16	1.27	1.36

Conclusion:

- 1) Simultaneous Transmission SAR evaluation is not required for WiFi and UMTS&GSM<E&NSA, because the sum of the 1g SAR is 1.36W/kg < 1.6 W/kg.
- 2) One way of determining the threshold power level available to the secondary transmitter($P_{available}$) is to calculate it from the measured peak spatial-average SAR of the primary transmitter (SAR1) according to the equation:

Test Position		Front Side 10mm	Back Side 10mm	Left Side 10mm	Right Side 10mm	Top Side 10mm	Bottom Side 10mm	Front Side 15mm	Back Side 15mm
	GSM850	0.34	0.45	0.23	0.20	0.43	0.31	0.19	0.30
	PCS1900	0.24	0.42	0.06	0.13	0.43	0.53	0.16	0.27
	WCDMA Band II	0.26	0.52	0.08	0.15	0.50	0.64	0.22	0.37
	WCDMA Band IV	0.25	0.51	0.07	0.09	0.42	0.52	0.19	0.35
	WCDMA Band V	0.28	0.43	0.20	0.16	0.35	0.27	0.17	0.26
	LTE Band 2	0.27	0.50	0.09	0.15	0.48	0.63	0.22	0.36
	LTE Band 4	0.25	0.49	0.07	0.08	0.39	0.50	0.18	0.32
	LTE Band 5	0.31	0.39	0.20	0.17	0.37	0.28	0.18	0.27
	LTE Band 7	0.14	0.54	0.12	0.10	0.46	0.24	0.13	0.54
	LTE Band13	0.22	0.34	0.27	0.17	0.24	0.24	0.18	0.23
	LTE Band26	0.29	0.39	0.21	0.17	0.35	0.30	0.18	0.27
	LTE Band 38	0.21	0.65	0.17	0.19	0.46	0.35	0.15	0.42
	LTE Band 41	0.22	0.63	0.16	0.19	0.44	0.35	0.15	0.46
	LTE Band 66	0.33	0.49	0.10	0.08	0.54	0.53	0.12	0.34
	WIFI2.4G	0.25	0.49	0.07	0.29	0.31	0.07	0.15	0.20
WIFI 5G	0.20	0.71	0.23	0.49	0.47	0.25	0.22	0.46	
BT	0.01	0.03	0.05	0.02	0.03	0.03	0.01	0.01	
Σ1g SAR(W/kg)		0.59	1.39	0.55	0.71	1.04	0.92	0.45	1.01

Conclusion:

- 1) Simultaneous Transmission SAR evaluation is not required for WiFi and UMTS&GSM<E&NSA, because the sum of the 1g SAR is 1.39W/kg <1.6 W/kg.
- 2) One way of determining the threshold power level available to the secondary transmitter(Pavailable) is to calculate it from the measured peak spatial-average SAR of the primarytransmitter (SAR1) according to the equation:

Test Position		Front Side 0mm	Back Side 0mm	Left Side 0mm	Right Side 0mm	Top Side 0mm	Bottom Side 0mm
	WIFI 5.3G	0.13	0.81	0.02	0.36	0.85	0.02
	WIFI 5.6G	0.16	0.77	0.03	0.54	0.86	0.05

Conclusion:

- 1) Simultaneous Transmission SAR evaluation is not required for WiFi and UMTS&GSM<E&NSA, because the sum of the 10g SAR is 0.86W/kg < 4.0 W/kg.
- 2) One way of determining the threshold power level available to the secondary transmitter ($P_{available}$) is to calculate it from the measured peak spatial-average SAR of the primary transmitter (SAR1) according to the equation:

12.4. Simultaneous Transmission Conclusion

The above numeral summed SAR results and SPLSR analysis is sufficient to determine that simultaneous cases will not exceed the SAR limit and therefore simultaneous transmission SAR with Volume Scan is not required per KDB 447498 D01v06

Appendix A. System Check Plots

(Pls see Appendix A)

Appendix B. MEASUREMENT SCANS

(Pls see Appendix B)

Appendix C RELEVANT PAGES FROM PROBE CALIBRATION REPORT(S)

(Pls see Appendix C)

Appendix D. RELEVANT PAGES FROM DAE&DIPOLE VALIDATION KIT REPORT(S)

(Pls see Appendix D)

Appendix E. Photographs of the Test Set-Up

(Pls see Appendix E)

Appendix F: Tune-up Limit & Power

(Pls see Appendix F)