

RF EXPOSURE EVALUATION METHOD
FCC ID:2AU EW-ZH700
SAR Test Exclusion Thresholds for 100 MHz - 6 GHz and ≤ 50 mm

Approximate SAR Test Exclusion Power Thresholds at Selected Frequencies and Test Separation Distances are illustrated in the following Table.

MHz	5	10	15	20	25	mm
150	39	77	116	155	194	SAR Test Exclusion Threshold (mW)
300	27	55	82	110	137	
450	22	45	67	89	112	
835	16	33	49	66	82	
900	16	32	47	63	79	
1500	12	24	37	49	61	
1900	11	22	33	44	54	
2450	10	19	29	38	48	
3600	8	16	24	32	40	
5200	7	13	20	26	33	
5400	6	13	19	26	32	
5800	6	12	19	25	31	

The 1-g and 10-g SAR test exclusion thresholds for 100 MHz to 6 GHz at test separation distances ≤ 50 mm are determined by:

$[(\text{max. power of channel, including tune-up tolerance, mW}) / (\text{min. test separation distance, mm})] \cdot [\sqrt{f(\text{GHz})}] \leq 3.0$ for 1-g SAR and ≤ 7.5 for 10-g extremity SAR, where $f(\text{GHz})$ is the RF channel transmit frequency in GHz

Power and distance are rounded to the nearest mW and mm before calculation

The result is rounded to one decimal place for comparison

The test exclusions are applicable only when the minimum test separation distance is ≤ 50 mm and for transmission frequencies between 100 MHz and 6 GHz. When the minimum test separation distance is < 5 mm, a distance of 5 mm is applied to determine SAR test exclusion.

BT-EDR

Modulation	Frequency (MHz)	Output Power (dBm)	Max Antenna Gain (dBi)
GFSK	2402	-0.800	1.2
GFSK	2441	0.163	1.2
GFSK	2480	0.830	1.2
Pi/4 DQPSK	2402	0.320	1.2
Pi/4 DQPSK	2441	1.051	1.2
Pi/4 DQPSK	2480	1.624	1.2
8DPSK	8DPSK	0.831	1.2
8DPSK	8DPSK	1.334	1.2
8DPSK	8DPSK	2.407	1.2

max possible output power (PK,conducted) : 3±1dbm

3dBi logarithmic terms convert to numeric result is nearly 1.995

4dbm=2.51mW

2402MHz

[(max. power of channel, including tune-up tolerance, mW)/(min. test separation

distance,mm)] · [$\sqrt{f(\text{GHz})}$] $2.51/5 \cdot \sqrt{2.402} = 0.78 \leq 3.0$

Threshold at which no SAR required is 10mw and ≤ 3.0 for 1-g SAR, Separation

distance is 5mm.

2441MHz

$[(\text{max. power of channel, including tune-up tolerance, mW})/(\text{min. test separation distance, mm})] \cdot [\sqrt{f(\text{GHz})}] = 2.51/5 \cdot \sqrt{2.441} = 0.78 \leq 3.0$

Threshold at which no SAR required is 10mw and ≤ 3.0 for 1-g SAR, Separation distance is 5mm.

Conclusion: No SAR is required.

2480MHz

$[(\text{max. power of channel, including tune-up tolerance, mW})/(\text{min. test separation distance, mm})] \cdot [\sqrt{f(\text{GHz})}] = 2.51/5 \cdot \sqrt{2.48} = 0.79 \leq 3.0$

Threshold at which no SAR required is 10mw and ≤ 3.0 for 1-g SAR, Separation distance is 5mm.