


WiFi PIR Motion Sensor User Manual




Packing List


Product should include below accessories.




WiFi PIR motion sensor(X 1)




User Manual(X 1)




QC PASS (X 1)



3M sticker(X 1), Bracket(X 1)




AA battery(X 3)




Expansion tubes(X 2), Screws(X 2)

Product Description




Fresnel lens




Back cover

Network Setting

1. Power on the product.




Open the back cover with screw driver



Power on the device with 3*AA batteries, the red indicator flashes slowly for one minute.

2. Press the reset button for 5S and release, the green LED will flash for network setting.



Press the reset button for 5s then release.



Distribution network hint:


- Press the button for 5s-10s, the red LED is on for 5 sec then turns off. Release the button for network setting, the green LED flashes during networking.
- The green LED will be on for 5s then turns off to indicate network setting succeeds. If fails, the green LED is off.

Installation Instructions


3. Installation Instructions:
- (1) After powered on, the product will enter self-checking state and the red LED will flash for 60s.
 - (2) After self-checking, the product enters test mode for 5 minutes. When it detects human motion, the red LED flash and sends an alarm signal.
 - (3) During working status, press set button, the red LED flash once, then enter testing mode.
 - (4) After testing mode, the detector enters working mode and no motion status. When human motion is detected, the red LED is on and sends an alarm signal. After alarm, if continuous motion is detected, it won't send alarm signal. Until no motion is detected for 1 minute, it restores to no motion status and working mode.

Installation Instructions

1. Installation position: Install the product where persons may be detected to cross. It is recommended that the product be about 2.2m above the ground, as shown in the following figure.




Valid detection area (side view)




Valid detection area (top view)

2.Wall mounted type

(1)Using screws:




Fix the bracket to the wall with screws




Then install the device to the bracket

(2)M sticker installation:

(2)M sticker installation:



Fix the device to bracket





Stick to suitable place with 3M sticker.

3.Notice:

a. Make sure no obstacle in detection area.

b. Wireless distance will be weakened if there is blocks (such as walls)between device and WiFi router.

c. Install the product away from objects that may cause temperature changes, such as the air conditioner, fan, refrigerator, and oven. Do not expose the product to the sun.





3.Notice:

a. Make sure no obstacle in detection area.

b. Wireless distance will be weakened if there is blocks (such as walls)between device and WiFi router.

c. Install the product away from objects that may cause temperature changes, such as the air conditioner, fan, refrigerator, and oven. Do not expose the product to the sun.



App Download

1. Search for "Smart Life" in APP Store or Google Play Store. Or, scan the below QR code to download the APP.



Scan to download
Smart Life APP

Network Setting

1. Power on the WiFi device;
2. Make sure the network indicator flash(if not, long press reset button until indicator flashes.)
3. On App homepage, click "+" on top right corner; Click "Security&Sensors" on the left side of the page, and select the right WiFi sensor type to add device;
4. If successfully added, device will be in "My home" list.

Technical Parameters

| | |
|------------------------|---|
| Wireless Technology | WiFi |
| Working Voltage | DC 4.5V (3*AA battery) |
| Transmission Frequency | 2.4GHz |
| Working Temperature | -10°C ~ +55°C |
| Low power indication | Yes |
| Detecting range | 8m |
| Detection angle | 90° |
| Installation height | 2.2m |
| Size | 95.0×56.0×42.0~53.0 (with bracket)mm |

Toxic or Hazardous Substances or Elements of this Product

| Component Name | Toxic or Hazardous Substances or Elements | | | | | |
|----------------------------|---|--------------|--------------|-------------------------------|---------------------------------|--|
| | Lead (Pb) | Mercury (Hg) | Cadmium (Cd) | Hexavalent chromium (Cr (VI)) | Polybrominated biphenyls (PBBs) | Polybrominated diphenyl ethers (PBDEs) |
| LED | 0 | 0 | 0 | 0 | 0 | 0 |
| PCB | 0 | 0 | 0 | 0 | 0 | 0 |
| Cover and other components | 0 | 0 | 0 | 0 | 0 | 0 |

This table complies with SJ/T 11364.

0: indicates that the toxic or hazardous substance amount contained in all homogeneous materials of a component does not exceed that stipulated in GB/T 26572.

X: indicates that the toxic or hazardous substance amount contained in at least one of the homogeneous materials of a component exceeds that stipulated in GB/T 26572.



Warranty Certificate

Warranty policy:

1. If the product has quality problems within 7 days of the payment date, you can apply for a refund based on the invoice price or to replace with the same model or have it repaired..
2. If the product has quality problems within 15 days of the payment date, you can apply to replace the product with the same model or have it repaired.
3. If the product has quality problems within 12 months of the payment date, you can apply to have it repaired.

What is not covered under this warranty:

1. The product owner has no warranty certificate or the warranty service has expired.
2. Damage caused by improper use, maintenance, or storage
3. Damage caused by disassembly and repair without Tuya's authorization
4. Damage caused by force majeure
5. Normal discoloration and depreciation after the product has been used

User Form

User information (Specify real information. Tuya promises to use the information only for after-sales services.)

Name _____

Phone number _____

Email _____

Zip code _____

Address _____

Product information

Name _____ Model _____

Color _____ Product SN _____

Service Return Replace Repair

Fault symptoms _____

Handling date _____

Maintenance personnel signature _____

Vendor Form

User information (Specify real information. Tuya promises to use the information only for after-sales services.)

Name _____

Phone number _____

Email _____

Zip code _____

Address _____

Product information

Name _____ Model _____

Color _____ Product SN _____

Service Return Replace Repair

Fault symptoms _____

Handling date _____

Maintenance personnel signature _____

Caution:

This device complies with Part 15 of the FCC rules and Industry Canada license-exempt RSS standard(s). Operation is subject to the following two conditions:
(1) this device may not cause harmful interference, and
(2) this device must accept any interference received, including interference that may cause undesired operation.

The manufacturer is not responsible for any radio or TV interference caused by unauthorized modifications or change to this equipment. Such modifications or change could void the user's authority to operate the equipment.

This radio transmitter (identify the device by certification number or model number if Category II) has been approved by Industry Canada to operate with the antenna types listed below with the maximum permissible gain indicated. Antenna types not included in this list, having a gain greater than the maximum gain indicated for that type, are strictly prohibited for use with this device.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation.

This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

The device has been evaluated to meet general RF exposure requirement.

To maintain compliance with FCC's RF exposure guidelines, this equipment should be installed and operated with a minimum distance of 20cm between the radiator and your body.

Caution:

This device complies with Part 15 of the FCC rules and Industry Canada license-exempt RSS standard(s). Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

The manufacturer is not responsible for any radio or TV interference caused by unauthorized modifications or change to this equipment. Such modifications or change could void the user's authority to operate the equipment.

This radio transmitter (identify the device by certification number or model number if Category II) has been approved by Industry Canada to operate with the antenna types listed below with the maximum permissible gain indicated. Antenna types not included in this list, having a gain greater than the maximum gain indicated for that type, are strictly prohibited for use with this device.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

The device has been evaluated to meet general RF exposure requirement.

To maintain compliance with FCC's RF exposure guidelines, this equipment should be installed and operated with a minimum distance of 20cm between the radiator and your body.